

产品升级啦!

- 1:增加 SOS 功能。用户可在紧急情况下一键自动拨打设定好的求救号码。
- 2: 增加平台查询功能。用户可登录平台查询实时位置，历史轨迹，电子围栏，等信息，更加方便，实用。

X009 说明书

(一)产品概述

该产品支持 GSM850/900/1800/1900 网络和 GPRS,并且可以在不同网络间无缝切换.体积小;信号强;声音大;定位精准;图片清晰;性能稳定;超长待机;全球通用.这些功能是它最大的优势.

(二)技术参数

型号	X009	
尺寸	长 55mm 宽 45mm 高 14mm	
摄像头	传感器类型	CMOS
	像素	200 万
扩展卡	micro SD 卡	
电池	聚合物 (450mAh)	
软件版本	X009DZ-FLASH128+32-LBS-01020120825	
方案	MTK	
待机时间	使用时 3-5 天	
	待机时 12-15 天	

(三)功能操作

开/关机

按住开关/机键 3-5 秒,指示灯 **不间断闪烁**即为 **开机** ,待指示灯灭后便可拨打

按住开关/机键 3-5 秒,指示**灯常亮**,稍后灯灭即为 **关机**

拍照

编辑短信"**000**"发送至本产品则会自动拍一张照片并存在 TF 卡上 像素 640*480

回复提示: The Photo has been save in the memory card,图片已存储

拍照回传

编辑短信"**111**"发送至本产品 (此功能需具有 GPRS 和彩信功能的卡) 像素 640*480

录像

编辑短信"**222**"发送至本产品 (录像时发送"**444**"则会结束并保存到 TF 卡上) 像素 480*320

回复提示: Start recording video,开始录像

录音

编辑短信"**333**"发送至本产品 (录音时发送"**444**"则会结束并保存到 TF 卡上)

回复提示: Start recording sound, 开始录音

格式化内存卡

编辑短信"999"发送至本产品, 格式化内存卡

声控回拨

(1)短信回拨

授权人编辑短信"777"发送至本产品.当产品周围的声音超过 30 分贝时, 会有中文短信“**安全提示: 有人私自闯入**”回复给授权人

(2)电话回拨

授权人编辑短信"888"发送至本产品.当产品周围的声音超过 30 分贝时, 会直接回拨电话给授权人手机

人工调节灵敏度: 授权人编辑短信“777#8#”(短信回拨) 或者“888#8#”(电话回拨) 到产品。该机器会开启声控功能, 并以 777 或 888 后面的数字设置成声音检测的灵敏度。设置成功, 会有短信回复提示。最后的数字可以是 8 至 255

定位

(1)定位查询:

国内定位: 用户编辑字母“DW”到机器, 一分钟左右会回复一条包含文字/网址等信息。手机和电脑均可登录链接查看详细位置。

LBS: [广东省深圳市三号路/离 7 天连锁酒店深圳华强店\(正南\)125米/离赤尾大厦\(正南\)133米](http://new.gpscar.cn/showMap.aspx?n=22.54404,114.08313) <http://new.gpscar.cn/showMap.aspx?n=22.54404,114.08313>

国外定位: 用户编辑字母“DWEN”到机器, 一分钟左右会回复一条包含英文/网址等信息。手机和电脑均可登录链接查看详细位置。

(3)平台查询: 用户编辑字母“PT”发送到机器, 将返回一条包含机器本身 IMEI 号和密码的短信, 用户凭借 IMEI 号和密码登陆 <http://www.dx009.net> 平台查询后台信息(支持多种地图查询, 可查询机器位置、历史轨迹、电子围栏、运行统计、修改密码等功能。)



提示：国外大部分国家定位可直接发“DWEN”，少数国家需先设置 APN 才能定位，格式为编辑短信“APN，APN 名称，用户名，密码#”发送至本产品（设备中插的是哪一家运营商的手机卡，就对应设置那一家运营商的 APN）。例如：埃及 click Vodafone；用户编辑短信“APN，internet.vodafone.net，internet，internet#”发送至本产品.收到短信回复“Set Ok”后再发送 DW 或 DJ 或 PT 即可查询相应信息

(4)连续数据上传 授权人编辑短信"**LXDWX**"发送至本产品.(X 代表定位的间隔时间，所以 **LXDWX 15** 就代表每隔 **15** 分钟定位上传一次，用户可登录平台查询轨迹。定位间隔时间 **1** 《X 《60。关闭连续数据上传指令：**GBDW**)

电量查询

编辑短信"**666**"发送至本产品

备注：本产品默认最后一条短信指令自动取消上一条短信指令,以上所有功能的结束操作均为编辑短信"**444**"至本产品

1.检验自动识别网关、检验自动更新时间(自动更新时间需发指令”szsj”或”SZSJ”更新，设置成功时则提示”Time already calibration.自动设置时间成功!”)。

(四)注意事项

- *电池电量耗尽，需连接充电器 3 分钟才能启动充电
- *新机使用前要充满电，以达到最佳效果，请使用原机配带的充电线
- *充电器标配：±5. 0V 300-500MA，以免损坏主机
- *灯不亮，电池没电，充电后再使用
- *打不通电话，重新插卡开机或充电后再测试
- *不自动接听，重新插卡开机

- *需外加控制器，要自行定做
- *请勿自行拆机，人为造成的损坏不在“三包”范围
- *本产品严禁用于非法用途，否则将追究其法律责任

X009 Operation Manual

I. Product Overview

The product supports GSM850/900/1800/1900 network and GPRS, and can switch seamlessly between different networks. Its biggest advantages are shown through the features of compact in size, strong signal, loud voice, precise positioning, clear pictures, stable performances, long standby time, and global application.

Microphone On/Off key USB Charger Interface Camera
SIM Card Connector Memory Card Connector

II. Technical Parameters

Model	X009	
Size	55mm (L) x 45mm (W) x 14mm (H)	
Camera	Sensor Type	CMOS
	Pixel	2.0 million
Expansion Card	micro SD card	
Battery	Polymer(450mAh)	
Software Version	X009DZ-FLASH128+32-LBS-01020120825	
Scheme	MTK	
Standby Time	When using: 3-5 days	
	Standby Mode: 12-15 days	

III. Functional Operation

Press and hold the On/Off key for 3-5 seconds. The indicator light flashes continuously, which means the product is switched on. After the indicator goes out, calls can be made.

Press and hold the On/Off key for 3-5 seconds. The indicator light keeps on. And later, it goes out, which means the product is switched off.

Photo Shooting

Edit the SMS “000” and send to the product. A photo will be automatically taken and saved in the TF card.

Reply: The Photo has been saved in the memory card.

Photo Shooting and Sending Back

Edit the SMS “111” and send to the product (A card with GPRS and colored SMS is required for this function.)

Video Recording

Edit the SMS “222” and send to the product (Send “444” during video recording will end the process and save to the TF card.)

Reply: Start recording video

Audio Recording

Edit the SMS “333” and send to the product (Send “444” during audio recording will end the process and save to the TF card.)

Reply: Start recording sound

Memory Card Formatting

Edit the SMS “999” and send to the product, the memory card will be formatted.

Sound Control Callback

(1) Message Callback

The authorized person edits the SMS “777” and send to the product. When the sound around the product exceeds 30 dB, there will be a Chinese SMS “Safety tips: Someone broke into secretly” replied to the authorized person.

(2) Phone Callback

The authorized person edits the SMS “888” and send to the product. When the sound around the product exceeds 30 dB, there will be a direct dial-back to the mobile phone of the authorized person.

Manual Adjustment of Sensitivity: The authorized person edits the SMS “777#8#”(SMS callback) or “888#8#” (phone callback) and send to the product. The machine will turn on the sound control function, and set the number after 777 or 888 as the sensitivity of sound detection. There will be a SMS reply when the feature is set successfully. The last number could be 8 to 255.

(1) location query:

Positioning: domestic user to edit the letter "DW" to the machine, a minute or so will reply to a text/url information, etc. Cell phones and computers can login link to see detailed location.

Foreign location: user to edit the letter "DWEN" into the machine, a minute or so will reply included an English/url information, etc. Cell phones and computers can login link to see detailed location.

(3) platform query: user to edit the letter "PT" sent to the machine, will return a machines contain IMEI number and the password, the user query with the IMEI number and password to <http://www.dx009.net> platform background information (supports multiple map query, can inquire the machine location, history, electronic enclosures, run statistics, change passwords, etc.)



Tip: most countries abroad positioning can be directly hair "DWEN", a handful of countries need to set the APN before positioning, format for editing text "APN, name of APN, user name, password #" sent to the product (equipment which is inserted in a carrier of phone card, set corresponds to the one operator APN). For example: click Vodafone Egypt; User to edit text

"Internet# APN, internet.vodafone.net, the Internet," to this product. After receiving the SMS reply "Set Ok" again send DW or DJ or PT can query the corresponding information

Text (4) continuous data uploaded to the authorized person "LXDWX" sent to the product. (X represents the orientation of time interval, so LXDWX 15 positioning means every 15 minutes to upload a, login user can query platform. Positioning interval 1 "X" 60. Close continuous data upload instructions: GBDW)

Battery Status

Remarks: With default setting of this product, the last SMS instruction will automatically cancel the previous SMS instruction. For ending the operation of all of the above functions, please edit the SMS "444" and send to the product.

1. Inspection of automatic gateway identification, Inspection of automatic time update (For automatic time update, the instruction "szsj" or "SZSJ" shall be sent. When the feature is set successfully, there will be a hint "Time already calibrated.")

IV. Notice

When the battery runs out, the product needs to be connected to the charger for 3 minutes to start charging.

Fully charge the new machine before using it, in order to achieve the best results. Please use the original charging cable come with the machine.

Standard configuration of the charger: $\pm 5.0V$ 300-500MA, to avoid damage the host machine

If the light is off and the battery runs out, please charge first.

If the call does not get through, insert the card again and turn on the machine, or charge first, then make the test.

If no automatic answering, insert the card again and turn on the machine.

If external controller is needed, it should be customized by yourself.

Do not disassemble the machine. Man-made damages do not belong to the warranty scope.

Using of this product for illegal purposes is strictly prohibited; otherwise, legal actions will be sought.