

产品使用说明书

Product Instruction

产品型号：YX-007-sp

Product Model: YX-007-sp

天津市英讯科技有限公司

目录

一、认识设备 Introduction of Equipment.....	3
1. 设备部件清单 List of Product.....	3
2. 设备部件介绍. Introduction of Equipment Units.....	5
二、使用说明 Instructions.....	6
1. 设备部件连接 Equipment connection and boot-up.....	6
2. 设备现场布置安装范例 Installation Example of Equipment Field Layout.....	7
3. 使用方法 Usage method.....	7
4. 应用场合 Applications.....	9
5. 测试及注意事项 Testing and precautions.....	9
三、技术参数 Technical Parameters.....	10
四、安全注意事项 Safety Cautions.....	11
五、温馨提示 Warm Warning.....	12
六、演示视频地址 Website of Demo Video.....	12
尊敬的用户.....	13
保修说明.....	13

一、认识设备 Introduction of Equipment

1. 设备部件清单 List of Product



YX-007-sp 主机 1 台



遥控器 1 个



12V 5A 电源适配器 1 个



电源转接线

2.设备部件介绍.Introduction of Equipment Units

FY-007-sp 主机

FY-007-sphost

FY-007-sp 音箱喇叭

FY-007-sp Speaker

loudspeaker

FY-007-sp 前端的信号发射端子

FY-007-sp front-end signal transmitting terminal



二、使用说明 Instructions

1. 设备部件连接 Equipment connection and boot-up

主机、电源转接线、电源适配器与电源插座连接图，接线方法如下图

Connection diagram between adapter and host, adapter and power supply. Connection method is as follows



2. 设备现场布置安装范例 Installation Example of Equipment Field Layout

注：更多现场布置方法请咨询经销商

3. 使用方法 Usage method

(1) 主机与电源链接后，主机喇叭自动发出提示音，设备进入待机状态，打开手机蓝牙链接 XY-P15W 的蓝牙设备，主机可以播放手机里面的音乐掩盖屏蔽器发出的声音。

After the host is connected with the power supply, the speaker of the host automatically sends out a prompt tone, and the device enters the standby state. Turn on the Bluetooth device with XY-P15W Bluetooth connection of the mobile phone, and the host can play the sound produced by the music masking screen in the mobile phone.

(2) 按遥控器开机键设备开始工作（参考图 1）

Press the remote control boot button to start the device (refer to Fig.1)

(3) 调节功率

Power adjusting knob

调节功率旋钮已达到最佳的屏蔽效果（旋钮顺时针旋转功率变大，逆时针旋转功率变小）

The power adjusting knob has achieved the best shielding effect (the knob rotates clockwise with greater power and counterclockwise with less power).

(4) 关闭设备,先关遥控器，再给主机断电

Turn off the device, turn off the remote control first, and then power off the host



特别注意：

开机后根据使用场景调整主机的位置和角度，主机作用区域不要有障碍物阻挡，主机的摆放原则参考下面视频

After power on, adjust the position and angle of the host according to the use scenario. The host area should not be blocked by obstacles. Please refer to the following video for the host placement principle

<https://detail.1688.com/offer/588586106810.html?spm=a2615.7691456.autotrace-offerGeneral.10.58182901mdkQbR>

主机放置完毕，用录音设备测试，并调节功率旋钮，以达到最佳屏蔽效果为宜。

When the expander is placed, it is appropriate to test with recording equipment and adjust the power knob to achieve the best shielding effect.

4. 应用场合 Applications

本款 YX-007-sp 录音屏蔽器是由天津市英讯科技有限公司自主研发的，高度集成化的高科技安全防护产品。当不法分子采用录音设备（如手机、录音笔、录音机等）对您进行录音时，录音屏蔽器会产生随机性的噪音信号，该信号能够对语音信号产生压制性干扰，使录音设备拾取的只有噪声信息，而无法分辨出语音信息，从而确保语音信息的安全。广泛应用于：领导办公室、保密会议室、军事作战室、商务谈判室等一切防止录音的场所。

This YX-007-sp recording shield independently researched and developed by Tianjin Yingxun Technology Ltd, is a high-tech safety protective apparatus with high level of integration. In case of being illegally recorded via recording devices (such as mobile phones, recording pens and recorders and so on), the recording shield will generate random noise signals which can oppressively interfere with speech signals so that only noise information is picked up by recording devices and the speech information cannot be distinguished to make sure of safety of speech information. Generally applied: head office, confidential meeting room, military operation room, business negotiation room and any other places which need to be protected from being recorded.

5. 测试及注意事项 Testing and precautions

此产品采用射频信号屏蔽录音设备，因此开启后有稍许声响属于正常，根据年龄对声响的反应有差异，此声响对人体没有任何影响。

This product uses radio frequency signal shielding recording equipment, so a little sound after opening is normal, according to the age of the response to sound is different, this sound has no impact on the human body.

测试时要模拟真实的使用环境，用正常的音量沟通即可，不必故意提高音量，此产品兼顾本身噪声和实际的屏蔽距离采用最佳软件版本，如有特殊需求可以向我们所要特殊版本的软件！

When testing, it is necessary to simulate the real environment and communicate with normal volume without intentionally increasing the volume. This product takes into account its own noise and actual shielding distance and adopts the best software version. If there are special requirements, it can give us the special version of the software we need!

注意：桌面型录音屏蔽器的发射端子正对录音设备的时候屏蔽效果最好。

Notes: there will be best effect of shielding when emission terminals of desktop recording shield are directly facing recording devices.

三、技术参数 Technical Parameters

项目	性能参数
屏蔽类型	手机、数码录音笔、录音机一切声音采集的设备
屏蔽距离	3-6m
屏蔽角度	90-120 度
调节方式	旋钮无极调节（非档位调节）
开启方式	遥控开启
产品尺寸	300*210*170mm
重量	2.95kg
环境温度	-40℃~55℃
相对湿度	35~85%
电源功耗	60w
电源输入	AC 100V~240V
电源输出	DC 12V/5A
包装说明	pp 保护箱
外壳材质	注塑
Shielding type	Mobile phones, digital recording pens, recorders and any other device for sound acquisition
Shielding distance	3-6m
Shielding angle	90-120 degrees
Adjustment mode	Knob stepless adjustment (non gear adjustment)
Opening mode	Remote-controlled opening
Size of product	220*195*80mm
weight	2.95kg
ambient temperature	-40℃~55℃
relative humidity	35~85%
Power consumption	60w
Power output	AC 100V~240V
Material of shell	DC 12V/5A
Packing instructions	PP protection box
Shell material	Injection molding

四、安全注意事项 Safety Cautions

使用前请仔细阅读以下安全注意事项：

Carefully read the following safety cautions before use:

发生以下情况请立即关闭设备，从电源插座中拔出电源适配器。

In case of the following circumstances, turn off equipment immediately and plug power adapter out of the outlet.

1.停电或者电压不稳定

Power failure or voltage instability

2.设备内部发出异常声音或者气味

Abnormal noise or smell from the inside of equipment

3.电源适配器损坏

Damages to power adapter

4.设备由于跌落、敲击、撞击而损坏

Damages to equipment due to falling off, being knocked on and being impacted

5.任何液体或其它异物调入机壳内

Falling of any other fluid or foreign bodies into the shell

五、温馨提示 Warm Warning

切勿使用交流 220V、50Hz 以外的电源。

1. Don't use any other power supply other than 220V AC, 50 Hz.

切勿改装或者损坏设备及电源适配器。

2. Don't refit or damage equipment and power adapter.

切勿用其它电源适配器对设备进行充电。

3. Don't employ other power adapter to charge the equipment.

切勿以任何方式自行拆装设备，所有修理都应委托专业的技术人员。

Don't assemble and disassemble equipment in any way by yourself, and all of repair should be consigned to professional technicians.

六、演示视频地址 Website of Demo Video

<https://detail.1688.com/offer/588586106810.html?spm=a2615.7691456.autotrace-offerGeneral.10.58182901mdkQbR>

保修卡

尊敬的用户

您好！感谢您购买天津市英讯科技有限公司的产品，为了更好的为您服务，在购买产品后，请认证阅读，填写并妥善保管好此保修卡。

用户名		联系人	
购买日期		联系电话	
产品名称		产品型号	
用户地址			
订单编号			
维修记录	日期	故障原因及处理情况	

保修说明

产品若出现质量问题需要维修时，请把此保修卡与所购产品一起妥善寄回我公司提供售后维修处

注意事项

- 1、自您选购本产品签收首日起，凡按照使用说明书安装使用，一年内出现非人为质量问题，我们提供免费维修，一年后维修只收取维修工本费。
- 2、非本公司产品质量原因引起的质量问题，如使用不当，保管不妥，擅自拆机等原因造成的损坏，本公司维修只收取维修工本费
- 3、本产品实行一年保修，内置电池一年保修。

服务联系信息：

天津市英讯科技有限公司

地址：天津市南开区宾水西道 333 号万豪大厦 C-1510

电话：022-23728011

<http://www.heroley.com>