80dB (typ)



LM48860 Boomer[®] Audio Power Amplifier Series Ground-Referenced, Ultra Low Noise, Fixed Gain Stereo **Headphone Amplifier**

General Description

The LM48860 is a ground referenced, fixed-gain audio power amplifier capable of delivering 40mW per channel of continuous average power into a 16Ω single-ended load with less than 1% THD+N from a 3V power supply.

The LM48860 features a new circuit technology that utilizes a charge pump to generate a negative reference voltage. This allows the outputs to be biased about ground, thereby eliminating output-coupling capacitors typically used with normal single-ended loads.

Boomer audio power amplifiers were designed specifically to provide high quality output power with a minimal amount of external components. The LM48860 does not require output coupling capacitors or bootstrap capacitors, and therefore is ideally suited for mobile phone and other low voltage applications where minimal power consumption is a primary requirement.

The LM48860 features a low-power consumption shutdown mode selectable for either channel separately. This is accomplished by driving either the SD_RC (Shutdown Right Channel) or SD_LC (Shutdown Left Channel) (or both) pins with logic low, depending on which channel is desired shutdown. Additionally, the LM48860 features an internal thermal shutdown protection mechanism.

The LM48860 contains advanced pop & click circuitry that eliminates noises which would otherwise occur during turn-on and turn-off transitions.

The LM48860 has an internal fixed gain of 1.5V/V.

Key Specifications

- PSRR at 217Hz (V_{DD} = 3.0V)
- Stereo Power Output at V_{DD} = 3V. $R_1 = 16\Omega$, THD+N = 1% 40mW (typ) 0.1µA (typ)
- Shutdown Current
- 1.5V/V (typ) Internal Fixed Gain
- 2.0V to 5.5V Operating Voltage

Features

- Fixed logic levels with supply voltage
- Ground referenced outputs
- -**High PSRR**
- Available in space-saving micro SMD package
- Ultra low current shutdown mode
- -Improved pop & click circuitry eliminates noises during turn-on and turn-off transitions
- No output coupling capacitors, snubber networks, -
- bootstrap capacitors, or gain-setting resistors required Shutdown either channel independently

Applications

- Mobile Phones
- **MP3** Players
- PDAs
- Portable electronic devices
- Notebook PCs

Boomer® is a registered trademark of National Semiconductor Corporation.



V_{DD}

20 kΩ

M R_i

 V_{DD}

Shutdown

Control

RIN

CCP+

 $c_5 = \frac{1+}{1}$

Ē

C₆

~~~

30 kΩ

Click/Pop

Suppression

0.1 µF ceramic

Headphone Jack

30006889

ROUT

4.7 μF

Typical Application

1 μ**F** 

٩ľ+

С<sub>1</sub>

SD\_LC

SD\_RC

LM48860

## **Connection Diagram**



#### Top View Order Number LM48860TL See NS Package Number TLA12XXX

### **Pin Descriptions**

| Pin | Name                | Function                                         |  |
|-----|---------------------|--------------------------------------------------|--|
| A1  | RIN                 | Right Channel Input                              |  |
| A2  | SGND                | Signal Ground                                    |  |
| A3  | LIN                 | Left Channel Input                               |  |
| B1  | ROUT                | Right Channel Output                             |  |
| B2  | SD_LC               | Active Low Shutdown, Left Channel                |  |
| B3  | LOUT                | Left Channel Output                              |  |
| C1  | V <sub>SS(CP)</sub> | Charge Pump Voltage Output                       |  |
| C2  | SD_RC               | Active-Low Shutdown, Right Channel               |  |
| C3  | V <sub>DD</sub>     | Supply Voltage                                   |  |
| D1  | CCP-                | Negative Terminal - Charge Pump Flying Capacitor |  |
| D2  | PGND                | Power Ground                                     |  |
| D3  | CCP+                | Positive Terminal - Charge Pump Flying Capacitor |  |

### Absolute Maximum Ratings (Notes 2, 2)

If Military/Aerospace specified devices are required, please contact the National Semiconductor Sales Office/ Distributors for availability and specifications.

| Supply Voltage             | 6.0V                     |
|----------------------------|--------------------------|
| Storage Temperature        | –65°C to +150°C          |
| Input Voltage              | -0.3V to V <sub>DD</sub> |
| Power Dissipation (Note 3) | Internally Limited       |
| ESD Rating(Note 4)         | 2000V                    |
| ESD Rating (Note 5)        | 200V                     |
|                            |                          |

| Junction Temperature                   | 150°C    |
|----------------------------------------|----------|
| Thermal Resistance                     |          |
| $\theta_{JA}$ (typ) TLA12XXX (Note 11) | 59.3°C/W |
|                                        |          |

### **Operating Ratings**

| Temperature Range               |  |
|---------------------------------|--|
| $T_{MIN} \leq T_A \leq T_{MAX}$ |  |

| $T_{MIN} \le T_A \le T_{MAX}$     | $-40^{\circ}C \le T_A \le 85^{\circ}C$ |
|-----------------------------------|----------------------------------------|
| Supply Voltage (V <sub>DD</sub> ) | $2.0V \le V_{DD} \le 5.5V$             |

# Electrical Characteristics V<sub>DD</sub> = 3V (Notes 1, 2)

| The following specifications apply for $V_{DD} = 3$ | V and 16 $\Omega$ load unless otherwise | e specified. Limits apply to $T_A = 25^{\circ}$ | С |
|-----------------------------------------------------|-----------------------------------------|-------------------------------------------------|---|
|-----------------------------------------------------|-----------------------------------------|-------------------------------------------------|---|

|                   |                                      |                                                                                      | LM48860             |                   | Unito                              |  |
|-------------------|--------------------------------------|--------------------------------------------------------------------------------------|---------------------|-------------------|------------------------------------|--|
| Symbol            | Parameter                            | Conditions                                                                           | Typical<br>(Note 6) | Limit<br>(Note 7) | (Limits)                           |  |
|                   | Quiescent Power Supply Current       | $V_{DD} = 3.0V,$<br>$V_{IN} = 0V,$ inputs terminated<br>both channels enabled        | 4                   | 5.5               | mA (max)                           |  |
| 'DD               | Full Power Mode                      | $V_{DD} = 5.0V,$<br>$V_{IN} = 0V,$ inputs terminated<br>both channels enabled        | 4.2                 |                   | mA                                 |  |
|                   |                                      | SD_LC = SD_RC= GND                                                                   | 0.1                 | 1                 | μA (max)                           |  |
| I <sub>SD</sub>   | Shutdown Current                     | SD_LC = SD_RC= GND,<br>V <sub>DD</sub> = 5.0V                                        | 0.1                 | 1                 | μA (max)                           |  |
| V <sub>os</sub>   | Output Offset Voltage                | $R_L = 32\Omega, V_{IN} = 0V$                                                        | 0.7                 | 5.5               | mV (max)                           |  |
| A <sub>V</sub>    | Voltage Gain                         |                                                                                      | -1.5                |                   | V/V                                |  |
| ΔA <sub>V</sub>   | Channel-to-channel Gain<br>Matching  |                                                                                      | 1                   |                   | %                                  |  |
| R <sub>IN</sub>   | Input Resistance                     |                                                                                      | 20                  | 15<br>25          | $k\Omega$ (min)<br>$k\Omega$ (max) |  |
|                   | Output Power                         | THD+N = 1% (max); f = 1kHz,<br>$R_L = 16\Omega$ , (two channels in phase)            | 40                  | 35                | mW (min)                           |  |
| Po                |                                      | THD+N = 1% (max); f = 1kHz,<br>$R_L = 32\Omega$ , (two channels in phase)            | 50                  | 40                | mW (min)                           |  |
|                   | Total Harmonic Distortion +<br>Noise | $P_O = 20$ mW, f = 1kHz, R <sub>L</sub> = 16 $\Omega$<br>(two channels in phase)     | 0.025               |                   | %                                  |  |
|                   |                                      | $P_O = 25$ mW, f = 1kHz, R <sub>L</sub> = 32 $\Omega$<br>(two channels in phase)     | 0.014               |                   | %                                  |  |
|                   |                                      | $V_{RIPPLE} = 200 mV_{PP}$ , Input Referred                                          |                     |                   |                                    |  |
| PSBB              | Power Supply Rejection Ratio         | f = 217Hz                                                                            | 80                  | 73                | dB (min)                           |  |
|                   | Full Power Mode                      | f = 1kHz                                                                             | 75                  |                   | dB                                 |  |
|                   |                                      | f = 20kHz                                                                            | 60                  |                   | dB                                 |  |
| SNR               | Signal-to-Noise Ratio                | $R_L = 32\Omega$ , $P_{OUT} = 50$ mW,<br>f = 1kHz, BW = 20Hz to 22kHz,<br>A-weighted | 105                 |                   | dB                                 |  |
| VIH               | Shutdown Input Voltage High          | V <sub>DD</sub> = 2.0V to 5.5V                                                       |                     | 1.2               | V (min)                            |  |
| V <sub>IL</sub>   | Shutdown Input Voltage Low           | V <sub>DD</sub> = 2.0V to 5.5V                                                       |                     | 0.45              | V (max)                            |  |
| X <sub>TALK</sub> | Crosstalk                            | $R_L = 16\Omega, P_O = 1.6mW,$<br>f = 1kHz                                           | 75                  |                   | dB                                 |  |
| ∈ <sub>OS</sub>   | Output Noise                         | A-weighted filter, V <sub>IN</sub> = 0V                                              | 8                   |                   | μV                                 |  |
|                   |                                      |                                                                                      |                     |                   |                                    |  |

|                  | Parameter        |                                                                                          | LM48860             |                   | Unite          |
|------------------|------------------|------------------------------------------------------------------------------------------|---------------------|-------------------|----------------|
| Symbol           |                  | Conditions                                                                               | Typical<br>(Note 6) | Limit<br>(Note 7) | (Limits)       |
| Z <sub>OUT</sub> | Output Impedance | V <sub>SD</sub> = GND<br>Input Terminated<br>Input not terminated<br>SD_LC = SD_RC = GND | 30<br>30            | 20                | kΩ (min)<br>kΩ |
| I <sub>L</sub>   | Input Leakage    |                                                                                          | ±0.1                |                   | nA             |

Note 1: "Absolute Maximum Ratings" indicate limits beyond which damage to the device may occur, including inoperability and degradation of device reliability and/or performance. Functional operation of the device and/or non-degradation at the Absolute Maximum Ratings or other conditions beyond those indicated in the Recommended Operating Conditions is not implied. The Recommended Operating Conditions indicate conditions at which the device is functional and the device should not be operated beyond such conditions. All voltages are measured with respect to the ground pin, unless otherwise specified

Note 2: The Electrical Characteristics tables list guaranteed specifications under the listed Recommended Operating Conditions except as otherwise modified or specified by the Electrical Characteristics Conditions and/or Notes. Typical specifications are estimations only and are not guaranteed.

**Note 3:** The maximum power dissipation must be derated at elevated temperatures and is dictated by  $T_{JMAX}$ ,  $\theta_{JA}$ , and the ambient temperature,  $T_A$ . The maximum allowable power dissipation is  $P_{DMAX} = (T_{JMAX} - T_A) / \theta_{JA}$  or the number given in *Absolute Maximum Ratings*, whichever is lower. For the LM48860, see power derating curves for additional information.

Note 4: Human body model, applicable std. JESD22-A114C.

Note 5: Machine model, applicable std. JESD22-A115-A.

Note 6: Typical values represent most likely parametric norms at  $T_{A} = +25^{\circ}$ C, and at the Recommended Operation Conditions at the time of product characterization and are not guaranteed.

Note 7: Datasheet min/max specification limits are guaranteed by test or statistical analysis.

Note 8: 0, a value is measured with the device mounted on a PCB with a 1.5" x 1.375", 1oz copper heatsink.

### **External Components Description**

| (Figure 1)                                                                                                                                                                                                                                                                                         |                |                                                                                                                                                                                                                                                                                                            |  |  |
|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|----------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|--|--|
| Comp                                                                                                                                                                                                                                                                                               | onents         | Functional Description                                                                                                                                                                                                                                                                                     |  |  |
| 1. $C_1$ Input coupling capacitor which blocks the DC voltage at the amplifier's input terminals. Also creates a hi pass filter with $R_i$ at $f_c = 1/(2R_iC_1)$ . Refer to the section <b>Proper Selection of External Components</b> , for explanation of how to determine the value of $C_1$ . |                | Input coupling capacitor which blocks the DC voltage at the amplifier's input terminals. Also creates a high pass-<br>pass filter with $R_i$ at $f_c = 1/(2R_iC_1)$ . Refer to the section <b>Proper Selection of External Components</b> , for an<br>explanation of how to determine the value of $C_1$ . |  |  |
| 2.                                                                                                                                                                                                                                                                                                 | C <sub>2</sub> | Input coupling capacitor which blocks the DC voltage at the amplifier's input terminals. Also creates a high pass-<br>pass filter with $R_i$ at $f_c = 1/(2R_iC_2)$ . Refer to the <b>Power Supply Bypassing</b> section for an explanation of how to<br>determine the value of $C_2$ .                    |  |  |
| 3.                                                                                                                                                                                                                                                                                                 | C <sub>3</sub> | Output capacitor. Low ESR ceramic capacitor ( $\leq 100 \text{m}\Omega$ )                                                                                                                                                                                                                                  |  |  |
| 4.                                                                                                                                                                                                                                                                                                 | C <sub>4</sub> | Flying capacitor. Low ESR ceramic capacitor (≤100mΩ)                                                                                                                                                                                                                                                       |  |  |
| 5.                                                                                                                                                                                                                                                                                                 | C <sub>5</sub> | Tantalum capacitor. Supply bypass capacitor which provides power supply filtering. Refer to the Power Supply Bypassing section for information concerning proper placement and selection of the supply bypass capacitor.                                                                                   |  |  |
| 6.                                                                                                                                                                                                                                                                                                 | C <sub>6</sub> | Ceramic capacitor. Supply bypass capacitor which provides power supply filtering. Refer to the Power Supply Bypassing section for information concerning proper placement and selection of the supply bypass capacitor.                                                                                    |  |  |







30006824

THD+N vs Output Power  $V_{DD} = 3V$ ,  $R_{L} = 32\Omega$ , f = 1kHz22kHz BW, two channels in phase



THD+N vs Output Power  $V_{DD}$  = 3.6V, R<sub>L</sub> = 16 $\Omega$ , f = 1kHz 22kHz BW, two channels in phase



























### **Application Information**

#### SUPPLY VOLTAGE SEQUENCING

It is a good general practice to first apply the supply voltage to a CMOS device before any other signal or supply on other pins. This is also true for the LM48860 audio amplifier which is a CMOS device.

Before applying any signal to the inputs or shutdown pins of the LM48860, it is important to apply a supply voltage to the  $V_{DD}$  pins. After the device has been powered, signals may be applied to the shutdown pins (see MICRO POWER SHUTDOWN) and input pins.

#### ELIMINATING THE OUTPUT COUPLING CAPACITOR

The LM48860 features a low noise inverting charge pump that generates an internal negative supply voltage. This allows the outputs of the LM48860 to be biased about GND instead of a nominal DC voltage, like traditional headphone amplifiers. Because there is no DC component, the large DC blocking capacitors (typically  $220\mu$ F) are not necessary. The coupling capacitors are replaced by two, small ceramic charge pump capacitors, saving board space and cost.

Eliminating the output coupling capacitors also improves low frequency response. In traditional headphone amplifiers, the headphone impedance and the output capacitor form a high pass filter that not only blocks the DC component of the output, but also attenuates low frequencies, impacting the bass response. Because the LM48860 does not require the output coupling capacitors, the low frequency response of the device is not degraded by external components.

In addition to eliminating the output coupling capacitors, the ground referenced output nearly doubles the available dynamic range of the LM48860 when compared to a traditional headphone amplifier operating from the same supply voltage.

#### OUTPUT TRANSIENT ('CLICK AND POPS') ELIMINATED

The LM48860 contains advanced circuitry that virtually eliminates output transients ('clicks and pops'). This circuitry prevents all traces of transients when the supply voltage is first applied or when the part resumes operation after coming out of shutdown mode.

#### AMPLIFIER CONFIGURATION EXPLANATION

As shown in Figure 2, the LM48860 has two internal operational amplifiers. The two amplifiers have internally configured gain.

Since this is an output ground-referenced amplifier, the LM48860 does not require output coupling capacitors.

#### POWER DISSIPATION

From the graph (THD+N vs Output Power , V<sub>DD</sub> = 3V, R<sub>L</sub> = 16 $\Omega$ , f = 1kHz, 22kH BW, two channels in phase, page 6) assuming a 3V power supply and a 16 $\Omega$  load, the maximum power dissipation point and thus the maximum package dissipation point is 281mW. The maximum power dissipation point obtained must not be greater than the power dissipation that results from Equation 1.

$$\mathsf{P}_{\mathsf{DMAX}} = (\mathsf{T}_{\mathsf{JMAX}} - \mathsf{T}_{\mathsf{A}}) / (\theta_{\mathsf{JA}}) \tag{1}$$

For the micro SMD package  $\theta_{JA} = 59.3^{\circ}$ C/W.  $T_{JMAX} = 150^{\circ}$ C for the LM48860. Depending on the ambient temperature,  $T_A$ , of the system surroundings, Equation 1 can be used to find the maximum internal power dissipation supported by the IC packaging. If the maximum power dissipation from the

graph is greater than that of Equation 1, then either the supply voltage must be decreased, the load impedance increased or  $T_A$  reduced (see power derating curves). For the application of a 5V power supply, with a 16 $\Omega$  load, the maximum ambient temperature possible without violating the maximum junction temperature is approximately 110°C provided that device operation is around the maximum power dissipation point. Power dissipation is a function of output power and thus, if typical operation is not around the maximum power dissipation point, the ambient temperature may be increased accordingly.

#### POWER SUPPLY BYPASSING

As with any power amplifier, proper supply bypassing is critical for low noise performance and high power supply rejection. Applications that employ a 3V power supply typically use a  $4.7\mu$ F capacitor in parallel with a  $0.1\mu$ F ceramic filter capacitor to stabilize the power supply's output, reduce noise on the supply line, and improve the supply's transient response. Keep the length of leads and traces that connect capacitors between the LM48860's power supply pin and ground as short as possible.

#### MICRO POWER SHUTDOWN

The voltage applied to the  $\overline{\text{SD}_LC}$  (shutdown left channel) pin and the  $\overline{\text{SD}_RC}$  (shutdown right channel) pin controls the LM48860's shutdown function. When active, the LM48860's micropower shutdown feature turns off the amplifiers' bias circuitry, reducing the supply current. The trigger point is 0.45V for a logic-low level, and 1.2V for logic-high level. The low 0.01µA (typ) shutdown current is achieved by applying a voltage that is as near as ground a possible to the  $\overline{\text{SD}_LC}/$  $\overline{\text{SD}_RC}$  pins. A voltage that is higher than ground may increase the shutdown current. Do not let  $\overline{\text{SD}_LC}/\overline{\text{SD}_RC}$  float, connect either to high or low.

#### SELECTING PROPER EXTERNAL COMPONENTS

Optimizing the LM48860's performance requires properly selecting external components. Though the LM48860 operates well when using external components with wide tolerances, best performance is achieved by optimizing component values.

#### **Charge Pump Capacitor Selection**

Use low ESR (equivalent series resistance) (<100m $\Omega$ ) ceramic capacitors with an X7R dielectric for best performance. Low ESR capacitors keep the charge pump output impedance to a minimum, extending the headroom on the negative supply. Higher ESR capacitors result in reduced output power from the audio amplifiers.

Charge pump load regulation and output impedance are affected by the value of the flying capacitor (C4). A larger valued C4 (up to 3.3uF) improves load regulation and minimizes charge pump output resistance. Beyond 3.3uF, the switch-on resistance dominates the output impedance.

The output ripple is affected by the value and ESR of the output capacitor (C3). Larger capacitors reduce output ripple on the negative power supply. Lower ESR capacitors minimize the output ripple and reduce the output impedance of the charge pump.

The LM48860 charge pump design is optimized for 2.2uF, low ESR, ceramic, flying and output capacitors.

#### Input Capacitor Value Selection

Amplifying the lowest audio frequencies requires high value input coupling capacitors (C1 and C2 in Figure 1). A high value capacitor can be expensive and may compromise space efficiency in portable designs. In many cases, however, the speakers used in portable systems, whether internal or external, have little ability to reproduce signals below 150Hz. Applications using speakers with this limited frequency response reap little improvement by using high value input and output capacitors.

As shown in Figure 1, the internal input resistor,  $R_i$  and the input capacitors, C1 and C2, produce a -3dB high-pass filter cutoff frequency that is found using Equation (2).

$$f_{i-3dB} = 1 / 2\pi R_{IN}C$$
 (Hz)

The value of  ${\rm R}_{\rm IN}$  can be found in the **Electrical Characteristics** tables.

(2)





**Top Silkscreen** 



Top Layer



Midlayer 1



Midlayer 2

LM48860

300068a5





**Bottom Layer** 

**Bottom Silkscreen** 

## **Revision History**

| Rev  | Date     | Description                         |  |
|------|----------|-------------------------------------|--|
| 1.0  | 01/16/08 | Initial release.                    |  |
| 1.01 | 01/29/08 | Text edits.                         |  |
| 1.02 | 02/14/08 | Fixed typos (x-axis) on few curves. |  |

Physical Dimensions inches (millimeters) unless otherwise noted SYMM  $-12X \ \phi_{0.250}^{0.275}$  $( \div )$  $( \cdot )$ (+)SYMM ହ (0.5) DIMENSIONS ARE IN MILLIMETERS DIMENSIONS IN ( ) FOR REFERENCE ONLY (+) -(0.5)LAND PATTERN RECOMMENDATION Х3 B X 2 SYMM C -TOP SIDE COATING-0.125 -BUMP + + SYMM <u>\*</u>\_\_ Ę 0.5 + Ā Р 0.265 -BUMP A1 CORNER Á SILICON-0.5  $\frac{12 \times \phi_{0.335}^{0.335}}{\Phi_{0.005}^{0.005} \text{ (AS BS)}}$ TLA12XXX (Rev C) 12 - Bump micro SMD Order Number LM48860TL NS Package Number TLA12XXX X1 = 2.0±0.03mm, X2 = 1.5±0.03mm, X3 = 0.600±0.075mm,

# Notes

| -or more National Semiconductor product information and proven design tools, visit the following Web sites at: |                              |                         |                                |  |  |  |
|----------------------------------------------------------------------------------------------------------------|------------------------------|-------------------------|--------------------------------|--|--|--|
| Pro                                                                                                            | oducts                       | Design Support          |                                |  |  |  |
| Amplifiers                                                                                                     | www.national.com/amplifiers  | WEBENCH                 | www.national.com/webench       |  |  |  |
| Audio                                                                                                          | www.national.com/audio       | Analog University       | www.national.com/AU            |  |  |  |
| Clock Conditioners                                                                                             | www.national.com/timing      | App Notes               | www.national.com/appnotes      |  |  |  |
| Data Converters                                                                                                | www.national.com/adc         | Distributors            | www.national.com/contacts      |  |  |  |
| Displays                                                                                                       | www.national.com/displays    | Green Compliance        | www.national.com/quality/green |  |  |  |
| Ethernet                                                                                                       | www.national.com/ethernet    | Packaging               | www.national.com/packaging     |  |  |  |
| Interface                                                                                                      | www.national.com/interface   | Quality and Reliability | www.national.com/quality       |  |  |  |
| LVDS                                                                                                           | www.national.com/lvds        | Reference Designs       | www.national.com/refdesigns    |  |  |  |
| Power Management                                                                                               | www.national.com/power       | Feedback                | www.national.com/feedback      |  |  |  |
| Switching Regulators                                                                                           | www.national.com/switchers   |                         |                                |  |  |  |
| LDOs                                                                                                           | www.national.com/ldo         |                         |                                |  |  |  |
| LED Lighting                                                                                                   | www.national.com/led         |                         |                                |  |  |  |
| PowerWise                                                                                                      | www.national.com/powerwise   |                         |                                |  |  |  |
| Serial Digital Interface (SDI)                                                                                 | www.national.com/sdi         |                         |                                |  |  |  |
| Temperature Sensors                                                                                            | www.national.com/tempsensors |                         |                                |  |  |  |
| Wireless (PLL/VCO)                                                                                             | www.national.com/wireless    |                         |                                |  |  |  |

THE CONTENTS OF THIS DOCUMENT ARE PROVIDED IN CONNECTION WITH NATIONAL SEMICONDUCTOR CORPORATION ("NATIONAL") PRODUCTS. NATIONAL MAKES NO REPRESENTATIONS OR WARRANTIES WITH RESPECT TO THE ACCURACY OR COMPLETENESS OF THE CONTENTS OF THIS PUBLICATION AND RESERVES THE RIGHT TO MAKE CHANGES TO SPECIFICATIONS AND PRODUCT DESCRIPTIONS AT ANY TIME WITHOUT NOTICE. NO LICENSE, WHETHER EXPRESS, IMPLIED, ARISING BY ESTOPPEL OR OTHERWISE, TO ANY INTELLECTUAL PROPERTY RIGHTS IS GRANTED BY THIS DOCUMENT.

TESTING AND OTHER QUALITY CONTROLS ARE USED TO THE EXTENT NATIONAL DEEMS NECESSARY TO SUPPORT NATIONAL'S PRODUCT WARRANTY. EXCEPT WHERE MANDATED BY GOVERNMENT REQUIREMENTS, TESTING OF ALL PARAMETERS OF EACH PRODUCT IS NOT NECESSARILY PERFORMED. NATIONAL ASSUMES NO LIABILITY FOR APPLICATIONS ASSISTANCE OR BUYER PRODUCT DESIGN. BUYERS ARE RESPONSIBLE FOR THEIR PRODUCTS AND APPLICATIONS USING NATIONAL COMPONENTS. PRIOR TO USING OR DISTRIBUTING ANY PRODUCTS THAT INCLUDE NATIONAL COMPONENTS, BUYERS SHOULD PROVIDE ADEQUATE DESIGN, TESTING AND OPERATING SAFEGUARDS.

EXCEPT AS PROVIDED IN NATIONAL'S TERMS AND CONDITIONS OF SALE FOR SUCH PRODUCTS, NATIONAL ASSUMES NO LIABILITY WHATSOEVER, AND NATIONAL DISCLAIMS ANY EXPRESS OR IMPLIED WARRANTY RELATING TO THE SALE AND/OR USE OF NATIONAL PRODUCTS INCLUDING LIABILITY OR WARRANTIES RELATING TO FITNESS FOR A PARTICULAR PURPOSE, MERCHANTABILITY, OR INFRINGEMENT OF ANY PATENT, COPYRIGHT OR OTHER INTELLECTUAL PROPERTY RIGHT.

#### LIFE SUPPORT POLICY

NATIONAL'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS PRIOR WRITTEN APPROVAL OF THE CHIEF EXECUTIVE OFFICER AND GENERAL COUNSEL OF NATIONAL SEMICONDUCTOR CORPORATION. As used herein:

Life support devices or systems are devices which (a) are intended for surgical implant into the body, or (b) support or sustain life and whose failure to perform when properly used in accordance with instructions for use provided in the labeling can be reasonably expected to result in a significant injury to the user. A critical component is any component in a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system or to affect its safety or effectiveness.

National Semiconductor and the National Semiconductor logo are registered trademarks of National Semiconductor Corporation. All other brand or product names may be trademarks or registered trademarks of their respective holders.

Copyright© 2008 National Semiconductor Corporation

For the most current product information visit us at www.national.com



Americas Technical Support Center Email: new.feedback@nsc.com Tel: 1-800-272-9959

National Semiconductor

National Semiconductor Europe Technical Support Center Email: europe.support@nsc.com German Tel: +49 (0) 180 5010 771 English Tel: +44 (0) 870 850 4288 National Semiconductor Asia Pacific Technical Support Center Email: ap.support@nsc.com National Semiconductor Japan Technical Support Center Email: jpn.feedback@nsc.com