



# INA143 INA2143

For most current data sheet and other product information, visit www.burr-brown.com

# High-Speed, Precision, G = 10 or G = 0.1 DIFFERENCE AMPLIFIERS

### **FEATURES**

- DESIGNED FOR LOW COST
- G = 10V/V or G = 0.1V/V
- SINGLE, DUAL VERSIONS
- LOW OFFSET VOLTAGE: ±250μV max, ±3μV/°C max
- LOW GAIN ERROR: 0.01%
- HIGH SLEW RATE: 5V/µs
- FAST SETTLING TIME: 9µs to 0.01%
- LOW QUIESCENT CURRENT: 950µA
- WIDE SUPPLY RANGE: ±2.25V to ±18V
- SO-8 and SO-14 PACKAGES

## DESCRIPTION

The INA143 and INA2143 are high slew rate, gain of 10V/V or 0.1V/V difference amplifiers consisting of a precision op amp with a precision resistor network. The on-chip resistors are laser trimmed for accurate gain and high common-mode rejection. Excellent TCR tracking of the resistor maintains gain accuracy and common-mode rejection over temperature. They operate over a wide supply range,  $\pm 2.25V$  to  $\pm 18V$  (+4.5V to +36V single supply), and input common-mode voltage range extends beyond the positive and negative supply rails.



### **APPLICATIONS**

- DIFFERENTIAL INPUT AMPLIFIER BUILDING BLOCK
- DIFF IN/DIFF OUT AMPLIFIER
- GAIN = -10 INVERTING AMPLIFIER
- GAIN = +10 NON-INVERTING AMPLIFIER
- GAIN = +11 NON-INVERTING AMPLIFIER
- SYNCHRONOUS DEMODULATOR
- CURRENT/DIFFERENTIAL LINE RECEIVER
- VOLTAGE-CONTROLLED CURRENT SOURCE
- BATTERY POWERED SYSTEMS
- LOW COST AUTOMOTIVE

The differential amplifier is the foundation of many commonly used circuits. The low cost INA143 and INA2143 provide this precision circuit function without using an expensive precision network.

The single version, INA143, package is the SO-8 surface mount. The dual version, INA2143, package is the SO-14 surface mount. Both are specified for operation over the extended industrial temperature range,  $-40^{\circ}$ C to  $+85^{\circ}$ C. Operation is from  $-55^{\circ}$ C to  $+125^{\circ}$ C.



International Airport Industrial Park • Mailing Address: PO Box 11400, Tucson, AZ 85734 • Street Address: 6730 S. Tucson Blvd., Tucson, AZ 85706 • Tel: (520) 746-1111 Twx: 910-952-1111 • Internet: http://www.burr-brown.com/ • Cable: BBRCORP • Telex: 066-6491 • FAX: (520) 889-1510 • Immediate Product Info: (800) 548-6132

# **SPECIFICATIONS:** $V_S = \pm 15V$ At $T_A = +25^{\circ}C$ , $V_S = \pm 15V$ , G = 10, $R_L = 10k\Omega$ connected to ground, and reference pin connected to ground, unless otherwise noted.

		INA143U INA2143U			INA143UA INA2143UA			
PARAMETER	CONDITIONS	MIN	ТҮР	MAX	MIN	ТҮР	MAX	UNITS
OFFSET VOLTAGE <sup>(1)</sup> Initial <sup>(1)</sup> vs Temperature vs Power Supply vs Time Channel Separation (dual)	RTI V <sub>CM</sub> = 0V V <sub>S</sub> = $\pm 2.25$ V to $\pm 18$ V dc		±100 ±1 ±5 0.2 140	±250 ±3 ±20	Se	* e Typical Cu * *	±500 urve ±30	μV μV/°C μV/V μV/√mo dB
INPUT IMPEDANCE <sup>(3)</sup> Differential Common-Mode			20 55			* *		kΩ kΩ
INPUT VOLTAGE RANGE Common-Mode Voltage Range Positive Negative Common-Mode Rejection Ratio	RTI $V_O = 0V \\ V_O = 0V \\ V_CM = -14.85V \text{ to } 14.85V, \text{ R}_S = 0\Omega$	1.1[(V+)-1.5] 1.1[(V-)+1.5] 86	1.1[(V+)-1] 1.1[(V-)+1] 96		* * 80	* * *		V V dB
OUTPUT VOLTAGE NOISE <sup>(3)</sup> f = 0.1Hz to 10Hz f = 10Hz f = 100Hz f = 1kHz	RTI		1 45 30 27			* * *		µVp-p nV/√Hz nV/√Hz nV/√Hz
GAIN Initial Error vs Temperature Nonlinearity	$V_0 = -14V$ to +13.5V $V_0 = -14V$ to +13.5V		10 ±0.01 ±1 ±0.0001	±0.05 ±10 ±0.001		* * * *	±0.1 * ±0.002	V/V % ppm/°C % of FS
OUTPUT Voltage Output Positive Negative Positive Negative Current Limit Capacitive Load (stable operation)	Gain Error < 0.1% $R_L = 10k\Omega$ to Ground $R_L = 10k\Omega$ to Ground $R_L = 100k\Omega$ to Ground $R_L = 100k\Omega$ to Ground Continuous-to-Common	(V+) -1.5 (V-) +1	(V+) -1.3 (V-) +0.8 (V+) -0.8 (V-) +0.3 -25, +32 1000		* *	* * * * *		V V V mA pF
FREQUENCY RESPONSE Small-Signal Bandwidth Slew Rate Settling Time: 0.1% 0.01% Overload Recovery Time	-3dB V <sub>O</sub> = 10V Step, C <sub>L</sub> = 100pF V <sub>O</sub> = 10V Step, C <sub>L</sub> = 100pF 50% Overdrive		0.15 5 6 9 6			* * * * *		MHz V/μs μs μs μs
POWER SUPPLY Rated Voltage Operating Voltage Range Dual Supplies Single Supply Quiescent Current (per amplifier)	l <sub>0</sub> = 0	±2.25 +4.5	±15 ±0.95	±18 +36 ±1.2	* *	*	* * *	V V V mA
TEMPERATURE RANGE   Specification   Operation   Storage   Thermal Resistance $\theta_{JA}$ SO-8 Surface Mount   SO-14 Surface Mount		40 55 55	150 100	+85 +125 +125	* * *	*	* * *	v S M S S S S S S S S S S S S S S S S S

\* Specifications the same as INA143U, INA2143U.

NOTES: (1) Includes the effects of amplifier's input bias and offset currents. (2) Internal resistors are ratio matched but have ±20% absolute value. (3) Includes effects of amplifier's input current noise and thermal noise contribution of resistor network.

The information provided herein is believed to be reliable; however, BURR-BROWN assumes no responsibility for inaccuracies or omissions. BURR-BROWN assumes no responsibility for the use of this information, and all use of such information shall be entirely at the user's own risk. Prices and specifications are subject to change without notice. No patent rights or licenses to any of the circuits described herein are implied or granted to any third party. BURR-BROWN does not authorize or warrant any BURR-BROWN product for use in life support devices and/or systems.



2

### SPECIFICATIONS: $V_s = \pm 5V$

At  $T_A = +25^{\circ}$ C,  $V_S = \pm 5V$ , G = 10,  $R_L = 10 k\Omega$  connected to ground, and reference pin connected to ground, unless otherwise noted.

		INA143U INA2143U			INA143UA INA2143UA			
PARAMETER	CONDITIONS	MIN	TYP	MAX	MIN	TYP	MAX	UNITS
OFFSET VOLTAGE <sup>(1)</sup>	RTI							
Initial <sup>(1)</sup>	$V_{CM} = 0V$		±200	±500		*	±750	μV
vs Temperature			±1			*		μV/°C
INPUT VOLTAGE RANGE	RTI							
Common-Mode Voltage Range								
Positive	$V_{O} = 0V$	1.1[(V+)-1.5]	1.1[(V+)-1]		*	*		V
Negative	$V_{O} = 0V$	1.1[(V–)+1.5]	1.1[(V–)+1]		*	*		V
Common-Mode Rejection Ratio	$V_{CM} = -3.85V \text{ to } +3.85V, R_{S} = 0\Omega$	86	96		80	*		dB
GAIN								
Initial			10			*		V/V
Gain Error	$V_0 = -4V \text{ to } +3.5V$		±0.01	±0.05		*	±0.1	%
Nonlinearity	$V_0 = -4V \text{ to } +3.5V$		±0.0001	±0.001		*	±0.002	% of FS
OUTPUT								
Voltage Output	Gain Error < 0.1%							
Positive	$R_L = 10k\Omega$ to Ground	(V+) –1.5	(V+)–1.3		*	*		V
Negative	$R_{L} = 10k\Omega$ to Ground	(V–) +1	(V–)+0.8		*	*		V
Positive	$R_L = 100k\Omega$ to Ground		(V+)–0.8			*		V
Negative	$R_{L} = 100k\Omega$ to Ground		(V–)+0.3			*		V
POWER SUPPLY								
Rated Voltage			+5			*		V
Operating Voltage Range								
Dual Supplies		±2.25		±18	*		*	V
Single Supply		+4.5		+36	*		*	V
Quiescent Current (per amplifier)	$I_{O} = 0$		±0.92	±1.2		*	*	mA

\* Specifications the same as INA143U, INA2143U.

NOTES: (1) Includes the effects of amplifier's input bias and offset currents.

#### ABSOLUTE MAXIMUM RATINGS<sup>(1)</sup>

Supply Voltage, V+ to V Input Signal (G = 10), Voltage Current Input Signal (G = 0.1), Voltage Current Output Short-Circuit (to ground) <sup>(2)</sup> Operating Temperature Storage Temperature	36V 
Operating Temperature	55°C to +125°C
Storage Temperature	55°C to +125°C
Junction Temperature Lead Temperature (soldering, 10s)	+150°C +300°C

NOTES: (1) Stresses above these ratings may cause permanent damage. Exposure to absolute maximum conditions for extended periods may degrade device reliability. (2) One channel per package.

#### PACKAGE/ORDERING INFORMATION

### ELECTROSTATIC DISCHARGE SENSITIVITY

This integrated circuit can be damaged by ESD. Burr-Brown recommends that all integrated circuits be handled with appropriate precautions. Failure to observe proper handling and installation procedures can cause damage.

ESD damage can range from subtle performance degradation to complete device failure. Precision integrated circuits may be more susceptible to damage because very small parametric changes could cause the device not to meet its published specifications.

PRODUCT	PACKAGE	PACKAGE DRAWING NUMBER <sup>(1)</sup>	SPECIFIED TEMPERATURE RANGE	PACKAGE MARKING	ORDERING NUMBER <sup>(2)</sup>	TRANSPORT MEDIA
Single INA143U " INA143UA "	SO-8 Surface Mount " SO-8 Surface Mount "	182 " 182 "	-40°C to +85°C " -40°C to +85°C "	INA143U " INA143UA "	INA143U INA143U/2K5 INA143UA INA143UA/2K5	Rails Tape and Reel Rails Tape and Reel
Dual INA2143U " INA2143UA "	SO-14 Surface Mount " SO-14 Surface Mount "	235 " 235 "	-40°C to +85°C " -40°C to +85°C "	INA2143U " INA2143UA "	INA2143U INA2143U/2K5 INA2143UA INA2143UA/2K5	Rails Tape and Reel Rails Tape and Reel

NOTES: (1) For detailed drawing and dimension table, please see end of data sheet, or Appendix C of Burr-Brown IC Data Book. (2) Models with a slash (/) are available only in Tape and Reel in the quantities indicated (e.g., /2K5 indicates 2500 devices per reel). Ordering 2500 pieces of "INA143UA/2K5" will get a single 2500-piece Tape and Reel. For detailed Tape and Reel mechanical information, refer to Appendix B of Burr-Brown IC Data Book.



### **PIN CONFIGURATIONS**







### **TYPICAL PERFORMANCE CURVES**

At  $T_A = +25^{\circ}$ C,  $V_S = \pm 15$ V, G = 10,  $R_L = 10$ k $\Omega$  connected to ground, and reference pin connected to ground, unless otherwise noted.









MAXIMUM OUTPUT VOLTAGE vs FREQUENCY 32  $V_{S} = \pm 15V$ 28 Peak-to-Peak Output Voltage (V) 24 20 16 12  $V_{S} = \pm 5 V$ 8 4 0 10k 1M 100k



TOTAL HARMONIC DISTORTION+NOISE vs FREQUENCY



### **TYPICAL PERFORMANCE CURVES (CONT)**

At  $T_A = +25^{\circ}$ C,  $V_S = \pm 15$ V, G = 10,  $R_L = 10$ k $\Omega$  connected to ground, and reference pin connected to ground, unless otherwise noted.











INA143, INA2143



### **TYPICAL PERFORMANCE CURVES (CONT)**

At  $T_A = +25^{\circ}$ C,  $V_S = \pm 15$ V, G = 10,  $R_L = 10$ k $\Omega$  connected to ground, and reference pin connected to ground, unless otherwise noted.



OFFSET VOLTAGE DRIFT

PRODUCTION DISTRIBUTION

 $V_{S} = \pm 15V$ 

Offset Voltage Drift (µV/°C)

Typical production distribution of

Singles and duals

packaged units.

included.

60

50

40

30

20

10

0

0 0.5 1 1.5 2 2.5 3 3.5 4 4.5 5 5.5 6

Percent of Units (%)













SETTLING TIME vs CAPACITIVE LOAD 20 - G = 10 --G=0.1 0.01%, V = +1515 Settling Time (µs) 0.01%, V<sub>S</sub> = ±15V 0.01%, V<sub>S</sub> = ±5\ 10 5 0.1%, V<sub>S</sub> = ±15V 0 0 500 1000 1500

Capacitive Load (pF)



## **TYPICAL PERFORMANCE CURVES (CONT)**

At  $T_A = +25^{\circ}$ C,  $V_S = \pm 15$ V, G = 10, R<sub>L</sub> = 10k $\Omega$  connected to ground, and reference pin connected to ground, unless otherwise noted.







### **APPLICATIONS INFORMATION**

The INA143 and INA2143 are high-speed difference amplifiers suitable for a wide range of general-purpose applications. Figure 1 shows the basic G = 10 configuration. The input and feedback resistors can be reversed to achieve G = 0.1, as shown in Figure 2. For applications requiring G = 1, the INA133 and INA2133 are recommended.

Decoupling capacitors are strongly recommended for applications with noisy or high impedance power supplies. The capacitors should be placed close to the device pins as shown in Figure 1. All circuitry is completely independent in the dual version assuring lowest crosstalk and normal behavior when one amplifier is overdriven or short-circuited.

As shown in Figure 1, the differential input signal is connected to pins 2 and 3. The source impedances connected to the inputs must be nearly equal to assure good common-mode rejection. A  $5\Omega$  mismatch in source impedance will degrade the common-mode rejection of a typical device to approximately 86dB (RTI). If the source has a known impedance mismatch, an additional resistor in series with the opposite input can be used to preserve good common-mode rejection.

The INA143's internal resistors are accurately ratio trimmed to match. That is,  $R_1/R_2$  and  $R_3/R_4$  are trimmed to equal 0.1. However, the absolute values may not be equal ( $R_1 + R_2$  may be slightly different than  $R_3 + R_4$ ). Thus, large series resistors on the input (greater than  $100\Omega$ ), even if well matched, will degrade common-mode rejection.



FIGURE 1. G = 10 Basic Power Supply and Signal Connections.

### **OPERATING VOLTAGE**

The INA143 and INA2143 operate from single (+4.5V to +36V) or dual ( $\pm 2.25V$  to  $\pm 18V$ ) supplies with excellent performance. Specifications are production tested with  $\pm 5V$  and  $\pm 15V$  supplies. Most behavior remains unchanged

throughout the full operating voltage range. Parameters which vary significantly with operating voltage are shown in the Typical Performance Curves.

#### OFFSET VOLTAGE TRIM

The INA143 and INA2143 are laser trimmed for low offset voltage and drift. Most applications require no external offset adjustment. Figure 3 shows an optional circuit for trimming the output offset voltage. The output is referred to the output reference terminal (pin 1), which is normally grounded. A voltage applied to the Ref terminal will be summed with the output signal. This can be used to null offset voltage as shown in Figure 3. The source impedance of a signal applied to the Ref terminal should be less than  $10\Omega$  to maintain good common-mode rejection.



FIGURE 2. G = 0.1 Difference Amplifier.



INA143, INA2143

FIGURE 3. Offset Adjustment.



FIGURE 4. Difference Amplifier with Gain and CMR Adjust.



FIGURE 5. Precision G = -10 Inverting Amplifier.



FIGURE 6. Voltage Follower with Input Protection.



The INA143 can be combined with op amps to form a complete instrumentation amplifier with specialized performance characteristics. Burr-Brown offers many complete high performance IAs. Products with related performances are shown at the right in the table below.

A <sub>1</sub> , A <sub>2</sub>	FEATURE	SIMILAR COMPLETE BURR-BROWN IA
OPA2227	Low Noise	INA103
OPA129	Ultra Low Bias Current (fA)	INA116
OPA2277	Low Offset Drift, Low Noise	INA114, INA128
OPA2130	Low Power, FET-Input (pA)	INA121
OPA2234	Single Supply, Precision, Low Power	INA122, INA118
OPA2237	Single Supply, Low Power, MSOP-8	INA122, INA126

FIGURE 7. Precision Instrumentation Amplifier.



FIGURE 8. Precision Summing Amplifier.



FIGURE 9. Precision G = 11 Buffer.



WWW ti com

### PACKAGING INFORMATION

Orderable Device	Status <sup>(1)</sup>	Package Type	Package Drawing	Pins	Package Qty	Eco Plan <sup>(2)</sup>	Lead/Ball Finish	n MSL Peak Temp <sup>(3)</sup>
INA143U	ACTIVE	SOIC	D	8	100	Pb-Free (RoHS)	CU NIPDAU	Level-3-260C-168 HR
INA143U/2K5	ACTIVE	SOIC	D	8	2500	Pb-Free (RoHS)	CU NIPDAU	Level-3-260C-168 HR
INA143UA	ACTIVE	SOIC	D	8	100	Pb-Free (RoHS)	CU NIPDAU	Level-3-260C-168 HR
INA143UA/2K5	ACTIVE	SOIC	D	8	2500	Pb-Free (RoHS)	CU NIPDAU	Level-3-260C-168 HR
INA2143U	ACTIVE	SOIC	D	14	58	TBD	CU NIPDAU	Level-3-220C-168 HR
INA2143U/2K5E4	ACTIVE	SOIC	D	14	2500	Pb-Free (RoHS)	CU NIPDAU	Level-3-260C-168 HR
INA2143UA	ACTIVE	SOIC	D	14	58	TBD	CU NIPDAU	Level-3-220C-168 HR
INA2143UA/2K5E4	ACTIVE	SOIC	D	14	2500	Pb-Free (RoHS)	CU NIPDAU	Level-3-260C-168 HR
INA2143UAE4	ACTIVE	SOIC	D	14	58	Pb-Free (RoHS)	CU NIPDAU	Level-3-260C-168 HR
INA2143UE4	ACTIVE	SOIC	D	14	58	Pb-Free (RoHS)	CU NIPDAU	Level-3-260C-168 HR

<sup>(1)</sup> The marketing status values are defined as follows:

ACTIVE: Product device recommended for new designs.

LIFEBUY: TI has announced that the device will be discontinued, and a lifetime-buy period is in effect.

NRND: Not recommended for new designs. Device is in production to support existing customers, but TI does not recommend using this part in a new design.

PREVIEW: Device has been announced but is not in production. Samples may or may not be available.

**OBSOLETE:** TI has discontinued the production of the device.

(2) Eco Plan - The planned eco-friendly classification: Pb-Free (RoHS) or Green (RoHS & no Sb/Br) - please check http://www.ti.com/productcontent for the latest availability information and additional product content details. TBD: The Pb-Free/Green conversion plan has not been defined.

**Pb-Free (RoHS):** TI's terms "Lead-Free" or "Pb-Free" mean semiconductor products that are compatible with the current RoHS requirements for all 6 substances, including the requirement that lead not exceed 0.1% by weight in homogeneous materials. Where designed to be soldered at high temperatures, TI Pb-Free products are suitable for use in specified lead-free processes.

Green (RoHS & no Sb/Br): TI defines "Green" to mean Pb-Free (RoHS compatible), and free of Bromine (Br) and Antimony (Sb) based flame retardants (Br or Sb do not exceed 0.1% by weight in homogeneous material)

<sup>(3)</sup> MSL, Peak Temp. -- The Moisture Sensitivity Level rating according to the JEDEC industry standard classifications, and peak solder temperature.

**Important Information and Disclaimer:**The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and continues to take reasonable steps to provide representative and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.

In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.

#### **IMPORTANT NOTICE**

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, modifications, enhancements, improvements, and other changes to its products and services at any time and to discontinue any product or service without notice. Customers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All products are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its hardware products to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by government requirements, testing of all parameters of each product is not necessarily performed.

TI assumes no liability for applications assistance or customer product design. Customers are responsible for their products and applications using TI components. To minimize the risks associated with customer products and applications, customers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any TI patent right, copyright, mask work right, or other TI intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information published by TI regarding third-party products or services does not constitute a license from TI to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. Reproduction of this information with alteration is an unfair and deceptive business practice. TI is not responsible or liable for such altered documentation.

Resale of TI products or services with statements different from or beyond the parameters stated by TI for that product or service voids all express and any implied warranties for the associated TI product or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

Following are URLs where you can obtain information on other Texas Instruments products and application solutions:

Products		Applications	
Amplifiers	amplifier.ti.com	Audio	www.ti.com/audio
Data Converters	dataconverter.ti.com	Automotive	www.ti.com/automotive
DSP	dsp.ti.com	Broadband	www.ti.com/broadband
Interface	interface.ti.com	Digital Control	www.ti.com/digitalcontrol
Logic	logic.ti.com	Military	www.ti.com/military
Power Mgmt	power.ti.com	Optical Networking	www.ti.com/opticalnetwork
Microcontrollers	microcontroller.ti.com	Security	www.ti.com/security
		Telephony	www.ti.com/telephony
		Video & Imaging	www.ti.com/video
		Wireless	www.ti.com/wireless

Mailing Address:

Texas Instruments

Post Office Box 655303 Dallas, Texas 75265

Copyright © 2005, Texas Instruments Incorporated