# **Mobile Phone Surveillance User Mannual**

# Catalogue

Catalogue	0
1 Symbian System	
1.1Brief Introduction	
1.2 Installation and Operation Instructions	
2 Windows mobile System	4
2.1 Brief Introductions	4
2.2 Installations and Operations Instructions	4
3 iPhone	9
3.1Brief Instructions	
3.2 Installations and Operation instructions	
4 Blackberry	
4.1 Brief Instructions	
4.2 Installation and Operation Instructions	
5 Android	
5.1Brief Instructions	
5.2 Installation and Operation Instructions	

#### **1** Symbian System

#### 1.1Brief Introduction

The main functions and characteristics of the Mobile Phone(Symbian System) are as below:

- Real time viewing video function
- PTZ control function(front end is the controllable dome camera)

#### Prerequisite

The mobile phone should support 9.1 Version Symbian System(just as said the Third and Fifth Generation of the Symbian System) such as Nokia 6120c, Nokiae71 and Nokia5800( all the mobile phones with a resolution of 240\*320,320\*240 in the third generation and a resolution of 360\*640,640\*360 in the fifth generation.

#### 1.2 Installation and Operation Instructions

1) Open the 'Symbian' folder of the CD disk files, then transfer the files (KMEYE\_3rd sisx or KMEYE\_5rd sisx) to the mobile phone for the installation on the phones

# Note:KMEYE\_3rd.sisx support Symbian system of the Third Generation,KMEYE\_5th.sisx support Symbian system of the Fifth Generation

There will be the programme icon on the mobile phones, try to find the KMEye under the designated root catalogue, as shown in the following image:



2) Click KMEye programme icon to enter into the interface as shown in the following image:

125.8	9.62.1	.87			4.0.76
Play					
1	2			•	€€
3	<b>4</b>		0	Θ	ΘΘ
	×	•0	۵	e	

The corresponding	functions	of the	Buttons:

Function Key	Name	Descriptions of the functions
	PLAY	Connect the device and play the video
•0	Screenshot	Screenshot of the available images(Save the screenshot image to the defaulted photo root of the mobile phones)
\$	Setting	Setting of the IP address, dynamic domain name,Port number,user,password and device names
e	Next Channels	Select to the next Channels
⊞	Exit	Exit
×	Full Screen	Full Screen Viewing
<ul><li>■1 ■2</li><li>■3 ■4</li></ul>	Channel Selection	Select to play the video of one channel
$\mathbf{S} \mathbf{S}$	PTZ Control	To control the PTZ(UP,DOWN,RIGHT,LEFT)
$\begin{array}{c} \oplus \oplus \oplus \\ \ominus \ominus \ominus \end{array}$	Focus,Zoom,Iris	To widen and Truncate, adept the focus distance

3) If using the mobile viewing for the first time or any need to modify the parameters, please click 'Setting' button to enter into the interface of parameter setting as shown in the following image:



Note:

Server Address: The IP address or Dynamic domain name of the DVR Server Port:The server port on the DVR Device Name:the alias to differentiate the different devices User ID: Default is [admin] Password:The default password with the password set on IE alias:create the corresponding alias.So the alias will appear the alias on the interface

Open the menu to enter into the list of the history record, or click the PLAY&BACK button to play, then the setting will be saved. The setting will not be saved if clicking BACK directly.



Select one of the history records and open the menu, then click OK to see the viewing

#### Deleting one history record

Select the record file to be deleted and open the menu, then click the delete button to delete the file



4) Video Display Format The switching between regular format and full screen format Regular Format



When extending the mobile phone, the video will be played with full screen automatically.

5)Channel Switching

Select any of the channels, then the programme will open the corresponding channel and also play the record video automatically. The defaulted programme setting is 1-4 channel, when you click the NEXT option, the channel number will be switched between 5-8,8-12,12-16 accordingly.

### 2 Windows mobile System

#### 2.1 Brief Introductions

The main functions and characteristics of the Mobile Phone(Windows Mobile System) are as below: Real time viewing video function PTZ control function(front end is the controllable dome camera)

#### Prerequisite

The mobile phone should support the Windows Mobile 2003 version or updated versions(only touch screen version supported for the present)

#### 2.2 Installations and Operations Instructions

1) Open the 'Windows Mobile' folder of the CD disk files, then transfer the files (KMEyesetup.cab) to the mobile phone for the installation on the phones

28	File Explorer	47	<u>7</u> ∥ 4€	2:55	8
. I	My Documents	Ŧ		Nan	ne 🗸
i 🔁 🔁	usiness				
	1y Music				
🔁 P	ersonal				
С	emplates				<u></u>
N N	MEyesetup	10/2	29/10	228K	

2) Try to find the KMEyesetup.cab under the designated file root, double-click it to install. After the installation, there will be the icons as following image:



3) Click KMEye Icon to enter into the interface as following image:



The corresponding functions of the Buttons:

Function Key	Name	Function Description
Connect	Connect and Play	Connect the device and begin to play the video
Setting	Setting	Setting of the IP address, dynamic domain name,Port number,user,password and device names
Disconnect	Stop	Stop the Video Playing
Items: cam01 ▼ cam01 ▲ cam02 cam03 cam04 cam05 cam06 ▼	Channel Selection	Select to play one video of one channel on the device
	PTZ Control	To control the PTZ(UP,DOWN,RIGHT,LEFT)
+	Zoom	Zoom
EE	Focus	Change the focus distance
00	Iris	Change the Iris
	Screenshot	Screenshot of the available image,the screenshot file is saved under the installation root as follows: File Explorer II < 3:02 Moveeye → Name → Photo skin amplayer 10/25/10 209K File Explorer II < 3:05 File Explorer II < 3:05 Doto → Name → 2010-10-29-1 10/29/10 16.1K 2010-10-29-1 10/29/10 16.0K 2010-10-29-1 10/29/10 16.1K

4) If using the mobile viewing for the first time or any need to modify the parameters, please click 'Setting' button to enter into the interface of parameter setting as shown in the following image:

username.	COMPANY
Password:	*****
Server:	58.251.136.51
Port:	4500
lotes:	
Ok	History
Ok	Connect
Ok Auto	Connect
Ok	Connect
Ok	Connect

Server Address: The IP address or Dynamic domain name of the DVR Server Port:The server port on the DVR Device Name:the alias to differentiate the different devices User ID: Default is [admin] Password:Default is empty alias:create the corresponding alias.So the alias will appear the alias on the interface

Click History button to enter into the history record interface

Server	Port	Note
58.251.136.51	4500	
mattphan.dvrdns	18600	
125.89.62.187	6002	
221.4.221.198	6002	
192.168.10.175	9190	
192.168.0.175	9190	
Ok Delete Cancel		
	<b>(2)</b>	

Select the record to be deleted, then press the Delete button to delete the record

Select one of the records and press OK button and then back to Setting interface

History	
History	_
History	
History	
History	
π	
	x.

Then press OK button to enter into the connecting interface



Enter into the PLAY interface after the successful connecting 5)Video Display Mode The switch between Regular Mode and Full Screen Mode Regular Mode



Click Disconnect Button to stop the playing

#### Full Screen Mode

Click the Screen with the finger or Mobile screen pen to switch into the full screen play



Click the Screen with the finger or Mobile screen pen when full screen playing, the screen will be switched into the regular play mode

#### 6) Channel Switching



Click carn06 to select the corresponding Channels, the program will open the corresponding channel and play hte record video automatically.

### 3 iPhone

#### 3.1Brief Instructions

The main functions and characteristics of the Mobile Phone(Iphone) are as below: Real time viewing video function PTZ control function(front end is the controllable dome camera)

#### Prerequisite

The mobile phone should support the iOS 3.0 version or updated versions(Including Iphone and Ipod touch)

#### 3.2 Installations and Operation instructions

1) To operate the APP Store Programme on IPHONE and switch into the search label web, then enter KMEye in the search column to find the corresponding programme installation files package. After that, click the file to install as shown in the following image:



2)Click KMEye Programme Icon to enter into the following image:

		· ·	0.1	P
The correspon	ding	tunctions	of the	Buttons
The correspon	amb	ranetions	or the	Dattono.

Function Key	Name	Function Description
	Play	Connect the device and play the video
<b>*</b> 0	Screen Shot	Screenshot of the available images(Save the screenshot image to the defaulted photo root of the mobile phones)

\$	Setting	Setting of the IP address, dynamic domain name,Port number,user,password and device names Select to the next Channels
	Next Group	Selection of next group
Ð	About	About Info
1 3 2 4	Channel Selection	select to play the video of one channel
< > < >	PTZ Control	To control the PTZ(UP,DOWN,RIGHT,LEFT)
®* 0*	ZOOM	ZOOM
3	Focus	Change the focus distance
0	Iris	Change the Iris

3) If using the mobile viewing for the first time or any need to modify the parameters, please click 'Setting' button to enter into the interface of parameter setting as shown in the following image:

Back	Settings	History
Server Info		
Name:	demo	
Address:	183.12.166.130	
Port:	15960	
Account Info	þ	
User ID:	admin	
Password:	••••	

Server Address: The IP address or Dynamic domain name of the DVR Server Port:The server port on the DVR Device Name:the alias to differentiate the different devices User ID: Default is [admin] Password:Default is empty

Settings	Edit
demo	183.12.166.130

Click History button to enter into the history record interface

Delete of one history record

Click 'Edit' button and click the red round button in one of the records as shown in the following image, then click Delete button

Clear		Done
🕕 demo	183.12.166.130	Delete

4)Video Display Mode Switch between Regular Mode and Full Screen Mode Regular Mode



When lying the mobile phone, the video will automatically be displayed with full screen.

#### 5)Channel Switching

Select any of the channels, then the programme will open the corresponding channel and also play the record video automatically. The defaulted programme setting is 1-4 channel, when you click the NEXT option, the channel number will be switched between 5-8,8-12,12-16 accordingly.

### **4 Blackberry**

#### 4.1 Brief Instructions

The main functions and characteristics of the Mobile Phone(Iphone) are as below: Real time viewing video function PTZ control function(front end is the controllable dome camera)

#### Prerequisite

The mobile phone should support 4.6 Version Blackberry System such as Blackberry 8900, Blackberry 9000, Blackberry 9700 and Blackberry 9630 with a resolution of 480\*360 and 480\*320.

#### 4.2 Installation and Operation Instructions

1) Open the 'Blackberry' folder of the CD disk files, then transfer the files (KMEYE.cod or KMEYE.alx) to the mobile phone for the installation on the phones



Click the Options on the Mobile Phones to enter into the following interface:

# Options About Advanced Options Applications Auto On/Off AutoText Custom Dictionary Date/Time Geolocation GPS Extended Ephemeris Language and Text Input Memory Mobile Network

Click 'application' option to find the KMEye,then click 'Authority Edit' to set all the authority as 'allow' 2) Click KMEye program icon. After that, enter into the initialization interface as shown in the following image:

	Setting	
Sever info		
Name: <mark>k</mark> t		
Address:183.12.137	7.119	
port: 15960		
User info		
User ID:		
Password:		
Network Info Network Type	WIFI 🔻	
	_	-

Server Address: The IP address or Dynamic domain name of the DVR Server Port:The server port on the DVR Device Name:the alias to differentiate the different devices User ID: Default is [admin] Password:Default is empty Network Type:Select the desired web The corresponding functions of the Buttons:

Function Key	Name	Function Description
Login	Login	Enter into the PLAY main interface, then the program is connected to the device and begin to play the video
Cancel	Cancel	Exit to the program
History	History	Enter into the history record interface

Click LOGIN to enter into the PLAY main interface



The corresponding functions of the Buttons:

Function Key	Name	Function Description	
	PLAY	Connect the device and play the video	
X	FULL SCREEN	FULL SCREEN PLAY	
	Screensho t	Screenshot of the available images(Save the screenshot image to the defaulted photo root of the mobile phones)	
$\Diamond$	Setting	Setting of the IP address, dynamic domain name,Port number,user,password and device names	
	Next Group	Select to the next group	
0	About	About Info	
1 3 2 4	Channel Selection	select to play the video of one channel	
< < >	PTZ Control	To control the PTZ(UP,DOWN,RIGHT,LEFT)	
୍ଟ ଦ	ZOOM	ZOOM	
£3 €3	Focus	Change the focus distance	
0	Iris	Change the Iris	

Click Cancel and exit the program as shown in the following image:

Setting	
Sure to exit the application?	
Yes No	
Login Cancel History	

3) Click 'History Record' to enter into the history record list as shown in the following image:

	History
DeviceName:	erru
DeviceName:	we
DeviceName:	al

Click the menu button to pop-up the menu

History		
DeviceName: erru		
DeviceName: we		
Open		
Edit		
Clear savePath record		
New Device		
Delete		
Delete All Records		
Switch Application		
Close		

The corresponding functions of the menu are as following

Function Key	Name	Function Description
open	PLAY	Connect the device and play the video
edit	EDIT	EDIT RECORD
Clear savePath record	CLEAR	Clear savePath record
New Device	New Device	New added record
Delete	delete	delete the records
Delete All Records	Delete All Records	Delete All Records
Switch Application	Switch Application	Switch Application
Close	Close	Close the program

4)Video Display Mode

The switch between the regular mode and full-screen mode

Regular Mode



Full Screen Mode



## 5 Android

#### 5.1Brief Instructions

The main functions and characteristics of the Mobile Phone(Android) are as below: Real time viewing video function

PTZ control function(front end is the controllable dome camera)

#### Prerequisite

The mobile phone should support 1.5 Version Android System such as HTC G1,HTC Magic,HTC Hero,HTC G5 and so on .

#### 5.2 Installation and Operation Instructions

1) Open the 'Android' folder of the CD disk files, then transfer the files (KMEye.apk) to the mobile phone for the installation on the phones



2)Try to find the KMEye.apk under the designated root and click the Ultilization Program to finish the installation3) Click the KMEye Icon to enter into the following interface:



The corresponding functions of the Buttons:

Function Key	Name	Function Description
	PLAY	Connect the device and play the video
•0	Screenshot	Screenshot of the available images(Save the screenshot image to the defaulted photo root of the mobile phones)
۵	Setting	Setting of the IP address, dynamic domain name,Port number,user,password and device names Select to the next Channels
	Next Group	Select to the next group
	About	About Info
1 3 2 4	Channel Selection	select to play the video of one channel
< < < >	PTZ Control	To control the PTZ(UP,DOWN,RIGHT,LEFT)

ତ୍ୟ ପ୍	ZOOM	ZOOM
11 H	Focus	Change the distance of focus
00	IRIS	Change the IRIS

4) If using the mobile viewing for the first time or any need to modify the parameters, please click 'Setting' button to enter into the interface of parameter setting as shown in the following image:

Address:	121.35.149.13
Port:	15960
DeviceName:	
User ID:	wujianghong1
Password:	

Server Address: The IP address or Dynamic domain name of the DVR Server Port:The server port on the DVR Device Name:the alias to differentiate the different devices User ID: Default is [admin] Password:Default is empty



is the Back button

is referred as the entry of the history record interface



Select one of the record in the history record list to watch the video

Delete of one history record

Select the record to be deleted and click it to pop up a selection column.select delete option to delete the history record



5)Video Display Mode The switch of the Regular Mode and Full Screen Mode Regular Mode



When the mobile phone is lying, the video is played with full screen automatically Full Screen Mode



#### 6)Channel Switch

Select any of the channels, then the programme will open the corresponding channel and also play the record video automatically. The defaulted programme setting is 1-4 channel, when you click the NEXT option, the channel number will be switched between 5-8,8-12,12-16 accordingly.