

# COP820CJ/COP840CJ Family 8-Bit CMOS ROM Based Microcontrollers with 1k or 2k Memory, Comparator and Brown Out Detector

# **General Description**

The COP820CJ/840CJ Family ROM based microcontrollers are integrated COP8<sup>™</sup> Base core devices with 1k or 2k memory, an Analog comparator and Brownout detection. These single-chip CMOS devices are suited for lowerfunctionality applications where power and voltage fluctuations are a consideration. Pin and software compatible (no Brownout; different Vcc range) 4k/32k OTP versions are available (COP87LxxCJ/RJ Family) for pre-production, and for use with a range of COP8 software and hardware development tools. Family features include an 8-bit memory mapped architecture, 10MHz CKI with 1us instruction cycle, one multifunction 16-bit timer/counter, MICROWIRE/PLUS<sup>™</sup> serial I/O, one analog comparator, power saving HALT mode, MIWU, on-chip R/C oscillator capacitor (COP840CJ), high current outputs, software selectable I/O options, WATCH-DOG<sup>™</sup> timer, modulator/timer, Brownout detector, Power on Reset, 2.5v-6.0v operation, and 16/20/28 pin packages.

In this datasheet, the term COP820CJ refers to packages including the COP820CJ, COP822CJ, and COP823CJ; and COP840CJ refers to COP840CJ, COP842CJ, COP940CJ, and COP942CJ.

Devices included in this data sheet are:

Device	Memory (bytes)	RAM (bytes)	I/O Pins	Packages	Temperature	Comments
COP820CJ	1k ROM	64	24	28 DIP/SOIC	-40 to +85°C	
COP822CJ	1k ROM	54	16	20 DIP/SOIC	-40 to +85°C	
COP823CJ	1k ROM	64	12	16 SOIC	-40 to +85°C	
COP840CJ	2k ROM	128	24	28 DIP/SOIC	-40 to +85°C	Low EMI
COP940CJ	2k ROM	128	24	28 DIP/SOIC	-0 to +70°C	2.5V-4.5V, CJH = 4V-6V
COP842CJ	2k ROM	128	16	20 DIP/SOIC	-40 to +85°C	
COP942CJ	2k ROM	128	16	20 DIP/SOIC	-0 to +70°C	2.5V-4.5V, CJH = 4V-6V

# **Key Features**

- Multi-Input Wake Up (on the 8-bit Port L)
- Brown out detector
- Analog comparator
- Modulator/timer (High speed PWM for IR transmission)
- 16-bit multi-function timer supporting
  - PWM mode
  - External event counter mode
  - Input capture mode
- 1024 or 2048 bytes of ROM
- 64 or 128 bytes of RAM
- Quiet design (low radiated emissions)
- Integrated capacitor for the R/C oscillator for COP840CJ

# I/O Features

- Software selectable I/O options (TRI-STATE<sup>®</sup> output, push-pull output, weak pull-up input, high impedance input)
- High current outputs (8 pins)
- Packages
  - 16 SO with 12 I/O pins for COP820CJ
  - 20 DIP/SO with 16 I/O pins
  - 28 DIP/SO with 24 I/O pins

- Schmitt trigger inputs on Port G
- MICROWIRE/PLUS serial I/O

# **CPU/Instruction Set Feature**

- 1 µs instruction cycle time
- Three multi-source vectored interrupts servicing
- External interrupt with selectable edge
- Timer interrupt
- Software interrupt
- 8-bit Stack Pointer (SP)—stack in RAM
- Two 8-bit register indirect data memory pointers (B, X)

# **Fully Static CMOS**

- Low current drain (typically < 1  $\mu$ A)
- Single supply operation: 2.5V to 6.0V
- Temperature ranges: -0°C to +70°C and -40°C to +85°C

# **Development Support**

- Emulation and OTP devices
- Real time emulation and full program debug offered by MetaLink Development System

Comparator and Brown Out Detector COP820CJ/COP840CJ Family, 8-Bit CMOS ROM Based Microcontrollers with 1k or 2k Memory,

TRI-STATE® is a registered trademark of National Semiconductor Corporation.

COP8<sup>™</sup>, MICROWIRE<sup>™</sup>, MICROWIRE/PLUS<sup>™</sup> and WATCHDOG<sup>™</sup> are trademarks of National Semiconductor Corporation. iceMASTER<sup>®</sup> is a registered trademark of MetaLink Corporation.



# Connection Diagrams (Continued)

COP820CJ/COP840CJ Pin Assignment

Port Pin	Тур.	ALT Function	16-Pin	20-Pin	28-Pin
LO	I/O	MIWU/CMPOUT	5	7	11
L1	I/O	MIWU/CMPIN-	6	8	12
L2	I/O	MIWU/CMPIN+	7	9	13
L3	I/O	MIWU	8	10	14
L4	I/O	MIWU	9	11	15
L5	I/O	MIWU	10	12	16
L6	I/O	MIWU	11	13	17
L7	I/O	MIWU/MODOUT	12	14	18
G0	I/O	INTR		17	25
G1	I/O			18	26
G2	I/O			19	27
G3	I/O	TIO	15	20	28
G4	I/O	SO		1	1
G5	I/O	SK	16	2	2
G6	1	SI	1	3	3
G7	1	СКО	2	4	4
10	1				7
11	I				8
12	I				9
13	I				10
D0	0				19
D1	0				20
D2	0				21
D3	0				22
V <sub>cc</sub>			4	6	6
GND			13	15	23
CKI			3	5	5
RESET			14	16	24

# Absolute Maximum Ratings (Note 1)

If Military/Aerospace specified devices are required, please contact the National Semiconductor Sales Office/ Distributors for availability and specifications.

Supply Voltage (V <sub>CC</sub> )	7.0V
Voltage at any Pin	-0.3V to V <sub>CC</sub> + 0.3V

# **DC Electrical Characteristics**

Total Current into  $V_{CC}$  pin (Source) Total Current out of GND pin (sink)

Storage Temperature Range –65

Note 1: Absolute maximum ratings indicate limits beyond which damage to the device may occur.

DC and AC electrical specifications are not ensured when operating the device at absolute maximum ratings.

	$10 - 40 C \le 1_A \le +03 C$ for all others		$-0^{\circ}C \le T_A \le + 70^{\circ}C$ for COP94x and $-40^{\circ}C \le T_A \le +85^{\circ}C$ for all others							
Parameter	Conditions	Min	Тур	Max	Units					
Operating Voltage	Brown Out Disabled	2.5		6.0	V					
COP94xCJ	Brown Out Disabled	2.5		4.5	V					
COP94xCJH	Brown Out Disabled	4.5		6.0	V					
Power Supply Ripple 1 (Note 2)	Peak to Peak			0.1 V <sub>CC</sub>	V					
Supply Current (Note 3)										
CKI = 10 MHz	$V_{\rm CC} = 6V$ , tc = 1 $\mu$ s			6.0	mA					
CKI = 4 MHz	$V_{\rm CC} = 6V,  tc = 2.5  \mu s$			3.5	mA					
CKI = 4 MHz	$V_{\rm CC}$ = 4.0V, tc = 2.5 µs			2.0	mA					
CKI = 1 MHz	$V_{\rm CC} = 4.0$ V, tc = 10 µs			1.5	mA					
HALT Current with Brown Out Disabled (Note 4)	$V_{CC} = 6V, CKI = 0 MHz$		<1	10	μA					
HALT Current with Brown Out Enabled	$V_{CC} = 6V, CKI = 0 MHz$		<50	110	μA					
COP840CJ Supply Current (Note 3)										
CKI = 10 MHz, R = 2.2k	$V_{CC} = 6V$ , tc = 1 $\mu$ s			8.0	mA					
CKI = 4 MHz, R = 4.7k	$V_{\rm CC} = 6V,  tc = 2.5  \mu s$			6.0	mA					
CKI = 4 MHz, R = 4.7k	$V_{\rm CC}$ = 4.5V, tc = 2.5 µs			2.5	mA					
CKI = 1 MHz, R = 20k	$V_{\rm CC} = 4.5 V$ , tc = 10 µs			1.5	mA					
HALT Current with Brown Out Disabled	$V_{CC} = 6V, CKI = 0 MHz$		<2.2	8	μA					
HALT Current with Brown Out Enabled	$V_{CC}$ = 6V, CKI = 0 MHz		<50	100	μA					
Brown Out Trip Level (Brown Out Enabled)		1.8	3.1	4.2	V					
COP840CJ Brown Out Trip Level (Brown Out Enabled)		1.9	3.1	3.9	V					
INPUT LEVELS (VIH, VIL)										
Reset, CKI:										
Logic High		0.8 V <sub>CC</sub>			V					
Logic Low				0.2 V <sub>CC</sub>	V					
All Other Inputs										
Logic High		0.7 V <sub>CC</sub>			V					
Logic Low				0.2 V <sub>CC</sub>	V					
Hi-Z Input Leakage	$V_{CC} = 6.0V$	-2		+2	μA					
Input Pullup Current	$V_{CC} = 6.0V, V_{IN} = 0V$	-40		-250	μA					
L- and G-Port Hysteresis (Note 6)			COP840CJ 0.05 V <sub>CC</sub>	0.35 V <sub>CC</sub>	V					

80 mA -65°C to +150°C

80 mA

# DC Electrical Characteristics (Continued)

Parameter	Conditions	Min	Тур	Max	Units
Output Current Levels					
D Outputs:					
Source	$V_{CC} = 4.5V, V_{OH} = 3.8V$	-0.4			mA
	$V_{CC} = 2.5V, V_{OH} = 1.8V$	-0.2			mA
Sink	$V_{CC} = 4.5V, V_{OL} = 1.0V$	10			mA
	$V_{CC} = 2.5 V, V_{OH} = 0.4 V$	2			mA
L4–L7 Output Sink	$V_{CC} = 4.5V, V_{OL} = 2.5V$	15			mA
All Others					
Source (Weak Pull-up Mode)	$V_{CC} = 4.5V, V_{OH} = 3.2V$	-10		-110	μA
	$V_{CC} = 2.5V, V_{OH} = 1.8V$	-2.5		-33	μA
Source (Push-pull Mode)	$V_{CC} = 4.5V, V_{OH} = 3.8V$	-0.4			mA
	$V_{CC} = 2.5V, V_{OH} = 1.8V$	-0.2			mA
Sink (Push-pull Mode)	$V_{CC} = 4.5 V, V_{OL} = 0.4 V$	1.6			mA
	$V_{CC} = 2.5 V, V_{OL} = 0.4 V$	0.7			mA
TRI-STATE Leakage		-2.0		+2.0	μA
Allowable Sink/Source					
Current Per Pin					
D Outputs				15	mA
L4–L7 (Sink)				20	mA
All Others				3	mA
Maximum Input Current	Room Temperature			±100	mA
without Latchup (Note 5)					
RAM Retention Voltage, V <sub>r</sub>	500 ns Rise and	2.0			V
	Fall Time (Min)				
Input Capacitance				7	pF
Load Capacitance on D2				1000	pF

Note 2: Rate of voltage change must be less than 10 V/mS.

Note 3: Supply current is measured after running 2000 cycles with a square wave CKI input, CKO open, inputs at rails and outputs open.

Note 4: The HALT mode will stop CKI from oscillating in the RC and crystal configurations. HALT test conditions: L, and G0..G5 ports configured as outputs and set high. The D port set to zero. All inputs tied to V<sub>CC</sub>. The comparator and the Brown Out circuits are disabled.

Note 5: Pins G6 and RESET are designed with a high voltage input network. These pins allow input voltages greater than V<sub>CC</sub> and the pins will have sink current to  $V_{CC}$  when biased at voltages greater than  $V_{CC}$  (the pins do not have source current when biased at a voltage below  $V_{CC}$ ). The effective resistance to  $V_{CC}$  is 750 $\Omega$  (typical). These two pins will not latch up. The voltage at the pins must be limited to less than 14V. COP820CJ/COP840CJ Family

# AC Electrical Characteristics $-40^{\circ}C \le T_{A} \le +85^{\circ}C$ upless otherwise specified

Parameter	Conditions	Min	Тур	Max	Units
Instruction Cycle Time (tc)					
Crystal/Resonator	$4.5V \le V_{CC} \le 6.0V$	1		DC	μs
	$2.5V \le V_{CC} \le 4.5V$	2.5		DC	μs
R/C Oscillator	$4.5V \le V_{CC} \le 6.0V$	3		DC	μs
	COP840CJ	2		DC	μs
	$2.5V \le V_{CC} \le 4.5V$	7.5		DC	μs
	COP840CJ	5		DC	μs
V <sub>CC</sub> Rise Time when Using Brown Out	$V_{\rm CC} = 0V$ to $6V$	50			μs
Frequency at Brown Out Reset				4	MHz
CKI Frequency For Modular Output				4	MHz
CKI Clock Duty Cycle (Note 6)	fr = Max	40		60	%
Rise Time (Note 6)	fr = 10 MHz ext. Clock			12	ns
Fall Time (Note 6)	fr = 10 MHz ext. Clock			8	ns
Inputs					
t <sub>Setup</sub>	$4.5V \le V_{CC} \le 6.0V$	200			ns
	$2.5V \le V_{CC} \le 4.5V$	500			ns
t <sub>Hold</sub>	$4.5V \le V_{CC} \le 6.0V$	60			ns
	$2.5V \le V_{CC} \le 4.5V$	150			ns
Output Propagation Delay	R <sub>L</sub> = 2.2k, CL = 100 pF				
t <sub>PD1</sub> , t <sub>PD0</sub>					
SO, SK	$4.5V \le V_{CC} \le 6.0V$			0.7	μs
	$2.5V \le V_{CC} \le 4.5V$			1.75	μs
All Others	$4.5V \le V_{CC} \le 6.0V$			1	μs
	$2.5V \le V_{CC} \le 4.5V$			5	μs
Input Pulse Width					
Interrupt Input High Time		1			tc
Interrupt Input Low Time		1			tc
Timer Input High Time		1			tc
Timer Input Low Time		1			tc
MICROWIRE Setup Time (t <sub>µWS</sub> )		20			ns
MICROWIRE Hold Time (t <sub>µWH</sub> )		56			ns
MICROWIRE Output				220	ns
Propagation Delay (t <sub>µPD</sub> )					
•		1			

Note 6: Parameter characterized but not production tested.



# **Comparator DC and AC Characteristics**

$4V \leq V_{CC} \leq 6V, \ -40^{\circ}C \leq T_A \leq$ + $85^{\circ}C$ (	Note 7)

Parameters	Conditions	Min	Туре	Max	Units
Input Offset Voltage	$0.4V < V_{IN} < V_{CC} - 1.5V$		±10	±25	mV
Input Common Mode Voltage Range		0.4		V <sub>CC</sub> – 1.5	V
Voltage Gain			300k		V/V
DC Supply Current (when enabled)	$V_{\rm CC} = 6.0 V$			250	μA
Response Time	100 mV Overdrive	60	100	140	ns
	500 mV Overdrive	80	125	165	ns
	1000 mV Overdrive	135	215	300	ns

Note 7: For comparator output current characteristics see L-Port specs.

# **Typical Performance Characteristics for COP820CJ**





#### Halt—I<sub>DD</sub> vs V<sub>CC</sub> (Brown Out Disabled)



Halt—I<sub>DD</sub> vs V<sub>CC</sub> (Brown Out Enabled)



Ports L/G Weak Pull-Up Source Current







#### Ports L/G Push-Pull Sink Current



DS011208-37

COP820CJ/COP840CJ Family



# Typical Performance Characteristics for COP820CJ (Continued)

#### Ports L4-L7 Port D Source Current Sink Current 8 35 7 V<sub>CC</sub>=6.0 30 6 =6.0 25 5 I<sub>OH</sub> (mA) I<sub>OL</sub> (mA) 4 20 Vcc=4.5V 3 15 2 10 2.5V 5 0 v<sub>cc</sub> :2 5 0 1 2 3 4 5 0 0 0.5 1.0 1.5 2.0 2.5 3.0 3.5 4.0 4.5 $V_{\mathsf{OH}}\left(V\right)$ DS011208-39 $V_{OL}(V)$ DS011208-38 4.2 Max 4.0 - -Brown Out Voltage (V) 3.8 3.6 3.4 Тур 3.2 3.0 2.8 2.6 Min 2.4 2.2



#### **Brown Out Voltage** vs Temperature



# **Typical Performance Characteristics for COP840CJ**

(mA)

Port D Sink current



#### Halt Current with **Brown Out Disabled**



#### Halt Current with **Brown Out Enabled**





# **Pin Description**

 $V_{cc}$  and GND are the power supply pins.

**CKI** is the clock input. This can come from an external source, a R/C generated oscillator or a crystal (in conjunction with CKO). See Oscillator description.

**RESET** is the master reset input. See Reset description.

**PORT I** is a 4-bit Hi-Z input port.

PORT L is an 8-bit I/O port.

There are two registers associated with the L port: a data register and a configuration register. Therefore, each L I/O bit can be individually configured under software control as shown below:

Port L	Port L	Port L	
Config.	Data	Setup	
0	0	Hi-Z Input (TRI-STATE)	
0	1	Input with Weak Pull-up	
1	0	Push-pull Zero Output	
1	1	Push-pull One Output	

Three data memory address locations are allocated for this port, one each for data register [00D0], configuration register [00D1] and the input pins [00D2].

Port L has the following alternate features:

- L7 MIWU or MODOUT (high sink current capability)
- L6 MIWU (high sink current capability)
- L5 MIWU (high sink current capability)
- L4 MIWU (high sink current capability)
- L3 MIWU
- L2 MIWU or CMPIN+
- L1 MIWU or CMPIN-
- L0 MIWU or CMPOUT

The selection of alternate Port L functions is done through registers WKEN [00C9] to enable MIWU and CNTRL2 [00CC] to enable comparator and modulator.

All eight L-pins have Schmitt Triggers on their inputs.

**PORT G** is an 8-bit port with 6 I/O pins (G0–G5) and 2 input pins (G6, G7).

All eight G-pins have Schmitt Triggers on the inputs.

There are two registers associated with the G port: a data register and a configuration register. Therefore each G port bit can be individually configured under software control as shown below:

Port G	Port G	Port G		
Config. Data		Setup		
0	0	Hi-Z Input (TRI-STATE)		
0	1	Input with Weak Pull-up		
1	0	Push-pull Zero Output		
1	1	Push-pull One Output		

Three data memory address locations are allocated for this port, one for data register [00D4], one for configuration register [00D5] and one for the input pins [00D6]. Since G6 and G7 are Hi-Z input only pins, any attempt by the user to configure them as outputs by writing a one to the configuration register will be disregarded. Reading the G6 and G7 configuration bits will return zeros. Note that the device will be placed in the Halt mode by writing a "1" to the G7 data bit. Six pins of Port G have alternate features:

- G7 CKO crystal oscillator output (selected by mask option) or HALT restart input/general purpose input (if clock option is R/C or external clock)
- G6 SI (MICROWIRE serial data input)
- G5 SK (MICROWIRE clock I/O)
- G4 SO (MICROWIRE serial data output)
- G3 TIO (timer/counter input/output)
- G0 INTR (an external interrupt)

Pins G2 and G1 currently do not have any alternate functions.

The selection of alternate Port G functions are done through registers PSW [00EF] to enable external interrupt and CN-TRL1 [00EE] to select TIO and MICROWIRE operations.

**PORT D** is a four bit output port that is preset when RESET goes low. One data memory address location is allocated for the data register [00DC].

Note: Care must be exercised with the D2 pin operation. At RESET, the external loads on this pin must ensure that the output voltages stay above 0.8 V<sub>CC</sub> to prevent the chip from entering special modes. Also keep the external loading on D2 to less than 1000 pF.

# **Functional Description**

The internal architecture is shown in the block diagram. Data paths are illustrated in simplified form to depict how the various logic elements communicate with each other in implementing the instruction set of the device.

#### ALU and CPU Registers

The ALU can do an 8-bit addition, subtraction, logical or shift operations in one cycle time. There are five CPU registers:

- A is the 8-bit Accumulator register
- PC is the 15-bit Program Counter register

PU is the upper 7 bits of the program counter (PC) PL is the lower 8 bits of the program counter (PC)

- B is the 8-bit address register and can be auto incremented or decremented.
- X is the 8-bit alternate address register and can be auto incremented or decremented.
- SP is the 8-bit stack pointer which points to the subroutine stack (in RAM).

B, X and SP registers are mapped into the on chip RAM. The B and X registers are used to address the on chip RAM. The SP register is used to address the stack in RAM during subroutine calls and returns. The SP must be preset by software upon initialization.

# Memory

The memory is separated into two memory spaces: program and data.

#### PROGRAM MEMORY

Program memory consists of  $1024 \times 8$  ROM or  $2048 \times 8$  ROM. These bytes of ROM may be instructions or constant data. The memory is addressed by the 15-bit program counter (PC). ROM can be indirectly read by the LAID instruction for table lookup.

#### DATA MEMORY

The data memory address space includes on chip RAM, I/O and registers. Data memory is addressed directly by the instruction or indirectly through B, X and SP registers. The device has 64 or 128 bytes of RAM. Sixteen bytes of RAM are

#### Memory (Continued)

mapped as "registers", these can be loaded immediately, decremented and tested. Three specific registers: X, B, and SP are mapped into this space, the other registers are available for general usage.

Any bit of data memory can be directly set, reset or tested. All I/O and registers (except A and PC) are memory mapped; therefore, I/O bits and register bits can be directly and individually set, reset and tested, except the write once only bit (WDREN, WATCHDOG Reset Enable), and the unused and read only bits in CNTRL2 and WDREG registers.

Note: RAM contents are undefined upon power-up.

# Reset

#### EXTERNAL RESET

The RESET input pin when pulled low initializes the micro-controller. The user must insure that the RESET pin is held low until  $V_{CC}$  is within the specified voltage range and the clock is stabilized. An R/C circuit with a delay 5x greater than the power supply rise time is recommended (*Figure 4*). The device immediately goes into reset state when the RESET input goes low. When the RESET pin goes high the device comes out of reset state synchronously. The device will be running within two instruction cycles of the RESET pin going high. The following actions occur upon reset:

Port L	TRI-STATE
Port G	TRI-STATE
Port D	HIGH
PC	CLEARED
RAM Contents	RANDOM with Power-On-
	Reset
	UNAFFECTED with external
	Reset (power already applied)
B, X, SP	Same as RAM
PSW, CNTRL1,	
CNTRL2	
and WDREG Reg.	CLEARED
Multi-Input Wakeup	
Reg.	
WKEDG, WKEN	CLEARED
WKPND	UNKNOWN
Data and Configuration	
Registers for L & G	CLEARED
WATCHDOG Timer	Prescaler/Counter each
	loaded with FF

The device comes out of the HALT mode when the RESET pin is pulled low. In this case, the user has to ensure that the RESET signal is low long enough to allow the oscillator to restart. An internal 256 t<sub>c</sub> delay is normally used in conjunction with the two pin crystal oscillator. When the device comes out of the HALT mode through Multi-Input Wakeup, this delay allows the oscillator to stabilize.

The following additional actions occur after the device comes out of the HALT mode through the RESET pin.

If a two pin crystal/resonator oscillator is being used:

UNCHANGED
UNKNOWN
ALTERED
used:
UNCHANGED
UNCHANGED

WATCHDOG Timer Prescaler/Counter ALTERED The external RESET takes priority over the Brown Out Reset.

Note: If the RESET pin is pulled low while Brown Out occurs (Brown Out circuit has detected Brown Out condition), the external reset will not occur until the Brown Out condition is removed. External reset has priority only if V<sub>CC</sub> is greater than the Brown Out voltage.



RC > 5 x Power Supply Rise Time

FIGURE 4. Recommended Reset Circuit

#### WATCHDOG RESET

With WATCHDOG enabled, the WATCHDOG logic resets the device if the user program does not service the WATCH-DOG timer within the selected service window. The WATCH-DOG reset does not disable the WATCHDOG. Upon WATCHDOG reset, the WATCHDOG Prescaler and Counter are each initialized with FF Hex.

The following actions occur upon WATCHDOG reset that are different from external reset.

WDREN WATCHDOG Reset Enable bit UNCHANGED WDUDFWATCHDOG Underflow bitUNCHANGED

Additional initialization actions that occur as a result of WATCHDOG reset are as follows:

M

#### **BROWN OUT RESET**

The on-board Brown Out protection circuit resets the device when the operating voltage ( $V_{CC}$ ) is lower than the Brown Out voltage. The device is held in reset when  $V_{CC}$  stays below the Brown Out Voltage. The device will remain in RESET as long as  $V_{CC}$  is below the Brown Out Voltage. The Device will resume execution if  $V_{CC}$  rises above the Brown Out Voltage. If a two pin crystal/resonator clock option is selected, the Brown Out reset will trigger a 256tc delay. This delay allows the oscillator to stabilize before the device exits the reset state. The delay is not used if the clock option is either R/C or external clock. The contents of data registers and RAM are unknown following a Brown Out reset. The external reset takes priority over Brown Out Reset and will deactivate the 256 t<sub>c</sub> cycles delay if in progress. The Brown Out reset takes priority over the WATCHDOG reset.

The following actions occur as a result of Brown Out reset:

Port L	TRI-STATE
Port G	TRI-STATE
Port D	HIGH
PC	CLEARED
RAM Contents	RANDOM
B, X, SP	UNKNOWN
PSW, CNTRL1, CNTRL2	
and WDREG Registers	CLEARED
Multi-Input Wakeup Registers	
WKEDG, WKEN	CLEARED
WKPND	UNKNOWN
Data and Configuration	
Registers for L & G	CLEARED
WATCHDOG Timer	Prescalar/Counter each loaded with FF
Timer T1 and Accumulator	Unknown data after coming out of the HALT (through Brown Out Reset) with any Clock option

**Note 8:** The development system will detect the BROWN OUT RESET externally and will force the RESET pin low. The Development System does not emulate the 256tc delay.

#### **Brown Out Detection**

An on-board detection circuit monitors the operating voltage ( $V_{\rm CC}$ ) and compares it with the minimum operating voltage specified. The Brown Out circuit is designed to reset the device if the operating voltage is below the Brown Out voltage (between 1.8V to 4.2V at -40°C to +85°C). The Minimum operating voltage for the device is 2.5V with Brown Out disabled, but with BROWN OUT enabled the device is guaranteed to operate properly down to minimum Brown Out

voltage **(Max frequency 4 MHz)**, For temperature range of 0°C to 70°C the Brown Out voltage is expected to be between 1.9V to 3.9V. The circuit can be enabled or disabled by Brown Out mask option. If the device is intended to operate at lower V<sub>CC</sub> (lower than Brown Out voltage VBO max), the Brown Out circuit should be disabled by the mask option.

The Brown Out circuit may be used as a power-up reset provided the power supply rise time is slower than 50  $\mu$ s (0V to 6.0V). Brown Out should not be used at frequencies over 4 MHz (COP840CJ).

Note: Brown Out Circuit is active in HALT mode (with the Brown Out mask option selected).

#### **Oscillator Circuits**

#### EXTERNAL OSCILLATOR

CKI can be driven by an external clock signal provided it meets the specified duty cycle, rise and fall times, and input levels. G7/CKO is available as a general purpose input G7 and/or Halt control.

#### CRYSTAL OSCILLATOR

By selecting G7/CKO as a clock output, CKI and G7/CKO can be connected to create a crystal controlled oscillator. *Table 1* shows the component values required for various standard crystal values.

#### **R/C OSCILLATOR (COP820CJ)**

For COP820CJ, selecting CKI as a single pin oscillator, CKI can make a R/C oscillator. G7/CKO is available as a general purpose input and/or HALT control. *Table 2* shows variation in the oscillator frequencies as functions of the component (R and C) values.



FIGURE 5. Clock Oscillator Configurations

TABLE 1	. Crystal	Oscillator	Configuration
---------	-----------	------------	---------------

R1 (kΩ)	R2 (ΜΩ)	C1 (pF)	C2 (pF)	CKI Freq. (MHz)	Conditions
0	1	30	30–36	10	$V_{\rm CC} = 5V$
0	1	30	30–36	4	$V_{\rm CC} = 5V$
5.6	1	100/200	100–156	0.455	$V_{\rm CC} = 5V$

TABLE 2. R/C Oscillator C	Configuration (	(Part-To-Part	Variation)
---------------------------	-----------------	---------------	------------

R (kΩ)	C (pF)	CK1 Freq. (MHz)	Instr. Cycle (μs)	Conditions
3.3	82	2.2 to 2.7	3.7 to 4.6	$V_{\rm CC} = 5V$
5.6	100	1.1 to 1.3	7.4 to 9.0	$V_{CC} = 5V$
6.8	100	0.9 to 1.1	8.8 to 10.8	$V_{CC} = 5V$

#### **R/C OSCILLATOR (COP840CJ)**

For COP840CJ, selecting the R/C oscillator option makes a R/C oscillator when connecting a resistor from the CKI pin to V . The capacitor is on-chip. The G7/CKO pin is available as

a general purpose input G7 and/or Halt control. Adding an external capacitor will jeopardize the clock frequency tolerance and increase EMI emissions. *Table 3* shows the clock frequency for the different resistor values.

TABLE 3. RC Oscillator Configuration	(Part-To-Part Variation)
--------------------------------------	--------------------------

<b>R (k</b> Ω)	CK1 Freq. (MHz)	Temperature	V <sub>cc</sub>
2.2	7.0 ± 15%	-40°C to +85°C	4.5V to 5.5V
4.7	4.2 ± 10%	-40°C to +85°C	4.5V to 5.5V
20.0	7.1 ± 10%	-40°C to +85°C	4.5V to 5.5V

Note 9: The resistance level is calculated with a total of 5.3 pF capacitance added from the printed circuit board. It is important to take this into account when figuring the clock frequency.

#### HALT Mode

The device is a fully static device. The device enters the HALT mode by writing a one to the G7 bit of the G data register. Once in the HALT mode, the internal circuitry does not receive any clock signal and is therefore frozen in the exact state it was in when halted. In this mode, the chip will only draw leakage current (output current and DC current due to the Brown Out circuit if Brown Out is enabled).

The device supports four different methods of exiting the HALT mode. The first method is with a low to high transition on the CKO (G7) pin. This method precludes the use of the crystal clock configuration (since CKO is a dedicated output). It may be used either with an RC clock configuration or an external clock configuration. The second method of exiting the HALT mode is with the multi-Input Wakeup feature on the L port. The third method of exiting the HALT mode is by pulling the RESET input low. The fourth method is with the operating voltage going below Brown Out voltage (if Brown Out is enabled by mask option).

If the two pin crystal/resonator oscillator is being used and Multi-Input Wakeup or Brown Out causes the device to exit the HALT mode, the WAKEUP signal does not allow the chip to start running immediately since crystal oscillators have a delayed start up time to reach full amplitude and freugency stability. The WATCHDOG timer (consisting of an 8-bit prescaler followed by an 8-bit counter) is used to generate a fixed delay of 256tc to ensure that the oscillator has indeed stabilized before allowing instruction execution. In this case, upon detecting a valid WAKEUP signal only the oscillator circuitry is enabled. The WATCHDOG Counter and Prescaler are each loaded with a value of FF Hex. The WATCHDOG prescaler is clocked with the  $t_{\rm c}$  instruction cycle. (The  $t_{\rm c}$  clock is derived by dividing the oscillator clock down by a factor of 10). The Schmitt trigger following the CKI inverter on the chip ensures that the WATCHDOG timer is clocked only when the oscillator has a sufficiently large amplitude to meet the Schmitt trigger specs. This Schmitt trigger is not part of the oscillator closed loop. The start-up timeout from the WATCH-DOG timer enables the clock signals to be routed to the rest of the chip. The delay is not activated when the device comes out of HALT mode through RESET pin. Also, if the clock option is either RC or External clock, the delay is not used, but the WATCHDOG Prescaler/Counter contents are changed. The Development System will not emulate the 256tc delay.

The RESET pin or Brown Out will cause the device to reset and start executing from address X'0000. A low to high transition on the G7 pin (if single pin oscillator is used) or Multi-Input Wakeup will cause the device to start executing from the address following the HALT instruction.

When RESET pin is used to exit the device from the HALT mode and the two pin crystal/resonator (CKI/CKO) clock option is selected, the contents of the Accumulator and the Timer T1 are undetermined following the reset. All other information except the WATCHDOG Prescaler/Counter contents is retained until continuing. If the device comes out of the HALT mode through Brown Out reset, the contents of data registers and RAM are unknown following the reset. All information except the WATCHDOG Prescaler/Counter contents is retained if the device exits the HALT mode through G7 pin or Multi-Input Wakeup.

G7 is the HALT-restart pin, but it can still be used as an input. If the device is not halted, G7 can be used as a general purpose input.

If the Brown Out Enable mask option is selected, the Brown Out circuit remains active during the HALT mode causing additional current to be drawn.

Note: To allow clock resynchronization, it is necessary to program two NOP's immediately after the device comes out of the HALT mode. The user must program two NOP's following the "enter HALT mode" (set G7 data bit) instruction.

#### **MICROWIRE/PLUS**

MICROWIRE/PLUS is a serial synchronous bidirectional communications interface. The MICROWIRE/PLUS capability enables the device to interface with any of National Semiconductor's MICROWIRE peripherals (i.e. A/D converters, display drivers, EEPROMS, etc.) and with other microcontrollers which support the MICROWIRE/PLUS interface. It consists of an 8-bit serial shift register (SIO) with serial data

input (SI), serial data output (SO) and serial shift clock (SK). *Figure 6* shows the block diagram of the MICROWIRE/PLUS interface.



#### FIGURE 6. MICROWIRE/PLUS Block Diagram

The shift clock can be selected from either an internal source or an external source. Operating the MICROWIRE/PLUS interface with the internal clock source is called the Master mode of operation. Operating the MICROWIRE/PLUS interface with an external shift clock is called the Slave mode of operation.

The CNTRL register is used to configure and control the MICROWIRE/PLUS mode. To use the MICROWIRE/PLUS, the MSEL bit in the CNTRL register is set to one. The SK clock rate is selected by the two bits, SL0 and SL1, in the CNTRL register. *Table 4* details the different clock rates that may be selected.

SL1	SL0	SK Cycle Time
0	0	2t <sub>c</sub>
0	1	4t <sub>c</sub>
1	x	8t <sub>c</sub>

where,

tc is the instruction cycle time.

#### **MICROWIRE/PLUS OPERATION**

Setting the BUSY bit in the PSW register causes the MICROWIRE/PLUS arrangement to start shifting the data. It gets reset when eight data bits have been shifted. The user may reset the BUSY bit by software to allow less than 8 bits to shift. The device may enter the MICROWIRE/PLUS mode either as a Master or as a Slave. *Figure 7* shows how two device microcontrollers and several peripherals may be interconnected using the MICROWIRE/PLUS arrangement.

#### MASTER MICROWIRE/PLUS OPERATION

In the MICROWIRE/PLUS Master mode of operation the shift clock (SK) is generated internally by the device. The MICROWIRE/PLUS Master always initiates all data exchanges (*Figure 7*). The MSEL bit in the CNTRL register must be set to enable the SO and SK functions on the G Port. The SO and SK pins must also be selected as outputs by setting appropriate bits in the Port G configuration register. *Table 5* summarizes the bit settings required for Master mode of operation.

#### SLAVE MICROWIRE/PLUS OPERATION

In the MICROWIRE/PLUS Slave mode of operation the SK clock is generated by an external source. Setting the MSEL bit in the CNTRL register enables the SO and SK functions on the G Port. The SK pin must be selected as an input and the SO pin selected as an output pin by appropriately setting up the Port G configuration register. *Table 5* summarizes the settings required to enter the Slave mode of operation.



The user must set the BUSY flag immediately upon entering the Slave mode. This will ensure that all data bits sent by the Master will be shifted properly. After eight clock pulses the BUSY flag will be cleared and the sequence may be repeated. (See *Figure 7*).

TABLE 5.	
----------	--

G4	G5	G4	G5	G6	
Config.	Config.	Fun.	Fun.	Fun.	Operation
Bit	Bit				
1	1	SO	Int. SK	SI	MICROWIRE Master
0	1	TRI-STATE	Int. SK	SI	MICROWIRE Master
1	0	SO	Ext. SK	SI	MICROWIRE Slave
0	0	TRI-STATE	Ext. SK	SI	MICROWIRE Slave

# **Timer/Counter**

The device has a powerful 16-bit timer with an associated 16-bit register enabling it to perform extensive timer functions. The timer T1 and its register R1 are each organized as two 8-bit read/write registers. Control bits in the register CN-TRL allow the timer to be started and stopped under software control. The timer-register pair can be operated in one of three possible modes. *Table 6* details various timer operating modes and their requisite control settings.

#### MODE 1. TIMER WITH AUTO-LOAD REGISTER

In this mode of operation, the timer T1 counts down at the instruction cycle rate. Upon underflow the value in the register R1 gets automatically reloaded into the timer which continues to count down. The timer underflow can be programmed to interrupt the microcontroller. A bit in the control register CNTRL enables the TIO (G3) pin to toggle upon timer underflows. This allows the generation of square-wave outputs or pulse width modulated outputs under software control (*Figure 8*).

#### MODE 2. EXTERNAL COUNTER

In this mode, the timer T1 becomes a 16-bit external event counter. The counter counts down upon an edge on the TIO pin. Control bits in the register CNTRL program the counter to decrement either on a positive edge or on a negative edge. Upon underflow the contents of the register R1 are automatically copied into the counter. The underflow can also be programmed to generate an interrupt (*Figure 9*).



FIGURE 8. Timer/Counter Auto Reload Mode Block Diagram

CNTRL			Timer
Bits	Operation Mode	T Interrupt	Counts
765			On
000	External Counter w/Auto-Load Reg.	Timer Underflow	TIO Pos. Edge
001	External Counter w/Auto-Load Reg.	Timer Underflow	TIO Neg. Edge
010	Not Allowed	Not Allowed	Not Allowed
011	Not Allowed	Not Allowed	Not Allowed
100	Timer w/Auto-Load Reg.	Timer Underflow	t <sub>c</sub>
101	Timer w/Auto-Load Reg./Toggle TIO Out	Timer Underflow	t <sub>c</sub>
110	Timer w/Capture Register	TIO Pos. Edge	t <sub>c</sub>
111	Timer w/Capture Register	TIO Neg. Edge	t <sub>c</sub>

#### TABLE 6. Timer Operating Modes

# Timer/Counter (Continued)





#### MODE 3. TIMER WITH CAPTURE REGISTER

Timer T1 can be used to precisely measure external frequencies or events in this mode of operation. The timer T1 counts down at the instruction cycle rate. Upon the occurrence of a specified edge on the TIO pin the contents of the timer T1 are copied into the register R1. Bits in the control register CNTRL allow the trigger edge to be specified either as a positive edge or as a negative edge. In this mode the user can elect to be interrupted on the specified trigger edge (*Figure 10*).



FIGURE 10. Timer Capture Mode Block Diagram

#### TIMER PWM APPLICATION

*Figure 11* shows how a minimal component D/A converter can be built out of the Timer-Register pair in the Auto-Reload mode. The timer is placed in the "Timer with auto reload" mode and the TIO pin is selected as the timer output. At the outset the TIO pin is set high, the timer T1 holds the on time and the register R1 holds the signal off time. Setting TRUN bit starts the timer which counts down at the instruction cycle rate. The underflow toggles the TIO output and copies the off time into the timer, which continues to run. By alternately loading in the on time and the off time at each successive interrupt a PWM frequency can be easily generated.



FIGURE 11. Timer Application

# WATCHDOG

The device has an on-board 8-bit WATCHDOG timer. The timer contains an 8-bit READ/WRITE down counter clocked by an 8-bit prescaler. Under software control the timer can be dedicated for the WATCHDOG or used as a general purpose counter. *Figure 12* shows the WATCHDOG timer block diagram.

#### MODE 1: WATCHDOG TIMER

The WATCHDOG is designed to detect user programs getting stuck in infinite loops resulting in loss of program control or "runaway" programs. The WATCHDOG can be enabled or disabled (only once) after the device is reset as a result of brown out reset or external reset. On power-up the WATCH-DOG is disabled. The WATCHDOG is enabled by writing a "1" to WDREN bit (resides in WDREG register). Once enabled, the user program should write periodically into the 8-bit counter before the counter underflows. The 8-bit counter (WDCNT) is memory mapped at address 0CE Hex. The counter is loaded with n-1 to get n counts. The counter underflow resets the device, but does not disable the WATCHDOG. Loading the 8-bit counter initializes the prescaler with FF Hex and starts the prescaler/counter. Prescaler and counter are stopped upon counter underflow. Prescaler and counter are each loaded with FF Hex when the device goes into the HALT mode. The prescaler is used for crystal/ resonator start-up when the device exits the HALT mode through Multi-Input Wakeup. In this case, the prescaler/ counter contents are changed.

# WATCHDOG (Continued)

#### MODE 2: TIMER

In this mode, the prescaler/counter is used as a timer by keeping the WDREN (WATCHDOG reset enable) bit at 0. The counter underflow sets the WDUDF (underflow) bit and the underflow does not reset the device. Loading the 8-bit counter (load n-1 for n counts) sets the WDTEN bit (WATCH-DOG Timer Enable) to "1", loads the prescaler with FF, and

starts the timer. The counter underflow stops the timer. The WDTEN bit serves as a start bit for the WATCHDOG timer. This bit is set when the 8-bit counter is loaded by the user program. The load could be as a result of WATCHDOG service (WATCHDOG timer dedicated for WATCHDOG function) or write to the counter (WATCHDOG timer used as a general purpose counter). The bit is cleared upon Brown Out reset, WATCHDOG reset or external reset. The bit is not memory mapped and is transparent to the user program.

#### TABLE 7. WATCHDOG Control/Status

	HALT	WD	EXT/BOR	Counter
Parameter	Mode	Reset	Reset	Load
			(Note 10)	
8-Bit Prescaler	FF	FF	FF	FF
8-Bit WD Counter	FF	FF	FF	User Value
WDREN Bit	Unchanged	Unchanged	0	No Effect
WDUDF Bit	0	Unchanged	0	0
WDTEN Signal	Unchanged	0	0	1

Note 10: BOR is Brown Out Reset.

#### CONTROL/STATUS BITS

#### WDUDF: WATCHDOG Timer Underflow Bit

This bit resides in the CNTRL2 Register. The bit is set when the WATCHDOG timer underflows. The underflow resets the device if the WATCHDOG reset enable bit is set (WDREN = 1). Otherwise, WDUDF can be used as the timer underflow flag. The bit is cleared upon Brown-Out reset, external reset, load to the 8-bit counter, or going into the HALT mode. It is a read only bit.

WDREN: WD Reset Enable

WDREN bit resides in a separate register (bit 0 of WDREG). This bit enables the WATCHDOG timer to generate a reset. The bit is cleared upon Brown Out reset, or external reset. The bit under software control can be written to only once (once written to, the hardware does not allow the bit to be changed during program execution).

WDREN = 1 WATCHDOG reset is enabled.

WDREN = 0 WATCHDOG reset is disabled.

*Table 7* shows the impact of Brown Out Reset, WATCHDOG Reset, and External Reset on the Control/Status bits.

# WATCHDOG (Continued)



FIGURE 12. WATCHDOG Timer Block Diagram

# **Modulator/Timer**

The Modulator/Timer contains an 8-bit counter and an 8-bit autoreload register (MODRL address 0CF Hex). The Modulator/Timer has two modes of operation, selected by the control bit MC3. The Modulator/Timer Control bits MC1, MC2 and MC3 reside in CNTRL2 Register.

#### MODE 1: MODULATOR

The Modulator is used to generate high frequency pulses on the modulator output pin (L7). The L7 pin should be configured as an output. The number of pulses is determined by the 8-bit down counter. Under software control the modulator input clock can be either CKI or tC. The t<sub>c</sub> clock is derived by dividing down the oscillator clock by a factor of 10. Three control bits (MC1, MC2, and MC3) are used for the Modulator/Timer output control. When MC2 = 1 and MC3 = 1, CKI is used as the modulator input clock. When MC2 = 0, and MC3 = 1,  $t_c$  is used as the modulator input clock. The user loads the counter with the desired number of counts (256 max) and sets MC1 to start the counter. The modulator autoreload register is loaded with n-1 to get n pulses. CKI or  $t_{\rm c}$  pulses are routed to the modulator output (L7) until the counter underflows (Figure 13). Upon underflow the hardware resets MC1 and stops the counter. The L7 pin goes low and stays low until the counter is restarted by the user program. The user program has the responsibility to timeout the

low time. Unless the number of counts is changed, the user program does not have to load the counter each time the counter is started. The counter can simply be started by setting the MC1 bit. Setting MC1 by software will load the counter with the value of the autoreload register. The software can reset MC1 to stop the counter.

#### MODE 2: PWM TIMER

The counter can also be used as a PWM Timer. In this mode, an 8-bit register is used to serve as an autoreload register (MODRL).

#### a. 50% Duty Cycle:

When MC1 is 1 and MC2, MC3 are 0, a 50% duty cycle free running signal is generated on the L7 output pin (*Figure 14*). The L7 pin must be configured as an output pin. In this mode the 8-bit counter is clocked by tC. Setting the MC1 control bit by software loads the counter with the value of the autore-load register and starts the counter. The counter underflow toggles the (L7) output pin. The 50% duty cycle signal will be continuously generated until MC1 is reset by the user program.

# COP820CJ/COP840CJ Family

# Modulator/Timer (Continued)

#### b. Variable Duty Cycle:

When MC3 = 0 and MC2 = 1, a variable duty cycle PWM signal is generated on the L7 output pin. The counter is clocked by tC. In this mode the 16-bit timer T1 along with the 8-bit down counter are used to generate a variable duty cycle PWM signal. The timer T1 underflow sets MC1 which starts the down counter and it also sets L7 high (L7 should be configured as an output). When the counter underflows the MC1 control bit is reset and the L7 output will go low until the next timer T1 underflow. Therefore, the width of the output pulse is controlled by the 8-bit counter and the pulse duration is controlled by the 16-bit timer T1 (*Figure 15*). Timer T1 must be configured in "PWM Mode/Toggle TIO Out" (CNTRL1 Bits 7,6,5 = 101).

*Table 8* shows the different operation modes for the Modulator/Timer.

	T/	ABLE 8	3. Modulator/Timer Modes								
Con	trol Bi	ts in	Operation Mode								
	'RL2(00	)CC)	L7 Function								
MC3	MC2	MC1									
0	0	0	Normal I/O								
0	0	1	50% Duty Cycle Mode (Clocked by								
			t <sub>c</sub> )								
0	1	Х	Variable Duty Cycle Mode (Clocked								
			by $t_c$ ) Using Timer 1 Underflow								
1	0	Х	Modulator Mode (Clocked by $t_c$ )								
1	1	Х	Modulator Mode (Clocked by CKI)								

Note 11: MC1, MC2 and MC3 control bits are cleared upon reset.









The device has one differential comparator. Ports L0–L2 are used for the comparator. The output of the comparator is brought out to a pin. Port L has the following assignments:

- L0 Comparator output
- L1 Comparator negative input
- L2 Comparator positive input

#### THE COMPARATOR STATUS/CONTROL BITS

These bits reside in the CNTRL2 Register (Address 0CC) CMPEN Enables comparator ("1" = enable) CMPRD Reads comparator output internally CMPOE Enables comparator output to pin L0 ("1"=enable), CMPEN bit must be set to enable this function. If CMPEN=0, L0 will be 0.

The Comparator Select/Control bits are cleared on RESET (the comparator is disabled). To save power the program should also disable the comparator before the device enters the HALT mode.

The user program must set up L0, L1 and L2 ports correctly for comparator Inputs/Output: L1 and L2 need to be configured as inputs and L0 as output. See *Table 9*.

#### **TABLE 9. Comparator DC and AC Characteristics**

 $4V \le V_{CC} \le 6V, -40^{\circ}C \le T_A \le + 85^{\circ}C$  (Note 7)

Parameters	Conditions	Min	Туре	Max	Units
Input Offset Voltage	$0.4V < V_{IN} < V_{CC} - 1.5V$		±10	±25	mV
Input Common Mode Voltage Range		0.4		V <sub>CC</sub> – 1.5	V
Voltage Gain			300k		V/V
DC Supply Current (when enabled)	$V_{\rm CC} = 6.0 V$			250	μA
Response Time	100 mV Overdrive	60	100	140	ns
	500 mV Overdrive	80	125	165	ns
	1000 mV Overdrive	135	215	300	ns
Note 12: For comparator output current character	eristics see L-Port specs.	*	•	*	1

# **Multi-Input Wake Up**

The Multi-Input Wakeup feature is used to return (wakeup) the device from the HALT mode. *Figure 16* shows the Multi-Input Wakeup logic.

This feature utilizes the L Port. The user selects which particular L port bit or combination of L Port bits will cause the device to exit the HALT mode. Three 8-bit memory mapped registers, Reg:WKEN, Reg:WKEDG, and Reg:WKPND are used in conjunction with the L port to implement the Multi-Input Wakeup feature.

All three registers Reg:WKEN, Reg:WKPND, and Reg:WKEDG are read/write registers, and are cleared at reset, except WKPND. WKPND is unknown on reset.

The user can select whether the trigger condition on the selected L Port pin is going to be either a positive edge (low to high transition) or a negative edge (high to low transition). This selection is made via the Reg:WKEDG, which is an 8-bit control register with a bit assigned to each L Port pin. Setting the control bit will select the trigger condition to be a negative edge on that particular L Port pin. Resetting the bit selects the trigger condition to be a positive edge. Changing an edge select entails several steps in order to avoid a pseudo Wakeup condition as a result of the edge change. First, the associated WKEN bit should be reset, followed by the edge select change in WKEDG. Next, the associated WKEN bit should be cleared, followed by the associated WKEN bit being re-enabled.

An example may serve to clarify this procedure. Suppose we wish to change the edge select from positive (low going high) to negative (high going low) for L port bit 5, where bit 5 has previously been enabled for an input. The program would be as follows:

- RBIT 5, WKEN ; Disable MIWU
- SBIT 5, WKEDG ; Change edge polarity
- RBIT 5, WKPND ; Reset pending flag

SBIT 5, WKEN ; Enable MIWU

If the L port bits have been used as outputs and then changed to inputs with Multi-Input Wakeup, a safety procedure should also be followed to avoid inherited pseudo wakeup conditions. After the selected L port bits have been changed from output to input but before the associated WKEN bits are enabled, the associated edge select bits in WKEDG should be set or reset for the desired edge selects, followed by the associated WKPND bits being cleared. This same procedure should be used following RESET, since the L port inputs are left floating as a result of RESET.

The occurrence of the selected trigger condition for Multi-Input Wakeup is latched into a pending register called Reg:WKPND. The respective bits of the WKPND register will be set on the occurrence of the selected trigger edge on the corresponding Port L pin. The user has the responsibility of clearing these pending flags. Since the Reg:WKPND is a pending register for the occurrence of selected wakeup conditions, the device will not enter the HALT mode if any Wakeup bit is both enabled and pending. Setting the G7 data bit under this condition will not allow the device to enter the HALT mode. Consequently, the user has the responsibility of clearing the pending flags before attempting to enter the HALT mode. If a crystal oscillator is being used, the Wakeup signal will not start the chip running immediately since crystal oscillators have a finite start up time. The WATCHDOG timer prescaler generates a fixed delay to ensure that the oscillator has indeed stabilized before allowing the device to execute instructions. In this case, upon detecting a valid Wakeup signal only the oscillator circuitry and the WATCHDOG timer are enabled. The WATCHDOG timer prescaler is loaded with a value of FF Hex (256 counts) and is clocked from the  $t_c$  instruction cycle clock. The  $t_c$  clock is derived by dividing down the oscillator clock by a factor of 10. A Schmitt trigger following the CKI on chip inverter ensures that the WATCHDOG timer is clocked only when the oscillator has a sufficiently large amplitude to meet the Schmitt trigger specs. This Schmitt trigger is not part of the oscillator closed loop. The startup timeout from the WATCHDOG timer enables the clock signals to be routed to the rest of the chip.



FIGURE 16. Multi-Input Wakeup Logic

#### **INTERRUPTS**

The device has a sophisticated interrupt structure to allow easy interface to the real world. There are three possible interrupt sources, as shown below.

— A maskable interrupt on external G0 input (positive or negative edge sensitive under software control)

- A maskable interrupt on timer carry or timer capture

- A non-maskable software/error interrupt on opcode zero

#### **INTERRUPT CONTROL**

The GIE (global interrupt enable) bit enables the interrupt function. This is used in conjunction with ENI and ENTI to select one or both of the interrupt sources. This bit is reset when interrupt is acknowledged.

ENI and ENTI bits select external and timer interrupts respectively. Thus the user can select either or both sources to interrupt the microcontroller when GIE is enabled.

IEDG selects the external interrupt edge (0 = rising edge, 1 = falling edge). The user can get an interrupt on both rising and falling edges by toggling the state of IEDG bit after each interrupt.

IPND and TPND bits signal which interrupt is pending. After an interrupt is acknowledged, the user can check these two bits to determine which interrupt is pending. This permits the interrupts to be prioritized under software. The

### Multi-Input Wake Up (Continued)

pending flags have to be cleared by the user. Setting the GIE bit high inside the interrupt subroutine allows nested interrupts.

The software interrupt does not reset the GIE bit. This means that the controller can be interrupted by other interrupt sources while servicing the software interrupt.

#### INTERRUPT PROCESSING

The interrupt, once acknowledged, pushes the program counter (PC) onto the stack and the stack pointer (SP) is decremented twice. The Global Interrupt Enable (GIE) bit is reset to disable further interrupts. The microcontroller then vectors to the address 00FFH and resumes execution from that address. This process takes 7 cycles to complete. At the end of the interrupt subroutine, any of the following three instructions return the processor back to the main program: RET, RETSK or RETI. Either one of the three instructions will pop the stack into the program counter (PC). The stack pointer is then incremented twice. The RETI instruction additionally sets the GIE bit to re-enable further interrupts.

Any of the three instructions can be used to return from a hardware interrupt subroutine. The RETSK instruction should be used when returning from a software interrupt subroutine to avoid entering an infinite loop.

Note: There is always the possibility of an interrupt occurring during an instruction which is attempting to reset the GIE bit or any other interrupt enable bit. If this occurs when a single cycle instruction is being used to reset the interrupt enable bit, the interrupt enable bit will be reset but an interrupt may still occur. This is because interrupt processing is started at the same time as the interrupt bit is being reset. To avoid this scenario, the user should always use a two, three, or four cycle instruction to reset interrupt enable bits.

#### DETECTION OF ILLEGAL CONDITIONS

The device incorporates a hardware mechanism that allows it to detect illegal conditions which may occur from coding errors, noise, and "brown out" voltage drop situations. Specifically, it detects cases of executing out of undefined ROM area and unbalanced tack situations.

Reading an undefined ROM location returns 00 (hexadecimal) as its contents. The opcode for a software interrupt is also "00". Thus a program accessing undefined ROM will cause a software interrupt.

Reading an undefined RAM location returns an FF (hexadecimal). The subroutine stack on the device grows down for each subroutine call. By initializing the stack pointer to the top of RAM, the first unbalanced return instruction will cause the stack pointer to address undefined RAM. As a result the program will attempt to execute from FFFF (hexadecimal), which is an undefined ROM location and will trigger a software interrupt.



FIGURE 17. Interrupt Block Diagram

# **Control Registers**

#### CNTRL1 REGISTER (ADDRESS 00EE)

TC3	TC2	TC1	TRUN	MSEL	IEDG	SL1	SL0					
Bit 7							Bit 0					
The Timer and MICROWIRE control register contains the fol- lowing bits:												
lowing bits.												
TC3		Timer	Timer T1 Mode Control Bit									
TC2		Timer	Timer T1 Mode Control Bit									
TC1		Timer	Timer T1 Mode Control Bit									
TRUN		Used	to start	and stop	the tim	er/coun	ter					
		(1 = 1	un, 0 =	stop)								
MSEL		Selec SK ai	ts G5 ai nd SO re	nd G4 as espective	s MICRO	OWIRE	signals					
IEDG		Exter	nal inter	rupt edge	e polarit	y select						
SL1 ar	nd SL0	Selec	t the MI	CROWIF	RE clock	divide-	by					
		(00 =	2, 01 =	4, 1x =	8)							

#### **PSW REGISTER (ADDRESS 00EF)**

HC	С	TPND	ENTI	IPND	BUSY	ENI	GIE
Bit 7							Bit 0

The PSW register contains the following select bits:

- HC Half-Carry Flip/Flop
- C Carry Flip/Flop
- TPND Timer T1 interrupt pending
- (timer Underflow or capture edge)
- ENTI Timer T1 interrupt enable
- IPND External interrupt pending
- BUSY MICROWIRE busy shifting flag
- ENI External interrupt enable
- GIE Global interrupt enable (enables interrupts)

The Half-Carry bit is also effected by all the instructions that effect the Carry flag. The flag values depend upon the instruction. For example, after executing the ADC instruction the values of the Carry and the Half-Carry flag depend upon the operands involved. However, instructions like SET C and RESET C will set and clear both the carry flags. *Table 10* lists the instructions that effect the HC and the C flags.

#### TABLE 10. Instructions Effecting HC and C Flags

Instr.	HC Flag	C Flag
ADC	Depends on	Depends on
	Operands	Operands
SUBC	Depends on	Depends on
	Operands	Operands
SET C	Set	Set
RESET C	Set	Set
RRC	Depends on	Depends on
	Operands	Operands

#### CNTRL2 REGISTER (ADDRESS 00CC)

МС3	MC2	MC1	CMPEN	CMPRD	CMPOE	WDUDF	unused						
R/W	R/W	R/W	R/W	R/O	R/W	R/O							
Bit 7							Bit 0						
MC3 Modulator/Timer Control Bit													
MC2	Ν	Modulator/Timer Control Bit											
MC1	Ν	/lodula	tor/Time	r Control	Bit								
CMPE	EN C	Compa	rator Ena	able Bit									
CMPF	RD C	Compa	rator Re	ad Bit									
CMP	DE C	Compa	rator Ou	tput Enal	ole Bit								
WDU	DF V	VATCH	HDOG Ti	mer Und	erflow Bi	t (Read C	Only)						

#### WDREG REGISTER (ADDRESS 00CD)

	UNUSED	WDREN
Bit 7		Bit 0
	WATCHDOC Baset Enable	Rit (Mrite Once Only)

WDREN WATCHDOG Reset Enable Bit (Write Once Only)

# **Memory Map**

All RAM, ports and registers (except A and PC) are mapped into data memory address space.

Address	Contents
00 to 2F	On-chip RAM bytes (48 bytes)
(820CJ)	
00 to 6F	On-chip RAM bytes (112 bytes)
(840CJ)	
30 to 7F	Unused RAM Address Space (Reads as All
(820CJ)	Unes)
/U to /F	Unused RAM Address Space (Reads as All
(040CJ)	Expansion Space for On-Chin EERAM
	(Reads Undefined Data)
C0 to C7	Reserved
C8	MIWU Edge Select Register (Reg:WKEDG)
C9	MIWU Enable Register (Reg:WKEN)
CA	MIWU Pending Register (Reg:WKPND)
СВ	Reserved
СС	Control2 Register (CNTRL2)
CD	WATCHDOG Register (WDREG)
CE	WATCHDOG Counter (WDCNT)
CF	Modulator Reload (MODRL)
D0	Port L Data Register
D1	Port L Configuration Register
D2	Port L Input Pins (Read Only)
D3	Reserved for Port L
D4	Port G Data Register
D5	Port G Configuration Register
D6	Port G Input Pins (Read Only)
D7	Port I Input Pins (Read Only)
D8 to DB	Reserved for Port C
DC	Port D Data Register
DD to DF	Reserved for Port D
E0 to EF	On-Chip Functions and Registers
E0 to E7	Reserved for Future Parts
E8	Reserved
E9	MICROWIRE Shift Register
EA	Timer Lower Byte
EB	Timer Upper Byte
EC	Timer1 Autoreload Register Lower Byte
ED	Timer1 Autoreload Register Upper Byte
EE	CNTRL1 Control Register
EF	PSW Register
F0 to FF	On-Chip RAM Mapped as Registers
FC	X Register
FD	SP Register
FE	B Register

Reading other unused memory locations will return undefined data.

# **Addressing Modes**

There are ten addressing modes, six for operand addressing and four for transfer of control.

#### **OPERAND ADDRESSING MODES**

#### REGISTER INDIRECT

This is the "normal" addressing mode for the chip. The operand is the data memory addressed by the **B** or **X** pointer.

REGISTER INDIRECT WITH AUTO POST INCREMENT OR DECREMENT

This addressing mode is used with the LD and X instructions. The operand is the data memory addressed by the **B** or **X** pointer. This is a register indirect mode that automatically post increments or post decrements the **B** or **X** pointer after executing the instruction.

#### DIRECT

The instruction contains an 8-bit address field that directly points to the data memory for the operand.

#### IMMEDIATE

The instruction contains an 8-bit immediate field as the operand.

#### SHORT IMMEDIATE

This addressing mode issued with the LD B,# instruction, where the immediate # is less than 16. The instruction contains a 4-bit immediate field as the operand.

#### INDIRECT

This addressing mode is used with the LAID instruction. The contents of the accumulator are used as a partial address (lower 8 bits of PC) for accessing a data operand from the program memory.

### TRANSFER OF CONTROL ADDRESSING MODES

#### RELATIVE

This mode is used for the JP instruction with the instruction field being added to the program counter to produce the next instruction address. JP has a range from -31 to +32 to allow a one byte relative jump (JP + 1 is implemented by a NOP instruction). There are no "blocks" or "pages" when using JP since all 15 bits of the PC are used.

#### ABSOLUTE

This mode is used with the JMP and JSR instructions with the instruction field of 12 bits replacing the lower 12 bits of the program counter (PC). This allows jumping to any location in the current 4k program memory segment.

#### ABSOLUTE LONG

This mode is used with the JMPL and JSRL instructions with the instruction field of 15 bits replacing the entire 15 bits of the program counter (PC). This allows jumping to any location in the entire 32k program memory space.

#### INDIRECT

This mode is used with the JID instruction. The contents of the accumulator are used as a partial address (lower 8 bits of PC) for accessing a location in the program memory. The contents of this program memory location serves as a partial address (lower 8 bits of PC) for the jump to the next instruction.

# **Instruction Set**

#### REGISTER AND SYMBOL DEFINITIONS

#### Registers

- A 8-bit Accumulator register
- B 8-bit Address register
- X 8-bit Address register
- SP 8-bit Stack pointer register
- PC 15-bit Program counter register
- PU upper 7 bits of PC
- PL lower 8 bits of PC
- C 1-bit of PSW register for carry
- HC Half Carry
- GIE 1-bit of PSW register for global interrupt enable

#### INSTRUCTION SET

#### Symbols

- [B] Memory indirectly addressed by B register
- [X] Memory indirectly addressed by X register
- Mem Direct address memory or [B]
- MemI Direct address memory or [B] or Immediate data Imm 8-bit Immediate data
- Reg Register memory: addresses F0 to FF (Includes B, X and SP)
- Bit Bit number (0 to 7)
- $\leftarrow \qquad \text{Loaded with} \qquad$
- $\leftrightarrow$  Exchanged with

ADD	add	$A \leftarrow A + Meml$
ADC	add with carry	$A \leftarrow A + Meml + C, C \leftarrow Carrv$
		$HC \leftarrow Half Carry$
SUBC	subtract with carry	$A \leftarrow A + \overline{Mem} + C. C \leftarrow Carry$
		$HC \leftarrow Half Carry$
AND	Logical AND	$A \leftarrow A$ and MemI
OR	Logical OR	$A \leftarrow A$ or MemI
XOR	Logical Exclusive-OR	$A \leftarrow A$ xor Meml
IFEQ	IF equal	Compare A and MemI, Do next if A = MemI
IFGT	IF greater than	Compare A and Meml, Do next if A > Meml
IFBNE	IF B not equal	Do next if lower 4 bits of B ≠ Imm
DRSZ	Decrement Reg. ,skip if zero	Reg $\leftarrow$ Reg – 1, skip if Reg goes to 0
SBIT	Set bit	1 to bit, Mem (bit= 0 to 7 immediate)
RBIT	Reset bit	0 to bit, Mem
IFBIT	If bit	If bit, Mem is true, do next instr.
Х	Exchange A with memory	$A \leftrightarrow Mem$
LD A	Load A with memory	A ← MemI
LD mem	Load Direct memory Immed.	$Mem \leftarrow Imm$
LD Reg	Load Register memory Immed.	Reg ← Imm
Х	Exchange A with memory [B]	$A \leftrightarrow [B] \qquad (B \leftarrow B \pm 1)$
Х	Exchange A with memory [X]	$A \leftrightarrow [X] \qquad (X \leftarrow X \pm 1)$
LD A	Load A with memory [B]	$A \leftarrow [B] \qquad (B \leftarrow B \pm 1)$
LD A	Load A with memory [X]	$A \leftarrow [X] \qquad (X \leftarrow X \pm 1)$
LD M	Load Memory Immediate	$[B] \gets Imm \; (B \gets B{\pm}1)$
CLRA	Clear A	$A \leftarrow 0$
INCA	Increment A	$A \leftarrow A + 1$
DECA	Decrement A	$A \leftarrow A - 1$
LAID	Load A indirect from ROM	$A \leftarrow ROM(PU,A)$
DCORA	DECIMAL CORRECT A	$A \leftarrow BCD$ correction (follows ADC, SUBC)
RRCA	ROTATE A RIGHT THRU C	$C \rightarrow A7 \rightarrow \rightarrow A0 \rightarrow C$
SWAPA	Swap nibbles of A	A7 A4 $\leftrightarrow$ A3 A0
SC	Set C	$C \leftarrow 1, HC \leftarrow 1$
RC	Reset C	$C \leftarrow 0, HC \leftarrow 0$
IFC	If C	If C is true, do next instruction
IFNC	If not C	If C is not true, do next instruction
JMPL	Jump absolute long	$PC \leftarrow ii$ (ii = 15 bits, 0 to 32k)

# COP820CJ/COP840CJ Family

# Instruction Set (Continued)

INSTRUCTIO	N SET (Continued)	
JMP	Jump absolute	PC110 ← i (i = 12 bits)
JP	Jump relative short	$PC \leftarrow PC + r (r \text{ is } -31 \text{ to } +32, \text{ not } 1)$
JSRL	Jump subroutine long	$[SP] \gets PL, [SP-1] \gets PU, SP-2, PC \gets ii$
JSR	Jump subroutine	$[SP] \leftarrow PL, [SP-1] \leftarrow PU, SP-2, PC11 \ 0 \leftarrow i$
JID	Jump indirect	$PL \leftarrow ROM(PU,A)$
RET	Return from subroutine	$SP+2,PL \leftarrow [SP],PU \leftarrow [SP-1]$
RETSK	Return and Skip	SP+2,PL $\leftarrow$ [SP],PU $\leftarrow$ [SP-1],Skip next instruction
RETI	Return from Interrupt	$SP+2,PL \leftarrow [SP],PU \leftarrow [SP-1],GIE \leftarrow 1$
INTR	Generate an interrupt	$[SP] \gets PL, [SP-1] \gets PU, SP-2, PC \gets 0FF$
NOP	No operation	$PC \leftarrow PC + 1$

# **Opcode Table**

		1													0-	ts 3	i8																
		0	-	<u>،</u>	1	с		4		5		9		2		ω		റ		A		ш		ပ				ш		ш			
	0	INTR	JP+2	Etdl.	2	JP+4		JP+5		9+dſ		7+4L		JP+8		9+4		JP+10		JP+11		JP+12		JP+13		JP+14		JP+15		JP+16			
	1	JP+17	JP+18	IP+10	2 - 5	JP+20		JP+21		JP+22		JP+23		JP+24		JP+25		JP+26		JP+27		JP+28		JP+29		JP+30		JP+31		JP+32			
	2	JMP 0000-00FF	JMP 0100-01FF	dWI.	0200-02FF	JMP	0300-03FF	JMP	0400-04FF	JMP	0500-05FF	JMP	0600-06FF	JMP	0700-07FF	JMP	0800-08FF	JMP	0900-09FF	JMP	0A00-0AFF	JMP	0B00-0BFF	JMP	0C00-0CFF	JMP	0D00-0DFF	JMP	0E00-0EFF	JMP	0F00-0FFF		
	3	JSR 0000-00FF	JSR 0100-01FF	and and	0200-02FF	JSR	0300-03FF	JSR	0400-04FF	JSR	0500-05FF	JSR	0600-06FF	JSR	0700-07FF	JSR	0800-08FF	JSR	0900-09FF	JSR	0A00-0AFF	JSR	0B00-0BFF	JSR	0C00-0CFF	JSR	0D00-0DFF	JSR	0E00-0EFF	JSR	0F00-0FFF		
	4	IFBNE 0	IFBNE 1	IFRNF 2		IFBNE 3		IFBNE 4		IFBNE 5		IFBNE 6		IFBNE 7		IFBNE 8		IFBNE 9		IFBNE	0A	IFBNE	0B	IFBNE	00	IFBNE	0D	IFBNE	0E	IFBNE	0F		
	5	LD B.0F	LD B OF		B,0D	ΓD	B,0C	LD	B,0B	LD	B,0A	LD B,9		LD B,8		LD B,7		LD B,6		LD B,5		LD B,4		LD B,3		LD B,2		LD B,1		LD B,0			
4-	9	*	*	*		*		CLRA		SWAPA		DCORA		*		RBIT	0,[B]	RBIT	1,[B]	RBIT	2,[B]	RBIT	3,[B]	RBIT	4,[B]	RBIT	5,[B]	RBIT	6,[B]	RBIT	7,[B]		
Bits 7	7	IFBIT 0.[B]	1 [B]T	FRIT	2,[B]	IFBIT	3,[B]	IFBIT	4,[B]	IFBIT	5,[B]	IFBIT	6,[B]	IFBIT	7,[B]	SBIT	0,[B]	SBIT	1,[B]	SBIT	2,[B]	SBIT	3,[B]	SBIT	4,[B]	SBIT	5,[B]	SBIT	6,[B]	SBIT	7,[B]		
	8	ADC A.[B]	SUBC A IB1	DHHI	A,[B]	IFGT	A,[B]	ADD	A,[B]	AND	A,[B]	XOR	A,[B]	OR	A,[B]	IFC		IFNC		INCA		DECA		*		RETSK		RET		RETI			
	6	ADC A.#i	SUBC A #i	IFFO	н _ с А,#i	IFGT	A,#i	ADD	A,#i	AND	A,#i	XOR	A,#i	OR	A,#i	LD A,#i		*		LD	[B+],#i	ΓD	[B-],#i	X A,Md		Г	A,Md	ГD	[B],#i	*			
	A	RC	sc	×	A,[B+]	×	A,[B-]	LAID		JID		Х	A,[B]	*		*		*		ΓD	A,[B+]	ΓD	A,[B-]	JMPL		JSRL		Γ	A,[B]	*			
	В	RRCA	*	×	A,[X+]	×	A,[X–]	*		*		X A,[X]		*		NOP		*		ΓD	A,[X+]	LD	A,[X-]	LD	Md,#i	DIR		LD	A,[X]	*			
	ပ	DRSZ	DRSZ 0F1	DR:S7	0F2	DRSZ	0F3	DRSZ	0F4	DRSZ	0F5	DRSZ	0F6	DRSZ	0F7	DRSZ	0F8	DRSZ	0F9	DRSZ	0FA	DRSZ	0FB	DRSZ	OFC	DRSZ	0FD	DRSZ	OFE	DRSZ	0FF		ation
	D	LD 0F0, #i	LD 0F1,#i	I D 0F2 #i	) 2 1	LD 0F3,#i		LD 0F4,#i		LD 0F5,#i		LD 0F6,#i		LD 0F7,#i		LD 0F8,#i		LD 0F9,#i		LD 0FA,#i		LD 0FB,#i		LD 0FC,#i		LD 0FD,#i		LD 0FE,#i		LD 0FF,#i		ta	sed memory loc
	ш	JP-31	JP-30	0C-01	5	JP-28		JP-27		JP-26		JP-25		JP-24		JP-23		JP-22		JP-21		JP-20		JP-19		JP-18		JP-17		JP-16		mediate da	sctly addres
	L	JP-15	JP-14	ID-13	5	JP-12		JP-11		JP-10		JP-9		JP-8		JP-7		JP-6		JP-5		JP-4		JP-3		JP-2		JP-1		JP-0		Where, i is the im	Md is a dir€

Instruction Set (Continued)

# Instruction Execution Time

Most instructions are single byte (with immediate addressing mode instruction taking two bytes).

Most single instructions take one cycle time to execute.

Skipped instructions require x number of cycles to be skipped, where x equals the number of bytes in the skipped instruction opcode.

See the BYTES and CYCLES per INSTRUCTION table for details.

#### Bytes and Cycles per Instruction

The following table shows the number of bytes and cycles for each instruction in the format of byte/cycle.

#### Arithmetic Instructions (Bytes/Cycles)

	[B]	Direct	Immed.
ADD	1/1	3/4	2/2
ADC	1/1	3/4	2/2
SUBC	1/1	3/4	2/2
AND	1/1	3/4	2/2
OR	1/1	3/4	2/2
XOR	1/1	3/4	2/2
IFEQ	1/1	3/4	2/2
IFGT	1/1	3/4	2/2
IFBNE	1/1		
DRSZ		1/3	
SBIT	1/1	3/4	
RBIT	1/1	3/4	
IFBIT	1/1	3/4	

#### Instructions Using A & C

Instructions	Bytes/Cycles
CLRA	1/1
INCA	1/1
DECA	1/1
LAID	1/3
DCOR	1/1
RRCA	1/1
SWAPA	1/1
SC	1/1
RC	1/1
IFC	1/1
IFNC	1/1

#### Transfer of Control Instructions

Instructions	Bytes/Cycles
JMPL	3/4
JMP	2/3
JP	1/3
JSRL	3/5
JSR	2/5
JID	1/3
RET	1/5
RETSK	1/5
RETI	1/5
INTR	1/7
NOP	1/1

#### Memory Transfer Instructions (Bytes/Cycles)

	Register				Register Indirect		
	Indi	rect	Direct	Immed.	Auto Incr & Decr		
	[B]	[X]			[B+, B–]	[X+, X–]	
X A,*	1/1	1/3	2/3		1/2	1/3	
LD A,*	1/1	1/3	2/3	2/2	1/2	1/3	
LD B,Imm				1/1			(If B < 16)
LD B,Imm				2/3			(If B > 15)
LD			3/3		2/2		
Mem,Imm							
LD				2/3			
Reg,Imm							

\* = > Memory location addressed by B or X or directly.

The following table shows the instructions assigned to unused opcodes. This table is for information only. The operations performed are subject to change without notice. Do not use these opcodes.

Unused	Instruction	Unused	Instruction
Opcode		Opcode	
60	NOP	A9	NOP
61	NOP	AF	LD A, [B]
62	NOP	B1	$C\toHC$
63	NOP	B4	NOP

Unused	Instruction	Unused	Instruction
Opcode		Opcode	
67	NOP	B5	NOP
8C	RET	B7	X A, [X]
99	NOP	B9	NOP
9F	LD [B], #i	BF	LD A, [X]
A7	X A, [B]		
A8	NOP		

# **Mask Options**

The mask programmable options are listed below. The options are programmed at the same time as the ROM pattern to provide the user with hardware flexibility to a variety of oscillation and packaging configuration.

#### **OPTION 1: CKI INPUT**

- = 1 Crystal (CKI/IO) CKO for crystal configuration
- = 2 External (CKI/IO) CKO available as G7 input
- = 3 R/C (CKI/IO) CKO available as G7 input

#### **OPTION 2: BROWN OUT**

- = 1 Enable Brown Out Detection
- = 2 Disable Brown Out Detection

#### **OPTION 3: BONDING**

#### COP820CJ COP840CJ

- = 1 28-pin DIP 28-pin DIP/SO
- = 2 20-pin DIP/SO 20-pin DIP/SO
- = 3 16-pin SO N/A
- = 4 28-pin SO N/A

# **Development Tools Support**

#### OVERVIEW

National is engaged with an international community of independent 3rd party vendors who provide hardware and software development tool support. Through National's interaction and guidance, these tools cooperate to form a choice of solutions that fits each developer's needs.

This section provides a summary of the tool and development kits currently available. Up-to-date information, selection guides, free tools, demos, updates, and purchase information can be obtained at our web site at: www.national.com/cop8.

#### SUMMARY OF TOOLS

#### COP8 Evaluation Tools

- COP8–NSEVAL: Free Software Evaluation package for Windows. A fully integrated evaluation environment for COP8, including versions of WCOP8 IDE (Integrated Development Environment), COP8-NSASM, COP8-MLSIM, COP8C, DriveWay<sup>™</sup> COP8, Manuals, and other COP8 information.
- COP8–MLSIM: Free Instruction Level Simulator tool for Windows. For testing and debugging software instructions only (No I/O or interrupt support).
- COP8–EPU: Very Low cost COP8 Evaluation & Programming Unit. Windows based evaluation and hardware-simulation tool, with COP8 device programmer and erasable samples. Includes COP8-NSDEV, Driveway COP8 Demo, MetaLink Debugger, I/O cables and power supply.
- **COP8–EVAL-ICUxx:** Very Low cost evaluation and design test board for COP8ACC and COP8SGx Families, from ICU. Real-time environment with add-on A/D, D/A, and EEPROM. Includes software routines and reference designs.
- Manuals, Applications Notes, Literature: Available free from our web site at: www.national.com/cop8.

#### COP8 Integrated Software/Hardware Design Development Kits

- COP8-EPU: Very Low cost Evaluation & Programming Unit. Windows based development and hardwaresimulation tool for COPSx/xG families, with COP8 device programmer and samples. Includes COP8-NSDEV, Driveway COP8 Demo, MetaLink Debugger, cables and power supply.
- **COP8-DM:** Moderate cost Debug Module from MetaLink. A Windows based, real-time in-circuit emulation tool with COP8 device programmer. Includes COP8-NSDEV, DriveWay COP8 Demo, MetaLink Debugger, power supply, emulation cables and adapters.

#### **COP8** Development Languages and Environments

- COP8-NSASM: Free COP8 Assembler v5 for Win32. Macro assembler, linker, and librarian for COP8 software development. Supports all COP8 devices. (DOS/Win16 v4.10.2 available with limited support). (Compatible with WCOP8 IDE, COP8C, and DriveWay COP8).
- COP8-NSDEV: Very low cost Software Development Package for Windows. An integrated development environment for COP8, including WCOP8 IDE, COP8-NSASM, COP8-MLSIM.

# **Development Tools Support**

(Continued)

- **COP8C:** Moderately priced C Cross-Compiler and Code Development System from Byte Craft (no code limit). Includes BCLIDE (Byte Craft Limited Integrated Development Environment) for Win32, editor, optimizing C Cross-Compiler, macro cross assembler, BC-Linker, and MetaLink tools support. (DOS/SUN versions available; Compiler is installable under WCOP8 IDE; Compatible with DriveWay COP8).
- EWCOP8-KS: Very Low cost ANSI C-Compiler and Embedded Workbench from IAR (Kickstart version: COP8Sx/Fx only with 2k code limit; No FP). A fully integrated Win32 IDE, ANSI C-Compiler, macro assembler, editor, linker, Liberian, C-Spy simulator/debugger, PLUS MetaLink EPU/DM emulator support.
- **EWCOP8-AS:** Moderately priced COP8 Assembler and Embedded Workbench from IAR (no code limit). A fully integrated Win32 IDE, macro assembler, editor, linker, librarian, and C-Spy high-level simulator/debugger with I/O and interrupts support. (Upgradeable with optional C-Compiler and/or MetaLink Debugger/Emulator support).
- **EWCOP8-BL:** Moderately priced ANSI C-Compiler and Embedded Workbench from IAR (Baseline version: All COP8 devices; 4k code limit; no FP). A fully integrated Win32 IDE, ANSI C-Compiler, macro assembler, editor, linker, librarian, and C-Spy high-level simulator/debugger. (Upgradeable; CWCOP8-M MetaLink tools interface support optional).
- **EWCOP8:** Full featured ANSI C-Compiler and Embedded Workbench for Windows from IAR (no code limit). A fully integrated Win32 IDE, ANSI C-Compiler, macro assembler, editor, linker, librarian, and C-Spy high-level simulator/debugger. (CWCOP8-M MetaLink tools interface support optional).
- **EWCOP8-M:** Full featured ANSI C-Compiler and Embedded Workbench for Windows from IAR (no code limit). A fully integrated Win32 IDE, ANSI C-Compiler, macro assembler, editor, linker, librarian, C-Spy high-level simulator/debugger, PLUS MetaLink debugger/hardware interface (CWCOP8-M).

#### **COP8 Productivity Enhancement Tools**

- WCOP8 IDE: Very Low cost IDE (Integrated Development Environment) from KKD. Supports COP8C, COP8-NSASM, COP8-MLSIM, DriveWay COP8, and MetaLink debugger under a common Windows Project Management environment. Code development, debug, and emulation tools can be launched from the project window framework.
- DriveWay-COP8: Low cost COP8 Peripherals Code Generation tool from Aisys Corporation. Automatically generates tested and documented C or Assembly source code modules containing I/O drivers and interrupt handlers for each on-chip peripheral. Application specific code can be inserted for customization using the integrated editor. (Compatible with COP8-NSASM, COP8C, and WCOP8 IDE.)
- **COP8-UTILS:** Free set of COP8 assembly code examples, device drivers, and utilities to speed up code development.
- **COP8-MLSIM:** Free Instruction Level Simulator tool for Windows. For testing and debugging software instructions only (No I/O or interrupt support).

#### **COP8 Real-Time Emulation Tools**

- COP8-DM: MetaLink Debug Module. A moderately priced real-time in-circuit emulation tool, with COP8 device programmer. Includes COP8-NSDEV, DriveWay COP8 Demo, MetaLink Debugger, power supply, emulation cables and adapters.
- IM-COP8: MetaLink iceMASTER<sup>®</sup>. A full featured, realtime in-circuit emulator for COP8 devices. Includes MetaLink Windows Debugger, and power supply. Packagespecific probes and surface mount adaptors are ordered separately.

#### **COP8** Device Programmer Support

- MetaLink's EPU and Debug Module include development device programming capability for COP8 devices.
- Third-party programmers and automatic handling equipment cover needs from engineering prototype and pilot production, to full production environments.
- Factory programming available for high-volume requirements.

# Development Tools Support (Continued)

#### TOOLS ORDERING NUMBERS FOR THE COP820CJ/COP840CJ FAMILY DEVICES

Vendor	Tools	Order Number	Cost	Notes		
National	COP8-NSEVAL	COP8-NSEVAL	Free	Web site download		
	COP8-NSASM	COP8-NSASM	Free	Included in EPU and DM. Web site download		
	COP8-MLSIM	COP8-MLSIM	Free	Included in EPU and DM. Web site download		
	COP8-NSDEV	COP8-NSDEV	VL	Included in EPU and DM. Order CD from website		
	COP8-EPU	Not available for this device				
	COP8-DM	Contact MetaLink				
	Development Devices	COP87L20/40CJxx COP87L22/42CJxx	VL	4k or 32k OTP devices. No windowed devices		
	OTP Programming	COP8SA-PGMA	L	For programming 16/20/28 SOIC and 44 PLCC on the EPU		
	Adapters	COP8-PGMA-44QFP	L	For programming 44QFP on any programmer		
		COP8-PGMA-28CSP	L	For programming 28CSP on any programmer		
		COP8-PGMA-28SO	VL	For programming 16/20/28 SOIC on any programmer		
	IM-COP8	Contact MetaLink				
MetaLink	COP8-EPU	Not available for this device	ł			
	COP8-DM	DM4-COP8-840CJ (10 MHz), plus PS-10, plus DM-COP8/xxx (ie. 28D)	Μ	Included p/s (PS-10), target cable of choice (DIP or PLCC; i.e. DM-COP8/28D), 16/20/28/40 DIP/SO and 44 PLCC programming sockets. Add OTP adapter (if needed) and target adapter (if needed)		
	DM Target Adapters	MHW-CONVxx (xx = 33, 34 etc.)	L	DM target converters for 16DIP/20/SO/28SO/44QFP/28CSP; (MHW-CNV38 for 20 pin DIP to SO package converter)		
	OTP Programming Adapters	MHW-COP8-PGMA-DS	L	For programming 16/20/28 SOIC and 44 PLCC on the EPU		
IM-COP8		IM-COP8-AD-464 (-220) (10 MHz maximum)	Н	Base unit 10 MHz; -220 = 220V; add probe card (required) and target adapter (if needed); included software and manuals		
		PC-840CJxxDW-AD-10 (xx = 20 or 28)	М	10 MHz 20 or 28 DIP probe card; 2.5V to 6.0V		
	IM Probe Target Adapter	MHW-SOICxx (xx = 16, 20, 28)	L	16 or 20 or 28 pin SOIC adapter for probe card		
ICU or National	COP8-EVAL-ICUxx	Not available for this device				
KKD	WCOP8-IDE	WCOP8-IDE	VL	Included in EPU and DM		
IAR	EWCOP8-xx	See summary above	L-H	Included all software and manuals		
Byte Craft	COP8C	COP8C	М	Included all software and manuals		
Aisys	DriveWay COP8	DriveWay COP8	L	Included all software and manuals		
OTP Prog	rammers	Contact vendors	L - H	For approved programmer listings and vendor information, go to our OTP support page at: www.national.com/cop8		

# **Development Tools Support** (Continued)

#### WHERE TO GET TOOLS

Tools are ordered directly from the following vendors. Please go to the vendor's web site for current listings of distributors.

Vendor	Home Office	Electronic Sites	Other Main Offices
Aisys	U.S.A.: Santa Clara, CA	www.aisysinc.com	Distributors
	1-408-327-8820	info@aisysinc.com	
	fax: 1-408-327-8830		
Byte Craft	U.S.A.	www.bytecraft.com	Distributors
	1-519-888-6911	info@bytecraft.com	
	fax: 1-519-746-6751		
IAR	Sweden: Uppsala	www.iar.se	U.S.A.: San Francisco
	+46 18 16 78 00	info@iar.se	1-415-765-5500
	fax: +46 18 16 78 38	info@iar.com	fax: 1-415-765-5503
		info@iarsys.co.uk	U.K.: London
		info@iar.de	+44 171 924 33 34
			fax: +44 171 924 53 41
			Germany: Munich
			+49 89 470 6022
			fax: +49 89 470 956
ICU	Sweden: Polygonvaegen	www.icu.se	Switzeland: Hoehe
	+46 8 630 11 20	support@icu.se	+41 34 497 28 20
	fax: +46 8 630 11 70	support@icu.ch	fax: +41 34 497 28 21
KKD	Denmark:	www.kkd.dk	
MetaLink	U.S.A.: Chandler, AZ	www.metaice.com	Germany: Kirchseeon
	1-800-638-2423	sales@metaice.com	80-91-5696-0
	fax: 1-602-926-1198	support@metaice.com	fax: 80-91-2386
		bbs: 1-602-962-0013	islanger@metalink.de
		www.metalink.de	Distributors Worldwide
National	U.S.A.: Santa Clara, CA	www.national.com/cop8	Europe: +49 (0) 180 530 8585
	1-800-272-9959	support@nsc.com	fax: +49 (0) 180 530 8586
	fax: 1-800-737-7018	europe.support@nsc.com	Distributors Worldwide

The following companies have approved COP8 programmers in a variety of configurations. Contact your local office or distributor. You can link to their web sites and get the latest listing of approved programmers from National's COP8 OTP Support page at: www.national.com/cop8.

Advantech; Advin; BP Microsystems; Data I/O; Hi-Lo Systems; ICE Technology; Lloyd Research; Logical Devices; MQP; Needhams; Phyton; SMS; Stag Programmers; System General; Tribal Microsystems; Xeltek.

#### Customer Support

Complete product information and technical support is available from National's customer response centers, and from our on-line COP8 customer support sites.



COP820CJ/COP840CJ Family





National Semiconductor Corporation Americas Tel: 1-800-272-9959 Fax: 1-800-737-7018 Email: support@nsc.com

www.national.com

National Semiconductor Europe Fax: +49 (0) 180-530 85 86 Email: europe.support@nsc.com Deutsch Tel: +49 (0) 69 9508 6208 English Tel: +44 (0) 870 24 0 2171 Français Tel: +33 (0) 1 41 91 87 90 National Semiconductor Asia Pacific Customer Response Group Tel: 65-2544466 Fax: 65-2504466 Email: ap.support@nsc.com National Semiconductor Japan Ltd. Tel: 81-3-5639-7560 Email: nsj.crc@jksmtp.nsc.com Fax: 81-3-5639-7507

National does not assume any responsibility for use of any circuitry described, no circuit patent licenses are implied and National reserves the right at any time without notice to change said circuitry and specifications.