DATASENSOR **S60 SERIES INSTRUCTION MANUAL**

CONTROLS

OUTPUT LED (S60...B01/B51/C01/C11/F01/T51) The yellow LED ON indicates that the N.O. (normally open) output status is closed

STABILITY LED (S60...B01/B51/C01/C11/F01) The green LED ON indicates that the received signal has a reserve

greater than 30% compared to the output switching value. POWER ON LED (S60...G00)

The green LED indicates that the sensor is operating.

TRIMMER (S60...B01/B51/C01/C11/F01/T51)

The trimmer can be used to adjust sensitivity; the operating distance increases turning the trimmer clockwise.

WARNING: The trimmer rotation is limited to 270° by a mechanical stop. Do not apply excessive torque when adjusting (max 40 Nmm).

INSTALLATION

The sensor can be positioned by means of the three housing's holes using two screws (M4x25 or longer, 1.5 Nm maximum tightening torque) with washers.

Various orientable fixing brackets to ease the sensor positioning are available (please refer to the accessories listed in the catalogue). The operating distance is measured from the front surface of the sensor optics

The M12 connector can be oriented at two different positions using the specific fastening spring and rotating the block of 180°.

CONNECTIONS

The connections are compliant to the EN 60947-5-2 standard.

S60B01/	B51/C0	1/C11/F01/T51		S60G	00
BROWN		• 10 30 Vdc	BROWN	-1 +	10 30 Vd
WHITE	2	N.C. OUTPUT	WHITE	2	TEST +
BLACK	4	N.O. OUTPUT	BLACK	4	TEST -
BLUE	3	- 0 V	BLUE	3	0 V

M12 CONNECTOR



50 42 N 20 42 18x45° ÐÐ 11 6 **⊂**314

C

STABILITY LED

TRIMMER

OUTPUT LED

POWER ON LED (S60-G00)



TECHN

Ripple: 2 Vpp max. Current consumption (output current excluded): 35 mA max. Outputs: PNP or NPN; 30 Vcc max. (short-circuit protection) Output current: 100 mA max. Output saturation voltage: <2 V Response time: 0.5 ms mod. B01/B51/T51; 1 ms mod. C01/C11/F01 Switching frequency: 1 kHz mod. B01/B51/T51; 500 Hz max. mod. C01/C11/F01 Indicators: OUTPUT LED (YELLOW) Stating: OUTPUT LED (GREEN) (mod. B01/B51/C01/C11/F01) POWER ON LED (GREEN) (mod. G00) Setting: Setting: -25 55 °C Storage temperature: -25 50 °C Electrical shock protection: Class 2 Operating distance (typical values): B01: 0.16 m on R2 Emission type: RED (660 nm) mod.B01/B51/C01/T51; INFRARED (880 nm) mod.C11/G00 Ambient light rejection: according to EN 60947-5-2 Vibrations: 0.5 mm amplitude, 10 55 Hz frequency, for every axis (EN60068-2-6) Shock resistance: 11 ms (30 G) 6 shock for every axis (EN60068-2-7)	Power supply:	10 30 Vdc (limit values)
Current consumption (output current excluded): 35 mA max. Outputs: PNP or NPN; 30 Vcc max. (short-circuit protection) Output current: 100 mA max. Output saturation voltage: < 2 V	Ripple:	2 Vpp max.
Outputs: PNP or NPN; 30 Vcc max. (short-circuit protection) Output current: 100 mA max. Output saturation voltage: < 2 V	Current consumption (output current excluded):	35 mA max.
Output current: 100 mA max. Output saturation voltage: < 2 V	Outputs:	PNP or NPN; 30 Vcc max. (short-circuit protection)
Output saturation voltage: ≤ 2 V Response time: 0.5 ms mod. B01/B51/T51; 1 ms mod. C01/C11/F01 Switching frequency: 1 kHz mod. B01/B51/T51; 500 Hz max. mod. C01/C11/F01 Indicators: OUTPUT LED (VELLOW) Statistics: STABILITY LED (GREEN) (mod. B01/B51/C01/C11/F01) POWER ON LED (GREEN) (mod.G00) Statistics: Setting: 0.5 ms mod.B01/B51/C01/C11/F01/T51) Operating temperature: -25 70 °C Electrical shock protection: Class 2 Operating distance (typical values): B01: 0.16 m on R2 B51: 03m on R2 (02 m on R2 mirror rejection) C01: 190 cm C1: 190 cm C11: 5200 cm F01/G00: 020 m T51: 01.5 m on R2 Emission type: RED (660 nm) mod.B01/B51/C01/T51; INFRARED (880 nm) mod.C11/G00 Ambient light rejection: according to EN 60947-5-2 Vibrations: 0.5 mm amplitude, 1055 Hz frequency, for every axis (EN60068-2-6) Shock resistance: 11 ms (30 G) 6 shock for every axis (EN60068-2-27)	Output current:	100 mA max.
Response time: 0.5 ms mod. B01/B51/T51; 1 ms mod. C01/C11/F01 Switching frequency: 1 kHz mod. B01/B51/T51; 500 Hz max. mod. C01/C11/F01 Indicators: OUTPUT LED (YELLOW) Indicators: OUTPUT LED (GREEN) (mod. B01/B51/C01/C11/F01) POWER ON LED (GREEN) (mod. B01/B51/C01/C11/F01) POWER ON LED (GREEN) (mod. G00) Setting: sensitivity trimmer (mod. B01/B51/C01/C11/F01) Operating temperature: -25 55 °C Storage temperature: -25 70 °C Electrical shock protection: Class 2 Operating distance (typical values): B01: 0.16 m on R2 B51: 03m on R2 (02 m on R2 mirror rejection) C01: 190 cm C11: 5200 cm F01/G00: 020 m T51: 01.5 m on R2 Emission type: RED (660 nm) mod.B01/B51/C01/T51; INFRARED (880 nm) mod.C11/G00 Ambient light rejection: according to EN 60947-5-2 Vibrations: 0.5 mm amplitude, 10 55 Hz frequency, for every axis (EN60068-2-6) Shock resistance: 11 ms (30 G) 6 shock for every axis (EN60068-2-27)	Output saturation voltage:	≤2 V
Switching frequency: 1 kHz mod. B01/B51/T51; 500 Hz max. mod. C01/C11/F01 Indicators: OUTPUT LED (YELLOW) STABILITY LED (GREEN) (mod. B01/B51/C01/C11/F01) POWER ON LED (GREEN) (mod.G00) Setting: sensitivity trimmer (mod. B01/B51/C01/C11/F01) Operating temperature: -25 55 °C Storage temperature: -25 70 °C Electrical shock protection: Class 2 Operating distance (typical values): B01: 0.16 m on R2 B51: 03m on R2 (02 m on R2 mirror rejection) C01: 190 cm C01: 190 cm C11: 5200 cm F01/G00: 020 m T51: 015 m on R2 Emission type: RED (660 nm) mod.B01/B51/C01/T51; INFRARED (880 nm) mod.C11/G00 Ambient light rejection: according to EN 60947-5-2 Vibrations: 0.5 mm amplitude, 1055 Hz frequency, for every axis (EN60068-2-6) Shock resistance: 11 ms (30 G) 6 shock for every axis (EN60068-2-27)	Response time:	0.5 ms mod. B01/B51/T51; 1 ms mod. C01/C11/F01
Indicators: OUTPUT LED (YELLOW) STABILITY LED (GREEN) (mod. B01/B51/C01/C11/F01) POWER ON LED (GREEN) (mod. G00) Setting: sensitivity trimmer (mod. B01/B51/C01/C11/F01/T51) Operating temperature: -25 55 °C Storage temperature: -25 70 °C Electrical shock protection: Class 2 Operating distance (typical values): B01: 0.16 m on R2 Desting: B01: 0.16 m on R2 C01: 190 cm C01: 190 cm F1: 05 m on R2 T51: 05 m on R2 Emission type: RED (660 nm) mod.B01/B51/C01/T51; INFRARED (880 nm) mod.C11/G00 Ambient light rejection: according to EN 60947-5-2 Vibrations: 0.5 mm amplitude, 10 55 Hz frequency, for every axis (EN60068-2-6) Shock resistance: 11 ms (30 G) 6 shock for every axis (EN60068-2-27)	Switching frequency:	1 kHz mod. B01/B51/T51; 500 Hz max. mod. C01/C11/F01
STABILITY LED (GREEN) (mod. B01/B51/C01/C11/F01) POWER ON LED (GREEN) (mod. G00) Setting: sensitivity trimmer (mod. B01/B51/C01/C11/F01/T51) Operating temperature: -25 55 °C Storage temperature: -25 70 °C Electrical shock protection: Class 2 Operating distance (typical values): B01: 0.16 m on R2 B51: 03m on R2 (02 m on R2 mirror rejection) C01: 190 cm C01: 190 cm F01/G00: 020 m T51: 01.5 m on R2 Emission type: RED (660 nm) mod.B01/B51/C01/T51; INFRARED (880 nm) mod.C11/G00 Ambient light rejection: according to EN 60947-5-2 Vibrations: 0.5 mm amplitude, 10 55 Hz frequency, for every axis (EN60068-2-6) Shock resistance: 11 ms (30 G) 6 shock for every axis (EN60068-2-27)	Indicators:	OUTPUT LED (YELLOW)
Setting: sensitivity trimmer (mod. B01/B51/C01/C11/F01/T51) Operating temperature: -25 55 °C Storage temperature: -25 70 °C Electrical shock protection: Class 2 Operating distance (typical values): B01: 0.1 6 m on R2 Description Class 2 Operating distance (typical values): B01: 0.1 6 m on R2 Emission type: RED (660 nm) mod.B01/B51/C01/T51; INFRARED (880 nm) mod.C11/G00 Ambient light rejection: according to EN 60947-5-2 Vibrations: 0.5 mm amplitude, 10 55 Hz frequency, for every axis (EN60068-2-6) Shock resistance: 11 ms (30 G) 6 shock for every axis (EN60068-2-27)		STABILITY LED (GREEN) (mod. B01/B51/C01/C11/F01) POWER ON LED (GREEN) (mod.G00)
Operating temperature: -25 55 °C Storage temperature: -25 70 °C Electrical shock protection: Class 2 Operating distance (typical values): B01: 0.16 m on R2 B51: 03m on R2 (02 m on R2 mirror rejection) C01: 190 cm C11: 5200 cm F01/G00: 020 m T51: 015 m on R2 T51: 015 m on R2 Emission type: RED (660 nm) mod.B01/B51/C01/T51; INFRARED (880 nm) mod.C11/G00 Ambient light rejection: according to EN 60947-5-2 Vibrations: 0.5 mm amplitude, 10 55 Hz frequency, for every axis (EN60068-2-6) Shock resistance: 11 ms (30 G) 6 shock for every axis (EN60068-2-27)	Setting:	sensitivity trimmer (mod. B01/B51/C01/C11/F01/T51)
Storage temperature: -25 70 °C Electrical shock protection: Class 2 Operating distance (typical values): B01: 0.16 m on R2 B51: 03m on R2 (02 m on R2 mirror rejection) C01: 190 cm C11: 5200 cm F01/G00: 020 m T51: 01.5 m on R2 T51: 01.5 m on R2 Emission type: RED (660 nm) mod.B01/B51/C01/T51; INFRARED (880 nm) mod.C11/G00 Ambient light rejection: according to EN 60947-5-2 Vibrations: 0.5 mm amplitude, 10 55 Hz frequency, for every axis (EN60068-2-6) Shock resistance: 11 ms (30 G) 6 shock for every axis (EN60068-2-27)	Operating temperature:	-25 55 °C
Electrical shock protection: Class 2 Operating distance (typical values): B01: 0.16 m on R2 B51: 03m on R2 (02 m on R2 mirror rejection) C01: 190 cm C01: 190 cm C11: 5200 cm F01/G00: 020 m T51: 015 m on R2 Emission type: RED (660 nm) mod.B01/B51/C01/T51; INFRARED (880 nm) mod.C11/G00 Ambient light rejection: according to EN 60947-5-2 Vibrations: 0.5 mm amplitude, 1055 Hz frequency, for every axis (EN60068-2-6) Shock resistance: 11 ms (30 G) 6 shock for every axis (EN60068-2-27)	Storage temperature:	-25 70 °C
Operating distance (typical values): B01: 0.16 m on R2 B51: 03m on R2 (02 m on R2 mirror rejection) C01: 190 cm C01: 190 cm C01: 5200 cm F601/G00: 020 m T51: 015 m on R2 Emission type: RED (660 nm) mod.B01/B51/C01/T51; INFRARED (880 nm) mod.C11/G00 Ambient light rejection: according to EN 60947-5-2 Vibrations: 0.5 mm amplitude, 1055 Hz frequency, for every axis (EN60068-2-6) Shock resistance: 11 ms (30 G) 6 shock for every axis (EN60068-2-27)	Electrical shock protection:	Class 2
B51: 03m on R2 (02 m on R2 mirror rejection) C01: 190 cm C11: 5200 cm F01/G00: 020 m T51: 015 m on R2 Emission type: RED (660 nm) mod.B01/B51/C01/T51; INFRARED (880 nm) mod.C11/G00 Ambient light rejection: vibrations: 0.5 mm amplitude, 1055 Hz frequency, for every axis (EN60068-2-6) Shock resistance: 11 ms (30 G) 6 shock for every axis (EN60068-2-27)	Operating distance (typical values):	B01: 0.16 m on R2
C01: 190 cm C1: 5200 cm F01/G00: 020 m T51: 01.5 m on R2 Emission type: Ambient light rejection: 20.5 mm amplitude, 10 55 Hz frequency, for every axis (EN60068-2-6) Shock resistance: 11 ms (30 G) 6 shock for every axis (EN60068-2-27)		B51: 03m on R2 (02 m on R2 mirror rejection)
C11: 5200 cm F01/G00: 020 m T51: 01.5 m on R2 Emission type: RED (660 nm) mod.B01/B51/C01/T51; INFRARED (880 nm) mod.C11/G00 Ambient light rejection: according to EN 60947-5-2 Vibrations: 0.5 mm amplitude, 10 55 Hz frequency, for every axis (EN60068-2-6) Shock resistance: 11 ms (30 G) 6 shock for every axis (EN60068-2-27)		C01: 190 cm
F01/G00: 020 m T51: 015 m on R2 Emission type: RED (660 nm) mod.B01/B51/C01/T51; INFRARED (880 nm) mod.C11/G00 Ambient light rejection: according to EN 60947-5-2 Vibrations: 0.5 mm amplitude, 10 55 Hz frequency, for every axis (EN60068-2-6) Shock resistance: 11 ms (30 G) 6 shock for every axis (EN60068-2-27)		C11: 5200 cm
Institution Institution Emission type: RED (660 nm) mod.B01/B51/C01/T51; INFRARED (880 nm) mod.C11/G00 Ambient light rejection: according to EN 60947-5-2 Vibrations: 0.5 mm amplitude, 10 55 Hz frequency, for every axis (EN60068-2-6) Shock resistance: 11 ms (30 G) 6 shock for every axis (EN60068-2-27)		F01/G00: 020 m
Emission type: RED (660 nm) mod.B01/851/C01/151; INFRARED (880 nm) mod.C11/G00 Ambient light rejection: according to EN 60947-5-2 Vibrations: 0.5 mm amplitude, 10 55 Hz frequency, for every axis (EN60068-2-6) Shock resistance: 11 ms (30 G) 6 shock for every axis (EN60068-2-27)		151: 01.5 m on R2
Ambient light rejection: according to EN 60947-5-2 Vibrations: 0.5 mm amplitude, 10 55 Hz frequency, for every axis (EN60068-2-6) Shock resistance: 11 ms (30 G) 6 shock for every axis (EN60068-2-27)	Emission type:	RED (660 nm) mod.B01/B51/C01/151; INFRARED (880 nm) mod.C11/G00
Vibrations: 0.5 mm amplitude, 10 55 Hz frequency, for every axis (EN60068-2-6) Shock resistance: 11 ms (30 G) 6 shock for every axis (EN60068-2-27)	Ambient light rejection:	according to EN 60947-5-2
Shock resistance: 11 ms (30 G) 6 shock for every axis (EN60068-2-27)	Vibrations:	0.5 mm amplitude, 10 55 Hz frequency, for every axis (EN60068-2-6)
	Shock resistance:	11 ms (30 G) 6 shock for every axis (EN60068-2-27)
Housing material: ABS	Housing material:	ABS
Lens material: PMMA window, polycarbonate lens / glass window and lens mod. B51/T51	Lens material:	PMMA window, polycarbonate lens / glass window and lens mod. B51/T51
Mechanical protection: IP67	Mechanical protection:	IP67
Connections: 2 m cable Ø 4 mm / M12-4 pole connector	Connections:	2 m cable Ø 4 mm / M12-4 pole connector
Weight: 90 g. max. cable vers. / 40 g. max. connector vers.	Weight:	90 g. max. cable vers. / 40 g. max. connector vers.

DIMENSIONS

S60...B01/C01/C11/F01/G00

15 ۱C 20. ശ M12 Ø15

CABLE VERSION



	positions A a
ICAL DATA	1
10 30 Vdc (limit values)	TI TE 07
2 Vpp max.	Ine IESI+
35 mA max.	The receive
PNP or NPN; 30 Vcc max. (short-circuit protection)	The inputs a
100 mA max.	polarity.
≤2 V	The emissio
0.5 ms mod. B01/B51/T51; 1 ms mod. C01/C11/F01	
Hz mod. B01/B51/T51; 500 Hz max. mod. C01/C11/F01	
OUTPUT LED (YELLOW)	
ABILITY LED (GREEN) (mod. B01/B51/C01/C11/F01) POWER ON LED (GREEN) (mod.G00)	DECLARAT
sensitivity trimmer (mod. B01/B51/C01/C11/F01/T51)	We DATAS
-25 55 °C	these produ
-25 70 °C	and success
Class 2	WARRANT
B01: 0.16 m on R2 B51: 03m on R2 (02 m on R2 mirror rejection)	DATASENS DATASENS
C01: 190 cm	found to be
C11: 5200 cm	manufacturi
FU1/GUU: U20 M	This warran
151. U 1.5 III UII KZ	improper ap

29.5

Setting of S60...B01/B51/T51

Position the sensor and reflector aligned on opposite sides. Turn the sensitivity trimmer to the maximum position.

Moving the sensor both vertically and horizontally, determine the power on and off points of the yellow LED (OUT) and then mount the sensor in the middle of the points defined.

Optimum operation is obtained when the green LED (mod.B01/B51) is ON and the vellow LED is OFF.

B01/B51 models: If necessary reduce sensitivity in order to detect very small targets. In order to improve alignment, repeat the procedure detailed above whilst progressively reducing the sensitivity.

MIN Zmay

T51 model: Turn the sensitivity trimmer counterclockwise until the yellow LED turns ON (pos.A).

Turn slowly the trimmer again clockwise until the yellow LED turns OFF (Operating condition, pos.B).

Setting of S60...F01/G00

Position the sensors aligned on opposite sides.

Turn the sensitivity trimmer to maximum; moving the sensor both vertically and horizontally, determine the power on and off points of the vellow LED (OUT) and then mount the sensor in the middle of the points defined. Optimum operation is obtained when the green LED is ON and the vellow I ED is OFF

If necessary, reduce sensitivity using the trimmer, in order to detect very small targets. In order to improve alignment, repeat the procedure detailed above whilst progressively reducing the sensitivity.

Setting of S60...C01/C11

Turn the sensitivity trimmer to minimum: the green LED is ON, the yellow LED is OFF.

Position the target to detect in front of the sensor. Turn the sensitivity trimmer clockwise until the yellow LED turns ON (Target detected state, pos.A).

Remove the target, the yellow LED turns OFF. Turn the sensitivity trimmer clockwise until the yellow LED turns ON (Background detected state, pos.B).

The trimmer reaches maximum if the background is not detected. Turn the trimmer to the intermediate position C, between the two

positions A and B. The green LED must be ON.

EST FUNCTION (S60...G00)

and TEST- inputs can be used to inhibit the emitter and he system is correctly operating.

er output should switch when the test is activated while the nterrupted.

activating voltage range is 10 ... 30 Vdc, whilst respecting the

on is switched off connecting TEST+ to Vdc and TEST- to 0V.

ION OF CONFORMITY

SENSOR S.p.A. declare under our sole responsibility that icts are conform to the 2004/108/CE. 2006/95/CE Directives sive amendments.

SOR S.p.A. warrants its products to be free from defects. OR S.p.A. will repair or replace, free of charge, any product defective during the warranty period of 36 months from the ng date.

nty does not cover damage or liability deriving from the plication of DATASENSOR products.

DATASENSOR S.p.A. Via Lavino 265 40050 Monte S. Pietro - Bologna - Italy

Tel: +39 051 6765611 Fax: +39 051 6759324 http://www.datasensor.com e-mail: info@datasensor.com

DATASENSOR S.p.A. cares for the environment: 100% æ recycled paper.

DATASENSOR S.p.A. reserves the right to make modifications and improvements without prior notification.

15 n 16 M12 Ø15

S60...B51/T51





S60...M IŻŇ Background suppression

S60...N Foreground / Background suppression

INSTRUCTION MANUAL

CONTROLS

OUTPUT I FD

The vellow LED ON indicates that the NO output is closed.

READY/ERROR (bicoloured) LED

When permanently green indicates a normal operating conditions and the sensor is ready to function correctly (stability condition). The alternative green / red blinking indicates a wrong detection. Please refer to the "SETTING" paragraph for acquisition or setup procedure indications.

SET PUSHBUTTON

A long pressure on the pushbutton activates the self-setting procedure. The REMOTE input allows the external SET control.

INSTALLATION

The sensor can be positioned by means of the three housing's holes using two screws (M4x25 or longer, 1.5Nm maximum tightening torque) with washers

Various orientable fixing brackets to ease the sensor positioning are available (please refer to the accessories listed in the general catalogue).

The operating distance is measured from the front surface of the sensor optics

The M12 connector can be oriented at two different positions using the specific fastening spring and rotating the block of 180°

CONNECTIONS



* = Connect to 0 V the REMOTE wire if not used.

Power supply:	10 30 Vdc (limit values)			
Ripple:	2 Vpp max.			
Current consumption (output current excluded):	50 mA max.			
Outputs:	PNP or NPN; 30 Vdc max. (short-circuit protection)			
Output current:	100 mA max.			
Output saturation voltage:	≤ 2 V			
Response time:	500 μs max.			
Switching frequency:	1 KHz			
Indicators:	OUTPUT LED (YELLOW) / READY/ERROR LED (GREEN/RED)			
Adjustment:	SET pushbutton			
Data retention:	EEPROM non volatile memory			
Operating temperature:	-10 55 °C			
Storage temperature:	-20 70 °C			
Electrical shock protection:	Class 2			
Operating distance (typical values):	Proximity 220 cm; foreground and/or background suppression 720 cm			
Spot dimension:	16 mm at 20 cm			
Emission type:	RED (670 nm)			
Ambient light rejection:	According to EN 60947-5-2			
Vibrations:	0.5 mm amplitude, 10 55 Hz frequency, for every axis (EN60068-2-6)			
Shock resistance:	11 ms (30 G) 6 shock for every axis (EN60068-2-27)			
DARK/LIGHT selection:	LIGHT mode with EASY TOUCH™ / automatic with fine acquisition			
Housing material:	ABS			
Lens material:	PMMA window; PC lens			
Mechanical protection:	IP67			
Connections:	2 m cable Ø 4 mm / M12-4 pole connector			
Weight:	90 g. max. cable vers. / 40 g. max. connector vers.			

TECHNICAL DATA

SETTING

EASY TOUCH™

The sensor uses the patent-covered EASY TOUCH™ technology that allows a rapid and safe self-setting of the product. Two different setting possibilities are available

- EASY TOUCHTM; press for 2 sec. of the SET pushbutton allows self-setting
- FINE DETECTION; to be used only in particularly critical conditions, this setting procedure is used only when the EASY TOUCH[™] is not sufficient.

S60...M setting

EASY TOUCH™ (standard detection)

Place the background or the object to be suppressed inside the operating range

Press the SET pushbutton until the READY/ERROR LED turns OFF.

Release the SET pushbutton and wait for the READY/ERROR LED to turn areen.

The sensor is now ready to detect all objects in the operating field distinguishing them from the suppressed background (output LED turns ON).

Fine detection

Place the background or the object to be detected inside the operating range. Press the SET pushbutton and keep it pressed until the

READY/ERROR LED blinks green. Place the object to be suppressed inside the operating distance.

Press again the SET pushbutton until the READY/ERROR LED turn OFF.

The sensor selects the best operating conditions according to the acquired points and adjusts itself in the LIGHT mode condition. The given acquisition sequence has to be inverted to select the DARK mode

S60...N setting

EASY TOUCHTM (standard detection)

Place the object to be detected in front of the sensor inside the operating range

Press the SET pushbutton until the READY/ERROR LED turns OFF

Release the SET pushbutton and wait for the READY/ERROR LED to turn green.

The sensor is ready to detect the object (output LED turns ON) excluding the background and foreground.

Fine detection

Place the object to be detected in front of the sensor at the nearest operating distance (Point A).

Press the SET pushbutton and keep it pressed until the READY/ERROR LED blinks green.

Place the object to be detected in front of the sensor at the farest operating distance (Point B).

Press again the SET pushbutton until the READY/ERROR LED turns OFF. The sensor is ready to detect the object inside the acquired A-B area, in the LIGHT mode. The given acquisition sequence has to be inverted to select the DARK mode.

Sen	sor		3	
	Foreground suppression area	Object detection area	Background suppression area]
	Sensor NO output OFF	Sensor NO output ON	Sensor NO output OFF	LIGHT MODE
	Sensor NO output ON	Sensor NO output OFF	Sensor NO output ON	DARK MODE
				r

DIMENSIONS



DELAY FUNCTION (S60...M)

Press the SET pushbutton and keep it pressed until the READY/ERROR LED turns off, blinks and turns off again, then release the SET pushbutton

If the delay function is not active the READY/ERROR LED blinks green with 2 quick pulses.

If the delay function is active the READY/ERROR LED blinks green with 4 quick pulses.

Press and release immediately the SET pushbutton in order to change the function status, the new function status is indicated by the READY/ERROR LED as the mode before described. The delay function adds 20ms to the duration of the sensor's ON pulse.

REMOTE FUNCTION

The REMOTE wire connected to +Vdc is equal to pressing the SET pushbutton. The keyboard block is activated if at the sensor powering the REMOTE wire is connected +Vdc, and thus the SET pushbutton is no longer active. To deactivate the keyboard block the sensor has to be turned off and then turned on with the REMOTE wire not connected.

DECLARATION OF CONFORMITY

We DATASENSOR S.p.A. declare under our sole responsibility that these products are conform to the 2004/108 CEE, 2006/25/CE Directives and successive amendments.

W/A	RR	ΔN	тγ	

DATASENSOR S.p.A. warrants its products to be free from defects DATASENSOR S.p.A. will repair or replace, free of charge, any product found to be defective during the warranty period of 36 months from the manufacturing date.

This warranty does not cover damage or liability deriving from the improper application of DATASENSOR products.

DATASENSOR S.p.A. Via Lavino 265 40050 Monte S. Pietro - Bologna - Italy

Tel: +39 051 6765611 Fax: +39 051 6759324 http://www.datasensor.com e-mail: info@datasensor.com

÷ DATASENSOR S.p.A. cares for the environment: 100% recycled paper.

DATASENSOR S.p.A. reserves the right to make modifications and improvements without prior notification.

DATASENSOR

S60-PL SERIES **INSTRUCTION MANUAL**



CONTROLS

OUTPUT LED (S60-PL...B01/C01/F01)

The yellow LED on indicates that the N.O. (normally open) output status is closed

POWER ON LED (S60-PL...B01/C01/F01/G00)

The green LED indicates that the sensor is operating and the laser is active

TRIMMER (S60-PL ... B01/C01/F01)

The trimmer can be used to adjust sensitivity: the operating distance increases turning the trimmer clockwise.

WARNING: The trimmer rotation is limited to 270° by a mechanical stop. Do not apply excessive torque when adjusting (max 40 Nmm).

INSTALLATION

The sensor can be positioned by means of the three housing's holes using two screws (M4x25 or longer, 1.5 Nm maximum tightening torque) with washers. Various orientable fixing brackets to ease the sensor positioning are available (please refer to the accessories listed in the general catalogue). The operating distance is measured from

the front surface of the sensor optics. The M12 connector can be oriented at two

different positions using the specific fastening spring and rotating the block of 180°.

CONNECTIONS

The connections are compliant to the EN 60947-5-2 standard.

S60-F	S60-PLB01/C01/F01			S60-PLG00		
BROWN	1	10 30 Vdc	BROWN	_ 1 _+	10 30 Vdc	
WHITE	2	N.C. OUTPUT	WHITE	2	TEST +	
BLACK	4	N.O. OUTPUT	BLACK	4	NOT USED	
BLUE	3	- 0 V	BLUE	<u> </u>	0 V	

M12 CONNECTOR





TRIMMER

TECHNICAL DATA

mm

Power supply:	10 30 Vdc limit values
Ripple:	2 Vpp max.
Consumption (output current excluded):	35 mA max.
Outputs:	N.O. and N.C.; PNP or NPN; 30 Vdc max. (short-circuit protection) (mod. B01/C01/F01)
Ouput current:	100 mA max.
Output saturation voltage:	≤2 V
Response time:	250 μs (mod. B01/C01); 333 μs (F01)
Switching frequency:	2 kHz (mod. B01/C01); 1,5 kHz (F01)
Indicators:	OUTPUT LED (YELLOW) (mod. B01/C01/F01) POWER ON LED (GREEN) (mod. B01/C01/F01/G00)
Setting:	senstivity trimmer (mod. B01/C01/F01)
Operating mode:	LIGHT mode on N.O. output / DARK mode on N.C. output (mod.C01) DARK mode on N.O. output / LIGHT mode on N.C. output (mod.B01/F01)
Operating temperature:	-10 50 °C
Storage temperature:	-25 70 °C
Electrical protection:	Class 2
Operating distance (typical values):	B01: 0.120 m on R2
	C01: 050 cm
	F01/G00: 060 m
Emission type:	RED LASER: Class 1 EN 60825-1 (1994) (mod.B01/C01/G00) Class II CDRH 21 CFR PART 1040.10 (mod.B01/C01/G00)
	Max. power \leq 1 mW; Pulse = 4.2 μ S (mod.B01/C01); 5 μ S (mod.G00);
	λ = 630680 nm; Frequency =33.5 kHz (mod.B01/C01); 10 kHz (mod.G00)
Ambient light rejection:	according to EN 60947-5-2
Vibrations:	0.5 mm amplitude, 10 55 Hz frequency, for every axis (EN60068-2-6)
Shock resistance:	11 ms (30 G) 6 shock for every axis (EN60068-2-27)
Housing material:	ABS
Lens material:	window in PMMA, lenses in glass and polycarbonate
Mechanical protection:	IP67
Connections:	2 m Ø 4 mm cable / M12 4-pole connector
Weight:	90 g. max. cable vers. / 40 g. max. connector vers.

DIMENSIONS

S60-PL...B01/C01/F01/G00

ŝ

26.

ø

Ø15

CABLE VERSION

Position the sensor and reflector aligned on opposite sides. Turn the sensitivity trimmer to the maximum position.

Moving the sensor both vertically and horizontally, determine the power on and off points of the yellow LED (OUT) and then mount the sensor in the middle of the points defined.

SETTING

Reduce sensitivity if very small objects have to be detected. Repeat procedure reducing progressively the sensitivity in orde to improve aligngment

Setting of S60-PL...F01/G00

Setting of S60-PL...B01

Position the sensors aligned on opposite sides.

Turn the sensitivity trimmer to maximum: moving the sensor both vertically and horizontally, determine the power on and off points of the yellow LED (OUT) and then mount the sensor in the middle of the points defined so that the vellow LED remains off.

If necessary, reduce sensitivity using the trimmer, in order to detect very small targets. In order to improve alignment, repeat the procedure detailed above whilst progressively reducing the sensitivity.

Setting of S60-PL...C01

Adjust the sentivity trimmer to minimum: the yellow LED is off.

Position the target to detect in front of the sensor Turn the sensitivity trimmer clockwise until the vellow LED turns ON (Target detected state, pos.A).

Remove the target, the vellow LED turns OFF.

Turn the sensitivity trimmer clockwise until the yellow LED turns ON (Background detected state, pos.B). The trimmer reaches maximum if the background is not detected.

Turn the trimmer to the intermediate position C, between the two positions A and B.

TEST FUNCTION (S60-PL...G00)

The TEST+ input can be used to inhibit the emitter and verify that the system is correctly operating.

The receiver output should switch when the test is activated while the beam is uninterrupted.

The inputs activating voltage range is 10 ... 30 Vdc, with respect to 0V input (blue wire pin3).

Connect the TEST+ input to 0V if not used.

DECLARATION OF CONFORMITY

We DATASENSOR S.p.A. declare under our sole responsibility that these products are conform to the 2004/108/CE, 2006/95/CE Directives and successive amendments.

WARRANTY

DATASENSOR S.p.A. warrants its products to be free from defects. DATASENSOR S.p.A. will repair or replace, free of charge, any product found to be defective during the warranty period of 36 months from the manufacturing date.

This warranty does not cover damage or liability deriving from the improper application of DATASENSOR products.

DATASENSOR S.p.A. Via Lavino 265

40050 Monte S. Pietro - Bologna - Italy

Tel: +39 051 6765611 Fax: +39 051 6759324

http://www.datasensor.com e-mail: info@datasensor.com

ð DATASENSOR S.p.A. cares for the environment: 100% recycled paper

DATASENSOR S.p.A. reserves the right to make modifications and improvements without prior notification.

826001581 Rev.C

CTi Automation - Phone: 800.894.0412 - Fax: 208.368.0415 - Web: www.ctiautomation.net - Email: info@ctiautomation.net





Background suppression



INSTRUCTION MANUAL

CONTROLS

OUTPUT LED

The yellow/orange LED ON indicates that the N.O. (normally open) output is closed. Please refer to the "SETTING" paragraph for the the correct setting procedure

READY/ERROR LED (bi-coloured)

The bi-coloured LED turned green indicates a normal operating condition and hence the sensor is ready to function correctly (LASER ON)

The red blinking LED indicates a wrong sensor setting. In this case the emission and the green LASER ON LED are turned off.

SET PUSH-BUTTON

A long pressure on the pushbutton activates the self-setting procedure. The same external SET control of the sensor can be obtained using the **REMOTE** input.

INSTALLATION

The sensor can be positioned by means of the three housing's holes using two screws (M4x25 or longer, 1.5 Nm maximum tightening torque) with washers.

Various orientable fixing brackets to ease the sensor positioning are available (please refer to the accessories listed in the general catalogue).

The operating distance is measured from the front surface of the sensor optics.

The M12 connector can be oriented at two different positions using the specific fastening spring and rotating the block to 180°.



Bower cupply:	
Power suppry:	10 30 Vac IImit Values
Rippie:	2 vpp max.
Current consumption	60 mA max.
(output current excluded):	DND or NDN: 000 (the reset of each element of the state)
Outputs:	PNP or NPN; 30 Vdc max. (short-circuit protection)
Output current:	100 mA max.
Output saturation voltage:	≤ 2 V
Response time:	500 µs max.
Switching frequency:	1 KHz
Indicators:	OUTPUT LED (YELLOW/ORANGE) / LASER ON/ERROR LED (GREEN /RED)
Setting:	SET pushbutton
Data retention:	EEPROM non volatile memory
Operating temperature:	-10 55 °C
Storage temperature:	-20 70 °C
Protezione elettrica:	Class 2
Operating distance (typical values):	510 cm
Spot dimension:	1.5 x 1 at 5 cm 1 x 1 at 7 cm 3 x 1.5 at 10 cm
Emission type:	RED LASER 650 nm: Class 1 EN 60825-1 (1994) Class II CDRH 21 CFR PART 1040.10
Ambient light rejection:	according to EN 60947-5-2
Vibrations:	0.5 mm amplitude, 10 55 Hz frequency, for every axis (EN60068-2-6)
Shock resistance:	11 ms (30 G) 6 shock for every axis (EN60068-2-27)
DARK/LIGHT selection:	LIGHT mode with EASY TOUCH [™] / automatic with fine detection
Housing material:	ABS
Lens material:	window in PMMA; lens in PC
Mechanical protection:	IP67
Connections:	2 m cable Ø 4 mm / M12-4 pole connector
Weight:	90 g. max. cable vers. / 40 g. max. connector vers.

TECHNICAL DATA



* = Connect to 0 V the REMOTE wire if not used

BROWN

WHITE

BLACK

BLUE

EASY TOUCH™

SETTING

Place the object to detect in front of the sensor at the desired distance.

Press the SET pushbutton and keep it pressed, without moving the object, until the output LED begins to blink. Release the button. Place the background to be suppressed. Press the SET pushbutton and wait unit the output LED turns OFF and release the button.

According to the points detected the sensor selects the best operating condition and sets the LIGHT functioning mode. To select the opposite operating mode, invert the defined detection sequence.

insufficient contrast and the procedure has to be repeated from the beginning.

DIMENSIONS



DELAY FUNCTION

Press the SET pushbutton and keep it pressed until the OUTPUT LED turns off, blinks and turns off again, then release the SET pushbutton. If the delay function is not active the OUTPUT LED blinks yellow/orange with 2 quick pulses.

If the delay function is active the OUTPUT LED blinks yellow/orange with 4 quick pulses.

Press and release immediately the SET pushbutton in order to change the function status, the new function status is indicated by the OUTPUT LED as described beforehand. The delay function adds 20 ms to the duration of the sensor's ON pulse.

REMOTE FUNCTION

The REMOTE wire connected to + Vdc is equal to pressing the SET pushbutton. The keyboard block is activated if at the sensor powering the REMOTE wire is connected + Vdc, and thus the SET pushbutton is no longer active. To deactivate the keyboard block the sensor has to be turned off and then turned on with the REMOTE wire not connected to 0V.

DECLARATION OF CONFORMITY

We DATASENSOR S.p.A. declare under our sole responsibility that these products are conform to the 2004/108/CE, 2006/95/CE Directives and successive amendments.

WARRANTY

DATASENSOR S.p.A. warrants its products to be free from defects. DATASENSOR S.p.A. will repair or replace, free of charge, any product found to be defective during the warranty period of 36 months from the manufacturing date.

This warranty does not cover damage or liability deriving from the improper application of DATASENSOR products.

DATASENSOR S.p.A. Via Lavino 265

40050 Monte S. Pietro - Bologna - Italy Tel: +39 051 6765611 Fax: +39 051 6759324 http://www.datasensor.com e-mail: info@datasensor.com

Ŕ DATASENSOR S.p.A. cares for the environment: 100% recycled paper.

DATASENSOR S.p.A. reserves the right to make modifications and improvements without prior notification.

826001721 Rev.B

The sensor uses the patent-covered EASY TOUCH™ technology

conditions, this setting procedure is used only when the EASY TOUCH[™] is not sufficient.

EASY TOUCH™ (standard detection)

Place the background or the object to be suppressed inside the operating distance.

Press the SET pushbutton until the output LED turns OFF and then release it. The sensor is now ready to detect all objects in the defined operating range. The LIGHT mode is automatically set.

FINE DETECTION

that allows a rapid and safe self-setting of the product. Two different setting possibilities are available: - EASY TOUCHTM; press for 2 sec. the SET pushbutton to obtain the self-setting adjustment. - FINE DETECTION; to be used only in particularly critical

If the red ERROR LED blinks the detection has failed due to



S60...U Luminescence sensor

INSTRUCTION MANUAL

CONTROLS

OUTPUT I FD

2

The vellow LED ON indicates that the N.O. (normally open) output status is closed.

READY/ERROR LED (bicolour)

When the bicoloured LED is continuously green, the sensor is operating in a normal condition and it is ready to function correctly (stability condition).

The red and green blinking of the LED indicates a wrong sensor setting. Please refer to the "SETTING" paragraph to get the correct setting procedure.

SET PUSH-BUTTON

A long pressure on the push-button activates the self-setting procedure. The REMOTE input allows the external control of the SET push-button.

INSTALLATION

The sensor can be positioned by means of the three housing's holes using two screws (M4x25 or longer, 1.5 Nm maximum tightening torque) with washers

Various orientable fixing brackets to ease the sensor positioning are available (please refer to the accessories listed in the general catalogue).

The operating distance is measured from the front surface of the sensor ontics

the block of 180°.



The M12 connector can be oriented at two different positions using the specific fastening spring and rotating

CONNECTIONS



* = Connect the REMOTE wire to 0 V if not used.

NOTE

If a setting error will occur please repeat again the EASY TOUCH™ setting procedure, in order to be sure to restart the setting procedure correctly



20

READY/ERROR LED

OUTPUT LED

SET PUSH-BUTTON

11



CABLE VERSION



TECHNICAL DATA

mm

18x45°

=ुः14

23.6

Power supply:	10 30 Vdc (limit values)
Ripple:	2 Vpp max.
Current consumption	- 30 mA max.
Output current excluded).	PNP or NPN: 30 Vdc max. (short-circuit protection)
Output current:	100 mA max.
Output saturation voltage:	≤2 V
Response time:	250 µs max.
Switching frequency:	2 KHz
Indicators:	OUTPUT LED (YELLOW) / READY/ERROR LED (GREEN/RED)
Adjustment:	SET push-button
Data retention:	non volatile EEPROM memory
Operating temperature:	-10 55 °C
Storage temperature:	-20 70 °C
Electrical shock protection:	Class 2
Operating distance (typical values):	040 mm range, maximum signal at 10 mm
Minimum spot dimension:	1.5 mm at 10 mm
Emission type:	UV LED (370 nm)
Ambient light rejection:	according to EN 60947-5-2
Vibrations:	0.5 mm amplitude, 10 55 Hz frequency, for every axis (EN60068-2-6)
Shock resistance:	11 ms (30 G) 6 shock for every axis (EN60068-2-27)
DARK/LIGHT selection:	LIGHT mode with EASY TOUCH™ / Automatic with fine detection
Housing:	ABS
Lens:	glass window (sloped); glass lens
Mechanical protection:	IP67
Connections:	2 m cable Ø 4 mm / M12-4 pole connector
Weight:	90 g. max. cable vers. / 40 g. max. connector vers.

DELAY FUNCTION

Press the SET push-button and keep it pressed until the READY/ERROR LED turns off, blinking and turns off again, then release the SET pushbutton.

If the delay function is not active the READY/ERROR LED blinks green with 2 quick pulses.

If the delay function is active the READY/ERROR LED blinks green with 4 quick pulses.

Press and release immediately the SET push-button in order to change the function status, the new function status is indicated the READY/ERROR LED as the mode before described. The delay function adds 20ms to the duration of the sensor's ON pulse.

SETTING

The supplied sensor is set at the maximum sensitivity, allowing the detection of the minimum luminescence intensity. No other setting procedure is necessary, unless luminescent objects placed on luminescence backgrounds have to be detected. EASY TOUCH™

The sensor uses the patent-covered EASY TOUCH™ technology that allows a rapid and safe self-setting of the product.

Two different setting possibilities are available:

- EASY TOUCH™: a long pressure of the SET push-button allows self-setting. FINE DETECTION; to be used only in particularly critical conditions, this setting procedure is used only when the EASY TOUCH™ is not sufficient.

S60...U setting

To achieve a correct sensor functioning, the luminescent mark or object to be detected has to be placed at the right reading distance.

EASY TOUCH™ (standard detection in the LIGHT mode)

The EASY TOUCH™ technology allows the functioning in the LIGHT mode (mark presents a higher luminescence respect to the background). The mark to detect has to be placed correctly at the right reading distance within the sensor spot.

Press the SET push-button until the READY/ERROR LED turns off. Release the SET push-button and wait for the READY/ERROR LED to turn green. The sensor is now ready to detect the pre-set luminescent mark or object (output LED turns on when the N.O. output is closed)

Note: The automatic EASY TOUCH™ setting has to be performed without any objects inside the sensor reading range (or using a nonluminescent object) in order to bring the sensor back to the maximum sensitivity condition.

Fine detection (DARK or LIGHT mode)

This mode offers an improved detection precision and also allows the detection of luminescent marks or objects placed on luminescent backgrounds.

The operating mode is selected automatically by the sensor: DARK operating mode (mark presents a minor luminescence respect to the background) or LIGHT operating mode (mark presents a higher luminescence respect to the background). Thus the output LED is ON and the N.O. output is closed, when the sensor is positioned on the pre-set luminescent mark. The mark to detect has to be placed correctly at the right reading distance within the sensor spot. Press the SET push-button. The READY/ERROR LED turns OFF. Keep the SET push-button pressed until the READY/ERROR LED blinks green. Place the background under the sensor spot. Press the SET push-button again until the READY/ERROR LED turns

OFF. The sensor is now ready to detect, with a very high precision, the pre-set luminescent mark (output LED turns ON, READY/ERROR LED turns green).

REMOTE FUNCTION

The REMOTE wire, if connected to +Vdc, is equal to the pressure of the SET push-button. If the REMOTE wire is connected to +Vdc, when the sensor is powered ON, the keyboard lock function is activated; the SET push-button is no longer active. To deactivate the keyboard lock function, the sensor has to be turned off and powered again with the REMOTE wire not connected or connected to 0V.

DECLARATION OF CONFORMITY

We DATASENSOR S.p.A. declare under our sole responsibility that these products are conform to the 2004/108/CE, 2006/95/CE Directives and successive amendments.

WARRANTY

DATASENSOR S.p.A. warrants its products to be free from defects. DATASENSOR S.p.A. will repair or replace, free of charge, any product found to be defective during the warranty period of 36 months from the manufacturing date.

This warranty does not cover damage or liability deriving from the improper application of DATASENSOR products.

DATASENSOR S.p.A. Via Lavino 265 40050 Monte S. Pietro - Bologna - Italy

Tel: +39 051 6765611 Fax: +39 051 6759324

- http://www.datasensor.com e-mail: info@datasensor.com
- ÷ DATASENSOR S.p.A. cares for the environment: 100% recycled paper. DATASENSOR S.p.A. reserves the right to make modifications and improvements without prior notification.

826001051 Rev.D

CTi Automation - Phone: 800.894.0412 - Fax: 208.368.0415 - Web: www.ctiautomation.net - Email: info@ctiautomation.net





S60...W Contrast sensor

INSTRUCTION MANUAL

CONTROLS

OUTPUT LED

The vellow LED ON indicates that the N.O. (normally open) output status is closed.

READY/ERROR LED (bicolour)

When the bicoloured LED is continuously green, the sensor is operating in a normal condition and it is ready to function correctly (stability condition).

The red and green blinking of the LED indicates a wrong sensor setting. Please refer to the "SETTING" paragraph to get the correct setting procedure.

SET PUSHBUTTON

A long pressure on the pushbutton activates the self-setting procedure. The REMOTE input allows the external control of the SET pushbutton.

INSTALLATION

The sensor can be positioned by means of the three housing's holes using two screws (M4x25 or longer, 1.5 Nm maximum tightening torque) with washers

Various orientable fixing brackets to ease the sensor positioning are available (please refer to the accessories listed in the general catalogue)

from the front surface of the sensor ontics

the block of 180°.

• /	n	N		E	\mathbf{c}	ТΙ	\sim	NI	С	
•	U	IN	IN		J.		U	IN	3	



* = Connect the REMOTE wire to 0 V if not used.

NOTE

If a setting error will occur please repeat again the EASY TOUCH™ setting procedure, in order to be sure to restart the setting procedure correctly



=ः314

23.6

ĽЩ.

06

11

6

20 42

READY/ERROR LED

OUTPUT LED

SET PUSH-BUTTON



CABLE VERSION

LC

50.

9



TECHNICAL DATA

mm

18x45°

Power supply:	10 30 Vdc (limit values)
Ripple:	2 Vpp max.
Current consumption (output current excluded):	30 mA max.
Outputs:	PNP or NPN; 30 Vdc max. (short-circuit protection)
Output current:	100 mA
Output saturation voltage:	≤ 2 V
Response time:	100 μs max.
Switching frequency:	5 KHz
Indicators:	OUTPUT LED (YELLOW) / READY/ERROR LED (GREEN/RED)
Setting:	SET pushbutton
Data retention:	non volatile EEPROM memory
Operating temperature:	-10 55 °C
Storage temperature:	-20 70 °C
Electrical shock protection:	Class 2
Operating distance (typical values):	19 mm ±2 mm
Minimum spot dimension:	3.5 mm at 19 mm
Emission type:	white light LED (400-700nm)
Ambient light rejection:	according to EN 60947-5-2
Vibrations:	0.5 mm amplitude, 10 55 Hz frequency, for every axis (EN60068-2-6)
Shock resistance:	11 ms (30 G) 6 shock for every axis (EN60068-2-27)
DARK/LIGHT selection:	DARK mode with EASY TOUCH™ / Automatic with fine detection
Housing:	ABS
Lens:	glass window (sloped); glass lens
Mechanical protection:	IP67
Connections:	2 m cable Ø 4 mm / M12-4 pole connector
Weight:	90 g. max. cable vers. / 40 g. max. connector vers.

DELAY FUNCTION

Press the SET pushbutton and keep it pressed until the READY/ERROR LED turns off, blinking and turns off again, then release the SET pushbutton

If the delay function is not active the READY/ERROR LED blinks green with 2 guick pulses.

If the delay function is active the READY/ERROR LED blinks green with 4 quick pulses.

Press and release immediately the SET pushbutton in order to change the function status, the new function status is indicated the READY/ERROR LED as the mode before described. The delay function adds 20ms to the variation of the sensor's ON pulse. CTi Automation - Phone: 800.894.0412 - Fax: 208.368.0415 - Web: www.ctiautomation.net - Email: info@ctiautomation.net

826001062 Rev.F

SETTING

EASY TOUCH™

The sensor uses the patent-covered EASY TOUCH™ technology that allows a rapid and safe self-setting of the product. Two different setting possibilities are available:

- EASY TOUCHTM: a long pressure of the SET pushbutton allows selfsetting
- FINE DETECTION; to be used only in particularly critical conditions. This setting procedure is used only when the EASY TOUCH™ is not sufficient.

S60...W setting

To achieve a correct sensor functioning, the coloured mark or object to be detected has to be placed at the right reading distance.

EASY TOUCH™ (standard detection in the DARK mode)

The EASY TOUCH[™] technology allows the functioning in the DARK mode (mark presents a lower light intensity respect to the background).

The mark to detect has to be placed correctly at the right reading distance within the sensor spot.

Press the SET pushbutton until the READY/ERROR LED turns off. Release the SET pushbutton and wait for the READY/ERROR LED to turn areen

The sensor is now ready to detect the pre-set coloured mark or object (output LED turns on when the N.O. output is closed).

Fine detection (DARK or LIGHT mode)

This mode offers an improved detection precision. The sensor can function either in the DARK operating or in the LIGHT operating mode (light-coloured mark on dark background).

The operating mode is selected automatically by the sensor.

The mark to detect has to be placed correctly at the right reading distance within the sensor spot.

Press the SET pushbutton. The READY/ERROR LED turns off, Keep the SET pushbutton pressed until the READY/ERROR LED blinks green. Place the background under the sensor spot.

Press the SET pushbutton again until the READY/ERROR LED turns

The sensor is now ready to detect, with a very high precision, the preset coloured mark (output LED turns on, READY/ERROR LED turns areen).

The output LED is ON and the N.O. output is closed, when the sensor is positioned on the pre-set coloured mark.

REMOTE FUNCTION

The REMOTE wire, if connected to +Vdc, is equal to the pressure of the SET button. If the REMOTE wire is connected to +Vdc, when the sensor is powered ON, the keyboard lock function is activated; the SET button is no longer active. To deactivate the keyboard lock function, the sensor has to be turned off and powered again with the REMOTE wire not connected or connected to 0V

DECLARATION OF CONFORMITY

We DATASENSOR S.p.A. declare under our sole responsibility that these products are conform to the 2004/108/CE. 2006/95/CE Directives and successive amendments.

WARRANTY

DATASENSOR S.p.A. warrants its products to be free from defects. DATASENSOR S.p.A. will repair or replace, free of charge, any product found to be defective during the warranty period of 36 months from the manufacturing date.

This warranty does not cover damage or liability deriving from the improper application of DATASENSOR products.

DATASENSOR S.p.A. Via Lavino 265 40050 Monte S. Pietro - Bologna - Italy

Tel: +39 051 6765611 Fax: +39 051 6759324

http://www.datasensor.com e-mail: info@datasensor.com



DATASENSOR S.p.A. reserves the right to make modifications and improvements without prior notification.



The operating distance is measured

The M12 connector can be oriented at two different positions using the specific fastening spring and rotating





Distance sensor

INSTRUCTION MANUAL

CONTROLS

OUTPUT LED

The yellow LED on indicates that the NO output status is closed.

READY/ERROR LED (bicolour)

The bicoloured LED permanently green indicates a normal operating condition and hence the sensor is ready to function correctly (stability condition).

The alternative green/red blinking of the LED signals a wrong detection.

SET PUSHBUTTON

A long pressure on the pushbutton activates the self-setting procedure. The REMOTE input allows the external SET control.

INSTALLATION

The sensor can be positioned by means of the three housing's holes using two screws (M4x25 or longer, 1.5Nm maximum tightening torque) with washers.

CONNECTIONS

Various orientable fixing brackets to ease the sensor positioning are available (please refer to the accessories listed in the catalogue). The operating distance is measured from the front surface of the sensor optics.

The M12 connector can be oriented at two different positions using the specific fastening spring and rotating the block of 180°.

001111	
BROWN - +	18 30 Vdc
	ANALOG OUTPUT
BLACK	SWITCHING OUTPUT
BLUE	0 V

M12 CONNECTOR



Power supply:	18 30 Vdc (limit values)
Ripple:	2 Vpp max.
Consumption:	60 mA max. (output current excluded):
Switching outputs:	PNP or NPN; 30 Vdc max. (short-circuit protection)
Switching output current:	100 mA max.
Switching output saturation voltage:	≤ 2 V
Analog output:	in tensione 010 V
Analog output current:	10mA max. (1KΩ minimum resistance load)
Analog output proportionality:	inverse with EASY TOUCH™ / programmable with 2 step detection
Resolution:	1 mm max
Temperature Drift:	0,35 mm/C° (from -10 C° to 55 C°)
Linearity:	± 2.5 mm
Response time:	1 msec. max.
Switching frequency:	500 Hz
Indicators:	OUTPUT LED (YELLOW) / READY/ERROR LED (GREEN/RED)
Setting:	SET pushbutton
Data retention:	non volatile EEPROM memory
Operating temperature:	-10 55 °C
Storage temperature:	-20 70 °C
Electrical protection:	Class 2 (TYPE 1 ENCLOSURE)
Operating distance (typical values):	50150 mm
Minimum spot dimension:	1620 mm
Emission type:	red (670 nm)
Ambient light rejection:	according to EN 60947-5-2
Vibrations:	0.5 mm amplitude, 10 55 Hz frequency, for every axis (EN60068-2-6)
Short resistance:	11 ms (30 G) 6 shock for every axis (EN60068-2-27)
DARK/LIGHT selection:	LIGHT mode with EASYtouch™ / automatic with two steps acquisition
Housing material:	ABS
Lens material:	PMMA
Mechanical protection:	IP67
Connections:	2 m Ø 4 mm cable / M12 4-pole connector
Weight:	90 g. max. cable vers. / 40 g. max. connector vers.

SETTING

EASYTOUCH™

The sensor uses the patent-covered EASY TOUCH™ technology that allows a rapid and safe self-setting of the product.

- Two different setting possibilities are available: - EASYtouch TM: a long pressure of the SET pushbutton allows
- self-setting.
 2 step detection, for the DARK/LIGHT selection of digital output
- and analog output proportionality.

Setting

<u>EASYtouch™ (switching output setting)</u>
 Place the backgroud inside the operating distance.

Press the SET pushbutton until the READY/ERROR LED turns off. Release the SET pushbutton and wait for the READY/ERROR LED turns green.

The sensor is now ready to detect all objects in the set range in the LIGHT operating output mode.

The analogue output is set in an inverse proportionality with field ranging from 50 to 150 mm.



TECHNICAL DATA

Output in the LIGHT switching mode, analog output in inverse proportionality:

- Step 1: place the target at the operating distance 1 nearest to the sensor. Press the SET pushbutton and keep it pressed until the READYLERROR LED turns off and then begins to blink areen.
- Step 2: place the target at the operating distance 2 furthest from the sensor. Press for a second time, the SET pushbutton until the READY/ERROR LED turns off.

Release the SET pushbutton and wait for the READY/ERROR LED turns green.

The switching threshold is set by the nearest point of the detection range fron 50 to 150mm.



DIMENSIONS



We DATASENSOR S.p.A. declare under our sole responsibility that

these products are conform to the 2004/108/CE, 2006/95/CE Directives

This warranty does not cover damage or liability deriving from the

DATASENSOR S.p.A. warrants its products to be free from defects. DATASENSOR S.p.A. will repair or replace, free of charge, any product found to be defective during the warranty period of 36 months from the

improper application of DATASENSOR products.

Tel: +39 051 6765611 Fax: +39 051 6759324

http://www.datasensor.com e-mail: info@datasensor.com

DATASENSOR S.p.A. Via Lavino 265 40050 Monte S. Pietro - Bologna - Italy E

DECLARATION OF CONFORMITY

and successive amendments.

WARRANTY

manufacturing date.

- 2 STEP DETECTION

Output in the DARK switching mode, analog output in direct proportionality:

- Step 1: place the target at the operating distance 1 furthest to the sensor. Press the SET pushbutton and keep it pressed until the READY/ERROR LED turns off and then begins to blink green.
- Step 2: place the target at the operating distance 2 nearest from the sensor. Press for a second time, the SET pushbutton until the READY/ERROR LED turns off.

Release the SET pushbutton and wait for the READY/ERROR LED turns green.

The switching threshold is set by the nearest point of the detection range fron 50 to 150mm.



- - - analog output

DATASENSOR S.p.A. cares for the environment: 100%

recycled paper. DATASENSOR S.p.A. reserves the right to make modifications and improvements without prior notification.

826001591 Rev.B

