

Dell Repository Manager Data Center Version 1.7

User's Guide



Notes, Cautions, and Warnings



NOTE: A NOTE indicates important information that helps you make better use of your computer.



CAUTION: A CAUTION indicates either potential damage to hardware or loss of data and tells you how to avoid the problem.



WARNING: A WARNING indicates a potential for property damage, personal injury, or death.

© 2013 Dell Inc.

Trademarks used in this text: Dell™, the Dell logo, Dell Boomi™, Dell Precision™, OptiPlex™, Latitude™, PowerEdge™, PowerVault™, PowerConnect™, OpenManage™, EqualLogic™, Compellent™, KACE™, FlexAddress™, Force10™ and Vostro™ are trademarks of Dell Inc. Intel®, Pentium®, Xeon®, Core® and Celeron® are registered trademarks of Intel Corporation in the U.S. and other countries. AMD® is a registered trademark and AMD Opteron™, AMD Phenom™ and AMD Sempron™ are trademarks of Advanced Micro Devices, Inc. Microsoft®, Windows®, Windows Server®, Internet Explorer®, MS-DOS®, Windows Vista® and Active Directory® are either trademarks or registered trademarks of Microsoft Corporation in the United States and/or other countries. Red Hat® and Red Hat® Enterprise Linux® are registered trademarks of Red Hat, Inc. in the United States and/or other countries. Novell® and SUSE® are registered trademarks of Novell Inc. in the United States and other countries. Oracle® is a registered trademark of Oracle Corporation and/or its affiliates. Citrix®, Xen®, XenServer® and XenMotion® are either registered trademarks or trademarks of Citrix Systems, Inc. in the United States and/or other countries. VMware®, vMotion®, vCenter®, vCenter SRM™ and vSphere® are registered trademarks or trademarks of VMware, Inc. in the United States or other countries. IBM® is a registered trademark of International Business Machines Corporation.

2013 - 07

Rev. A00

Contents

1 Overview.....	7
What Is New In This Release.....	7
Accessing Documents From Dell Support Site.....	7
Other Documents You May Need.....	8
2 Updating Dell Repository Manager.....	9
Updating Dell Repository Manager At Launch.....	9
Updating Dell Repository Manager Using The Application Settings.....	9
Updating The Dell Repository Manager Using The Updater.....	10
3 System Requirements And Uninstalling The Dell Repository Manager	11
Prerequisites For Installing The Dell Repository Manager.....	11
Hardware Requirements.....	11
Software Requirements.....	11
Optional Requirements.....	12
Supported Dell Systems For Exported Repositories And Bundles.....	12
Uninstalling Dell Repository Manager.....	12
Repairing Dell Repository Manager.....	12
4 User Scenarios.....	15
Using FileStore Save Disk Space In System Drive (C: Drive).....	15
Searching The Dell Support Site For Updates.....	17
Export Updates To Lightweight Deployment Package.....	18
Updating The Local Repository.....	20
Creating Bootable CD or USB Keys For Updates.....	21
Creating A Custom Repository Using Dell OpenManage Essentials.....	22
Launching DRM Using Command Line Options.....	24
Creating An Update Repository Using Dell Management Plug-In For VMware vCenter.....	24
5 Using The Dell Repository Manager.....	27
Configuring Settings For The Dell Repository Manager.....	27
Configuring Source Repository.....	28
Configuring Default Proxy Settings.....	28
Configuring Plug-In Update Check And Settings.....	28
Configuring FileStore Settings.....	29
Creating A Customized Repository.....	30
Creating An Empty Repository.....	32
Working With My Repositories.....	32

Functionalities Of My Repositories.....	32
Opening From My Repositories.....	32
Deleting From My Repositories.....	33
Refreshing From My Repositories.....	33
Saving The Repository To A Local Disk.....	33
Importing A Legacy Repository.....	34
Comparing And Updating Repositories.....	34
Repository Update Report.....	35
Editing A Repository.....	35
Opening The Dell Online Repository.....	36
Viewing The Properties Of A Repository.....	36
Viewing The Inventory Information Of A Repository.....	36
Refreshing Inventory For Repositories.....	37
Working With Bundles.....	37
Adding Bundles.....	38
Viewing The Size Of Bundles.....	40
Deleting Bundles.....	40
Cloning Bundles.....	40
Comparing Bundles.....	41
Deleting Components From Bundles.....	41
Changing The Component Sequence.....	42
Bundle Filters.....	43
Exporting Bundles.....	44
Exporting To Light Weight Deployment Scripts.....	46
Exporting To Bootable ISO.....	46
Exporting As A Server Update Utility (SUU).....	47
Working With Components.....	48
Adding Components.....	49
Creating A Bundle For Selected Components.....	50
Viewing The Size Of Components.....	51
Downloading Components.....	51
Copying Components.....	52
Deleting Components.....	53
Component Filters.....	54
Working With Filters.....	56
Saving Filters.....	56
Managing Filters.....	56
Working With Jobs Queue.....	57
Stopping Jobs In The Jobs Queue.....	57
Starting Jobs In The Jobs Queue.....	57
Removing Jobs In The Jobs Queue.....	57
Jobs Queue Details.....	58

Updating A Local Repository.....	58
Creating A Custom Repository Using Dell OpenManage Essentials.....	58
Scheduling Automatic Search.....	59
Searching Dell Support Site.....	61
Exporting Updates From Support Site.....	62
Filter Options For Search Results.....	63

6 Frequently Asked Questions.....65

Where is the Dell Repository Manager runtime log located?.....	65
I see an update present in dell.com/support but when I install the repository from ftp.dell.com using the Dell Repository Manager, I do not see that update.....	65
How do I view the unassigned components in a repository?.....	65
How do I edit the search criteria of the filter that I created?.....	65
Can the Dell Repository Manager be run through a Proxy Server?.....	65
Why would I use the Dell Repository Manager to create the catalog that LifeCycle Controller uses, instead of just using the catalog on the Server Update Utility (SUU)?.....	66
When I select Schedule Automatic Search, there is a pop-window that appears with the following message: Dell Repository Manager Fatal UI, Error: Dell Repository Manager has encountered an error.....	66
If I export a bundle using Export to light weight deployment scripts, am I going to re-download the DUPs which are already in my system?	66

Overview

The Dell Repository Manager (DRM) ensures that the Dell systems are up-to-date with the latest BIOS, driver, firmware, and software. DRM allows you to:

- Create repositories of customized bundles and updates
- Create groups of related updates for systems running the Microsoft Windows Operating System (32 and 64bits) and Linux Operating System
- Generate comparison reports and update baselines of custom repositories

The customized bundles and repositories are made up of Dell Update Packages (DUPs) or Non-DUPs (such as .exe, .msi, .bin or any other file formats) files. DUPs are software utilities provided by Dell to update specific software and firmware components on Dell PowerEdge systems, Dell desktops, and Dell laptops. You can arrange these components in bundles to group the related updates together. Every repository has a **catalog.xml** or **catalog.cab** file that specifies the contents of that repository. The **catalog.cab** file, downloaded from **ftp.dell.com**, is digitally signed by Dell to ensure system security.

You can deploy the repository through bootable ISO images, raw driver packs, deployment scripts, or Server Update Utilities (SUU).

Dell Repository Manager can run in two modes — Data Center version and Business Client version. The Data Center version manages repositories for Dell servers and storage systems. The Business Client version manages repositories for Dell Precision Workstations, Dell Inspiron, or Dell Optiplex systems. For more information on the client version, see *Dell Repository Manager Business Client User's Guide* at dell.com/support/manuals.



NOTE: Dell Repository Manager can only be installed on systems running the Microsoft Windows operating system.

What Is New In This Release

This release of Dell Repository Manager (DRM) introduces the following new features:

- Manages 64bit update content.
- Manages update content sequence for a bundle.
- Supports Dell PowerEdge VRTX update content.
- Supports addition of Non-DUP files (not only Dell Update Package file) into a repository.
- Supports force update option while exporting bundles to a deployment media.

Accessing Documents From Dell Support Site

To access the documents from Dell Support site:

1. Go to dell.com/support/manuals.
2. In the **Tell us about your Dell system** section, under **No**, select **Choose from a list of all Dell products** and click **Continue**.
3. In the **Select your product type** section, click **Software and Security**.

4. In the **Choose your Dell Software** section, click the required link from the following:

- **Client System Management**
- **Enterprise System Management**
- **Remote Enterprise System Management**
- **Serviceability Tools**

5. To view the document, click the required product version.



NOTE: You can also directly access the documents using the following links:

- For Enterprise System Management documents — [**dell.com/openmanagemanuals**](http://dell.com/openmanagemanuals)
- For Remote Enterprise System Management documents — [**dell.com/esmmanuals**](http://dell.com/esmmanuals)
- For Serviceability Tools documents — [**dell.com/serviceabilitytools**](http://dell.com/serviceabilitytools)
- For Client System Management documents — [**dell.com/OMConnectionsClient**](http://dell.com/OMConnectionsClient)
- For OpenManage Connections Enterprise systems management documents — [**dell.com/OMConnectionsEnterpriseSystemsManagement**](http://dell.com/OMConnectionsEnterpriseSystemsManagement)
- For OpenManage Connections Client systems management documents — [**dell.com/OMConnectionsClient**](http://dell.com/OMConnectionsClient)

Other Documents You May Need

In addition to this guide, you can access the following guides available at [**dell.com/support/manuals**](http://dell.com/support/manuals).

- *Dell Repository Manager Quick Installation Guide*
- *Dell Systems Management - OpenManage Software Support Matrix*
- *Dell Update Packages User's Guide*
- *Dell OpenManage Server Update Utility User's Guide*
- *Dell OpenManage Server Administrator Installation Guide**
- *Dell OpenManage Essentials User's Guide**

* This guide is also found on the *Dell Systems Management Tools and Documentation* DVD.

For information on terms used in this document, see the *Glossary* on the Dell support website.

Updating Dell Repository Manager

You can update the Dell Repository Manager to the latest available version using the following methods:

- [Updating Dell Repository Manager At Launch](#)
- [Updating Dell Repository Manager Using The Application Settings](#)
- [Updating Dell Repository Manager Using Updater](#)

Updating Dell Repository Manager At Launch

1. Launch the Dell Repository Manager.

The Dell Repository Manager checks for the latest available version of the application at **ftp.dell.com**. If a new version is available, the **Dell Repository Manager Update Manager** window is displayed with the following:

- **Current Installed Version:**
- **New Version:**
- **Release Date:**
- **New Release Location:**
- **Release Notes:**

2. Click **Update**.

You can click **Skip** to retain the existing version of the **Dell Repository Manager**.

 **NOTE:** The **Update** button is enabled only when the version of the Repository Manager installed on your system is out-of-date.

 **NOTE:** If you do not want the Dell Repository Manager to check for the latest available versions at launch, in the **Dell Repository Manager Update Manager** screen, clear the **Check for new version at launch** check box.

Updating Dell Repository Manager Using The Application Settings

1. On the **Dell Repository Manager** screen, click **Application** → **Check for Application Update**.

The **Application Update** window is displayed with the following:

- **Current Installed Version:**
- **New Version:**
- **Release Date:**
- **New Release Location:**
- **Release Notes:**

2. The Dell Repository Manager checks for the latest available version of the application at **ftp.dell.com**. If a newer version is available, the application prompts you to install the same.

 **NOTE:** The **Update** button is enabled only when the version of the Dell Repository Manager installed on the system is out-of-date. You can click **Skip** to retain the existing version of the Dell Repository Manager.

 **NOTE:** If you do not want the Dell Repository Manager to check for the latest available versions at launch, in the **Dell Repository Manager Update Manager** screen, clear the **Check for new version at launch** check box.

 **NOTE:** For more information on installing the Dell Repository Manager on the system, see the *Dell Repository Manager Quick Installation Guide* at dell.com/support/manuals.

Updating The Dell Repository Manager Using The Updater

1. Click **Start** → **All Programs** → **Dell Repository Manager v <x.x.x>** folder.

Where x.x.x is the version number of the Dell Repository Manager installed on the system.

 **NOTE:** For Microsoft Windows 8 and Microsoft Windows Server 2012, a shortcut key is available for Dell Repository Manager, once you press the **Start** button.

2. Select the **Dell Repository Manager Updater** option.

If a new version is available, the **Dell Repository Manager Update Manager** dialog box appears displaying the:

- **Current Installed Version:**
- **New Version:**
- **Release Date:**
- **New Release Location:**
- **Release Notes:**

3. Click **Update**.

You can click **Skip** to retain the existing version of the **Dell Repository Manager**.

 **NOTE:** The **Update** button is enabled only when the version of the Dell Repository Manager installed on your system is out-of-date.

 **NOTE:** If you do not want the Dell Repository Manager to check for the latest available versions at launch, in the **Dell Repository Manager Update Manager** screen, clear the **Check for new version at launch** check box.

 **NOTE:** In systems running Microsoft Windows Server 2012 (64-bit Operating Systems), you can start the update by running the **RMUpdater.exe** file at: **c:\Program Files (x86)\Dell\Dell Repository Manager vx.x.x\RMUpdater.exe**.

System Requirements And Uninstalling The Dell Repository Manager

This chapter lists the systems requirements and procedures to uninstall DRM.

Related Topic

- [Hardware Requirements](#)
- [Software Requirements](#)
- [Optional Requirements](#)
- [Uninstalling Dell Repository Manager](#)
- [Repairing Repository Manager](#)

Prerequisites For Installing The Dell Repository Manager

This section lists the specific prerequisites for installing the DRM.

Hardware Requirements

Requirement	Details
Processor	1 GHz Pentium processor or equivalent
RAM	1024 MB
Hard Disk	Up to 1 GB of available space
Display	1024 x 768 high color, 32-bit
Optical Drive (Optional)	CD/DVD writer

Software Requirements

Requirement	Details
System Requirement	• Microsoft .NET Framework 4.0 full version
Supported Operating Systems	• Microsoft Windows Server 2008 (32-bit and 64-bit) • Microsoft Windows Server 2008 R2 • Microsoft Windows Server 2012 • Microsoft Windows 7 (32-bit and 64-bit) • Microsoft Windows 8 (32-bit and 64-bit)

Requirement	Details
Supported Internationalized Operating Systems	• English • French • German • Spanish • Japanese • Simplified Chinese • Russian • Portuguese



NOTE: The Dell Repository Manager user interface is displayed only in English irrespective of the language of the operating system on which it is installed.



NOTE: Internet connectivity and DVD burning software are optional requirements. You can use the Dell Repository Manager for local repositories, without Internet connectivity. The DVD burning software is required only for functions such as burning a custom Server Update Utility DVD or a bootable Linux CD.

Optional Requirements

Internet connectivity and DVD burning software are optional requirements. You can use the Dell Repository Manager for local repositories, without Internet connectivity. The DVD burning software is required only for functions such as burning a custom Server Update Utility DVD or a bootable Linux CD.

Supported Dell Systems For Exported Repositories And Bundles

You can use the exported bundles on Dell systems that support Dell Update Packages (DUPs). With Dell Repository Manager, you can use the FTP catalog, which contains the support for n and n-1 blocks. For more information about the supported system models for the FTP catalog, see ftp.dell.com/cmsdk/PDK_Readme.doc.

Uninstalling Dell Repository Manager

To uninstall Dell Repository Manager:

1. From the **Control Panel** → **Programs and Features**.
2. In the **Programs and Features** window, select **Dell Repository Manager**, and click **Uninstall**.
3. Click **Yes** to confirm.



NOTE: You must have administrative privileges in the system to uninstall Dell Repository Manager.

Repairing Dell Repository Manager

1. Double-click the **Repository Manager.msi** file located on the system.
2. On the **Dell Repository Manager - InstallShield Wizard**, click **Next**.



NOTE: By default, the **Repair** option is selected on the **Program Maintenance** window.

3. Confirm that **Repair** is selected, and click **Next**.
4. In the **Ready to Repair the Program** window, click **Install** to complete the repair or click **Cancel** to exit without making any changes.



NOTE: If you click **Cancel**, a pop-up window is displayed. Click **Yes** to finish or **No** to return to the **Ready to Repair the Program** window.

5. Click **Finish**.

The repaired Dell Repository Manager is installed on the system.

User Scenarios

This section describes the various features of the Dell Repository Manager (DRM) and the user scenarios.

Related Topics

- [Using FileStore Save Disc Space In System Drive \(C: Drive\)](#)
- [Searching The Dell Support Site For Updates](#)
- [Export Updates To Lightweight Deployment Package](#)
- [Updating The Local Repository](#)
- [Creating Bootable CD or USB Keys For Updates](#)
- [Launching DRM Using Command Line Options](#)
- [Creating A Custom Repository Using Dell OpenManage Essentials](#)
- [Creating An Update Repository Using Dell Management Plug-In For VMware vCenter](#)

Using FileStore Save Disk Space In System Drive (C: Drive)

DRM 1.6 onwards, the configurable FileStore feature helps the user to save disk space on the System Hard Disk. The default file location for the FileStore is **C:\Users\<User Name>\AppData\Local\RepositoryManager\FileStore**. However, the FileStore can be moved to a different location after DRM is installed on the system.




NOTE:

- You are restricted from performing any other operations while moving the FileStore from its original location.
- Stop any running jobs before initiating the FileStore movement. You can restart the stopped jobs once the FileStore is moved successfully. DRM starts communicating with the required files from the new location to resume the stopped jobs.
- Moving the FileStore folder from its default location permanently deletes the folder and its contents. However, the data of the default FileStore folder is saved in the new location.
- DRM cannot recover deleted files and folders.

Moving the FileStore folder from the default location to another location in the same drive, another drive, or another computer on the network is recommended. The **Use Default** button moves back the FileStore folder to the default location. For more information on FileStore, see [Configuring FileStore Setting](#).

The following flow chart describes the process in detail.



Searching The Dell Support Site For Updates


On DRM 1.6 and later, you can search the Dell support site for the latest catalog files and Dell Update Packages (DUPs) and non DUP packages. These updates can be exported to an existing or a new repository.

You can search the Dell Support Site using the following methods:

- Automated Search
- Manual Search

For more information, see [Search Dell Support Site](#) and [Schedule Automatic Search](#)

The following flowchart describes the process of searching the support site:




Export Updates To Lightweight Deployment Package

LightWeight Deployment Package provides scripts (batch and shell) to apply the updates (DUP) for multiple products in an automated manner. DRM generates the batch file for the user. The file is located in the same folder along with the

DUPs. After you copy the LWDP file to the system, it provides necessary updates (drivers, BIOS, and firmware) to the system. The script provided by Dell is used to apply all the updates. For more information on Lightweight Deployment Package, see [Schedule Automatic Search](#).


The following flowchart describes the process of exporting the updates to a Lightweight Deployment Package.



Updating The Local Repository

The Local Repository can be updated with the latest available updates (DUPs). The selected repository compares against the latest catalog file, which consists the latest available updates. You have the options to update the repository with all the available DUPs for the system. Also, you can choose a specific DUP as per the requirement. Different DUPs exist for newer version, changed files, obsoleted files, and other files in the source screen. These options guide you further to drill down your search to the exact DUP for a system. **Repository Update Report** can be saved to the local system, with the details of the downloaded and installed updates. For more information about updating a local repository, see [Updating A Local Repository](#).

The following flowchart describes the process of updating the Local Repository.



Creating Bootable CD or USB Keys For Updates

You can create bootable USB keys for updates, using any third party or free tool. You can start your managed system by the bootable CD or USB storage. After the system starts up, it automatically runs the selected updates. After the update is complete, you can remove the CD or USB storage, and reboot the system to your host operating system.

You can use the bootable ISO to apply the updates if:

- You have a server running an operating system that is not supported by Dell Repository Manager, such as Berkeley Software Distribution (BSD), Solaris, or older versions of Microsoft Windows, RedHat Linux or SUSE Linux.
- You are using Linux versions such as Ubuntu or Debian.
- You prefer to do your updates (regardless of OS) in an out-of-band method.

To create bootable USB keys, using the tool - UNetBootIn as an example:

1. Download the UNetBootIn for Windows available at <http://sourceforge.net/projects/unetbootin/files/UNetbootin/>.
2. Run the Dell Repository Manager and generate the bootable ISO.
3. Start UNetBootIn and select the **Diskimage** option.
4. Click [...] adjacent to the ISO drop-down and navigate to the ISO created by Dell Repository Manager.
5. Ensure that the type setting is equal to USB drive and the location where you want to download the USB key displays in the drive drop-down.
6. Click **OK** to start the USB writing.
7. After the USB key writing is complete, insert the USB key into a USB port on the system you want to upgrade.
8. Press <F11>.

The boot menu is displayed.
9. Select the USB key as the boot target.
10. Select option 1 in the UNetBootIn menu's boot menu to proceed with the component updates.


Creating A Custom Repository Using Dell OpenManage Essentials

OpenManage Essentials (OME) is a hardware management application that provides comprehensive view of Dell systems, devices, and components in the enterprise's network. With OpenManage Essentials, a web-based and one-to-many systems management application for Dell systems and other devices, you can:

- Discover and inventory the systems.
- Monitor systems' health.
- View and manage system alerts.
- Perform system updates.
- View hardware inventory and compliance reports.

You can create a local repository using the Dell OpenManage Essentials inventories. For more information on creating repositories using OME, see [Creating A Custom Repository Using Dell OpenManage Essentials](#).

The following flow chart describes the process in detail.



Launching DRM Using Command Line Options

Navigate to the location where DRM is installed in the system. By default, for 64 bit DRM is installed at `c:\Program Files (x86)\Dell\Dell Repository Manager v1.7.0`. For 32 bit the DRM is installed at `c:\Program Files\Dell\Dell Repository Manager v1.7.0`. Go to **Start** → **Run**, type `cmd` and press enter.

Run the Dell Repository Manager using the following command:

- **RepositoryManager.exe -server** — Launches the application in Data Center version.

Creating An Update Repository Using Dell Management Plug-In For VMware vCenter

1. On the **My Repositories** tab, select **New** → **Dell System Mgmt Plug-in for vCenter inventory**.
2. Type a **Name**: and **Description**: for the repository, and click **Next**.
3. On the **Base Repository** screen, select one of the following options and click **Next**:
 - **Source Repository** — Imports the default repository. This option is enabled only if you have access to the Internet. You can import the bundle(s) and components from this repository into the repositories you create.
 - **My Repositories** — Allows you to select an existing repository as the base repository.

The **System inventory** window is displayed.

4. Under **Use inventory data from Dell Management Virtual Appliance Host**, select one of the following:
 - **Yes** — To retrieve inventory data.
 - **No** — To proceed without retrieving inventory data.

5. Select **Yes**, click **Connect**.

The **Dell Management Virtual Appliance User Credentials** window is displayed.

 **NOTE:** If you select **No**, the only available option is to create the custom repository with the **Latest updates for all devices**.

6. Provide the **Dell Virtual Appliance IP** or **Host** and click **Check Availability**.

 **NOTE:** The **Getting Inventory from Dell Management Appliance** window is displayed. The **Connection Error** window is displayed if the IP or Host name is not found.

7. After it is confirmed that the **Host** is available, type the **Registered vCenter Server IP** or **Host**, the **vCenter Server Username**, and the **vCenter Server Password**.

 **NOTE:** If the vCenter Host information is wrong, a pop-up window is displayed with the following message:
There are no systems available for inventory. Please try again from another Dell Management Appliance.

8. Click **OK** to continue or **Cancel** to exit without making changes.

The **Getting inventory from Dell Management Appliance** window appears. There may be a Security Warning if the certificate has issues.

9. Click **Yes** to continue or **Cancel** to exit without making changes.

10. Select one of the following options, and click **Next** to continue.

The available options are:

- **Latest updates for all devices** — Creates a repository where all the listed systems fetch their corresponding updates.
- **Latest updates for only out-of-date devices** — Creates a repository and update only the out-of-date components.



NOTE: Click **Resync** to retrieve the updated inventory data, if you have modified or removed certain systems from the systems managed by **Dell Management Virtual Appliance Host**.

11. Click **Next** click **Cancel** to exit without making any changes.

The **Summary** window is displayed. Select the options you want to include in the repository:

- Windows x32 Bundles and Components
- Windows x64 Bundles and Components

The **Please wait...** dialog box appears while creating the new repository.

12. Verify the summary and click **Finish**.

The **Results** window is displayed listing the total new bundles and components.

13. Click **Close** to exit.

Using The Dell Repository Manager

You can perform the following tasks:

- Create repositories
- Import legacy repositories
- Update repositories
- Export catalog
- Export repositories
- Modify repository
- Work with bundles
- Work with components
- Search repositories based on different criterion by setting the filters
- Work with jobs queue
- Search Dell Support Site
- Scheduling Automatic Search

Related Topics

- [Creating A Customized Repository](#)
- [Working With My Repositories](#)
- [Importing A Legacy Repository](#)
- [Comparing And Updating Repositories](#)
- [Saving The Repository To Local Disk](#)
- [Editing A Repository](#)
- [Working With Bundles](#)
- [Working With Components](#)
- [Working With Filters](#)
- [Working With Jobs Queue](#)
- [Searching Dell Support Site](#)
- [Scheduling Automatic Search](#)

Configuring Settings For The Dell Repository Manager

You can configure the following settings on the Dell Repository Manager:

- **Source Repository**
- **Default Proxy**
- **Plug-in**
- **FileStore**

Configuring Source Repository

To configure a default repository:

1. On the **Dell Repository Manager** screen, click **Application** → **Settings** → **Source Repository**.
2. In the **Source Repository** window, select one of the following as the default repository:
 - **Dell online repository (ftp.dell.com)**
 **NOTE:** When a new catalog file is available from dell, the **New Catalog Available** notification appears on the menu bar. You can import the latest catalog file using this notification.
 - **A Local Repository**
 **NOTE:** If you select **A Local Repository**, click **Browse** and select the **catalog.xml** file.
 **NOTE:** If **Check the update of source repository while starting** check box is selected, DRM checks for an update on every launch.
3. Click **Finish** to accept changes or **Cancel** to exit without making changes.

Configuring Default Proxy Settings

To configure the default proxy settings for a repository:

1. On the **Dell Repository Manager** screen, click **Application** → **Settings** → **Default Proxy**.
The **Proxy Server Settings** window is displayed.
2. Select **Use Proxy Server (These settings will override the settings from the current user's Internet Explorer (IE) proxy settings)**.
 **NOTE:** The proxy server settings you configure affect all outbound network traffic from the Dell Repository Manager.
3. Type the proxy server address and the server port in the **Proxy Server Address:** and **Proxy Server Port:** fields.
4. Click **Apply** to accept changes or click **Cancel** to exit without making changes.

Configuring Plug-In Update Check And Settings

You can configure the settings and check for updates using the **Dell Repository Manager Plug-ins** window. Identify the related updates for the SUU plug-in packages for bundle(s) and download the new payload and save them on the system. The SUU plug-in enables the Dell Repository Manager to generate an ISO, with Windows and Linux DUPs. These ISO (s) are useful for post-operating system updates.

You can also download the bootable ISO plug-ins from this window. The bootable ISO plug-ins enable the Dell Repository Manager to generate new bootable ISOs. With Linux DUPs, the bootable ISO updates the pre-OS BIOS and firmware. To configure the plug-in notification settings:

1. On the **Dell Repository Manager** screen, click **Application** → **Settings** → **Plug-in Update**.
The **Checking for new Plug-ins** window is displayed. After checking for the new plug-ins, the **Plug-ins** window appears with a list of plug-ins and their location.
2. Click **Settings....**
The **Plug-in Notification Settings** window appears.
3. Under **Update Settings**, select one of the following options:

- **Automatically download new plugins when application is launched**
 - **Notify me of new plugins when application is launched**
 - **Manually check for new plugins**
4. Under the **Source of Plugin Update**, select one of the following options:
 - **Online (ftp.dell.com)** — Downloads the plug-in from the FTP site.
 - **Folder** — Updates the plug-in from a local folder on your system.
 5. If you select **Online (ftp.dell.com)**, click **Download** to save the plug-ins. If you select **Folder**, click **Browse** to navigate to the location of the plugin.
The **Browse For Folder** window is displayed.
 6. Navigate to the folder location where the plug-in is saved. Click **OK** to return to the **Plug-in Notification Settings** window.
 7. Click **OK** accept changes and return to the **Plug-ins** window, or click **Cancel** to exit without making changes.
 8. Click **Download** to save the plug-ins or **Cancel** to exit without making changes.
If the source of the update has been changed, DRM checks for the update at the source location and returns to the **Plug-ins** window.

Configuring FileStore Settings

The **FileStore** option helps you to save disk space on system (C:) drive.

1. On the **Dell Repository Manager** window, click **Application** → **Settings** → **FileStore**.
The **FileStore** window is displayed.
 2. On the **FileStore** window, click **Browse** if you want to save the FileStore to another location on the same drive, another drive, or another computer on your network. By default, DRM creates the FileStore under **C:\Users\<User Name>\AppData\Local\RepositoryManager\FileStore**.
 3. Once you **Select New FileStore Location** click **Open**.
If you choose to save the file store to a new location, ensure that:
 - The destination folder is blank.
 - The destination folder is not the same as the source folder.
 - You have write permission on the destination folder.
 - One of the parent folders is not in use as a FileStore.
-  **NOTE:** Ensure that there are no running or queued jobs in the **Jobs Queue**. While moving the FileStore, DRM will not be able to perform any other operations.
-  **NOTE:** The **Used Size:** field provides the details of the FileStore size. The **Available:** field provides the details of the available blank space of the system (by default DRM creates the FileStore at C) drive. The **Use Default** button is enabled when another location is selected for the **FileStore**.
4. Click **Ok** to move the **FileStore**, or click **Cancel** to exit without making any changes.
If you select **Ok**, a warning appears for further confirmation. The action will permanently delete following folder and its contents. Dell Repository Manager cannot recover deleted files. Are you sure you want to continue?
 5. Click **Yes** to confirm, or **No** to exit making any changes.
If you select **Yes**, the **Moving to new FileStore location...** window appears while moving the FileStore. **FileStore moved successfully.** message appears once the FileStore is moved to the new location. The operation cannot be canceled during this phase.
 6. Click **OK** to exit the **Settings** window.

Creating A Customized Repository

To create a new repository:

1. On the **My Repositories** tab, click **New** → **Customize Repository**.

The **Create Repository** window is displayed.

2. Type the **Name:** and **Description:**.

3. Click **Next**.

The **Base Repository** window is displayed.



NOTE: Click **Cancel** at any time to exit without creating a new repository.

4. Select a source for the repository.

The options available are:

- **Source Repository** — You can import the bundle(s) and components from the source repository into the repositories you create. The **Source Repository** option can be set to the Dell online repository or any other local repository. For more information on setting the Source Repository see [Configuring Source Repository](#).
- **My Repositories** — Allows you to select an existing repository as the base repository.

5. Click **Next**.

The **Generic Inventory** window is displayed.

6. Under **Do you wish to load an inventory file?** select any of the following options:

- **Yes** — Allows you to select an inventory file.
- **No** — Allows you to create a repository without using an inventory file.



NOTE:

The **Browse** button becomes active only if **Yes** is selected.

7. Click **Browse** to navigate the location where you have stored the inventory.

The **Inventory file Schema Validation** window shows validation result.

8. Select one of the following options you want to include in the repository:

- **Latest updates for all devices** — The available updates for existing and outdated devices are added to the repository.
- **Latest updates for only out-of-date devices** — Only the latest updates for all outdated devices are added to the repository.

9. Click **Next**.

The **Summary** window is displayed. Select the options you want to include in the repository:

- Windows x32 Bundles and Components
- Windows x64 Bundles and Components



NOTE: You are directed to , step 23 to create the repository.

The **Please wait...** dialog box appears while creating the new repository.

10. If you are selecting at step 6 to create a repository without using an inventory file, Click **Next**.

The **Select Brand** window is displayed.

11. Select the desired system type (**Server, Storage**) and the brands (**PowerEdge, EqualLogic, PowerVault**) for the repository.

If you select **Server**, select **PowerEdge**, you have the option to select one or more from the following options:

- **Rack** — Includes Dell system models of the rack mount or monolithic type of form factor.
- **Blade** — Includes Dell system models of the blade chassis or modular type of form factor.
- **Tower** — Includes Dell system models of the tower or monolithic type of form factor.

If you select **Storage**, you can select one or more from the following options:

- **EqualLogic**
- **PowerVault**

12. Click **Next.**

The **Select OS** window is displayed.

13. Select the operating system(s) to include the corresponding components in the repository.

The available options are:

- **Windows 32-bit** — Allows to select component(s) pertaining to the systems running the Windows 32 bit operating systems supported by Dell Repository Manager.
- **Windows 64-bit** — Allows to select component(s) pertaining to the systems running the Windows 64 bit operating systems supported by Dell Repository Manager.
- **Linux (32-bit and 64-bit)** — Allows to select component(s) pertaining to the systems running the Linux operating systems supported by Dell Repository Manager.
- **OS Independent** — Allows to select component(s) that are independent of an operating system.

14. Click **Next.**

The **Select Models** window is displayed.

15. Select the system model(s) based on the form factor you selected.

The available options are:

- **Include All Models supported by this repository** — Includes all the available systems.
- **Select Model(s)** — Allows you to select specific systems from the displayed list of systems.

16. Click **Next.**

The **Select Bundles** window is displayed.

17. In the **Select Bundles window, select the bundle(s) to include in the repository.**

The available options are:

- **ONLY include most recent and custom bundle(s)** — Provides the list of the most recently created bundles (latest versions) and user created (custom) bundles.
- **Select Bundle(s)** — Allows you to select specific bundle(s) from the list of available bundles.

18. Click **Next.**

The **Additional Components** window is displayed.

19. Click **Select Components to include additional components in the repository, which are not included in the bundle(s) that you selected.**

20. In the **Select Additional Components window, select the system(s) to include their components in the repository. Once you select a system, the list of the related components is displayed under the **Current View** window.**

21. Select the check box corresponding to the components to include the component in the repository, and click **OK.**

22. Click **Next after you have selected any additional components.**

The **Summary** window displays the properties of the repository based on the selections.

23. Click **Finish to create the repository.**

The **Create repository** dialog box appears while creating the new repository.

The **Repository Created** window displays the message: `New repository was created successfully.`

The new repository comprises catalogs and packages defined in it. It also includes the Dell Inventory Collector.

- Name of the repository.
- Number of Bundle(s) and Component(s).
- Number of the additional component files.



NOTE: Ensure that the bundle(s) and components you add to the repository belong to the specified criteria. Dell Repository Manager does not restrict you from adding components that do not belong to the specified criteria into the repository.

24. Click **Close** to exit the repository created window.

Creating An Empty Repository

To create an empty repository:

1. In the Dell Repository Manager, click on the **My Repositories** → **New** → **Empty (no inventory)**.
2. The new empty repository is created and added under the **My Repositories** tab.

The name of the empty repository appears in the following format:

Repository <number of the repository>

You can add bundle(s) and component(s) to the empty repository.

Working With My Repositories

The My Repositories screen displays the list of available repositories. You can control and perform various tasks using the **New**, **Open**, **Delete**, and **Refresh** options available on the screen. You can also compare repositories using **Run a Comparison** once a repository is open. During the installation, Dell Repository Manager creates a database in the system.

Functionalities Of My Repositories

Create New repositories using any of the following options:

- **Customize Repository** — Allows you to create a new repository by selecting a source for the repository.
- **Dell OpenManage Essentials (OME) inventory** — Allows you to create a new repository by using the inventory data generated by the Dell OpenManage Essentials.
- **Dell System Mgmt Plug-in for vCenter inventory** — Allows you to create a new repository by using inventory data generated by the Dell Management plug-in for VMware vCenter.
- **Empty (no inventory)** — Allows you to create an empty repository.

Opening From My Repositories

Select the check box next to the Repository from the **My Repositories** list and click **Open**. To view information on **Bundles** and **Components** of a particular repository, you can select the respective repository tab once it is opened.



NOTE: The **Open** option is disabled until you select a particular repository.

 **NOTE:** You can also double-click a repository to open the repository.

Deleting From My Repositories

1. Select the repository from the **My Repositories** list, and click **Delete**. Check for any open jobs in the **Jobs Queue** related to the repository that you want to delete. Wait until the job completes or **Stop** and **Remove** that job from the **Jobs Queue** before deleting.

Are you sure you want to permanently delete selected repository? window appears.

 **NOTE:** You cannot stop this process once it is started.

2. Click **Yes** to confirm or click **No** to exit the window.
The repository is deleted from the Repository Manager.

 **NOTE:** Deleting a repository deletes the repository data and the associated files from the database, once you confirm the operation.

 **NOTE:** The **Delete** option is disabled until you select any particular repository.

Refreshing From My Repositories

You can use the **Refresh** option to refresh the list of repositories that appear in the **My Repositories** screen, observe the changes to the components or bundles. **Refresh** is also used to refresh the table to find the repositories that are added by the **Automatic Search Update** option.

Saving The Repository To A Local Disk

You can save the **catalog.xml**, **catalog.cab** or the full repositories (with the DUPs) file to the local system. The catalog file contains details of the repository you created or customized. To save the catalog file:

1. On the **My Repositories** tab, select the repository and click **Open**.
2. Click **Save** to save the catalog file.
The **Save Repository** window is displayed.
3. Under **Save repository to:** click **Browse** to navigate to the location where you want to save the catalog file.
The **Save As** window is displayed.
4. Click **Save** to save the file to the new location or click **Cancel** to exit without making any changes.
5. Under **What to Save:** select one of the following:
 - **Full repository (Catalog file and all the update packages)** — Saves the entire repository including the catalog file and the packages defined in it.
 - **Catalog file only** — Allows you to save only the catalog file and also provides an option to change the base location of the catalog file.
6. If you select **Full repository (Catalog file and all the update packaged)**, then proceed to step 7.
7. If you select **Catalog file only**, then the **Advanced...** section is enabled.
 - a) Under, **Advanced...** select **Change the base location in catalog XML** to change the base location of the catalog file.
The two options listed under the **Change the base location in catalog XML** become active.
 - b) Select one of the following:
 - * **ftp.dell.com** — Allows you to save the catalog file to the default FTP location.

* Empty field — Allows you to type the new location where you want to save the catalog file.

8. Click **Generate report**, if you want to view the report of the saved catalog file.



NOTE: The report is generated and saved in the same location that is specified in step 4.

9. Click **Save** or click **Cancel** to exit without making any changes.
The **Please wait...** dialog box appears while processing the job before submission.
10. Monitor the progress from **Jobs Queue**, after the **Export Queued** window is displayed.
11. Click **OK** to return to the **Dell Repository Manager** screen.

Importing A Legacy Repository

1. In the Dell Repository Manager, click on **Repository Import Legacy Repository** window is displayed.
The **Import Repository** window is displayed.
2. Click **Browse** to navigate to the location of the file.
3. Once you select the file, click **Open**.
The **File Path Location:** shows the details of the file.
4. Under **Select the repository content to import:**, select one of the following.
 - **Import only the catalog reference file (e.g. catalog.xml)**
 - **Import the catalog reference file and download the actual update files contained within it**
5. Click **Import**.
Import Repository Queued window appears indicating that the job has been added to the **Jobs Queue**.
 **NOTE:** The job is submitted to the **Jobs Queue**. You can expand and check the **Jobs Queue** to follow the progress.
6. Click **OK** to close it.
To view the component(s) in this repository, click **My Repositories**, select the imported repository, and click **Open**.
The bundle(s) are displayed in the **Bundle(s)** tab and the component(s) are displayed in the **Components** tab.

Comparing And Updating Repositories

You can compare the repositories you created or imported with the **Source Repository**, as well as with other available repositories to view the differences and update the destination repository.

To compare and update repositories:

1. From the **My Repositories** tab, select the repository, and click **Open**.
2. Click **Run a comparison**.
The **Update Repository** window is displayed. The instructions on updating the repository appear on the **Summary** screen.
3. From the **Source Repository** drop-down list, select a repository or the **Source** with which you want to compare the repository you selected initially.
4. Click **Compare**.
The comparison details appear in the categorized tabs in the **Update Repository** window.

Tab	Description
Summary	View the comparison summary of the selected repositories. The summary displays the number of new version files, changed files, obsolete files, and other files in

source. This also displays the total number of files that are different among these repositories.

The **Summary** tab is displayed by default.

Newer Versions

Click to view the latest versions of the updates available in the source repository. Select the check box corresponding to the system from which you want to add files to the destination repository. The source and destination files appear on the right-hand side. Select the check box corresponding to the files you want to add and click **Update**.

Changed Files

Click to view any component files whose hash values are different in the destination and source repositories. Select the check box corresponding to the files you want to update in the destination repository and click **Update**.

Obsolete Files

Click to view the files that exist in the destination repository but, not in the source repository. Select the check box corresponding to the system from which you want to remove the files. The file names appear on the right-hand side. Select the check box corresponding to the files you want to remove and click **Update**.

Other Files in Source

Click to view new files in the source repository. Select the check box corresponding to the system from which you want to add files to the destination repository. The source files appear on the right-hand side. Select the check box corresponding to the files you want to add to the destination repository and click **Update**.

You can filter the files using the **System** or **Device** filters.

5. Select the updates for the destination repository.
 6. Select the **Show report after update** check box if you want to view the update report.
The destination repository is updated with the latest versions of the updates available in the source repository.
The update report for the selected repositories appears in the **Repository Update Report** window.
-  **NOTE:** If you do not want to view the report, clear the **Show report after update** check box.
7. If you click **Save As...** select the location to save the report in the **Where would you like to save the report?** option.
Click **Close** to return to the **Update Repository** window.
 8. Click **Close** again to return to the Dell Repository Manager screen.

Repository Update Report

The update report displays the timestamp when the report was generated, names of the source and destination repositories, newer versions of components, changed files, obsolete files, and other files in the source repository.

Click **Save As...** to save the report, in html format, on the system.

Click **Close** to exit the report. Click **Close** to exit the **Update Repository** window.

Editing A Repository

You can only edit the name and description of a selected repository, if the repository is editable.

To edit a repository:

1. On the **My Repositories** tab select the repository you want to edit, and click **Open** to view the repository.
2. Click **Repository** —> **Properties**.
3. In the **Repository Properties** window, edit the **Name:** or **Description:** information.

4. Click **OK** to apply the changes or click **Cancel** to exit without making any changes.

Opening The Dell Online Repository

To open the Dell online catalog directly:

1. On the **My Repositories** tab, click **View Source**.

 **NOTE:** By default, the source is set to **Dell online repository (ftp.dell.com)**. You can change the source to a different repository by clicking **Application** → **Settings** → **Source Repository** on the Dell Repository Manager window.

 **NOTE:** You may have to provide your user credentials, if prompted.

2. If you are using the **View Source** option for the first time, the **Source Repository** window is displayed with the following message: To view the source catalog and files, the application database must first be populated with data from the source. Would you like to update the database now?
3. Click **Yes** to continue or click **No** to exit the window.

The **Please wait...** window is displayed while the catalog is being downloaded.

 **NOTE:** When a new catalog file is available from Dell, **New Catalog Available** notification appears on the menu bar. Click the notification to import the latest catalog file. Once the online repository is loaded, the components in the repository appear under the respective tabs.

 **NOTE:** Once the **Source Catalog** is installed on the Dell Repository Manager, it enables the **Sync Database with Source** option.

Viewing The Properties Of A Repository

To view the properties of a repository:

1. On the **My Repositories** tab, select the desired repository, and click **Open**.
2. Click **Properties**.

The **Repository Properties** window is displayed.

The following details are displayed:

- **Name:** and **Description:** of the repository
 - **Date Created:**
 - **Date Imported:**
 - **Number of Bundles:**
 - **Number of Components:**
 - **Form Factor:**
 - **System Models:**
 - **Dell Update Package Format:**
 - **Unassigned Components:**
3. Click **Cancel** to exit the **Repository Properties** window.

Viewing The Inventory Information Of A Repository

You can view the inventory information of repositories that are created using generic inventory, inventory from OME or Dell Management Plugin for VMware vCenter.

To view the inventory information of an OME or vCenter repository:

1. On the **My Repositories** tab, select an existing OME or vCenter repository, and click **Open**.
2. On the **Dell Repository Manager** screen, click the **Inventory** tab to view the list of the systems, which are retrieved from the OME or vCenter servers.
3. Click the specific platform once you have clicked, **Click any platform name** in order to see the **Device Name, Type, and Version** on the right-hand side of the window.
The **Name** of the system, the **OS** (operating system), **Inventory time** (the timestamp of the inventory verification), and the **Total Devices** appear on the left-hand side of the window once the specific device is selected.

Refreshing Inventory For Repositories

You can refresh information of repositories that are created using generic inventory, inventory from OME or Dell Management Plug-in for VMware vCenter.

To refresh the details of an OME or vCenter repository:

1. On the **My Repositories** tab, select an existing OME or vCenter repository, and click **Open**.
2. Click the **Inventory** tab to view the list of systems.
3. Select the **Refresh Inventory** option.
 - For OME, confirm the **Host Name** or **IP Address** is correct and if needed, provide the **User Name** and **Password**.
 - For vCenter, confirm the **Dell Virtual Appliance IP** or **Host** that is auto populated and then click **Check Availability**. Once it is confirmed, the **Registered vCenter Server IP** or **Host** is auto populated. Verify that the information is correct and then provide the vCenter server username and password.
4. Click **OK** to continue.
After refreshing the inventory information, new updates, if any, are added to the repository as new bundle(s) with a new version and timestamp in the bundle name. The total number of bundle(s) and component(s) added appear in the inventory refresh results.
If no new updates are found, the **Inventory Refresh** window is displayed with the message: No new updates found after inventory refresh.
5. Click **OK** to return to the repository.

Working With Bundles

A bundle is a collection of Dell Update Packages (DUPs), called components, that are related to a certain platform, for example, Dell PowerEdge R410 and operating system, Microsoft Windows Server 2008.

You can use Dell Repository Manager to:

- Import existing bundle(s) or manually create bundle(s).
- Delete existing bundle(s).
- Clone existing bundle(s).
- Compare existing bundle(s).
- Export bundle(s) to external repositories or deploy them to applicable systems in the form of bootable ISOs, deployment packs, driver packs, or a fully functional Server Update Utility (SUU).
- View and Edit Bundle Properties.
- Modify the Component Install Sequence.

The list of bundle(s), created or imported, appear in the **Bundles** screen. You can sort the list of bundle(s) based on the name of the bundle, version, operating system, or date on which the bundle(s) were created, size, author, server generation, and brand of the bundle(s).

You can view the number of bundle(s) in the list and the number of bundle(s) you select, at the top of the list. The numbers are displayed in the **Selected/Total** format. The name of the repository to which the bundles belong, is displayed at the top of the bundles list.

Adding Bundles

You can add bundle(s) from repositories to the repository you select. You can add bundle(s) by:

- Directly importing the bundle from one repository to another repository.
- Manually creating a bundle.

Importing Bundles

To import a bundle:

1. On the **My Repositories** tab, select the repository to which you want to add the bundle, and click **Open**.
2. On the **Bundles** screen, click **+ Add**.
The **Import Bundle(s)** window is displayed.
3. On the **Import Bundle(s)** window, click **Next**.
The **Import or Create** window is displayed.
4. On the **Import or Create** window, select **Import bundle(s) from an existing repository**, and click **Next**.
The **Select Repository** window is displayed.
5. On the **Select Repository** window, select one of the following and click **Next**.
 - **Source Repository** — Imports the default repository. This option is enabled only if you have access to the internet. You can import the bundle(s) and components from this repository into the repositories you create.
 - **My Repositories** — Allows you to select an existing repository as a base repository.
The **Select Brand(s)** window is displayed.
6. On the **Select Brand** window, select the desired product type (**Server** or **Storage**) and the brands (**PowerEdge**, **EqualLogic**, or **PowerVault**) for the repository.
Under **PowerEdge**, you have the following form factors:
 - **Rack** — Includes Dell system models of the rack mount or monolithic type of form factor.
 - **Blade** — Includes Dell system models of the blade chassis or modular type of form factor.
 - **Tower** — Includes Dell system models of the tower or monolithic type of form factor.
Under **Storage** you have the following form factors:
 - **EqualLogic**
 - **PowerVault**
7. Click **Next**.
The **Select OS** window is displayed.
8. On the **Select OS** window, select the operating system(s) to include the corresponding components in the repository, and click **Next**.
 - **Windows 32-bit** — Allows you to select component(s) pertaining to systems running the Windows 32 bit operating system supported by Dell Repository Manager.

- **Windows 64-bit** — Allows you to select component(s) pertaining to systems running the Windows 64 bit operating system supported by Dell Repository Manager.
- **Linux (32-bit and 64-bit)** — Allows you to select component(s) pertaining to systems running the Linux operating system supported by Dell Repository Manager.
- **OS Independent** — Allows you to select component(s) that are independent of an operating system.

The **Select Model(s)** window is displayed.

9. On the **Select Model(s)** window, select the system model(s) based on the form factor you selected, and click **Next**.
 - **Include All** — Includes Dell Update Packages (DUPs) for all available systems based on the form factor and operating system you selected, in your repository. For example, if you selected between **Include All** and **Select Model(s)**, as the form factor, selecting **Include All** includes DUPs of all the Dell tower system(s) in the repository.
 - **Select Model(s)** — Displays all the available systems based on the form factor and operating system you selected. You can select individual or multiple systems as required from the list box. For example, if you selected between **Include All** and **Select Model(s)**, selecting **Select Model(s)** displays all the Dell tower systems. You can then choose the tower system(s) whose DUPs you want to include in the repository.

The **Select Bundle(s)** window is displayed.

10. In the **Select Bundles** window, select the bundle(s) to include in the repository, and click **Next**.
 - **ONLY include most recent and custom bundle(s)** — Includes recently released bundle(s) in the repository.
 - **Select Bundle(s)** — Allows you to select bundle(s) from the list displayed.

The **Summary and Finish** window is displayed.

11. On the **Summary and Finish** window, click **Finish**.

The bundle(s) is added under the list of bundle(s) on the **Bundles** tab. The Dell default bundle(s) are indicated by the term **DELL** under **Author** and the custom bundle(s) you create are indicated by the term **User** in the **Author** column.

Creating Custom Bundles

You can create a custom bundle, and then import components to that bundle.

To create a bundle:

1. On the **My Repositories** tab, select the repository to which you want to add the bundle, and click **Open**.
2. On the **Bundles** tab, click + **Add**.
The **Import Bundle(s)** window is displayed.
3. Click **Next**.
The **Import or Create** window is displayed.
4. On the **Import or Create** window, select **Manually create a bundle**. Click **Next**.
5. In the **Name** and **Version** window, type the name and version for the bundle.
6. Under **OS Type**, select the operating system that applies to this bundle:
 - **Windows 32-bit** — Allows you to select component(s) pertaining to systems running the Windows 32 bit operating system supported by Dell Repository Manager.
 - **Windows 64-bit** — Allows you to select component(s) pertaining to systems running the Windows 64 bit operating system supported by Dell Repository Manager.
 - **Linux 32-bit and 64-bit** — Allows you to select component(s) pertaining to systems running the Linux operating system supported by Dell Repository Manager.
 - **OS Independent** — Allows you to select component(s) that are independent of an operating system.
7. Click **Next** to continue.
The **Select OS** window is displayed.

- On the **Select OS** window, select one of the following and click **Next**:

- **Select all Operating Systems**
- **Select specific Operating Systems**

 **NOTE:** The options are available only when the selected **OS Type** in the previous window is **Windows** or **Linux**.

The **Select Platform(s)** window is displayed.

- On the **Select Platform(s)** window, select one of the following, and click **Next**:

- **No platform is specified** — Selects the platform by default.
- **Select specific Platform(s)** — Allows you to select multiple platforms by pressing and holding <CTRL> and using the left-mouse button.

The **Summary and Finish** window is displayed. This window displays the properties of the custom bundle(s) that you are about to create based on the selections you made.

- On the **Summary and Finish** window, click **Finish**.
- Once the bundle is created, a **Success** window is displayed confirming that **Bundle Created...**
- Click **OK** to close the window.

The custom bundle(s) is added under the list of bundle(s) on the **Bundles** tab. The custom bundle(s) you create are indicated by the term **User** in the **Author** column.

Viewing The Size Of Bundles

In the **Bundles** screen, you can view the size of all the bundle(s) you selected in the repository, at the top of the bundle(s) list. The size is displayed in MB or GB.

You can also view the size of individual bundle(s) in the **Size** column, in the bundle(s) list.

Deleting Bundles

To delete a bundle:

- On the **My Repositories** tab, select the desired repository, and click **Open**.
- On the **Bundles** screen, select the bundle you want to delete.
- Click **Delete**.

The following message appears: Are you sure you want to permanently delete selected bundles?

- Click **Yes** to delete the bundle(s) or click **No** to exit without deleting bundles and return to the main page.
If you click **Yes**, the **Please Wait...** window appears while optimizing the database.

Cloning Bundles

You can create an exact copy of an existing bundle with a new name and version for the copy.

To clone a bundle:

- On the **My Repositories** tab select the desired repository, and click **Open**.
- On the **Bundles** screen, select a single bundle you want to copy from the list of displayed bundle(s), and click **Clone**.
The **Clone Bundle** window is displayed. The options available are:

- **Bundle Name:** Displays the bundle that you selected to be copied or cloned.
 - **New Name:** Displays the new name of the copied or cloned bundle.
 - **Version:** Displays the version of the DUP.
 - **OS:** Displays the type of the Operating System.
3. Click **Clone** to create the new bundle or click **Cancel** to exit without making any changes.
The **Please wait...** dialog box appears while creating the new bundle. The new bundle appears in the bundle list once the bundle is cloned.

Comparing Bundles

You can compare bundle(s), view and compare the DUPs that have changed in the bundle(s) you selected.

To compare bundle(s):

1. On the **My Repositories** tab select the desired repository, and click **Open**.
2. On the **Bundles** screen, select the bundle you want to compare.
The selected bundle is the base bundle.
3. Click **Compare**.
The **Compare Bundles** window is displayed.
4. On the **Compare Bundles** window, select a repository that contains the bundle with which you want to compare the base bundle, from the **Repository** drop-down box.
The **Bundle:** list box displays the bundle(s) contained in the selected repository.
5. Select the bundle you want to compare with the base bundle.
 **NOTE:** The **Bundle:** list box displays bundle(s) from the selected repository based on the base bundle(s). If you select a Linux bundle as the base bundle, then Linux bundle(s) are displayed. If you select a Windows bundle as the base bundle, then Windows bundle(s) are displayed.
6. Under **Options**, you can select:
 - **Newer Versions** — To view newer versions of the components in the bundle you selected.
 - **Changed Files** — To view component files that have changed in the selected bundle.
 - **Other Files in Source** — To view updates that are present in the comparison bundle but not in the base bundle.
 - **Obsolete Files** — To view updates that are present in the base bundle but not in the comparison bundle.
 **NOTE:** You can select one or more of these options to compare.
7. Click **Compare** to view the comparison report for the selected bundle based on the specified criteria.
The first time you click **Close**, it closes the **Comparison Report** and returns to the **Compare Bundles** window. You must click **Cancel** to close the **Compare Bundles** window.

Deleting Components From Bundles

You can customize the Dell recommended bundle(s) by removing components, adding DUPs, or modifying the titles of bundle(s).

To customize bundle(s):

1. On the **My Repositories** tab, select the repository to which you want to add the component, and click **Open**.
2. In the **Bundles** tab, select the bundle(s) you want to customize.
3. Click **Component**.

4. Select the component(s) you want to remove from the existing list, and then click **Delete**.
5. You can click:
 - **Delete from all Bundles**
 - **Delete from Repository**
 - **Cancel**
6. After you have made the selection, the **Bundle Disclaimer** window is displayed listing all of the bundles that the deletion will change.

 **NOTE:** **Bundle disclaimer** window appears only for Dell bundles.

7. Click **OK** to continue.
The following message is displayed: Some of the selected component(s) are part of a bundle. Are you sure you want to permanently delete the selected component(s)?
8. Click **Yes**.

Changing The Component Sequence

You can view the Bundle Properties details of a bundle by double-clicking it or by clicking the **Properties** in the Task menu. You have the **Name**, **Version**, **OS type**, **Operating System**, **Platforms**, and **Size**; details of that particular bundle.

After you click the **Component Sequence** tab, the list of components for that bundle are displayed. You can move component up or down in the load order by selecting each component and using the **Move Up** or **Move Down** buttons. You can manually set the order in to a specific sequence using this function. With a logical order, you can apply the relevant components reliably with less number of system restarts. If you are not sure about the correct sequence, use the **Default Order** to install the components.

To change the sequence of the components:

1. On the **My Repositories** tab, select the repository to which you want to add the component, and click **Open**.
2. In the **Bundles** tab, select the bundle you want to customize.
3. Double-click the bundle.
The **Bundle Properties** window is displayed.
4. Click **Component Sequence** tab.
The list of the components is displayed.
5. In the **Component Sequence** window, select one of the following:
 - **Move Up** — Select the component that you want to deploy first and click **Move Up** to bring that component at the top.
 - **Move Down** — Select the component that you want to deploy later and click **Move Down** to bring that component down to that list.
 - **Default Order** — **Default Order** is the order of the component added to the bundle or its order when it was imported from a catalog file.

 **NOTE:** If you have already initiated a job (such as export updates to Lightweight Deployment package, exporting to Bootable ISO and saving the repositories to a local disk) and want to rearrange the sequence of the components, the changes are not going to reflect for the ongoing jobs.

 **NOTE:** By selecting **Move Up** or **Move Down** you can change the **Order** by 1 with each click.

6. Click **OK**.
The **Bundle content order** window is displayed. The **Bundle content order** window prompts you to confirm the changes. The order of components in the bundle was changed. The **Do you want to Save the changes?** window appears for confirmation.

7. Click **Yes** to continue or click **No** to exit the window.
8. If you select **Yes** the **Bundle Disclaimer** window is displayed with the following message: **You are about to modify Dell recommended bundle(s). Please test the bundle(s) before deployment if you want to continue.** You have the list of bundle(s) displayed under the **Dell Recommended bundles** window.

 **NOTE:** If you do not want to view the disclaimer, select the **Do not show again during this session** check box.
9. Click **Ok** or click **Cancel** to exit without making any changes.
 Once you click **Ok**, the **Please wait...** dialog box appears while **Saving component order changes....**

Bundle Filters

The filter properties table lists the options which you can use to filter your search results:

Property	Description
Keyword Search	Filters components based on the text you provided. For example, if you provide PowerEdge, Dell Repository Manager displays all the latest repositories and components applicable to the Latitude systems.  NOTE: You can enter only regular search syntax in this field.
Brand	The available options are: • All or Selected – Server * PowerEdge • Rack • Blade • Tower – Storage * EqualLogic * PowerVault
Supported Platforms	Filters components based on the selected platform. The available options are: • All • Selected For example, if you select PowerEdge R720, Dell Repository Manager displays the components applicable to the Dell PowerEdge R720 system.  NOTE: When you select a platform, Dell Repository Manager displays all the applicable updates relevant to that platform. However, not all these updates may be available at www.dell.com/support.
Operating System	Filters components based on the file format. The options available options are: • Windows 32-bit • Windows 64-bit • Linux (32-bit and 64-bit) • OS Independent For example, if you select Windows-DUP, Dell Repository Manager displays the components applicable to the Windows operating system. If you select Non-DUP,

Dell Repository Manager displays components that are operating system-independent.

Release Date

Filters components based on the release date of the components. The available options are:

- **Any Date**
- **Exact Date**
- **Prior To**
- **Most Recent**

For example, if you enter 12/12/2012 and select **Prior to**, Dell Repository Manager displays all the components released earlier than December 12, 2010.

Exporting Bundles

You can export a bundle to an existing repository, export to a new repository, or you can export it as RAW Driver Packs (Using Windows Bundle), light weight deployment scripts, bootable ISO (using Linux Bundle), or as an SUU and use it to update applicable systems.

To export bundle(s) locally or on a shared network using deployment script, raw driver pack, Bootable ISO, and SUU:

- In case, you are exporting the bundles on a shared network, map the shared network before exporting.
 - Select the mapped network as the destination location.
1. On the **My Repositories** tab, select the desired repository, and click **Open**.
 2. Click the **Bundles** screen.
 3. Select the bundle(s) you want to export from the list of displayed bundle(s), and click **Export**.
The **Export Bundle(s)** window is displayed.
 4. On the **Export Bundle(s)** window, and click **Next**.
The **Select Destination** window is displayed.
 5. On the **Select Destination** window, select the destination from the following options, and click **Next**.
 - **Export to Repository**
 - * **Export to existing Repository**
 - * **Export as NEW Repository**
 - **Raw Driver Pack (Using Windows Bundle)**
 - **Export to light weight deployment scripts**
 - **Bootable ISO (Using Linux Bundle)**
 - **Export as SUU**
 - * **Export as SUU to Directory**
 - * **Export as SUU to ISO**
 6. If you have selected **Export to existing Repository**, then the **Select Repository** window is displayed, in the **Select Repository** window, select the repository you want the bundle(s) to be moved to and then click **Next** to proceed to Step 8.
The **Summary and Finish** window is displayed.
 7. If you selected **Export as New Repository** then the **Name and Description** window is displayed.
 - a. Provide a name for the new repository in the **Name:** and a description (optional) in the **Description:** field.

b. Click **Next**.

The **Summary and Finish** window is displayed.

8. On the **Summary and Finish** window, click **Finish** to complete the export.

9. Click **OK**.

`Bundles exported successfully.` message is displayed for confirmation, click **OK** to close the message box.

Selecting A Destination For Bundle Exports

You can select an export destination for the bundle(s) in the **Select Destination** window.

Select one of the following options:

- **Export to Repository** — Exports the bundle(s) to a repository. You can choose to export to an existing repository or create a new repository. If you select the **Export as NEW Repository** option, Dell Repository Manager creates a repository containing only the bundle(s) you selected. If you choose to **Export to existing Repository**, all existing repositories appear in a window allowing you to select one as the destination repository.
- **Raw Driver Pack (Using Windows Bundle)** — It extracts the .INF and .SYS files from the DUPs and creates the Driver pack. This option is applicable to only for the bundle(s) that contain driver updates for the supported Microsoft Windows operating system.



NOTE: Bundle(s) containing Linux components are skipped during the export process. Only bundle(s) containing INF/SYS files are exported.

For every exported bundle(s), a folder is created with the name of the bundle(s). To install the updates for the required drivers, navigate to the required bundle folder and run the **DellDrvrInstall.bat** file.

- **Export to light weight deployment scripts** — Exports the bundle(s) in the form of deployment scripts. Select a location to save these bundle(s). Dell Repository Manager saves the scripts for bundle(s) pertaining to Microsoft Windows in the .bat format and Linux in the .sh format. You can then run the .bat and .sh scripts on systems running Microsoft Windows and Linux respectively.

When a deployment folder is created, a new **Readme.html** is added. The Readme file describes what the deployment kit contains, like supported platforms, operating system, and information about components.



NOTE: You can edit these scripts to add or remove components of your choice.

- **Bootable ISO (Using Linux Bundle)** — Updates the system irrespective of the operating system installed on them. It can be used to update systems that do not have an operating system installed.

The **Bootable ISO** option exports the bundle(s) as ISO images. You can burn these ISO images to a CD and boot the CD, or create a bootable USB key on the systems that you want to update with the latest bundle(s). This option is available for deployment only if you select Linux custom bundle(s). This ISO image uses Bootable ISO Linux Kernel to execute the DUPs and update the system. The update package is compatible only when you select Linux bundles and components.

If the server you boot through the Bootable ISO (ISO) is not supported by any base lines bundle(s) on this media, all the base lines are displayed on the console. To force the execution, enter the number corresponding to the required baseline and press <Enter>. For example, if PowerEdge M710 is the second in the list, press <2> and apply the bundle.

If the system you boot through Bootable ISO is supported by one base line (bundle), execution automatically starts.

When a deployment folder is created, a new **Readme.html** is created within the ISO file along with the bundle(s) in the location you provided. The readme file describes the contents of the deployment kit such as platform included, operating system (OS), and information about components.



NOTE: If you select a Windows bundle(s), the bundle(s) are skipped.

You can also customize the Dell default script or add your own scripts for deployment.

- **Export as SUU** — Exports a selected Dell recommended or custom bundle as a fully functional SUU.
 - **Export as SUU to Directory** — This is the extracted version of the ISO files in folder format in case if you share them or you don not want to burn a CD/DVD.
 - **Export as SUU to ISO** — Creates the standard SUU CD image, which can be burnt on a CD/DVD for further usage.

Exporting To Light Weight Deployment Scripts

You can export a selected Dell-recommended or a custom bundle as a light weight deployment script.

To export a Dell recommended or a custom bundle as a light weight deployment script:

1. On the **My Repositories** tab select the desired repository, and click **Open**.
 2. Click the **Bundles** tab.
 3. Select the bundle(s) you want to export from the list of displayed bundle(s), and click **Export**.
The **Export Bundle(s)** window is displayed.
 4. In the **Export Bundle(s)** window, click **Next** to continue.
The **Select Destination** page is displayed.
 5. In the **Select Destination** page, select **Export to light weight deployment scripts**, click **Next** to continue.
The **Select Deployment Options** page is displayed.
 6. In the **Select Deployment Options** page, select one or both options:
 - **Force scripts to upgrade regardless of version or date.**
 - **Combine selected bundles into one folder. Each bundle will have a separate script. This will minimize disk space.**
-  **NOTE:** Selecting these options is optional.
7. Click **Next** to continue.
The **Browse For Folder** window is displayed.
 8. In the **Browse For Folder** window, navigate to the folder on your local drive or a network drive location, where you want to export the light weight deployment script, and click **OK** the **Summary and Finish** window is displayed.
 9. Click **Finish**.
Once you click **Finish**, the **Please wait...** dialog box appears while processing the job before submission. Click **Cancel** to exit without making any changes
 10. **Light Weight Deployment Scripts Export Queued** window appears with the confirmation. You can check the **Jobs Queue** for further progress.
 11. Click **OK** to close the **Light Weight Deployment Scripts Export Queued** window.

Exporting To Bootable ISO

You can use your customized BASH script instead of the Dell default script, or append the custom script to default script in the ISO, for deploying Linux bundle(s) on the server.

To customize the script for deployment:

1. On the **My Repositories** tab select the specific repository, and click **Open**.
2. Click the **Bundles** tab.
3. Select the bundle(s) you want to export from the list of displayed bundle(s), and click **Export**.
The **Export Bundle(s)** window is displayed.

4. In the **Export Bundle(s)** window, click **Next**.
The **Select Destination** window is displayed.
5. In the **Select Destination** window, select **Bootable ISO (Using Linux Bundles)** and click **Next**.
 **NOTE:** The **Bootable ISO (Using Linux Bundles)** option is enabled only for Linux bundle(s). The version number of the available plug-in is displayed.
The **Select Plugins** window is displayed.
6. Click **Next**.
The **Browse For Folder** window is displayed.
7. In the **Browse For Folder** window, navigate to the folder on the local drive or select any network location, where you want to export the Bootable ISO, and click **OK**.
The **Select Custom Script** window is displayed.
8. In the **Select Custom Script** window, select **Yes** to include a custom script in the Bootable ISO.
 **NOTE:** By default, **No** is selected. Selecting these options is optional.
9. Under **Select Script**, select one of the following:
 - **Replace default script** — To execute the customized script instead of the Dell default script. Click **Browse** to navigate to the folder where the customized script is located.
 - **Append to default script** — To execute the customized script after the Dell default script is executed. **NOTE:** Ensure that the customized script is of **.sh** format.
 **NOTE:** Ensure that the script is edited and saved in UNIX format. Scripts with Windows end-line characters are unusable.
 **NOTE:** This step applies if you select **Yes** in Step 8.
10. You have the option to tick **Force scripts to update regardless of version or date**. check box under the **Update options** to install the DUPs irrespective of the installed or the packaged version.
11. Click **Next**.
The **Summary and Finish** window is displayed.
12. The **Summary and Finish** window displays the details of the selected bundle(s), destination properties, and custom bundle script used.
13. Click **Finish**.
A **Jobs Queue** message is displayed.
14. Click **OK** to close the message window.

Exporting As A Server Update Utility (SUU)

You can export selected Dell recommended and/or custom bundle(s) as a fully functional SUU.

To export selected Dell recommended and/or custom bundle(s) as a fully functional SUU:

1. On the **My Repositories** tab select the desired repository, and click **Open**.
2. Click the **Bundles** tab.
3. Select the bundle(s) you want to export from the list of displayed bundle(s), and click **Export**.
The **Export Bundle(s)** window is displayed.
4. In the **Export Bundle(s)** window, click **Next** to continue.
The **Select Destination** window is displayed.
5. In the **Select Destination** window, select **Export as SUU** and select one of the following, and click **Next** to continue.

The **Select Plugins** page is displayed.

- **Export as SUU to Directory** — Creates a SUU pack in the provided directory.
- **Export as SUU to ISO** — Creates an ISO image of the SUU pack.

The system checks for availability of the latest SUU plug-in. If a plug-in is available, the version number of the plug-in is displayed and the application prompts you to proceed with the exporting process.

For more information on the usage of SUU on Windows and Linux servers, see the *Dell OpenManage Server Update Utility User's Guide* at dell.com/openmanagemanuals.

- While Dell Repository Manager checks for availability of the required SUU plug-ins, the **Checking to see if the required plug-in is installed...** dialog box is displayed.
- If the latest plug-in is already downloaded the following message displays: Required plug-in found.

The version number of the plug-in found is also displayed.

- The **Select Plugins** shows the following details:

Plug-in type	Installed	Version
Generate 32– Bit SUU*	Status	SUU version
Generate 64– Bit SUU**	Status	SUU version

- When ftp.dell.com is accessible and the latest plug-in does not exist on the system, DRM will download the required plug-ins in the run time.



NOTE: * — Only 32-bit Windows bundles or any Linux bundles can be included in 32-bit plug-in.

** — Only 64-bit Windows bundles or any Linux bundles can be included in 64-bit plug-in.



NOTE: Ensure that the system is connected to the Internet and the ftp.dell.com is accessible.

6. Click **Next** to continue.

The **Browse For Folder** window is displayed.

7. In the **Browse For Folder** window, navigate to the folder on your local drive, where you want to export the SUU, and click **OK**.

The **Summary and Finish** window is displayed.

8. Click **Finish** to complete.

After you click **Finish** the **SUU Export Queued** message appears informing you that the job has been scheduled in the **Jobs Queue**.



NOTE: SUU ISO can be burnt on a DVD or mounted on the target system to update the particular system.



NOTE: SUU directory can be copied on a USB device or accessed from a network share from which the SUU can be launched.

9. Click **OK** to close the **SUU Export Queued** window.

Working With Components

Dell Update Packages (DUPs) are also known as components. Also, we consider all the non-DUPs (such as .exe, .msi, .bin or any other file formats) files as components. DUPs are executable files in a standard package format for updating a single software element on the system. DUPs are used for updating the Basic Input Output System (BIOS), firmware, RAID controller firmware, and drivers on specific platforms.

The list of components you add appear in the **Components** tab.

You can sort the list of components based on **Keyword Search**, **Update Type**, **Criticality**, **Supported Platforms**, **Component Version**, **Operating System**, **Supported Devices**, **Release Date**, **PCI Device Info**, and **Driver Packs**.

You can view the number of components in the list, the number of components you have selected, as well as the total selected size, at the top of the list. The numbers are displayed in the **Selected/Total:** format.

Adding Components

You can add components from other bundle(s) and repositories to the bundle, or the repository you select. Before you add components, you must download them and save them to a specific location. To import components to the repository:

- [Importing Dell Update Packages](#)
- [Importing Non- Dell Update Package \(Non DUPs\)](#)

Importing Dell Update Packages (DUPs)

1. On the **My Repositories** tab, select the repository where the components are located that you want to download and click **Open**.
2. Select the **Components** that you want to import to another location and click **Download File**.
The **Browse For Folder** window is displayed.
3. In the **Browse For Folder** window, navigate to the location where you want to save these components before adding them to another bundle or repository, and then click **OK**.
The **Component download Queued** window is displayed.
 **NOTE:** The job is submitted to the **Jobs Queue**. You can check the **Jobs Queue** to know more about the progress.
4. Click **OK** to close the **Component download Queued** window.
5. Under the **My Repositories** tab, select the repository to which you want to add the component and click **Open**.
6. Click the **Components** tab, and then click **Import**. Click **Open**.
The **Import new DUP files** window is displayed.
 **NOTE:** If the files are not **.exe**, you need to change the file extension from **.exe** to **.bin** or **any**.
7. Under **Selected DUP Files**, click **Browse**. Navigate to the location where the component(s) are located and then select them.
The **Select DUP File to Add** window is displayed.
8. In the **Select DUP File to Add** window, select the component(s) that you want to add, and then click **Open**.
You can browse through and search through for the component(s) from all the repositories available on the system.
 **NOTE:** Select the component(s) you want to remove from the existing list, and then click **Remove**.
9. In the **Import new DUP files** window, select the component(s) you want to add.
10. Select any of the following options.
 - **Add to repository only**
 - **Add to repository and all the following bundles:**

You can view the list of the bundle(s) you have selected. If you do not select a bundle, all the bundles will be displayed under the list. You can select the desired bundles from the list.
11. Click **OK**. There may be a **Security Warning** if the certificate has issues. Click **Accept**, if the source is trusted. You have the option to **Reject** or **View Certificate** details. You have the option to tick **Do not notify when rest of the files are not signed**. check box to avoid this scenario for multiple DUPs.
The **Adding Components to Repository** page displays a summary of the DUP files imported and the bundles to which the DUP files added.



NOTE: For Windows DUP, the signature is embedded into the same file. If it is a Linux DUP, make sure that the relevant DUP signature file <DUP file name>.sign is located in the same folder as the DUP file. Else, the import process will not be successfully completed.

12. Click **Close**.

Importing Non- Dell Update Package (Non DUPs)

DRM 1.7 and later, you can import non-DUP files (such as .exe, .msi, .bin, or any other file formats) to a repository or in selective bundles.

To import non- DUP components:

1. Under the **My Repositories** tab, select the repository to which you want to add the component and click **Open**.
The Non- DUPs files must first be downloaded and saved to a local or network drive location.
2. Click the **Components** tab, and then click **Import**.
The **Import new DUP files** window is displayed.
3. Under **Selected DUP Files**, click **Browse**.
The **Select DUP File to Add** window is displayed.
4. In the **Select DUP File to Add** window, select the component(s) that you want to add, and then click **Open**.
You can browse and search for any non-DUP file available on the system.
The **Import new DUP files** window is displayed when **Open** is selected.
5. In the **Import new DUP files** window, select the component(s) you want to add.



NOTE: Select the component(s) you want to remove from the existing list, and then click **Remove**.

6. Select any of the following options.
 - **Add to repository only**
 - **Add to repository and all the following bundles:**

If you are not selecting any bundle, all the bundles will be displayed under the list. You can select the desired bundles from the list.

7. Click **OK** or click **Cancel** to exit without making any changes. A **Security Warning** appears **do you want to accept this file?** if the certificate has issued. You have the option to **Accept**, **Reject**, or **View Certificate**.
After you **Accept** the certificate, **Please wait...** dialog box appears while adding the non-DUP files.
8. The **Import non-DUP files** window displays the details of the non-DUP file.
The **File Name** and **Add Description** field provide further details of the non-DUP file.



NOTE: The description can be edited.

9. Click **OK**.
The **Adding Components to Repository** window displays a summary of the non-DUP files imported and the bundles the non-DUP files that have been added to.
10. Click **Close**.

Creating A Bundle For Selected Components

In the Components tab, you can create bundles for selected components.

To create a bundle for a component:

1. On the **My Repositories** tab, select the desired repository, and click **Open**.
2. In the **Components** tab, select the component(s) for which you want to create a bundle.

3. Click **New Bundle**.
The **Name and Version** window is displayed.
4. Type the name and version of the bundle.
By default, the name of the bundle is **New Bundle (Windows 32-bit)** for Windows 32-bit, **New Bundle (Windows 64-bit)** for Windows 64-bit, **New Bundle (Linux)** for Linux it is **Linux** and for any other options (which is OS independent), it is **New Bundle (OS Independent)**. Also the version number is **1.0** for all these options.
5. Click **Next**.
The **Select OS** window is displayed.
6. Under **OS Type**, select any one of the following options:
 - **Windows 32-bit**
 - **Windows 64-bit**
 - **Linux 32-bit and 64-bit**
 - **OS Independent**
7. Select one of the following, and click **Next**.
 - **Select all Operating Systems** — This option is selected by default.
 - **Select specific Operating Systems** — You can select multiple platforms by pressing and holding the <CTRL> key while selecting the platforms.

 **NOTE:** You can only choose **Select specific Operating Systems** if you have selected **Windows**. This function is disabled if you selected **Linux** or **OS Independent** in Step 4.

 **NOTE:** The options listed above are available only when the selected **OS Type** in the previous window is **Windows** or **Linux**.

The **Select Model(s)** window is displayed.
8. Select one of the following and click **Next**.
 - **No platform is specified** — This option is selected by default.
 - **Select specific Platform(s)** — You can select multiple platforms by pressing and holding the <CTRL> key while selecting the platforms.

The **Summary and Finish** window is displayed.
9. Click **Finish**, click **Cancel** to exit without making any changes.
The **Copy Components** window is displayed the details of the **Selected Components:** and **Destination Components:** fields.

 **NOTE:** If any error or warnings are found in the export, a message is displayed on **Copy Components** window. Click the **Errors/Warnings** button to view the details.
10. Click **Close** to return to the **Components** tab.

Viewing The Size Of Components

In the **Components** tab, you can view the size of all the components you select in the repository, at the top of the components list. The size is displayed in MB or GB.

You can also view the size of individual components in the **Size** column, in the components list.

Downloading Components

You can download one or multiple components to the local drives on your system.

To download components:

1. On the **My Repositories** tab, select the desired repository, click **Open**.
2. In the **Components** tab, select the component you want to download, and click **Download File**.
The **Browse For Folder** window displayed.
3. In the **Browse For Folder** window navigate to where you want to save these components before adding them to another bundle or repository, and click **OK**.
A **Component download Queued** window is displayed.



NOTE: The job has been submitted to the **Jobs Queue**. You can check the **Jobs Queue** to follow the progress.

Copying Components

To copy to components:

1. On the **My Repositories** tab select the desired repository, and click **Open**.
2. On the **Components** tab, select the component(s) to copy.
3. Click **Copy To**.
The **Copy Component(s)** window is displayed.
4. Click **Next**.
The **Select Destination** window is displayed.
5. In the **Select Destination** window, select one of the four options:
 - **Copy component(s) into an Existing Repository** — Exports component(s) to an existing repository. Select the repository to export the components.
 - **Create a NEW Repository and copy component(s) into it** — Exports component(s) to a new repository that you create.
 - **Add component(s) into an Existing Bundle in the same repository** — Exports component(s) to an existing bundle in the same repository.
 - **Create a NEW bundle in the same repository and add component(s) into it** — Exports component(s) to a bundle in the same repository.
6. If you select **Copy component(s) into an Existing Repository**, in the **Select Destination** window, click **Next** and select a repository from the list of repositories displayed.
7. Click **Next**.
The **Summary and Finish** window is displayed. This window displays information about the component(s) under **Selected Components:** and **Destination Components**.
8. Click **Finish**.
The **Copy Components** window is displayed.
9. Click **Close** to return to the **Components** tab.
10. If you select **Create a NEW Repository and copy component(s) into it**, click **Next** and in the **Name and Description** window, type a **Name:** and **Description:** for the new repository.
11. Click **Next**.
The **Summary and Finish** window is displayed. This window displays information about the component(s) under **Selected Components:** and **Destination Components**.
12. Click **Finish**.
The **Copy Components** window is displayed.
13. Click **Close** to return to the **Components** tab.
14. If you select **Add component(s) into an Existing Bundle in the same repository** and click **Next**.

The **Select Bundle(s)** window is displayed.

- a) In the **Select Bundle(s)** window, select the bundle(s) to be added.

You can select multiple platforms by pressing and holding the <CTRL> key while selecting the platforms.

The **Copy Component Summary** window is displayed.

- b) Click **Next**.

The **Summary and Finish** window is displayed. This window displays information about the component(s) under **Selected Components:** and **Destination Components:**.

- c) Click **Finish**.

The **Copy Components** window is displayed with the details in the **Selected Components:** and **Destination Components:** fields.



NOTE: If any error or warnings are found in the export, a message is displayed on **Copy Components** window. Click the **Errors/Warnings** button to view the details.

- d) Click **Close** to return to the **Components** tab.

15. If you select **Create a NEW bundle in the same repository and add component(s) into it** and click **Next**. The **Name and Version** window is displayed.

- a) Type the name and version of the bundle and click **Next**.

By default, the name of the bundle is **New Bundle (Windows 32-bit)** and the version number, **1.0**.

The **Select OS** window is displayed.

- b) Select one of the following, and click **Next**.

The options available are:

- * **Select all Operating Systems** — This option is selected by default.
- * **Select specific Operating Systems** — You can select multiple platforms by pressing and holding the <CTRL> key while selecting the platforms.

The **Select Model(s)** window is displayed.

- c) Select one of the following and click **Next**.

The options available are:

- * **No platform is specified** — This option is selected by default.
- * **Select specific Platform(s)** — You can select multiple platforms by pressing and holding the <CTRL> key while selecting the platforms.

The **Summary and Finish** window is displayed.

- d) The **Summary and Finish** window displays the Selected Components and the Destination Components details. Click **Finish**.

The **Copy Components** window is displayed with the details of the number of components copied, the number of bundles, and the name of the new bundles.



NOTE: If any error or warnings are found in the export, a message is displayed on **Copy Components** window. Click the **Errors/Warnings** button to view the details.

- e) Click **Close** to return to the **Components** tab.

Deleting Components

You can delete components from a bundle or a repository.

To delete components:

1. On the **My Repositories** tab, select the desired repository, and click **Open**.
2. Click **Components**.
3. On the **Components** screen, select the component(s) you want to delete, and click **Delete**.
The **Delete Component(s)** window is displayed.
4. In the **Delete Component(s)** window, select one of the following:
 - **Delete from all Bundles** — Deletes the component from all the bundle.
 - **Delete from Repository** — Deletes the component from the corresponding repository.
 - **Cancel** — Exits the **Delete Component(s)** window.
5. Click **OK** to proceed.
If you click **OK**, the **Please Wait...** window is displayed while optimizing the database.

Component Filters

The filter properties table lists the options which you can use to filter your search results:

Property	Description
Keyword Search	Filters components based on the text you provide. For example, if you type PowerEdge, Dell Repository Manager displays all the latest repositories and components applicable to the PowerEdge systems.  NOTE: You can provide only regular search syntax in this field.
Update Type	Filters components based on the type of components. The available options are: • Drivers • Firmwares • BIOS • Applications • Utilities For example, if you select BIOS, Dell Repository Manager displays all the components that require only BIOS updates.
Criticality	Filters components based on the criticality of the update. The available options are: • Optional • Recommended • Urgent For example, if you select Urgent, Dell Repository Manager displays all the components that you need to immediately update your system with.
Supported Platforms	Filters components based on the selected platform. The available options are: • All • Selected For example, if you select PowerEdge T710, Dell Repository Manager displays the components applicable to the Dell PowerEdge T710 system.



NOTE: When you select a platform, Repository Manager displays all the applicable updates relevant to that platform. However, not all these updates may be available at www.dell.com/support.

Component Version

Filters components based on the version of the component. The available options are:

- **All** — Displays all the components in the selected repository irrespective of the component version.
- **Most Recent** — Displays the most recent version of the component in the selected repository.
- **Contains** — Displays all the components whose version contain the text you provided. For example, if you provided **A01**, **Dell Repository Manager** displays all the components whose version is **A01**.

Operating System

Filters components based on the file format. The options available options are:

- **Windows-DUP (32-bit)**
- **Windows-DUP (64-bit)**
- **Linux-DUP (32-bit and 64-bit)**
- **Non-DUP**

For example, if you select **Windows-DUP**, Dell Repository Manager displays the components applicable to the Windows operating system. If you select **Non-DUP**, Dell Repository Manager displays components that are operating system-independent.

Supported Devices

Filters components based on supported hardware devices. The available options are:

- **All**
- **NIC**
- **Hard Disk**
- **Storage Controllers**

For example, if you select **NIC**, Dell Repository Manager displays all the components that contain updated Network Interface Cards (NICs).

Release Date

Filters components based on the release date of the components. The available options are:

- **Any Date**
- **Exact Date**
- **Prior To**
- **Most Recent**

For example, if you type 12/12/2012 and select **Prior to** the Dell Repository Manager displays all the components released earlier than December 12, 2012.

PCI Device Info

Filters components based on the PCI devices. The available options are:

- **All**
- **Contains**

Driver Packs

Filters components based on the Driver Packs. The available options are:

- **PE Maintenance**
- **USC**

Working With Filters

The Dell Repository Manager has an extensive search mechanism that allows you to query repositories, create filters, save, and load filters. Using the filtering capabilities of the Dell Repository Manager, you can view specific bundle(s) and Dell Update Packages (DUPs) from any selected repository.

You can create filters based on the following criteria:

- **Keyword Search**
- **Brand**
- **Supported Platforms**
- **Operating System**
- **Release Date**

Saving Filters

To create or save a filter:

1. On the **My Repositories** tab, select a repository for which you want to search the bundle(s) and component(s) and click **Open**.
The bundle(s) and component(s) for that repository are displayed under their specific tabs.
2. There are no saved filters to select from until you have created and saved them. Once you have gone through the process of saving them, then they appear in the drop-down list. Select the desired filter options from the **Select a filter** drop-down list once you have created one or more filter(s).



NOTE: Refer [Bundle Filters](#) and [Component Filters](#) to analyze the details of each filter before you use them for your customized filter.

3. Once you have finalized the filter properties for your customized filter, click **Save** to save your search and use it in the future.
The **Save Filter** window is displayed.
4. Type a **Name:** and **Description:** for your filter.
5. Click **Save** or click **Cancel** to exit without making any changes.
You can access the saved search/filter from the drop-down list located above the **Keyword Search** field.
The following message displays: `Search Filter Saved...`
6. Click **OK** to close the pop-up window.

Managing Filters

The drop-down box on the left side of the Dell Repository Manager displays the filters that you created and saved.

You need to select the specific filter and use the **Properties** button to view the options:

To view a summary of the all existing filters, click **Manage**. The **Manage Filters** window displays each of the filters that have been saved. The **Filter Name** and **Description** columns can be used to sort the filters. Select the filters you want to manage and click one of the three buttons:

- **Properties** — Allows you to edit the name and description of a selected filter. In the **Properties** window, click **Save** to keep changes or **Cancel** to return to the **Manage Filters** window. If you select **Save**, a **Success** window is displayed. Click **OK** to close it and return to the **Manage Filters** window.
- **Delete** — Click **Delete** → **Yes**, to delete the filter, or click **No** to return to the **Manage Filters** window.

- **Close** — Closes the **Manage Filters** window.

Working With Jobs Queue

The **Jobs Queue** option is available once you launch the Dell Repository Manager. Jobs Queue is a feature which is added to the Dell Repository Manager to enhance usability. You can control and perform different tasks for various repositories under the same console using this feature. With the previous versions of the DRM (until DRM 1.4) users needed to wait for one job to complete before performing another job. Using this feature the user can perform, monitor, and prioritize different jobs at the same time. The tasks can be performed using the [Stop](#), [Start](#), [Remove](#), and [Details](#) tabs.

 **NOTE:** Some of the jobs in the Jobs Queue require the end user to confirm them before it is completed. You can Accept or Reject the job before it goes to the Jobs Queue.

Stopping Jobs In The Jobs Queue

Select the check box next to the job from the **Jobs Queue** and click **Stop** to halt that particular job. You can stop a job at any time while it is running. Once you **Start** a job that has been stopped, the job restarts from the beginning.

Starting Jobs In The Jobs Queue

Select the job from the **Jobs Queue**, and click **Start** to initiate any particular job. Refer to the **Status** and **Progress** tab next to the **Job Name** tab to check the completion. You need to stop the job that is running first if you want to change the order for any job. Also, as soon as you stop the currently running job, the next one in the queue will start to run. Make sure that there is no job in the queue while you are trying to start a previously stopped job.

 **NOTE:** You can only start jobs that have been stopped previously.

Removing Jobs In The Jobs Queue

Select the job from the **Jobs Queue**, and click **Remove** to delete that particular job.

 **NOTE:** You must first **Stop** a job and then it can be **Removed** from the queue. This only applies if that particular job is running at the time. If the job is in the queue, it can be removed without stopping it first. You can select multiple jobs together and remove them from the **Jobs Queue**.

If you close the Dell Repository Manager while a job is still being processed in the **Jobs Queue**, the **Processing Jobs** window displays the following message:

```
You have one job being processed.
Would you like to Stop processing and Exit now?
```

Job names of the jobs which are in processing state is displayed under the **Jobs Queue**.

- Click **Cancel** to close the window and allow the job to finish processing.
- Click **Stop and Exit** to exit the application without completing the jobs in the **Jobs Queue**.

 **NOTE:** You can select multiple jobs together and remove them from the Jobs Queue. The **Remove** option prompts you to reconfirm the removal of the job. Are you sure you want to permanently remove the selected Job(s)? window appears for confirmation. If, the job is already completed, removing the job will not remove the work that is completed, it will only remove the job listed in the jobs queue.

Jobs Queue Details

1. Select the job from the **Jobs Queue**, and click **Details** to view the **Job Execution Details**.
2. Click **Report** tab to view the Job Details.
The **Job Details** window displays the information on the **Job Name**, **Repository**, **Job Status**, **Job Result**, **Download Path**, and the information on the **Files failed** to download.
3. Click **Log** to view the timing details.
4. Click **Close**.

Updating A Local Repository

1. On the **My Repositories** tab, select a local repository, which is located on the system, and click **Open**.
2. Click **Run a comparison** on the top of the **Dell Repository Manager** screen.
The **Update Repository** window is displayed.
3. On the **Update Repository** screen, the **Destination Repository** box displays the name of the repository open at the time **Run a comparison** was selected. The **Source Repository** box defaults to **Source**. However, any existing repository can be selected from the drop down menu in this box. Click **Compare**.
The **Comparing Repositories** window is displayed with the progress bar while **Setting up comparison result....** The **Comparison Summary:** window is displayed.
 **NOTE:** **Newer Versions**, **Changed Files**, **Obsolete Files** and **Other Files in Source** screens provide further details on DUPs that can be installed to update the repository. You can see a list of the DUPs once you select any system from the **System Filter** or **Device Filter**.
4. You can select **All** or any specific DUP to update that local repository from the **Newer Versions**, **Changed Files**, **Obsolete Files** and **Other Files in Source** screens.
 **NOTE:** By default, the **Show report after update** check box is marked at the bottom of the **Update Repository** window. You can uncheck this box if you don't want to see the report after every update.
5. Click **Update**.
The **Comparing Repositories** window appears with the progress bar while **Updating Base repository components....** The **Update Report** window is displayed.
 **NOTE:** A check box appears next to **Name** of the particular DUPs once you add them to the repository.
6. Click **Close** to exit from the **Repository Update Report**. Click **Save As...** to store the **Repository Update Report** in the system.
7. Click **Close** to close the **Update Repository** window.

Creating A Custom Repository Using Dell OpenManage Essentials

To create a local repository for Dell OpenManage Essentials:

1. On the **My Repositories** tab, select **New** → **Dell OpenManage Essentials (OME) inventory**.
2. Type a **Name**: and **Description**: for the repository, and click **Next**.
3. On the **Base Repository** screen, select one of the following options and click **Next**.
The options are:
 - **Source Repository** — Imports the default repository. This option is enabled only if you have access to the Internet. You can import the bundle(s) and components from this repository into the repositories you create.

- **My Repositories** — Allows you to select an existing repository as the base repository.

The **System inventory** window is displayed.

4. Under **Use inventory data from Dell OpenManage Essentials?** option select one of the following:

- **Yes** — To create a custom repository using the inventory option.
- **No** — To create a custom repository without using the inventory option.

5. Select **Yes**, click **Connect**.

The **Dell OME Host Details** window is displayed.

 **NOTE:** If you select **No**, the only available option is to create the custom repository with the **Latest updates for all devices**.

6. Provide the **Host Name or IP Address**.

 **NOTE:** Select **Use different user credentials** if the user identification is different and provide the **User Name** and **Password**.

7. Click **OK** or **Cancel** to exit without making changes.

The **Getting OME Inventory** window appears while retrieving inventory from the server. A list of the systems, which displays the discovered systems under OME appear. You can select one of the following options:

- **Latest updates for all devices** — Creates a repository where all the listed systems fetch their corresponding updates.
- **Latest updates for only out-of-date devices** — Creates a repository and update only for the out-of-date components.

 **NOTE:** Click **Resync** to retrieve the updated inventory data, if you have modified or removed certain systems from the systems managed by **Dell Management Virtual Appliance Host**.

8. Click **Next** or **Cancel** to exit without making changes.

The **Summary** window is displayed. Select the options you want to include in the repository:

- Windows x32 Bundles and Components
- Windows x64 Bundles and Components

The **Please wait...** dialog box appears while creating the new repository.

9. Click **Finish** or **Cancel** to exit without making changes.

Once completed, the **Repository created** window is displayed. A **New repository was created successfully** summary page appears with the name of the new repository, number of new bundles added to the repository, and the number of new components added to the repository. Also a list of hosts with errors, if any are found, will be displayed.

10. Click **Close**.

 **NOTE:** OME 1.0 and DRM 1.7 must be installed on the same system; however, OME 1.1 and higher versions and DRM 1.7 can be installed and run on different systems. DRM 1.7 can access OME 1.1 and higher versions inventory data from a remote system. In DRM 1.7, you must click **Connect** to obtain inventory data from OME irrespective of the version of OME it interacts.

Scheduling Automatic Search

The following are the benefits of using the **Automatic Search** feature to schedule an automatic download and/or build an update repository from the support site:

- Downloading updates from Dell Support site for one or more Dell products based on the brands and service tags can be scheduled. This schedule can be used to check and download updates periodically, during the off peak hours.
- The updates downloaded from the Dell Support site can be saved as a local repository which can be used with system management tools such as OpenManage Essentials, to update one or more systems.
- Updates can be saved as a new repository in the Dell Repository Manager database, which can be used to update other custom repositories in the database.
- Updates can be packaged in a Lightweight Deployment Pack (LWDP) available to be used directly to update the systems. The update process can be automated with the help of the batch (.bat for Windows) or shell (.sh for Linux) files created as part of the LWDP.



NOTE: The Windows Task Scheduler must be started to enable the **Automatic Search** feature. You can enable The Windows Task Scheduler service in the Windows Services console. To use the **Automatic Search** feature, you require an internet connection.



NOTE: Updates for Dell legacy systems are available with this search feature.

You can automate and schedule the search option for updating files from dell.com/support.

1. On the **Dell Repository Manager** screen, click **Source** → **Schedule Automatic Search**.
The **Automatic Search** window is displayed. You can select **Cancel** at any time to exit without making any changes.
2. Under **Search Method**, select any one of the following:
 - **Brand** — Search based on selected brands.
 - **Service Tag** — Search a system based on the Service Tag provided.
3. If you select the **Brand** option, select a brand from the **Brand** drop-down list box.
The list of models for the selected brand appears in the **Models** box.
4. From the **Models**: select the desired model and click **Add >**.
Repeat step 3 to add more models to the selected items list. The model(s) selected are displayed on the right.



NOTE: The **Service Tag** option allows you to search a device based on the Service Tag provided.



NOTE: To remove a model from the selected items, select the model from the **Selected:** box and click **Remove**.
Repeat the step, if you want to remove more models from the selected items.

5. Under **Include the following types of update files in the search results**, select the type(s) of update files from the following list:
 - **Update Type**
 - * **Application**
 - * **BIOS**
 - * **Driver**
 - * **Firmware**
 - * **Utilities**
 - **Criticality**
 - * **Optional**
 - * **Recommended**
 - * **Urgent**
 - **Operating System**
 - * **Windows 32-bit**
 - * **Windows 64-bit**

- * **Linux (32-bit & 64-bit)**
 - **Availability**
 - * **All available files**
 - * **New files not in Dell FTP Catalog**
 - * **All files not in Dell FTP Catalog**
6. Click the **Actions** tab, and select one of the following options:
 - **Import updates to an existing repository** — This option allows you to import update files to repositories that exist in the Dell Repository Manager.
 - **Import updates to a new repository** — This option is selected by default. You can type a prefix for the new repository. By default the prefix is **Repo**.
 - **Save updates to a local repository** — This option is also selected by default. If you want to save the update file locally, then click **Browse** to navigate to that location where you want to save the update file.
 - **Export updates as a Lightweight Deployment Package (LWDP)** — Select this option and click **Browse** to navigate to the location where you want to save the update file as an LWDP. You can save all the updates to a folder or do a force update.
 7. Click the **Schedule** tab.
 8. Select **Enable automatic searching for update files from Dell Support Site (www.dell.com/support)**.
 9. Select the **Start** date, **Settings**, and **Security Options**.
 - **Start:** — You can set the date and time for the automatic search.
 - **Settings** — You can set the frequency of the schedule.
 - **Security Options** — You can set the type of security.
-  **NOTE:** The **Save** button becomes active after all of the options have been selected.
10. Click **Save** to complete the process.
A **Task Creation** pop-up window is displayed.
 11. Click **Yes** or click **No** to exit the window.
An **Automatic Search** widow is displayed confirming that the task has been successfully created.
 12. Click **OK**.

Searching Dell Support Site

This feature allows the users to search for the latest updates from the Dell Support site for more than one platform. The updates can be downloaded using DRM, which save time as compared to searching the support site for individual updates related to different platforms.

1. On the **Dell Repository Manager** screen, click **Source** → **Search the Dell Support Site**.
The **Search Dell Support Site** screen is displayed.
 2. On the **Search** tab (open by default), under **Search Method**, select the **Brand** option and select the type of device.
 3. Under **Models**: select the desired model and click **Add >**.
Repeat step 3 to add more models to the selected items list. The model(s) selected are displayed on the right.
-  **NOTE:** The **Service Tag** option allows you to search a device based on the Service Tag provided.
-  **NOTE:** To remove a model from the selected items, select the model from the **Selected:** box and click **Remove**.
Repeat the step, if you want to remove more models from the selected items.
4. Under **Search Options (File Format)**, select one of the following options:

- **Dell Update Packages** — This is the default option. You can import all the DUPs to the local repository when you use the default option.
 - **All file formats** — You can download all the non DUP files to the system by choosing this option, but you cannot import other non DUP files to the local repository.
5. Click **Search**.
- The **Searching for Latest updates** window is displayed. This may take several minutes to generate the list of all the updates, depending on the number of updates.
- Or click **Clear** to reset the search options and start from the beginning.
- In the **Search Results** window you can view the details for individual updates. The **Dell Update Package** column displays whether the update is a DUP or non-DUP file. You can download a file or export a DUP file to the local system as well as a component for an existing or new repository. You can also download the non-DUP files to the system, however, you cannot export the non-DUP files.
-  **NOTE:** If there are no updates found, a window is displayed with the message `There are currently no updates available for the selected platform(s)` . Click **OK** to exit.

Exporting Updates From Support Site

1. On the Dell Repository Manager screen, click **Source** → **Search the Dell Support Site** .
2. On the **Search** tab, select the **Brand** option and select the type of device.
3. Under **Models**: select the desired model and click **Add >**.
4. Under **Search Options (File Format)**, select one of the following options:
 - **Dell Update Packages**
 - **All file formats**
5. Click **Search**.
- The **Searching for Latest updates** window is displayed.
6. Once the results are displayed, select one or more updates (these updates can be filtered).
7. Click **Export**.
- The **Export to repository** window is displayed.
8. You can choose the following options from the **Repository Export options**:
 - **Select one or more repositories to Export to:** — You can select the desired repositories from this list.
 - **Exports update to a new repository** — You can exports update to a new repository. The **Export to New repository** window is displayed. You need to provide details for the **Name:** and **Description:** fields.
9. Select one or both of the **Bundle Options** to export updates to bundles in repositories. Click **Ok** to proceed further or click **Cancel** to exit without making any changes.
 - **Replace old files in new files in all bundles** — Replaces all the older versions of the DUPs in the bundles.
 -  **NOTE:** The Bundle disclaimer window is displayed with all the Dell bundles which can be updated with this export.
 - **Create new bundle** — Creates a new bundle for different platforms and operating systems with generic names.
10. The **Support Files download Queued** window is displayed.
A **Support file export** job has been submitted to the Jobs Queue.
11. Click **OK** to close the window.

Filter Options For Search Results

You can use the following filters in the Dell Repository Manager:

OS Type (DUP Only)

- Allows you to filter the search based on the operating system selected. The options available are:
 - Windows 32-bit
 - Windows 64-bit
 - Linux (32-bit & 64-bit)

Criticality

- Filters the component(s) based on the criticality of the update. The available options are **Recommended**, **Urgent**, and **Optional**.

For example, if you select **Urgent**, the Dell Repository Manager displays all the components that require an immediate update.

Update Type

- Filters the component(s) based on the type of update required for the component. The available options are **BIOS**, **Firmware**, **Driver**, **Application**, and **Utilities**.

For example, if you select **BIOS**, the Dell Repository Manager displays all the bundle(s) and components that require a BIOS update.



NOTE: This filter displays the components only if they match the search criteria.

Availability

- Filters based on the availability of the update file. You can select from the following options:
 - **All available files** — Lists all the possible files from the catalog file.
 - **New files not in Dell FTP Catalog** — Lists the files that are posted later than the FTP catalog date.
 - **All files not in Dell FTP catalog** — Lists the files that are already part of the Dell FTP catalog.

File Format

- Filters based on the required file format for the update. You can select from the following options:
 - **Dell Update Packages (DUP)** — This is the default option. You can import all the DUPs to the local repository when you use the default option and chose download.
 - **Non-DUPS** — You can download all the non DUP files to the system by choosing this option, but you cannot import non DUP files to the local repository.

Dates

- Filters updates based on the selected time period. You can select from the following options:
 - **Any Date** — Display updates for any dates.
 - **Date Range** — You can assign a **Start** and **End** date to filter the updates periodically using this filter.

Frequently Asked Questions

This section lists some frequently asked questions about the Dell Repository Manager.

Where is the Dell Repository Manager runtime log located?

Dell Repository Manager creates two log files at runtime:

- **DellRepositoryManager_Server.svclog** — Data Center Version
- **DellRepositoryManager_Client.svclog** — Business Client Version

The log file is located in `C:\Users\<user name>\AppData\Local\RepositoryManager\Log`.

I see an update present in dell.com/support but when I install the repository from ftp.dell.com using the Dell Repository Manager, I do not see that update.

The Dell online repository, which is supported by Dell OpenManage, is released monthly and is qualified by the Dell testing process. Occasionally, updates may be available on **dell.com/support** before the contents of the repository on **ftp.dell.com** are updated. The new **dell.com/support** feature of Dell Repository Manager can search the latest update(s) from the Dell support site. You can use Dell Repository Manager to add the new updates into your repository.

How do I view the unassigned components in a repository?

1. Select a repository and click the **Components** tab.
2. From the **Display from bundles** drop-down list, select **Unassigned Components**. The Dell Repository Manager displays the unassigned components.



NOTE:

The **Unassigned Components** option is not displayed if the repository does not have any unassigned components.

How do I edit the search criteria of the filter that I created?

In the left pane of Dell Repository Manager, select the filter criteria from **Filter <Bundles/Components> by:** list: You can edit the filter criteria for these features or specify new criteria.

Can the Dell Repository Manager be run through a Proxy Server?

Yes, install Dell Repository Manager inside the firewall and connect to a catalog located outside the firewall (ftp.dell.com or a local repository) through a proxy server. You can use the proxy server settings of Internet Explorer. If the proxy settings for Internet Explorer are not working, the proxy can be set in DRM. You can then use Dell Repository Manager to customize the catalog as per the requirement and store the customized catalog inside the firewall.

Why would I use the Dell Repository Manager to create the catalog that LifeCycle Controller uses, instead of just using the catalog on the Server Update Utility (SUU)?

Since, SUU supports Dell systems from Dell PowerEdge 8th generation systems to the most current systems, the catalog size on SUU is greater (over 7 GB), than the catalog size on the Dell Repository Manager. In the Dell Repository Manager you can select the systems that you want to manage, thereby decreasing the catalog size (PowerEdge R710 = 729 MB).

When I select Schedule Automatic Search, there is a pop-window that appears with the following message:

Dell Repository Manager Fatal UI, Error: Dell Repository Manager has encountered an error.

DRM creates a Windows Scheduler task behind the scenes to perform automatic search of the Dell update files. The error can occur when you open the **Schedule Automatic Search** screen and set a **Start Date** that is set in the past. You can change the **Start Date** on the **Windows Task** to a future date.

1. Launch **Windows Task Scheduler** from **Programs Menu**.
2. Navigate and click on the **Task Scheduler library** node on the left pane.
3. Search for **DellRepositoryManagerDataCenterVersion-FindNewUpdates-...** task. This is a Windows tasks that is created by DRM.
4. Click **Properties**.
5. Select the **Triggers** tab.
6. Search for the trigger that you specified using DRM. Edit this trigger and change the **Start** date to a future time.
7. Once the **Start** date has changed, re-launch DRM to make any changes to **Automatic Search**.

If I export a bundle using Export to light weight deployment scripts, am I going to re-download the DUPs which are already in my system?

Whenever a DUP is downloaded, it is stored locally in a file system [%localappdata%\RepositoryManager\FileStore] location. It is not stored using the DUP file name in that location, hence it is not traceable with the exact DUP names. For further use of the DUPs, DRM will fetch them from this location and will NOT re-download.