

Print Services Facility for z/OS



Security Guide

Version 4, Release 1.0

Print Services Facility for z/OS



Security Guide

Version 4, Release 1.0

Note

Before using this information and the product it supports, be sure to read the general information in "Notices" on page 33.

First Edition (November 2005)

This edition applies to the IBM Print Services Facility Version 4 Release 1 Modification 0 for z/OS, Program Number 5655-M32, and to all subsequent releases and modifications until otherwise indicated in new editions or technical newsletters. Be sure to use the correct edition for the level of the product.

Order publications through your IBM representative or the IBM branch office serving your locality. Publications are not stocked at the address given below.

The IBM Printing Systems Division welcomes your comments. A form for reader's comments is provided at the back of this publication. If the form has been removed, you may send your comments to the following address:

INFORMATION DEVELOPMENT
THE IBM PRINTING SYSTEMS DIVISION
DEPARTMENT H7FE BUILDING 004N
PO BOX 1900
BOULDER CO 80301-9191
U.S.A.

If you prefer to send comments electronically, use one of the following methods:

- Internet: printpub@us.ibm.com
- Fax: 1-800-524-1519 or 1-303-924-6873

Internet

Visit our home page at <http://www.ibm.com/printers>.

When you send information to IBM, you grant IBM a nonexclusive right to use or distribute the information in any way it believes appropriate without incurring any obligation to you.

© Copyright International Business Machines Corporation 1989, 2005. All rights reserved.

US Government Users Restricted Rights – Use, duplication or disclosure restricted by GSA ADP Schedule Contract with IBM Corp.

Contents

Figures	v
Tables	vii
About This Publication	ix
Who Should Read This Publication	ix
How This Publication Is Organized	ix
Fast Path	x
Understanding the Syntax Notation Used in This Publication	x
Related Information.	x
Using LookAt to View Message Explanations	xi
Summary of Changes	xiii
Chapter 1. Introducing the Print Labeling Function	1
Understanding Print Labeling	1
User-Printable Area.	2
Distributing Secure PSF Output	3
Auditing PSF Output for Security.	3
Introducing Trusted Computing Base Components	3
Trusted Software	4
Trusted Hardware	5
End Users	6
Choosing from a List of Security-Related PSF Tasks	6
Chapter 2. Using Print Labeling	7
Installing PSF	7
Printer Support in PSF	7
Designing Pages for Print Labeling	8
Creating Security Overlays	8
Allocating the Security Definitions Library.	8
Security Definitions Library Attributes	9
Defining a Security Definitions Library	9
Syntax for a Security Definitions Member.	9
Rules for Defining a Security Definitions Member	11
Sample Security Definitions Member	12
Defining Security Resource Libraries	13
Defining a Security Console	14
Assembling Separator Pages.	14
Enabling Print Labeling	15
Using RACF with PSF for z/OS.	15
PSF Processing Differences When Using the Print Labeling Function	16
Updating Initialization Parameters	17
Updating Print Labeling Parameters	18
Defining Data Definition Names in the PRINTDEV Statement	19
Submitting a Print Job that Includes Identification Labels	20
Overriding Print Labeling Defaults	21
Maintaining PSF for z/OS with Print Labeling Enabled	21
Auditing PSF Printing	21
Interpreting Security-Related Messages	22
Diagnosing Print Labeling Problems	22
Appendix A. Security Page Layout	27

Appendix B. PAPERNAME Table for System-Defined Paper Names.	29
Appendix C. Accessibility	31
Using Assistive Technologies.	31
Keyboard Navigation of the User Interface.	31
z/OS Documentation.	31
Notices	33
Trademarks	34
Glossary	35
Bibliography	39
Print Services Facility (PSF) for z/OS	39
Infoprint Server.	39
Advanced Function Presentation (AFP)	40
Data Transforms	40
Text Processing	40
Infoprint Manager	41
Content Manager OnDemand	41
i-data	42
z/OS Version 1 Release 7.	42
Index	45

Figures

1. Print Labeling	1
2. Placing Identification Labels on the Physical Page	2
3. Random Numbering of Printed Output	3
4. Typical Components of a Trusted Computing Base	4
5. Library Attributes for the Security Definitions Library	9
6. Syntax for a Security Definitions Library Member	9
7. Sample Coding of a Member	12
8. Page Layout for a Cut-Sheet Page	13
9. Page Layout for a Continuous Form	13
10. ROUTCODE Option for Routing Messages	14
11. ROUTCODE Option for Stopping Messages	14
12. Activating SECLABEL	15
13. Using the RACF SETROPTS and RDEFINE Commands	15
14. Adding a User ID to a RACF Profile	16
15. Refreshing RACF	16
16. Sample PSF Startup Procedure with Security-Related Parameters Highlighted	17
17. Sample JCL Job Card	21
18. Sample JCL Output Statement	21
19. Security Page Layout	27

Tables

1.	Security Tasks and the People Who Perform Them.	6
2.	Library Attributes for a Security Resource Library	13
3.	PSF Exit Routines in SYS1.SAMPLIB	14
4.	Parameters for Enabling Print Labeling.	19
5.	Print Labeling Diagnosis	23
6.	PAPERNAME Parameter Values.	29

About This Publication

This publication is designed to help programmers, analysts, and administrators who install, customize, or maintain Print Services Facility™ (PSF) for z/OS® (hereafter referred to as PSF) as a component of a trusted computing base.¹ PSF runs on z/OS and z/OS.e systems. In this publication, the term “z/OS” refers to both systems, unless otherwise specified.

This publication describes the PSF function called print labeling. This function can be used to produce printed output containing special labels. These labels can be used for security purposes or other installation-defined purposes.

Note: Print labeling can be done with PSF even if PSF is not a part of a trusted computing base.

Who Should Read This Publication

You should use this publication if you are a system programmer, a system analyst, a security administrator, a security auditor, or an application programmer who is responsible for data security.

You should be familiar with the material contained in *PSF for z/OS: Customization* and *PSF for z/OS: User's Guide* before attempting any of the procedures described in this publication.

How This Publication Is Organized

This publication is intended to help you perform the tasks in Table 1 on page 6. The information in this publication must not be used for programming purposes.

This publication is organized so that you can read it sequentially or refer directly to individual tasks.

- Use Chapter 1, “Introducing the Print Labeling Function,” on page 1 for an overview of the PSF print labeling function and how PSF operates within a trusted computing base.
- Use Chapter 2, “Using Print Labeling,” on page 7 when working with an operating system that supports print labeling.
- Use Appendix A, “Security Page Layout,” on page 27 when designing pages for printing using the print labeling function of PSF.
- Use Appendix B, “PAPERNAME Table for System-Defined Paper Names,” on page 29 to find a list of system-defined paper names used when establishing a security definitions library.
- Use Appendix C, “Accessibility,” on page 31 to obtain information about the accessibility features available in z/OS.

A notices section, glossary, bibliography, and index are included. The bibliography lists the publications containing additional information about the system, hardware, or software used by PSF, or about installation and maintenance.

1. A trusted computing base consists of components that together enforce a unified security policy over a computing environment. See “Introducing Trusted Computing Base Components” on page 3 for more information.

Fast Path

For a list of security-related tasks, see Table 1 on page 6. This fast path is provided so that you can quickly access task information if you are already familiar with the PSF print labeling function.

Understanding the Syntax Notation Used in This Publication

The following rules apply to syntax examples and coding illustrations throughout this publication:

- The uppercase letters are to be entered as shown; however, you do not need to type them in uppercase.
- The variable data you must provide is printed in italics. Enter specific data to replace the characters in italics; for example, for *PRTnnnn* you could enter PRT2.
- Do not enter any of the following symbols as part of a parameter or an option:

Vertical bar	
Underscore	—
Braces	{ }
Brackets	[]

- A vertical bar between two values means that you are to select only one of the values.
- If one value in a set of values is underscored, that value is the default—that is, the value that PSF uses if no option is specified.
- If values are enclosed in braces { }, one or the other of the values in the braces must be selected.
- If a value is enclosed in brackets [], you do not have to select that value.

Related Information

Publications that are referred to in this document or that contain additional information about AFP™, the z/OS operating system, PSF, and related products are listed in the “Bibliography” on page 39.

For additional information about z/OS and PSF for z/OS, refer to these Web pages:

<http://www.ibm.com/servers/eserver/zseries/zos/>
http://www.printers.ibm.com/internet/wwwsites.nsf/vwwebpublished/zseriessoftware_ww
http://www.printers.ibm.com/internet/wwwsites.nsf/vwwebpublished/psfhome_z_ww

To obtain the latest documentation updates for z/OS base elements and optional features that result from DOC APARs and PTFs, refer to this DOC APARs and ++HOLD DOC Web page:

http://publibz.boulder.ibm.com/cgi-bin/bookmgr_0S390/B00KS/ZIDOCMST/CCONTENTS

To obtain the latest documentation updates for PSF for z/OS, refer to these members in SYS1.SAMPLIB:

Member	Publication
APSGADP1	<i>PSF for z/OS: AFP Download Plus</i> , S550-0433
APSGCUS1	<i>PSF for z/OS: Customization</i> , S550-0427
APSGDGN1	<i>PSF for z/OS: Diagnosis</i> , G550-0428

Member	Publication
APSGDLG1	<i>PSF for z/OS: Download for z/OS</i> , S550-0429
APSGMAC1	<i>PSF for z/OS: Messages and Codes</i> , G550-0432
APSGSEC1	<i>PSF for z/OS: Security Guide</i> , S550-0434
APSGUSR1	<i>PSF for z/OS: User's Guide</i> , S550-0435

Using LookAt to View Message Explanations

LookAt is an online facility that lets you view explanations for most IBM® messages and some system abends and codes. Using LookAt to find information is faster than a conventional search because in most cases LookAt goes directly to the message explanation. To find a message explanation in LookAt, you enter the message identifier (for example, IAT1836 or IAT*).

You can access LookAt from these locations:

Internet

You can access the LookAt Web site at:

<http://www.ibm.com/eserver/zseries/zos/bkserv/lookat/>

z/OS TSO/E host system

You can install code on your z/OS or z/OS.e system to access LookAt from a TSO/E command line, such as TSO/E prompt, ISPF, or z/OS UNIX® System Services.

Microsoft® Windows® workstation

You can install code on your workstation to access LookAt from a Microsoft Windows command prompt (also known as the DOS command line).

Wireless handheld device

You can link to the LookAt Mobile Edition from the LookAt Web site to access LookAt from a handheld device that has wireless access and an Internet browser, such as Internet Explorer for Pocket PCs; Blazer or Eudora for Palm OS; or Opera for Linux™ handheld devices.

To install LookAt on your TSO/E host system or Microsoft Windows workstation, you can obtain the code from:

- A CD-ROM in the *z/OS Collection*
- The *z/OS and Software Products DVD Collection*
- The LookAt Web site's **Download** link. More information is available in the LOOKAT.ME files available during the download process.

Some messages have information in more than one document. For those messages, LookAt displays a list of documents that contain the message.

Summary of Changes

Summary of Changes for *PSF for z/OS: Security Guide*, S550-0434-00

This publication contains additions and changes to information previously presented in *PSF for z/OS: Security Guide*, S544-3291-02. The technical additions and changes are marked with a revision bar (|) in the left margin.

These changes have been made throughout the document:

- References to OS/390® have been removed.
- This publication has been enabled for these z/OS Library Center advanced searches: concepts, references, and tasks.

The following information is new or updated:

- “Syntax for a Security Definitions Member” on page 9 has been updated to indicate that there can be multiple secure font, overlay, and page-segment libraries.
- “Enabling Print Labeling” on page 15 has been edited for accuracy.
- “Defining Data Definition Names in the PRINTDEV Statement” on page 19 has been updated with eight new parameters.
- Terms in the glossary have been updated so that they are consistent with term definitions used across IBM.

Chapter 1. Introducing the Print Labeling Function

This chapter introduces the concept of print labeling and explains how PSF for z/OS operates within a secure computing environment.

Understanding Print Labeling

The PSF function called print labeling lets you place identification labels on each page of printed output. An identification label can be composed of text, graphics, or a combination of both. Identification labels can be used for security information, such as a TOP SECRET security level, or for other installation-defined purposes. Identification labels can be placed on the top, bottom, or sides of all pages within a job. Up to eight labels can be defined to print on every page of the job.

An identification label is positioned on the page using a resource called a security overlay. The overlays, as well as the resources used by the overlays, such as fonts and page segments, are stored in special security libraries.

Print labeling can be applied to data pages, as well as to separator pages. Figure 1 shows labeling applied to a data page from one job and a separator page from another job.




Figure 1. Print Labeling. Identification labels can be placed on the top, bottom, or sides of all pages within a job. This example shows a page from two different jobs.

The two types of print labeling are *guaranteed print labeling* and *nonguaranteed print labeling*. Guaranteed print labeling works with a subset of Advanced Function Presentation™ (AFP) printers and ensures the integrity of the identification label by preventing the user from changing the label. Nonguaranteed print labeling works on most AFP printers, but the integrity of the identification labels cannot be guaranteed. For a list of printers that support print labeling, see “Printer Support in PSF” on page 7.

Print labeling works like this:

1. The end user submits a print request that uses data and resources from host libraries. The print request has a security label associated with it. The label is a combination of both the security level and the security class.
2. Resource Access Control Facility (RACF[®]), a component of z/OS Security Server, checks to ensure that the end user's security label matches the security labels of all requested user data or user resources. If the labels match, the data is placed on the spool.
3. PSF formats the data and resources, using the security label of the print job to apply the appropriate security overlays to all pages of the printed output.

The integrity of the identification label is ensured by the positioning of the label in an area of the page where user data cannot be placed. To enforce this, the valid printable area of a form for user data is reduced by the definition of a user-printable area.

User-Printable Area

The user-printable area (UPA) is the area on the page that contains all user-generated data. If an attempt is made to print user-generated data outside the UPA, an exception condition occurs. Identification labels are placed outside of the UPA, but within the valid printable area of the form. Figure 2 shows a layout of where an identification label can be placed.

When guaranteed print labeling is enabled, an appropriate UPA must be defined by the system programmer for each paper size that can be used to print data with a particular identification label. Different UPAs can be defined for the same paper size when different identification labels are used.




Figure 2. Placing Identification Labels on the Physical Page. Identification labels should be placed outside the UPA but must be placed within the physical page boundaries.

For a template that you can use to lay out your pages and define the UPA, see Appendix A, “Security Page Layout,” on page 27.

Distributing Secure PSF Output

PSF prints a randomly generated number for each job on the header and the trailer pages of the job if guaranteed print labeling is being performed. The printer operator matches the number on the header page to the number on the trailer page before distributing the job output. By ensuring that the numbers match, the printer operator ensures output security. Figure 3 illustrates the printed numbers.




Figure 3. Random Numbering of Printed Output. The printer operator is responsible for matching the random numbers and distributing the printed output.

Auditing PSF Output for Security

PSF and RACF record security exceptions and help the security administrator audit PSF activity. For more information about auditable conditions, see “Auditing PSF Printing” on page 21.

Introducing Trusted Computing Base Components

A *trusted computing base* consists of components that together enforce a unified security policy over a computer environment. Components of a trusted computing base include hardware and software. PSF is a software component used in conjunction with hardware and other software components to provide a trusted computing base. Figure 4 on page 4 illustrates a sample trusted computing base.




Figure 4. Typical Components of a Trusted Computing Base. Your installation might have different components installed.

Trusted Software

Trusted software is the software portion of the trusted computing base. It includes:

Access control software

Access control is regulated by RACF, which:

- Authorizes user sessions based on user ID.
- Authorizes resource access.
- Ensures that only users identified to RACF can access the processor or resources.

For more information about how to protect processing with RACF, refer to *z/OS Security Server RACF Security Administrator's Guide*.

Trusted spooling software

In a trusted computing base, spool files are protected through RACF and your spooling software. For example, in z/OS, the Job Entry Subsystem (JES) spool is protected by activating the RACF JESSPOOL security class and by defining RACF profiles. For information about defining PSF-related RACF profiles, see "Using RACF with PSF for z/OS" on page 15.

Trusted printer-driver software

In a trusted computing base, secure printed output is controlled through PSF (the printer-driver software) and RACF. Output from a trusted printer has identification labels printed on each page.

Trusted communications software

In a trusted computing base, communications software is used to connect input and output devices to the main processor. For example, Communications Server: IP Services can be used to connect end-user terminals to the main processor and let users communicate with one another.

In a trusted computing base, communication through networking software is controlled through RACF, and communication between users can be restricted or prohibited based on defined security clearances. Refer to your networking software publications for more information about controlling network access with RACF and for defining security clearances for end-user terminals.

Trusted resources

In a trusted computing base, some resources are defined as security resources and are managed differently from other resources. For example, fonts, overlays, and page segments that are used to print identification labels are stored in secure libraries, and only the printer driver can access these resources for printing.

Trusted Hardware

Trusted hardware is the set of equipment protected through RACF in the trusted computing base. It includes:

Trusted processor

In a trusted computing base, the main processor provides access control for admittance to all resources and end-user processing. Communication between trusted and nontrusted processors is restricted.

Trusted printers

In a trusted computing base, a trusted printer is one that supports guaranteed print labeling. For more information on guaranteed print labeling and printers that support guaranteed print labeling, see “Printer Support in PSF” on page 7.

In addition, a trusted printer is located in a controlled area. Only the printer operator is allowed to distribute output to the end user.

Trusted console

In a trusted computing base, a trusted console is a computer terminal that is defined to RACF with a security label. In addition, a trusted console is located in a controlled area where only authorized personnel are allowed to access the console.

A trusted console, or *security console*, can still be restricted from accepting certain console operator commands. For example, in z/OS, JES3 commands are grouped into command authority levels, and consoles can be defined to accept only certain levels of JES3 commands from the console operator. For more information about defining a console to RACF, refer to the RACF publication for your operating system.

For information about diverting PSF messages from a master console to a security console, see “Defining a Security Console” on page 14.

End Users

In a trusted computing base, the end user must be defined to RACF using a security level and a security class. Both the security level and the security class make up the *security label* of the end user. Only end users who have a security label assigned to the end-user terminal can use the trusted computing base.

Choosing from a List of Security-Related PSF Tasks

Table 1 matches personnel with security-related tasks described in detail within this publication. You can use this table as a fast path that directs you to security-related tasks contained in this publication.

Note: Your installation might or might not have the unique personnel listed in the table.

Table 1. Security Tasks and the People Who Perform Them

Security-Related Tasks	Personnel	See Page:
Install PSF	System programmer	7
Determine how your printer supports print labeling	System programmer and security administrator	7
Allocate security definitions libraries	System programmer and security administrator	8
Define security definitions library	System programmer and security administrator	9
Define security resource libraries	System programmer and security administrator	13
Design page layouts for each size of paper	System programmer, security administrator, and application programmer	27
Create security overlays	System programmer, security administrator, and application programmer	8
Define security consoles	System programmer and security administrator	14
Update the PSF startup procedure	System programmer and security administrator	17
Enable print labeling	System programmer and security administrator	15
Activate separator page content (random numbering)	System programmer or security administrator	14
Submit a print job that requires identification labels	End user who is RACF authorized	20
Check PSF output for security	Printer operator	3
Diagnose print-labeling problems	System programmer and security administrator	22
Interpret security-related error messages	Console operator, system programmer, security administrator, and application programmers	22
Perform security audits	Security administrator and installation auditor	21

Chapter 2. Using Print Labeling

This chapter describes how to enable, customize, and maintain the print labeling function of PSF for z/OS. The procedures, examples, and parameters given in this chapter apply only to a z/OS or z/OS.e operating system.

While using this chapter, you can find helpful information in the following publications:

- *PSF for z/OS: Customization*
- *PSF for z/OS: User's Guide*
- *Overlay Generation Language User's Guide and Reference*

You should be familiar with PSF customization before attempting to enable the print labeling function.

The following tasks are described in this chapter and could be performed in the following sequence. Your installation might not require all tasks.

1. "Installing PSF"
2. "Designing Pages for Print Labeling" on page 8
3. "Allocating the Security Definitions Library" on page 8
4. "Defining a Security Definitions Library" on page 9
5. "Defining Security Resource Libraries" on page 13
6. "Defining a Security Console" on page 14
7. "Assembling Separator Pages" on page 14
8. "Enabling Print Labeling" on page 15
9. "Updating Initialization Parameters" on page 17
10. "Submitting a Print Job that Includes Identification Labels" on page 20
11. "Maintaining PSF for z/OS with Print Labeling Enabled" on page 21

Installing PSF

Install PSF as instructed in the *Program Directory for Print Services Facility for z/OS*, which is shipped with the PSF licensed program tapes. This directory contains information about the microcode levels for specific printers. You need to make sure that the appropriate level of microcode is installed on your printer before your printer can support guaranteed print labeling.

Printer Support in PSF

AFP printers can support guaranteed print labeling or nonguaranteed print labeling. To determine the type of print labeling your printer supports in PSF for z/OS, use the display printer information function. If the Define User Area is listed in the DEVICE CONTROL COMMAND Set Vector of the Sense Type and Model (STM), the printer supports guaranteed print labeling; if it is not, the printer supports nonguaranteed print labeling. For more information about the display printer information function, refer to *PSF for z/OS: Customization*.

For more information about guaranteed print labeling and nonguaranteed print labeling, see "Enabling Print Labeling" on page 15.

For more information about AFP printers, refer to *IBM Printing Systems: Printer Summary* and *IBM Printing Systems: Printer Information*.

Designing Pages for Print Labeling

These are the steps required to design pages for print labeling:

1. Identify any fonts or page segments that you want to use in the identification label. For information about identifying fonts and page segments, see “Defining Security Resource Libraries” on page 13 and “Defining Data Definition Names in the PRINTDEV Statement” on page 19.
2. Construct a page layout. See Appendix A, “Security Page Layout,” on page 27 for a page layout tool.
3. Create security overlays as needed. See “Creating Security Overlays.”
4. Create a security definitions library (allocate and define members). Each combination of security label, paper size, and page top must be defined to PSF in a member of a security definitions library. To define members in a security definitions library, see “Defining a Security Definitions Library” on page 9.

Creating Security Overlays

You should create at least one security overlay for each security label that you are using on your system. The same overlay can be used on different paper sizes and orientations but the overlay must be carefully designed, taking into consideration the media origin and the printable area differences. More than one security overlay can be created for each combination of security label, paper size, and orientation, if desired.

Security overlays are created as you would create other overlays, but RACF is used to protect overlays that reside in a secure library from any unauthorized modification. For example, a user of Overlay Generation Language (OGL) would have to be RACF-authorized to access an overlay in a secure library. Refer to your RACF documentation for more information about how users are authorized to access secure libraries. For more information about creating overlays, refer to *Overlay Generation Language User's Guide and Reference*.

Printing with Security Overlays

Printing security overlays is not specified with a form definition but with the SECOVLY option. This option is coded in a member of the security definitions library. See “Defining a Security Definitions Library” on page 9 for more information.

Allocating the Security Definitions Library

The *security definitions library* is a partitioned data set or a series of concatenated partitioned data sets. A security definitions library contains separate definitions for each type of security label available on the system. A single member contains the definitions for one security label that is used with all paper sizes and page orientations. For example, a security definitions library called SECURE.SECDEFS could contain two members, named TOPSEC and UNCL. The member SECURE.SECDEFS(TOPSEC) could contain definitions for printing a top secret identification label. The member SECURE.SECDEFS(UNCL) could contain definitions for printing an unclassified identification label.

A member of a security definitions library contains the size and origin of the user-printable area (UPA) for each paper size and page orientation used by the printer. The security definitions library can optionally contain the names of any security overlays.

You should define the minimum number of paper sizes required for each security label. This reduces PSF search time. For example, you can create a security definitions library for all of your printers that use cut-sheet paper and another library for all of your printers that use continuous-forms paper.

Names used to identify the security definitions library are defined in a PSF startup procedure. The DD statement is used to associate a security definitions library name to the printer that uses that library. See Figure 16 on page 17 for an example of how a DD statement is used to refer to a security library name.

Security Definitions Library Attributes

You should allocate a security definitions library with the attributes listed in Figure 5.

```
DSORG=PO
LRECL=80
BLKSIZE=multiple_of_80
RECFM={FB | F}
```

Figure 5. Library Attributes for the Security Definitions Library

Note: The security definitions library cannot have records that contain machine or American National Standards Institute (ANSI) control characters and cannot use the track overflow feature.

Defining a Security Definitions Library

You should define a member in the security definitions library for each security label that you need.

Syntax for a Security Definitions Member

Figure 6 illustrates the syntax for a security definitions library member.

```
{PAPERNAME papername | PAPERSIZ width_value height_value}
[ TOP { NARROW | WIDE } ]
[ UPAORG xorg_value yorg_value ]
[ UPADIM xlength_value ylength_value ]
[ SECOVLY name1 name2...name8 ]
```

Figure 6. Syntax for a Security Definitions Library Member

The parameters and values for a security definitions library member are:

{PAPERNAME *papername* | PAPERSIZ *width_value height_value*}

Specifies the size of the paper. You must use either PAPERNAME or PAPERSIZ.

PAPERNAME specifies the system-defined paper names for each paper size. See Appendix B, “PAPERNAME Table for System-Defined Paper Names,” on page 29 for a list of valid names and the dimensions for each system-defined paper name.

PAPERSIZ specifies the width and height of the paper and the units of measurement, either in inches (IN) or in millimeters (MM). The PAPERSIZ parameter should be used if the size of the paper loaded in the printer does not correspond to one of the PSF system-defined paper names.

The valid values for inches can be from 0 to 22.75. The valid values for millimeters can be from 0 to 577.97. The values do not need to be in the same units and are entered as follows (the decimal point is optional for integer values):

nnn.nn { IN | MM }

See Figure 7 on page 12 for an example of this parameter.

[TOP { NARROW | WIDE }]

Specifies which edge of the paper is the top by identifying whether the media origin² is located at the top-left corner of a narrow or wide edge of the paper. The TOP parameter has two options:

- NARROW is the default and specifies that the security overlays and UPA in this security definition entry use the top-left corner of a narrow edge of the paper as the media origin.
- WIDE specifies that the security overlays and UPA in this security definition entry use the top-left corner of a wide edge of the paper as the media origin.

For continuous-forms printers, a security definitions member can contain both a NARROW and WIDE entry if:

- Both narrow and wide forms are used for the security label.³
- The form definition contains page-presentation and print-direction controls that change the default media origin.

For cut-sheet printers, only one entry (NARROW) is needed. Because the media origin for cut sheets is always the top-left corner of a narrow edge, the WIDE option is ignored for cut-sheet forms.

Determine whether to use the WIDE or NARROW entry for continuous-forms printers:

- WIDE for wide forms if the form definition contains LANDSCAPE ACROSS or PORTRAIT DOWN controls
- WIDE for narrow forms if the form definition contains PORTRAIT ACROSS or LANDSCAPE DOWN controls
- NARROW for narrow forms if the form definition contains PORTRAIT ACROSS or LANDSCAPE DOWN controls
- NARROW for wide forms if the form definition contains LANDSCAPE ACROSS or PORTRAIT DOWN controls

For more information about the page-presentation and print-direction controls in a form definition, refer to *IBM Printing Systems: Printer Information and Page Printer Formatting Aid: User's Guide*.

See Figure 7 on page 12 for an example of this parameter.

[UPAORG xorg_value yorg_value]

Specifies the origin, in inches (IN) or millimeters (MM), of the UPA.

The origin is expressed as horizontal offsets (*xorg*) and vertical offsets (*yorg*) from the media origin for a particular page size and origin.

2. Media origin used by any security overlays or the media origin used by the UPA. For more information about media origins and the coordinate system used by AFP printers, refer to *Intelligent Printer Data Stream Reference*.

3. Narrow forms are those that have perforations on the shorter edge of the paper and tractor holes on the longer edge. Wide forms are those that have perforations on the longer edge of the paper and tractor holes on the shorter edge.

The valid values for inches can be from 0 to 22.75. The valid values for millimeters can be from 0 to 577.97. The values do not need to be in the same units and are entered as follows (the decimal point is optional for integer values):

nnn.nn {IN | MM}

See Figure 7 on page 12 for an example of this parameter.

Note: This parameter is required if Restrict printable area=YES is specified (or is a default) in the Infoprint® Server Printer Inventory, SYSAREA=YES is specified (or is a default) in the PRINTDEV statement for the data set, or UPADIM is specified.

[**UPADIM** *xlength_value ylength_value*]

Specifies the size, in inches (IN) or millimeters (MM), of the UPA.

The size of the UPA is expressed as horizontal (*xlength*) and vertical (*ylength*) dimensions of the UPA for a particular page size and origin.

The valid values for inches can be from 0 to 22.75. The valid values for millimeters can be from 0.1 to 577.97. The values do not need to be in the same units and are entered as follows (the decimal point is optional for integer values):

nnn.nn {IN | MM}

See Figure 7 on page 12 for an example of this parameter.

Note: This parameter is required if Restrict printable area=YES is specified (or is a default) in the Infoprint Server Printer Inventory, SYSAREA=YES is specified (or is a default) in the PRINTDEV statement for the data set, or UPAORG is specified.

[**SECOVLY** *name1 name2...name8*]

Specifies the names of the overlays to be used for this security label on both the separator pages and the data pages.

One to eight overlays can be specified. These overlays must reside in a security overlay library.

See Figure 7 on page 12 for an example of this parameter.

Notes:

1. Overlay names are restricted to six characters; PSF appends a two-character prefix (O1).
2. If fonts or page segments are used in any of these overlays, the fonts must reside in a security font library and the page segments must reside in a security page-segment library.
3. This parameter is required if Label data pages=YES or Label separator pages=YES is specified in the Infoprint Server Printer Inventory, or DPAGELBL=YES or SPAGELBL=YES is specified in the PRINTDEV statement.

Rules for Defining a Security Definitions Member

This list describes the rules for defining a single member in a security definitions library:

- For each PAPERNAME or PAPERSIZ parameter, up to two sets of TOP, UPAORG, UPADIM, and SECOVLY parameters can be specified, one for the TOP WIDE

parameter and one for the TOP NARROW parameter. If duplicate parameters within a set are specified, the last option for that parameter is used.

- The TOP parameter, if present, must be specified before the SECOVLY, UPAORG, and UPADIM parameters that correspond to the TOP parameter.
- The UPAORG, UPADIM, and SECOVLY parameters can be specified in any order. Either SECOVLY or both the UPAORG and the UPADIM parameter must be specified. All three can be used together.
- Multiple parameters and options can be specified in a single record.
- The delimiters that separate the parameters and options are one or more consecutive blanks, or the end of the line.
- Comments can be entered in the security member by entering an asterisk (*) as the first nonblank character in a line. The rest of the record is ignored. Comments cannot appear on the same line as the parameters or options.

Note: When the paper is to be cut after printing (for example, 2-up printing), you must take care to create secure overlays that appropriately label each of the subsheets.

Sample Security Definitions Member

The member definition in Figure 7 is used when a SECLABEL of TOPSEC is specified in the print job JCL and can be used for two paper types.

```
* SECURE.SECDEFS(TOPSEC)
*** DEFINITION FOR CUT SHEET PAPER
PAPERSIZ 216    MM  11.00  IN
TOP      NARROW
UPAORG   0      IN   1      IN
UPADIM   8.5    IN  10.00  IN
SECOVLY  TOPSEC
*** DEFINITION FOR CONTINUOUS FORMS
PAPERNAME LISTING1
TOP      WIDE
UPAORG   0      IN   1      IN
UPADIM  13.88  IN  10.00  IN
SECOVLY  TOPSEC
* END SECURE.SECDEFS(TOPSEC)
```

Figure 7. Sample Coding of a Member. This member contains two entries, one for cut sheet and one for continuous forms.

The coding for PAPERSIZ in Figure 7 produces a layout as illustrated in Figure 8 on page 13.




Figure 8. Page Layout for a Cut-Sheet Page

The coding for PAPERNAME LISTING1 in Figure 7 on page 12 produces a layout as illustrated in Figure 9.



Figure 9. Page Layout for a Continuous Form

Defining Security Resource Libraries

The three types of security resources are overlays, page segments, and fonts. These types of resources are stored in a secure library, and they are managed differently from other resources stored on the system. You should allocate a security resource library with the attributes listed in Table 2.

Table 2. Library Attributes for a Security Resource Library

Overlays and Page Segments	Fonts
DSORG=PO LRECL=8205 BLKSIZE=8209 RECFM=VBM	DSORG=PO LRECL=12284 BLKSIZE=12288 RECFM=VBM

Security overlays are produced for each security label defined. One or more security overlays can be defined for each size paper and page orientation being used. Security fonts and security page segments are those that are used within the security overlay. Security resource libraries are named in the PRINTDEV statement of the PSF startup procedure. See “Defining Data Definition Names in the PRINTDEV Statement” on page 19 for the syntax used in the PRINTDEV statement.

Defining a Security Console

You can optionally receive security-related PSF messages at a security console, and you can optionally elect not to receive PSF security-related messages at the master console.

To route messages to a security console, change the ROUTCODE in the SYS1.PARMLIB(CONSOLxx) as illustrated in Figure 10.



ROUTCODE(9)

Figure 10. ROUTCODE Option for Routing Messages

To stop security-related PSF messages from reaching the master console, change the ROUTCODE in SYS1.PARMLIB(CONSOLxx) as shown in Figure 11. This lets all messages except security-related messages reach the master console.



ROUTCODE(1-8,10-128)

Figure 11. ROUTCODE Option for Stopping Messages

Assembling Separator Pages

Optional exits are provided if random numbering of separator pages is needed. For information about the exits that PSF provides, refer to *PSF for z/OS: Customization*.

The installation exits in Table 3 must be modified, assembled, installed, or link-edited with the REPLACE option to print random numbers on job separator pages.

Table 3. PSF Exit Routines in SYS1.SAMPLIB

Sample Routine	Description
APSUX01S	Source routine for security job headers.
APSUX02S	Source routine for security job trailers.

Either use the supplied source or modify the source to meet your needs. Figure 3 on page 3 illustrates the IBM-supplied security header and trailer pages in a printed format.

Notes:

1. If APSUX01S and APSUX02S are used, they must replace APSUX01 and APSUX02. Ensure that APSUC01 and APSUC02 are not used. If they are, delete them because they will override APSUX01 and APSUX02.

2. Separator pages do not have a UPA.

Enabling Print Labeling

PSF supports print labeling in two ways:

Guaranteed print labeling

Guaranteed print labeling ensures the integrity of the identification label by preventing the user from changing the label. (See “Printer Support in PSF” on page 7 for information about determining whether a printer supports guaranteed print labeling.) Ensure that the RACF option PSFMPL is set according to Figure 13.

Nonguaranteed print labeling

Printers that do not support guaranteed print labeling can still print identification labels, but the integrity of the labels cannot be guaranteed. For nonguaranteed print labeling, you must:

1. Define the valid security labels to RACF as described in the *z/OS Security Server RACF Security Administrator's Guide*.
2. Activate security label checking through TSO commands as in Figure 12.

In addition, the RACF parameters shown in Figure 13 are optional for nonguaranteed print labeling. Other parameters in the PSF startup procedure are used to enable nonguaranteed print labeling. For more information, see “Updating Initialization Parameters” on page 17.

Note: PSF processing is different if print labeling is enabled. See “PSF Processing Differences When Using the Print Labeling Function” on page 16 for a list of differences.

```
SETROPTS CLASSACT(SECLABEL)
SETROPTS RACLIST(SECLABEL) REFRESH
```

Figure 12. Activating SECLABEL

Using RACF with PSF for z/OS

Use RACF to activate PSFMPL and create RACF profiles.

Note: RACF CLASS PSFMPL must be refreshed after activating PSFMPL or creating new profiles.

- To activate print labeling, use SETROPTS. To set print labeling defaults to YES, use the RDEFINE command. RDEFINE creates RACF profiles. See Figure 13 for examples of using SETROPTS and RDEFINE.

```
SETROPTS CLASSACT(PSFMPL)
RDEFINE PSFMPL PSF.DPAGELBL UACC(NONE)
RDEFINE PSFMPL PSF.SYSAREA UACC(NONE)
```

Figure 13. Using the RACF SETROPTS and RDEFINE Commands

- If you want to authorize a print job submitter to override printer defaults, issue the PERMIT commands in Figure 14 on page 16 to add the user ID to the RACF profile.

```
PERMIT PSF.DPAGELBL CLASS(PSFMPL) ID(userid) ACCESS(READ)
PERMIT PSF.SYSAREA CLASS(PSFMPL) ID(userid) ACCESS(READ)
```

Figure 14. Adding a User ID to a RACF Profile

- Whenever any of the commands shown in Figure 13 on page 15 or Figure 14 are used, issue the REFRESH command illustrated in Figure 15 to refresh RACF.

```
SETROPTS RACLIST(PSFMPL) REFRESH
```

Figure 15. Refreshing RACF

For more information about RACF commands, refer to *z/OS Security Server RACF Security Administrator's Guide*.

PSF Processing Differences When Using the Print Labeling Function

When using the print labeling function, PSF processing is different. The differences include:

- Security resources are accessed only from security libraries. A resource loaded in the printer from a security library cannot be used to print user data.
- User resources are accessed only from user resource libraries. A resource loaded in the printer from a user library cannot be used to print identification labels.
- Security resources are loaded into the printer as required by the print data set. They normally are not deleted at the end of a data set, except when:
 - The resource deletion exit is used to delete the resources.
 - A job-trailer page has been printed.

For more information about resource loading, deleting, and using installation exits, refer to *PSF for z/OS: Customization*.

- Suppression of trailer pages using JES operator commands can impact printer performance because printer storage can be exceeded.
- An audit is performed whenever a data set is printed on a nonguaranteed printer.

Printable Area Considerations

If PSFMPL is active, the *Restrict printable area* parameter in the Infoprint Server Printer Inventory or the SYSAREA parameter in the PRINTDEV statement defaults to YES.

If PSFMPL is not active, the *Restrict printable area* parameter in the Printer Inventory or the SYSAREA parameter in the PRINTDEV statement defaults to NO.

If you are using a nonguaranteed printer, these parameters must be set to NO or an abend occurs. For more information, see “Updating Print Labeling Parameters” on page 18.

Updating Initialization Parameters

Before starting a PSF functional subsystem (FSS), you must have a cataloged PSF startup procedure in SYS1.PROCLIB or in a procedure library concatenated to the JES startup procedure. The PSF startup procedure specifies PSF initialization parameters that tell PSF where security resources and security definitions are located. Figure 16 lists a sample PSF startup procedure that includes parameters modified for print labeling.

```
//J2PSF00  PROC
//STEP01   EXEC PGM=APSPPIEP,REGION=4096K,PARM=(,FULL)
//SYSABEND DD SYSOUT=A
//SYSUDUMP DD SYSOUT=A
//JOBHDR   OUTPUT PAGEDEF=A06462,
//          FORMDEF=A10110
//JOBTLR   OUTPUT PAGEDEF=A06462,
//          FORMDEF=A10110
//DSHDR    OUTPUT PAGEDEF=A06462,
//          FORMDEF=A10110
//MSGDS    OUTPUT PAGEDEF=A06462,
//          FORMDEF=A10110
//FONT01   DD DSN=TEST.FONTLIBB,DISP=SHR
//          DD DSN=SYS1.FONTLIBB,DISP=SHR
//PSEG01   DD DSN=TEST.SEGMENT,DISP=SHR
//          DD DSN=SYS1.SEGMENT,DISP=SHR
//OLAY01   DD DSN=TEST.OVERLAY,DISP=SHR
//          DD DSN=SYS1.OVERLAY,DISP=SHR
//FDEF01   DD DSN=TEST.FORMDEF,DISP=SHR
//          DD DSN=SYS1.FORMDEF,DISP=SHR
//PDEF01   DD DSN=TEST.PAGEDEF,DISP=SHR
//          DD DSN=SYS1.PAGEDEF,DISP=SHR
//SFONT1   DD DSN=SECURE.FONTLIBB,DISP=SHR
//SFONT2   DD DSN=SECURE.FONTL240,DISP=SHR
//SFONT3   DD DSN=SECURE.FONTL300,DISP=SHR
//SOLAY1   DD DSN=SECURE.OVERLAY,DISP=SHR
//SPSEG1   DD DSN=SECURE.SEGMENT,DISP=SHR
//SPSEG2   DD DSN=SECURE.SEGMT240,DISP=SHR
//SPSEG3   DD DSN=SECURE.SEGMT300,DISP=SHR
//SDEF1    DD DSN=SECURE.SECDEFS,DISP=SHR
//SDEF2    DD DSN=SECURE.SECDF240,DISP=SHR
//SDEF3    DD DSN=SECURE.SECDF300,DISP=SHR
//PRT10    CNTL
//PRT10    PRINTDEV FONTDD=*.FONT01,
//          OVLYDD=*.OLAY01,
//          PSEGDD=*.PSEG01,
//          PDEFDD=*.PDEF01,
//          FDEFDD=*.FDEF01,
//          JOBHDR=*.JOBHDR,
//          JOBTRLR=*.JOBTLR,
//          DSHDR=*.DSHDR,
//          MESSAGE=*.MSGDS,
```

The statements in **bold** (including ***bold italics***) are DD statements used for print labeling.

A member in one of the libraries in the statements in ***bold italics*** matches the SECLABEL on the job card.

Figure 16. Sample PSF Startup Procedure with Security-Related Parameters Highlighted (Part 1 of 2). A sample startup procedure is provided in SYS1.PROCLIB.

Table 4. Parameters for Enabling Print Labeling

Printer Inventory		PRINTDEV	OUTPUT	Description
ISPF Panel	PIDU			
Label data pages Values: 1 = Yes 2 = No	label-data-pages Values: yes no	DPAGELBL Values: YES NO	DPAGELBL Values: YES NO	Indicates whether a label is printed on each data page.
Label separator pages Values: 1 = Yes 2 = No	label-separator-pages Values: yes no	SPAGELBL Values: YES NO		Indicates whether a label is printed on a separator page.
Restrict printable area Values: 1 = Yes 2 = No	restrict-printable-area Values: yes no	SYSAREA Values: YES NO	SYSAREA Values: YES NO	Indicates whether the printable area is restricted to the system-defined UPA. If the printable area is restricted, the area outside the UPA is reserved for a security label and any attempt to print in the reserved area results in error messages. If your printer does not support guaranteed print labeling, this parameter must be set to NO.
Note: In these parameters, the default is YES if PSFMPL is active; NO if PSFMPL is not active.				

Defining Data Definition Names in the PRINTDEV Statement

These parameters are used to define security-related data definition names in the PRINTDEV statement:

SFONTDD=*.ddname

Defines the default secure font library. This ddname is required if a security overlay references a font.

SFONT240=*.ddname

Defines the secure font library for 240-pel fonts. This ddname is optional if all referenced 240-pel fonts are found in the default secure font library.

SFONT300=*.ddname

Defines the secure font library for 300-pel fonts. This ddname is optional if all referenced 300-pel fonts are found in the default secure font library.

SOVLYDD=*.ddname

Defines the default secure overlay library. This ddname is required if a security overlay is used to print identification labels.

SOVLY240=*.ddname

Defines the secure overlay library for overlays that print best at 240-pel resolution. This ddname is optional if all such overlays are found in the default secure overlay library.

| **SOVLY300=*.ddname**

| Defines the secure overlay library for overlays that print best at 300-pel
| resolution. This ddname is optional if all such overlays are found in the default
| secure overlay library.

| **SPSEGDD=*.ddname**

| Defines the default secure page segment library. This ddname is required if a
| security overlay references a page segment.

| **SPSEG240=*.ddname**

| Defines the secure page segment library for page segments that print best at
| 240-pel resolution. This ddname is optional if all such page segments are found
| in the default secure page segment library.

| **SPSEG300=*.ddname**

| Defines the secure page segment library for page segments that print best at
| 300-pel resolution. This ddname is optional if all such page segments are found
| in the default secure page segment library.

| **SDEFDD=*.ddname**

| Defines the default security definitions library. This ddname is required for print
| labeling.

| **SDEF240=*.ddname**

| Defines the security definitions library for printing at 240-pel resolution. This
| ddname is optional if all such page segments are found in the default security
| definitions library.

| **SDEF300=*.ddname**

| Defines the security definitions library for printing at 300-pel resolution. This
| ddname is optional if all such page segments are found in the default security
| definitions library.

These parameters refer to the libraries named in the startup procedure; see
Figure 16 on page 17.

Note: Even if you used the Printer Inventory to enable print labeling, you must still
specify these parameters in the PRINTDEV statement.

Submitting a Print Job that Includes Identification Labels

Once you have defined a security definitions library, updated PSF initialization parameters, and created security resources, you are ready to submit a print job. To submit a print job and have that job print with the correct identification label, follow this procedure to ensure that there is a member in the security definitions library with the same name as each SECLABEL that has been defined to RACF by the security administrator:

1. The security administrator defines a set of security labels to be used by the installation.
2. The security administrator associates SECLABELs with every user on the system.
3. The print administrator creates a member in the security definitions library to match the name of every SECLABEL defined to the system.
4. The user submits the job, the user's SECLABEL is matched and the appropriate security labeling is printed on the user's output.

For example, if you want to print the identification label associated with the security label of TOPSEC, you would specify SECLABEL=TOPSEC in the job card and PSF would use the member named SECURE.SECDEFS(TOPSEC) to find the security overlay identified for that security label.

Figure 17 shows an example of using the SECLABEL parameter in the job card. Figure 7 on page 12 shows an example of the definitions used in SECURE.SECDEF(TOPSEC).

```
//TESTER1 JOB (SYS10000),USER=TESTER1,  
//  CLASS=A,MSGCLASS=T,MSGLEVEL=(1,1),REGION=4096K,  
//  SECLABEL=TOPSEC  
.  
.  
.
```

Figure 17. Sample JCL Job Card. The SECLABEL=TOPSEC points to a member named TOPSEC in a security definitions library .

Overriding Print Labeling Defaults

If authorized by RACF, you can use these JCL keywords in the OUTPUT statement to change the definition of print labeling:

DPAGELBL=YESINO

Indicates whether a label is printed on each data page.

SYSAREA=YESINO

Indicates whether the printable area is restricted to the system-defined UPA.

If SYSAREA=YES is specified, any attempt to print outside the UPA results in error messages.

If your printer does not support guaranteed print labeling, use SYSAREA=NO. To determine if your printer supports guaranteed print labeling, see “Printer Support in PSF” on page 7.

Figure 18 shows an example of the OUTPUT statement used to override PSF defaults.

```
.  
.  
.  
//OUTPUT1 OUTPUT FORMDEF=IPGP00,DATAACK=UNBLOCK,  
//  DPAGELBL=YES,SYSAREA=NO  
//SYSUT1 DD  SYSOUT=L,DCB=(RECL=VBA,BLKSIZE=8192),  
//  OUTPUT=*.OUTPUT1
```

Figure 18. Sample JCL Output Statement. The statement shows an override that activates data page labeling without UPA enforcement.

Maintaining PSF for z/OS with Print Labeling Enabled

The following sections are used to maintain PSF when print labeling is enabled.

Auditing PSF Printing

PSF uses the SMF type 6 record to audit certain events that can indicate a security exception. Only one record is written per data set, but the record can contain numerous conditions.

The following information is included in the SMF type 6 record to support print labeling:

- Indicator that flags JCL keywords that were in effect during printing
- Indicator that flags a successful print operation
- Indicator that flags an error that occurred during overlay processing
- Indicator that flags a hardware error that occurred
- Indicator that flags printed job-trailer pages
- Indicator that flags printed job-header pages
- Indicator that flags that the user suppressed data-page labeling
- Indicator that flags that the user suppressed UPA enforcement
- Identifier for the job or group identifier for the data set
- Identifier for the page definition name
- Identifier for the form definition name
- Identifier for the number of security overlays used
- Identifier for the number of security fonts used
- Identifier for the number of security page segments used

Refer to *PSF for z/OS: Customization* for more information about the SMF type 6 record that PSF generates.

Interpreting Security-Related Messages

If you receive a PSF error message that relates to print labeling, refer to *PSF for z/OS: Messages and Codes* for more information.

PSF security-related messages are received at these locations:

- Within a print job
- At the security console
- At the master console

A PSF message number can be placed in these JES messages:

- HASP704
- IAT706I

Diagnosing Print Labeling Problems

The problems in Table 5 on page 23 can occur when you are using the print labeling function.

Table 5. Print Labeling Diagnosis

Problem	Possible Causes
No identification label printed on any page.	• Security definitions library member does not name a security overlay or names an overlay that does not contain any labeling information. • PSFMPL is not active and: – Label data pages and Label separator pages are not specified in the Printer Inventory or DPAGELBL and SPAGELBL are not specified in the PRINTDEV statement for the printer that printed the file. – Label data pages=NO and Label separator pages=NO are specified in the Printer Inventory or DPAGELBL=NO and SPAGELBL=NO are specified in the PRINTDEV statement for the printer that printed the file. – Label data pages=YES and Label separator pages=NO are specified in the Printer Inventory or DPAGELBL=YES and SPAGELBL=NO are specified in the PRINTDEV statement for the printer that printed the file, but the print-job submitter specified DPAGELBL=NO on the OUTPUT statement for the file. – Label data pages=NO and Label separator pages=YES are specified in the Printer Inventory or DPAGELBL=NO and SPAGELBL=YES are specified in the PRINTDEV statement for the printer that printed the file, but separator pages were suppressed by an operator command. – Label data pages=YES and Label separator pages=YES are specified in the Printer Inventory or DPAGELBL=YES and SPAGELBL=YES are specified in the PRINTDEV statement for the printer that printed the file, but separator pages were suppressed by an operator command and the print-job submitter specified DPAGELBL=NO on the OUTPUT statement for the file. • PSFMPL is active and: – Label data pages=NO and Label separator pages=NO are specified in the Printer Inventory or DPAGELBL=NO and SPAGELBL=NO are specified in the PRINTDEV statement for the printer that printed the file. – Label data pages=YES and Label separator pages=NO are specified in the Printer Inventory or DPAGELBL=YES and SPAGELBL=NO are specified in the PRINTDEV statement for the printer that printed the file, but the print-job submitter specified DPAGELBL=NO on the OUTPUT statement for the file and is RACF-authorized to override data page labeling. – Label data pages=NO and Label separator pages=YES are specified in the Printer Inventory or DPAGELBL=NO and SPAGELBL=YES are specified in the PRINTDEV statement for the printer that printed the file, but separator pages were suppressed by an operator command. – Label data pages=YES and Label separator pages=YES are specified in the Printer Inventory or DPAGELBL=YES and SPAGELBL=YES are specified in the PRINTDEV statement for the printer that printed the file, but separator pages were suppressed by an operator command and the print-job submitter specified DPAGELBL=NO on the OUTPUT statement for the file and is RACF-authorized to override data page labeling.

Table 5. Print Labeling Diagnosis (continued)

Problem	Possible Causes
Identification label printed on separator pages, but not printed on data pages.	• PSFMPL is not active and: – Label separator pages=YES but Label data pages is not specified in the Printer Inventory, or SPAGELBL=YES but DPAGELBL is not specified in the PRINTDEV statement for the printer that printed the file. – Label data pages=NO and Label separator pages=YES are specified in the Printer Inventory or DPAGELBL=NO and SPAGELBL=YES are specified in the PRINTDEV statement for the printer that printed the file. – Label data pages=YES and Label separator pages=YES are specified in the Printer Inventory or DPAGELBL=YES and SPAGELBL=YES are specified in the PRINTDEV statement for the printer that printed the file, but the print-job submitter specified DPAGELBL=NO on the OUTPUT statement for the file. • PSFMPL is active and: – Label data pages=NO but Label separator pages is not specified in the Printer Inventory, or DPAGELBL=NO but SPAGELBL is not specified in the PRINTDEV statement for the printer that printed the file. – Label data pages=NO and Label separator pages=YES are specified in the Printer Inventory or DPAGELBL=NO and SPAGELBL=YES are specified in the PRINTDEV statement for the printer that printed the file. – Label data pages=YES and Label separator pages=YES are specified in the Printer Inventory or DPAGELBL=YES and SPAGELBL=YES are specified in the PRINTDEV statement for the printer that printed the file, but the print-job submitter specified DPAGELBL=NO on the OUTPUT statement for the file and is RACF-authorized to override data page labeling.

Table 5. Print Labeling Diagnosis (continued)

Problem	Possible Causes
Identification label printed on data pages, but not on separator pages.	• PSFMPL is not active and: – Label data pages=YES but Label separator pages is not specified in the Printer Inventory, or DPAGELBL=YES but SPAGELBL is not specified in the PRINTDEV statement for the printer that printed the file. – Label data pages=YES and Label separator pages=NO are specified in the Printer Inventory or DPAGELBL=YES and SPAGELBL=NO are specified in the PRINTDEV statement for the printer that printed the file. – Label data pages=NO and Label separator pages=NO are specified in the Printer Inventory or DPAGELBL=NO and SPAGELBL=NO are specified in the PRINTDEV statement for the printer that printed the file, but the print-job submitter specified DPAGELBL=YES on the OUTPUT statement for the file. – Label data pages=NO and Label separator pages=YES are specified in the Printer Inventory or DPAGELBL=NO and SPAGELBL=YES are specified in the PRINTDEV statement for the printer that printed the file, but the print-job submitter specified DPAGELBL=YES on the OUTPUT statement for the file and separator pages were suppressed by an operator command. • PSFMPL is active and: – Label separator pages=NO but Label data pages is not specified in the Printer Inventory, or SPAGELBL=NO but DPAGELBL is not specified in the PRINTDEV statement for the printer that printed the file. – Label data pages=YES and Label separator pages=NO are specified in the Printer Inventory or DPAGELBL=YES and SPAGELBL=NO are specified in the PRINTDEV statement for the printer that printed the file. – Label data pages=NO and Label separator pages=NO are specified in the Printer Inventory or DPAGELBL=NO and SPAGELBL=NO are specified in the PRINTDEV statement for the printer that printed the file, but the print-job submitter specified DPAGELBL=YES on the OUTPUT statement for the file. – Label data pages=NO and Label separator pages=YES are specified in the Printer Inventory or DPAGELBL=NO and SPAGELBL=YES are specified in the PRINTDEV statement for the printer that printed the file, but the print-job submitter specified DPAGELBL=YES on the OUTPUT statement for the file and separator pages were suppressed by an operator command.
Wrong data in identification label.	• Print-job submitter specified wrong SECLABEL on job card. • Wrong security overlay specified in the security definitions library member for the SECLABEL on the job card and the size of paper in the printer that printed the file. • Security definitions library member names an overlay that contains the wrong labeling information. • Overlay names were changed in the security overlay library.
Wrong page segment in identification label.	• Security overlay named the wrong page segment. • Page segment names were changed in the security page segment library.
Wrong overlay used for identification label.	• Print-job submitter specified wrong SECLABEL on job card. • Wrong security overlay specified in the security definitions library member for the SECLABEL on the job card and the size of paper in the printer that printed the file. • Overlay names were changed in the security overlay library.

Appendix A. Security Page Layout

The template in Figure 19 is provided to help you determine the dimensions that you need when designing pages for the print labeling function. This template can be used to help define where identification label placement should occur and to help determine the dimensions of the user-printable area (UPA). For information about using these measurements to code a security definition, see “Defining a Security Definitions Library” on page 9. For more information about printable area dimensions for specific printers, refer to *IBM Printing Systems: Printer Information*.




Figure 19. Security Page Layout. This template is for a page defined as TOP=NARROW.

Appendix B. PAPERNAME Table for System-Defined Paper Names

Table 6 lists the paper names that you can select for the PAPERNAME parameter.

Table 6. PAPERNAME Parameter Values

Paper Name	Paper Size: Width by Height in Millimeters	Paper Size: Width by Height in Inches
A4	210 x 297	8.27 x 11.69
B4	257 x 364	10.12 x 14.33
B5	182 x 257	7.17 x 10.12
EXEC1	178 x 267	7.00 x 10.50
EXEC2	184 x 267	7.25 x 10.50
EXEC3	190 x 267	7.50 x 10.50
LEGAL	216 x 356	8.50 x 14.00
LETTER	216 x 279	8.50 x 11.00
LISTING1	378 x 279	14.88 x 11.00
LISTING2	305 x 216	12.00 x 8.50

Appendix C. Accessibility

Accessibility features help a user who has a physical disability, such as restricted mobility or limited vision, use software products successfully. The major accessibility features in z/OS let users:

- Use assistive technologies such as screen readers and screen magnifier software.
- Operate specific or equivalent features using only the keyboard.
- Customize display attributes such as color, contrast, and font size.

Using Assistive Technologies

Assistive technology products, such as screen readers, function with the user interfaces found in z/OS. Consult the assistive technology documentation for specific information when using it to access z/OS interfaces.

Keyboard Navigation of the User Interface

Users can access z/OS user interfaces using TSO/E or ISPF. For more information, refer to *z/OS TSO/E Primer*, SA22–7787, *z/OS TSO/E User's Guide*, SA22–7794, and *z/OS ISPF User's Guide Vol I*, SC34–4822. These guides describe how to use TSO/E and ISPF, including the use of keyboard shortcuts or function keys (PF keys). Each guide includes the default settings for the PF keys and explains how to modify their functions.

z/OS Documentation

Most z/OS documentation is accessible using screen readers with the BookServer/Library Server versions of z/OS documents in the Internet library at:

<http://www.ibm.com/servers/eserver/zseries/zos/bkserv/>

Notices

This information was developed for products and services offered in the U.S.A.

IBM may not offer the products, services, or features discussed in this document in other countries. Consult your local IBM representative for information on the products and services currently available in your area. Any reference to an IBM product, program, or service is not intended to state or imply that only that IBM product, program, or service may be used. Any functionally equivalent product, program, or service that does not infringe any IBM intellectual property right may be used instead. However, it is the user's responsibility to evaluate and verify the operation of any non-IBM product, program, or service.

IBM may have patents or pending patent applications covering subject matter described in this document. The furnishing of this document does not give you any license to these patents. You can send license inquiries, in writing, to:

IBM Director of Licensing
IBM Corporation
North Castle Drive
Armonk, NY 10594-1785
U.S.A.

For license inquiries regarding double-byte (DBCS) information, contact the IBM Intellectual Property Department in your country or send inquiries, in writing, to:

IBM World Trade Asia Corporation
Licensing
2-31 Roppongi 3-chome, Minato-ku
Tokyo 106, Japan

The following paragraph does not apply to the United Kingdom or any other country where such provisions are inconsistent with local law:

INTERNATIONAL BUSINESS MACHINES CORPORATION PROVIDES THIS PUBLICATION "AS IS" WITHOUT WARRANTY OF ANY KIND, EITHER EXPRESS OR IMPLIED, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF NON-INFRINGEMENT, MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE. Some states do not allow disclaimer of express or implied warranties in certain transactions, therefore, this statement may not apply to you.

This information could include technical inaccuracies or typographical errors. Changes are periodically made to the information herein; these changes will be incorporated in new editions of the publication. IBM may make improvements and/or changes in the product(s) and/or the program(s) described in this publication at any time without notice.

Any references in this information to non-IBM Web sites are provided for convenience only and do not in any manner serve as an endorsement of those Web sites. The materials at those Web sites are not part of the materials for this IBM product and use of those Web sites is at your own risk.

IBM may use or distribute any of the information you supply in any way it believes appropriate without incurring any obligation to you.

Licensees of this program who wish to have information about it for the purpose of enabling: (i) the exchange of information between independently created programs and other programs (including this one) and (ii) the mutual use of the information which has been exchanged, should contact:

IBM Corporation
Department 11PA, Building 002S
P.O. Box 1900
Boulder, CO 80301
U.S.A.

Such information may be available, subject to appropriate terms and conditions, including in some cases, payment of a fee.

The licensed program described in this information and all licensed material available for it are provided by IBM under terms of the IBM Customer Agreement, IBM International Program License Agreement, or any equivalent agreement between us.

Trademarks

The following are trademarks or registered trademarks of the IBM Corporation:

Advanced Function Presentation
AFP
@server
IBM
Infoprint
MVS
OS/390
Print Services Facility
RACF
S/390
System z9
z/OS
zSeries

The following terms appear in this publication and are trademarks of other companies:

- Microsoft and Windows are trademarks of Microsoft Corporation in the United States, other countries, or both.
- Linux is a trademark of Linus Torvalds in the United States, other countries, or both.
- UNIX is a registered trademark of The Open Group in the United States and other countries.

Other company, product, and service names might be trademarks or service marks of others.

Glossary

This glossary defines technical terms and abbreviations used in PSF for z/OS documentation. If you do not find the term you are looking for, see this publication's index or view *IBM Glossary of Computing Terms*, available from: <http://www.ibm.com/ibm/terminology>

Definitions reprinted from the *American National Dictionary for Information Processing Systems* are identified by the symbol (A) following the definition.

Definitions reprinted from a published section of the International Organization for Standardization (ISO) *Vocabulary—Information Processing* or from a published section of *Vocabulary—Office Machines* developed by Subcommittee 1, Joint Technical Committee 1, of the International Organization for Standardization and the International Electrotechnical Committee (ISO/IEC JTC1/SC1) are identified by the symbol (I) following the definition. Because many ISO definitions are also reproduced in the *American National Dictionary for Information Processing Systems*, ISO definitions can also be identified by the symbol (A).

Definitions reprinted from working documents, draft proposals, or draft international standards of ISO Technical Committee 97, Subcommittee 1 (Vocabulary), Joint Technical Committee 1 are identified by the symbol (T) following the definition, indicating that final agreement has not yet been reached among its participating members.

Definitions that are specific to IBM products are so labeled—for example, “In SNA,” or “In the 3820 printer.”

These cross-references are used in this glossary:

- **Contrast with.** Refers to a term that has an opposite or substantively different meaning.
- **See.** Refers to multiple-word terms in which this term appears.
- **See also.** Refers to related terms that have similar, but not synonymous, meanings.
- **Synonym for.** Appears in the commentary of a less desirable or less specific term and identifies the preferred term that has the same meaning.
- **Synonymous with.** Appears in the commentary of a preferred term and identifies less desirable or less specific terms that have the same meaning.

A

| **access control.** In computer security, the process of
| ensuring that only authorized users can access the
| resources of a computer system in authorized ways.

C

| **concatenated data set.** A group of logically connected
| data sets that are treated as one data set for the
| duration of a job step. See also *data set*, *partitioned*
| *data set*, and *library*.

| **console.** An input/output device on a computer,
| reserved for communication between the computer
| operator or maintenance engineer and the computer.

D

| **data set.** The major unit of data storage and retrieval,
| consisting of a collection of data in one of several
| prescribed arrangements and described by control
| information to which the system has access. See *file*.
| See also *concatenated data set*, *partitioned data set*,
| and *sequential data set*.

| **data set header.** A page in printed output that
| separates multiple data sets or multiple copies of a data
| set within a print job. See also *job header*.

F

| **file.** (1) A collection of related data that is stored and
| retrieved by an assigned name. A file can include
| information that starts a program (program-file object),
| contains text or graphics (data-file object), or processes
| a series of commands (batch file). (2) A collection of
| information treated as a unit. (3) Synonymous with *data*
| *set*. See *partitioned data set*, *sequential data set*, and
| *library*.

| **font.** A set of graphic characters with a common
| design that reflects the font designer's concept of how
| the graphic characters should appear. The common
| design specifies the characteristics of its graphic
| characters. Examples of characteristics are shape,
| graphic pattern, style, size, weight, and increment.
| Examples of fonts are fully described fonts, symbol sets,
| outline fonts, and their internal printer representations.

form definition. An AFP resource object that defines the characteristics of the form or printed media, including: overlays to be used, duplex printing, text suppression, the position of composed-text data on the form, and the number and modifications of a page. Contrast with *page definition*.

FSA. See *functional subsystem application*.

FSS. See *functional subsystem*.

functional subsystem (FSS). The PSF address space created by JES.

functional subsystem application (FSA). An area within the PSF FSS that drives and manages a single printer.

G

guaranteed print labeling. A method of print labeling that ensures the integrity of the identification label by preventing the user from changing the label. If attempts are made to override print labeling, printing is stopped, and an audit record is written. Contrast with *nonguaranteed print labeling*. See also *identification label*.

I

identification label. In PSF, a protected set of resources (fonts, overlays, and page segments) that are used to label PSF output for security purposes. Contrast with *security label*.

J

JCL. See *job control language*.

JES. See *Job Entry Subsystem*.

job. (1) A separately executable unit of work defined by a user and run by a computer. (2) A representation of a unit of work for the operating system, such as a set of programs, files, and control statements.

| **job control language (JCL).** A command language
| that is used to identify a job to an operating system and
| to describe the job's requirements.

| **Job Entry Subsystem (JES).** An IBM licensed
| program that receives jobs into the system and
| processes all output data that is produced by jobs.

| **job header.** A page in the printed output that indicates
| the beginning of a user job. A user job can contain one
| or more data sets, or one or more copies of a print job.
| See also *data set header*.

job separation. The ability to identify job boundaries by placing marks or sheets of paper between successive jobs.

job trailer. A page in the printed output that indicates the end of a user job.

L

| **library.** (1) A system object that serves as a directory
| to other objects. A library groups related objects, and
| allows the user to find objects by name. (2) A data file
| that contains copies of a number of individual files and
| control information that allows them to be accessed
| individually. A library exists as a partitioned data set or a
| series of concatenated partitioned data sets in z/OS.

| **licensed program.** A separately priced program and
| its associated materials that bear a copyright and are
| offered to customers under the terms and conditions of
| a licensing agreement.

M

| **media origin.** The reference point from which the
| logical page origin is positioned by the medium map.
| This point is represented by $X_m=0$, $Y_m=0$ in the X_m ,
| Y_m coordinate system. The media origin is defined
| relative to the top-left corner of the form.

N

nonguaranteed print labeling. Some printers that do not support guaranteed print labeling can still print identification labels, but the integrity of the labels cannot be guaranteed using PSF. Contrast with *guaranteed print labeling*. See also *identification label*.

O

OGL. See *Overlay Generation Language*.

| **operating system.** A collection of system programs
| that control the overall operation of a computer system.

OS/390. An IBM operating system for the IBM S/390® family of enterprise servers that includes and integrates functions previously provided by many IBM software products (including the MVS™ operating system). See z/OS.

| **overlay.** An AFP resource object that is a collection of
| predefined data, such as lines, shading, text, boxes, or
| logos, that can be merged with variable data on a page
| or form while printing. An overlay can be either an
| electronic overlay or a forms flash. Contrast with *page
| segment*.

Overlay Generation Language (OGL). An IBM licensed program used for designing objects (such as

lines, boxes, shadings, and irregular shapes, to create graphics) for electronic overlays.

P

page definition. An AFP resource object that defines the rules for transforming line data and XML data into MO:DCA-P data and text controls. Contrast with *form definition*.

Page Printer Formatting Aid (PPFA). An IBM licensed program with which to create and store form definitions and page definitions, which are resource objects used for print-job management. These stored objects are used to format printed output.

page segment. An AFP resource object containing text, image, graphics, or bar code data that can be positioned on any addressable point on a page or an electronic overlay. Contrast with *overlay*.

parameter. A value or reference passed to a function, command, or program that serves as input or to control actions. The value is supplied by a user or by another program or process.

partitioned data set (PDS). A data set in direct-access storage that is divided into partitions, which are called members. Each partition can contain a program, part of a program, or data. Contrast with *sequential data set*. See also *library*.

PDS. See *partitioned data set*.

physical page. A single surface (front or back) of a form.

PPFA. See *Page Printer Formatting Aid*.

print job. The print data that has been submitted for printing.

print labeling. A controlled method of placing identification labels on each page of PSF printed output.

Print Services Facility (PSF). An IBM licensed program that manages and controls the input data stream and output data stream required by supported IBM page printers.

processor. In a computer, a functional unit that interprets and executes instructions. A processor consists of at least an instruction control unit and an arithmetic and logic unit.

PSF. See *Print Services Facility*.

R

RACF. See *Resource Access Control Facility*.

record. (1) In programming languages, an aggregate that consists of data objects, possibly with different attributes, that usually have identifiers attached to them. In some programming languages, records are called structures. (2) A group of related data, words, or fields treated as a unit, such as one name, address, and telephone number.

resource. A collection of printing instructions used by PSF, in addition to the print data set, to produce the printed output. Resources include coded fonts, font character sets, code pages, page segments, overlays, form definitions, and page definitions.

Resource Access Control Facility (RACF). An IBM licensed program that provides for access control by identifying and verifying users to the system, authorizing access to protected resources, logging detected unauthorized attempts to enter the system, and logging detected accesses to protected resources.

S

security definition. In z/OS, a member containing the definitions for one identification label. These definitions include instructions for the overlay name, and the size and origin of paper to be used.

security definitions library. In z/OS, a partitioned data set or a series of concatenated partitioned data sets that contain the security definitions for an entire system.

security label. In a trusted computing base, a label used to maintain multiple levels of security on a system. This label is a combination of a security class and a security level. Contrast with *identification label*.

security overlay. An overlay, such as one created by use of Overlay Generation Language, that resides in a secure library and is used to place security resources on a page.

separator page. An identifying sheet of paper between successive jobs. See also *job header* and *job trailer*.

sequential data set. In z/OS, a data set whose records are organized on the basis of their physical positions, such as on magnetic tape. Contrast with *partitioned data set*.

SMF. See *system management facilities*.

SMF type 6 record. The record that PSF uses to record data for each print data set.

spool. The system function of putting files or jobs into disk storage for later processing or printing.

spool file. A file containing output that has been saved for later processing.

| **spooling.** (1) The use of auxiliary storage as buffer
| storage in order to reduce processing delays when
| transferring data between peripheral equipment and
| computer processors. (2) The process of reading and
| writing input and output streams on an intermediate
| device, concurrently with job execution, in a format that
| is convenient for later processing or output.

| **statement.** (1) In programming languages, a language
| construct that represents a step in a sequence of
| actions or a set of declarations. (2) An instruction in a
| program or procedure.

system management facilities (SMF). The part of the operating system that collects and records system and job-related information used in billing users, reporting reliability, analyzing the configuration, scheduling jobs, summarizing direct access volume activity, evaluating data set activity, profiling system resource use, and maintaining system security.

T

terminal. In data communication, a device, usually equipped with a keyboard and display device, capable of sending and receiving information.

| **trusted computing base.** The components in a
| system (hardware, microcode, and software) that
| together enforce a unified security policy to protect
| information on the system.

U

UPA. See *user printable area*.

user ID. User identifier. A string of characters that uniquely identifies a user to a system.

user printable area (UPA). The area within the valid printable area (VPA) where user-generated data can print without causing an exception condition. See also *valid printable area*.

V

valid printable area (VPA). The intersection of the current logical page or current overlay with the physical page in which printing is allowed. See also *user printable area*.

VPA. See *valid printable area*.

X

Xm, Ym coordinate system. The media coordinate system.

Z

| **z/OS.** An IBM operating system for the IBM zSeries®
| and System z9™ families of enterprise servers that
| includes and integrates functions previously provided by
| many IBM software products (including the MVS and
| OS/390 operating systems).

z/OS.e. An IBM operating system available on the IBM @server® zSeries 800 (z800) and zSeries 890 (z890) that provides select z/OS function at a reduced price.

Bibliography

This bibliography lists the titles of publications containing additional information about PSF, AFP, the z/OS operating system, and related products.

The titles and order numbers may change from time to time. To verify the current title or order number, consult your IBM marketing representative.

You can obtain many of the publications listed in this bibliography from the Printing Systems support and maintenance Web page:

http://www.printers.ibm.com/internet/wwsites.nsf/vwwebpublished/supportmanuals_ww

Print Services Facility (PSF) for z/OS

Publication	Order Number
<i>AFP Conversion and Indexing Facility: User's Guide</i>	S550-0436
<i>PSF for z/OS: AFP Download Plus</i>	S550-0433
<i>PSF for z/OS: Customization</i>	S550-0427
<i>PSF for z/OS: Diagnosis</i>	G550-0428
<i>PSF for z/OS: Download for z/OS</i>	S550-0429
<i>PSF for z/OS: Introduction</i>	G550-0430
<i>PSF for z/OS: Licensed Program Specifications</i>	G550-0431
<i>PSF for z/OS: Messages and Codes</i>	G550-0432
<i>PSF for z/OS: Security Guide</i>	S550-0434
<i>PSF for z/OS: User's Guide</i>	S550-0435
<i>PSF for AIX: AFP Upload Configuration Guide Using SNA</i>	S544-5422
<i>PSF for AIX: AFP Upload Configuration Guide Using TCP/IP</i>	S544-5423
<i>PSF for z/OS Collection Kit CD-ROM (BookManager)</i>	SK3T-9927
<i>PSF for z/OS Collection Kit CD-ROM (PDF)</i>	SK3T-9928

Infoprint Server

Title	Order Number
<i>Infoprint Server Transforms Licensed Program Specifications</i>	G544-5797
<i>z/OS Infoprint Server Customization</i>	S544-5744
<i>z/OS Infoprint Server Introduction</i>	S544-5742
<i>z/OS Infoprint Server Messages and Diagnosis</i>	G544-5747
<i>z/OS Infoprint Server Operation and Administration</i>	S544-5745
<i>z/OS Infoprint Server User's Guide</i>	S544-5746

Advanced Function Presentation (AFP)

Publication	Order Number
<i>Advanced Function Printing: Host Font Data Stream Reference</i>	S544-3289
<i>AFP Conversion and Indexing Facility: User's Guide</i>	S550-0436
<i>AFP Toolbox User's Guide</i>	G544-5292
<i>AFP Workbench for Windows: Using the Viewer Application</i>	G544-3813
<i>Guide to Advanced Function Presentation</i>	G544-3876
<i>IBM Printing Systems: Printer Information</i>	S544-5750
<i>IBM Printing Systems: Printer Summary</i>	S544-5749
<i>Overlay Generation Language User's Guide and Reference</i>	S544-3700
<i>Page Printer Formatting Aid: User's Guide</i>	S544-5284
Architecture	
<i>Advanced Function Presentation: Programming Guide and Line Data Reference</i>	S544-3884
<i>Bar Code Object Content Architecture Reference</i>	S544-3766
<i>Font Object Content Architecture Reference</i>	S544-3285
<i>Graphics Object Content Architecture Reference</i>	SC31-6804
<i>Using OpenType Fonts in an AFP System</i>	G544-5876
<i>Image Object Content Architecture Reference</i>	SC31-6805
<i>Intelligent Printer Data Stream Reference</i>	S544-3417
<i>Mixed Object Document Content Architecture Reference</i>	SC31-6802
<i>Presentation Text Object Content Architecture Reference</i>	SC31-6803
Fonts	
<i>IBM AFP Fonts: Font Samples</i>	S544-3792
<i>IBM AFP Fonts: Font Summary for AFP Font Collection</i>	S544-5633
<i>IBM AFP Fonts: Type Transformer User's Guide</i>	G544-3796
<i>IBM Infoprint Fonts: Font Summary</i>	G544-5846
<i>IBM Infoprint Fonts: Introduction to Type Transformer and Utilities for Windows</i>	G544-5853

Data Transforms

Publication	Order number
<i>Infoprint XML Extender for z/OS</i>	S544-5855
<i>Infoprint XT Extender for z/OS: Customization and Usage</i>	S544-5879
<i>Infoprint XT Extender for z/OS: Messages and Diagnosis</i>	G544-5878

Text Processing

Publication	Order number
<i>DCF/DLF General Information</i>	GH20-9158

Publication	Order number
<i>Document Composition Facility: Bar Code User's Guide</i>	S544-3115
<i>Document Composition Facility: SCRIPT/VS Text Programmer's Guide</i>	SH35-0069
<i>Document Composition Facility: SCRIPT/VS Language Reference</i>	SH35-0070
<i>Publishing Systems BookMaster General Information</i>	GC34-5006
<i>Publishing Systems BookMaster User's Guide</i>	SC34-5009

Infoprint Manager

Publication	Order Number
<i>IBM Infoprint Manager for AIX: Getting Started</i>	G544-5817
<i>IBM Infoprint Manager for AIX: Introduction and Planning Guide</i>	G544-5833
<i>IBM Infoprint Manager for AIX: Procedures</i>	G544-5815
<i>IBM Infoprint Manager for Windows: Getting Started</i>	G544-5717
<i>IBM Infoprint Manager for Windows: Introduction and Planning Guide</i>	G544-5716
<i>IBM Infoprint Manager for Windows: Procedures</i>	G544-5814
<i>IBM Infoprint Manager for Windows: PSF Direct Network Configuration Guide</i>	Web-based
<i>IBM Infoprint Manager: Reference</i>	S544-5475
<i>PSF for AIX: AFP Upload Configuration Guide Using SNA</i>	S544-5422
<i>PSF for AIX: AFP Upload Configuration Guide Using TCP/IP</i>	S544-5423

Content Manager OnDemand

Publication	Order Number
<i>IBM DB2 Content Manager OnDemand for Multiplatforms: Administration Guide</i>	SC18-9237
<i>IBM DB2 Content Manager OnDemand for Multiplatforms: Indexing Reference</i>	SC18-9235
<i>IBM DB2 Content Manager OnDemand for Multiplatforms: Installation and Configuration Guide</i>	SC18-9232
<i>IBM DB2 Content Manager OnDemand for Multiplatforms: Introduction and Planning Guide</i>	GC18-9236
<i>IBM DB2 Content Manager OnDemand: Messages and Codes</i>	SC27-1379
<i>IBM DB2 Content Manager OnDemand: Report Distribution Installation, Use, Reference</i>	SC18-9233
<i>IBM DB2 Content Manager OnDemand: User's Guide</i>	SC27-0836
<i>IBM DB2 Content Manager OnDemand for Multiplatforms: Web Enablement Kit Implementation Guide</i>	SC18-9231
<i>IBM DB2 Content Manager OnDemand: Windows Client Customization Guide</i>	SC27-0837

i-data

Publication	Order Number
<i>i-data 7913 IPDS Printer LAN Attachment for Ethernet Installation Guide</i>	none
<i>i-data 7913 IPDS Printer LAN Attachment for Token Ring Installation Guide</i>	none

z/OS Version 1 Release 7

Publication	Order Number
<i>SMP/E User's Guide</i>	SA22-7773
<i>z/OS Collection</i>	SK3T-4269
<i>z/OS and Software Products DVD Collection</i>	SK3T-4271
<i>z/OS Communications Server: IP Sockets Application Programming Interface Guide and Reference</i>	SC31-8788
<i>z/OS Communications Server: IP Configuration Reference</i>	SC31-8776
<i>z/OS Communications Server: IP and SNA Codes</i>	SC31-8791
<i>z/OS Communications Server: SNA Diagnosis Vol 1, Techniques and Procedures</i>	GC31-6850
<i>z/OS Communications Server: SNA Diagnosis Vol 2, FFST Dumps and the VIT</i>	GC31-6851
<i>z/OS Communications Server: SNA Messages</i>	SC31-8790
<i>z/OS Communications Server: SNA Network Implementation Guide</i>	SC31-8777
<i>z/OS Communications Server: SNA Operation</i>	SC31-8779
<i>z/OS Communications Server: SNA Programming</i>	SC31-8829
<i>z/OS Communications Server: SNA Resource Definition Reference</i>	SC31-8778
<i>z/OS DFSMS Macro Instructions for Data Sets</i>	SC26-7408
<i>z/OS DFSMS Using Data Sets</i>	SC26-7410
<i>z/OS DFSMSdfp Utilities</i>	SC26-7414
<i>z/OS HCD Planning</i>	GA22-7525
<i>z/OS HCD User's Guide</i>	SC33-7988
<i>z/OS HCD Scenarios</i>	SC33-7987
<i>z/OS JES2 Commands</i>	SA22-7526
<i>z/OS JES2 Initialization and Tuning Guide</i>	SA22-7532
<i>z/OS JES2 Initialization and Tuning Reference</i>	SA22-7533
<i>z/OS JES2 Messages</i>	SA22-7537
<i>z/OS JES3 Commands</i>	SA22-7540
<i>z/OS JES3 Initialization and Tuning Guide</i>	SA22-7549
<i>z/OS JES3 Initialization and Tuning Reference</i>	SA22-7550
<i>z/OS JES3 Messages</i>	SA22-7552
<i>z/OS Language Environment Programming Guide</i>	SA22-7561
<i>z/OS MVS Diagnosis: Procedures</i>	GA22-7587
<i>z/OS MVS Diagnosis: Tools and Service Aids</i>	GA22-7589

Publication	Order Number
<i>z/OS MVS Initialization and Tuning Reference</i>	SA22-7592
<i>z/OS MVS IPCS User's Guide</i>	SA22-7596
<i>z/OS MVS IPCS Commands</i>	SA22-7594
<i>z/OS MVS JCL Reference</i>	SA22-7597
<i>z/OS MVS JCL User's Guide</i>	SA22-7598
<i>z/OS MVS Programming: Authorized Assembler Services Guide</i>	SA22-7608
<i>z/OS MVS Programming: Authorized Assembler Services Reference ALE-DYN</i>	SA22-7609
<i>z/OS MVS Programming: Authorized Assembler Services Reference ENF-IXG</i>	SA22-7610
<i>z/OS MVS Programming: Authorized Assembler Services Reference LLA-SDU</i>	SA22-7611
<i>z/OS MVS Programming: Authorized Assembler Services Reference SET-WTO</i>	SA22-7612
<i>z/OS MVS Recovery and Reconfiguration Guide</i>	SA22-7623
<i>z/OS MVS System Codes</i>	SA22-7626
<i>z/OS MVS System Commands</i>	SA22-7627
<i>z/OS MVS System Management Facilities (SMF)</i>	SA22-7630
<i>z/OS MVS Using the Functional Subsystem Interface</i>	SA22-7641
<i>z/OS SDSF Operation and Customization</i>	SA22-7670
<i>z/OS Security Server RACF General User's Guide</i>	SA22-7685
<i>z/OS Security Server RACF Security Administrator's Guide</i>	SA22-7683
<i>z/OS Security Server RACF System Programmer's Guide</i>	SA22-7681
<i>z/OS Support for Unicode: Unicode Services</i>	SA22-7649
<i>z/OS UNIX System Services Command Reference</i>	SA22-7802

Index

A

- accessibility 31
- activating print labeling with RACF 15
- activating security labeling checking 15
- adding user IDs to RACF profiles 15
- allocating security resource libraries 13
- allocating the security definitions library 8
- areas, physical page 2
- assembling separator pages 14
- attributes for security definitions library 9
- auditing printing 21
- auditing PSF output for security 3

C

- commands, RACF
 - PERMIT 15
 - RDEFINE 15
 - REFRESH 16
 - SETROPTS 15
- computing base, trusted 3
- consoles, defining security 14
- creating RACF profiles 15
- creating security overlays 8

D

- data definition names, defining 19
- DD statements
 - SDEF240
 - SDEF300 19
 - SFONT300 19
 - SOVLY300 19
 - SPSEG300 19
 - SDEFDD 19
 - SFONT240 19
 - SFONTDD 19
 - SOVLY240 19
 - SOVLYDD 19
 - SPSEG240 19
 - SPSEGDD 19
- defaults, overriding print labeling 21
- defining
 - security consoles 14
 - security definitions library 9
 - security resources 13
 - security-related data definition names 19
- deleting security resources 16
- designing pages for print labeling 8
- diagnosing print labeling problems 22
- disability 31
- distributing secure PSF output 3
- DPAGELBL parameter 18

E

- enabling print labeling 15
- end-user security label 6
- error messages, interpreting 22
- exits for assembling separator pages 14

G

- guaranteed print labeling 15

H

- hardware, trusted 5

I

- identification labels
 - description of 1
 - layout for 2, 27
 - printing correct 20
- initialization parameters, updating 17
- installation exits for separator pages 14
- installing PSF 7
- interpreting error messages 22

J

- JES messages, interpreting 22

K

- keyboard 31

L

- Label data pages parameter 18
- Label separator pages parameter 18
- label, security 2, 6
- layout, security page 27
- libraries
 - attributes for 9
 - defining security definitions 9
 - defining security resource 13
- loading security resources 16
- LookAt message retrieval tool xi

M

- maintaining PSF with print labeling enabled 21
- message retrieval tool, LookAt xi
- messages, interpreting 22

N

- names, system-defined paper 29
- nonguaranteed print labeling 15

numbering, random job 3

O

OUTPUT statement for overriding defaults 21
overlays, creating security 8
overriding print labeling defaults 21

P

page layout template 27
pages, designing for print labeling 8
paper names, system-defined 29
PAPERNAME parameter 29
parameters and options
 DD statement 19
 PAPERNAME 29
 PRINTDEV statement 18, 19
 Printer Inventory 18
 PSFMPL 15
 SECLABEL 20
 SECLABEL in RACF 15
 security definitions library 9
PERMIT command 15
physical page, printable area 2
print job, submitting secure 20
print labeling function
 activating with PSFMPL 15
 allocating the security definitions library 8
 assembling separator pages 14
 defining
 security consoles 14
 security definitions library 9
 security resource libraries 13
 designing pages 8
 diagnosing problems 22
 enabling 15
 guaranteed 15
 installing PSF 7
 maintaining PSF with print labeling enabled 21
 nonguaranteed 15
 overriding defaults 21
 page template 27
 printer support for 7
 PSF processing differences 16
 random numbering of printed output 3
 security auditing of output 3
 security-related PSF tasks 6
 submitting secure print jobs 20
 trusted computing base components 3
 understanding 1
 UPA 2
 updating initialization parameters 17
 using 7
Print Services Facility (PSF)
 auditing printing 21
 distributing secure output 3
 error messages, interpreting 22
 installing 7
 maintaining with print labeling enabled 21, 22
 printer support in 7

Print Services Facility (PSF) (*continued*)
 processing differences when using print labeling 16
 security auditing of output 3
 security-related tasks 6
 using print labeling 7
printable area considerations 16
PRINTDEV statement parameters 18, 19
Printer Inventory parameters 18
printer support for print labeling 7
problems, diagnosing print labeling 22
processing differences when using print labeling 16
profiles, creating RACF 15
PSFMPL option 15
publications, related 39

R

RACF
 adding user IDs to profiles 15
 profiles, creating 15
 refreshing 16
random numbering for print labeling 3
RDEFINE command 15
refreshing RACF 16
related publications 39
resources
 defining security 13
 loading and deleting security 16
Restrict printable area parameter 18
rules for defining a security definitions member 11

S

sample security definitions member 12
SDEF240 parameter 19
SDEF300 parameter 19
SDEFDD parameter 19
SECLABEL option in RACF 15
SECLABEL parameter 20
secure print jobs, submitting 20
secure PSF output, distributing 3
security auditing of PSF output 3
security consoles, defining 14
security definitions library
 allocating 8
 attributes 9
 defining 9
 rules for defining a member 11
 sample member 12
 syntax for members 9
security label 2, 6
security overlays, creating 8
security page layout 27
security resource library, allocating and defining 13
security resources, loading and deleting 16
security-related messages, interpreting 22
security-related tasks 6
separator pages, assembling 14
SETROPTS command 15
SFONT240 parameter 19
SFONT300 parameter 19

- SFONTDD parameter 19
- shortcut keys 31
- SMF type 6 record auditing 21
- software, trusted 4
- SOVLY240 parameter 19
- SOVLY300 parameter 19
- SOVLYDD parameter 19
- SPAGELBL parameter 18
- SPSEG240 parameter 19
- SPSEG300 parameter 19
- SPSEGDD parameter 19
- submitting secure print jobs 20
- syntax for security definitions member 9
- SYSAREA parameter 18
- system-defined paper names 29

T

- tasks, security-related 6
- trusted computing base 3
 - end users 6
 - hardware 5
 - software 4

U

- UPA 2
- updating initialization parameters 17
- user IDs, adding to RACF profiles 15
- user-printable area 2

Readers' Comments — We'd Like to Hear from You

Print Services Facility for z/OS
Security Guide
Version 4, Release 1.0

Publication No. S550-0434-00

Overall, how satisfied are you with the information in this book?

	Very Satisfied	Satisfied	Neutral	Dissatisfied	Very Dissatisfied
Overall satisfaction	☐	☐	☐	☐	☐

How satisfied are you that the information in this book is:

	Very Satisfied	Satisfied	Neutral	Dissatisfied	Very Dissatisfied
Accurate	☐	☐	☐	☐	☐
Complete	☐	☐	☐	☐	☐
Easy to find	☐	☐	☐	☐	☐
Easy to understand	☐	☐	☐	☐	☐
Well organized	☐	☐	☐	☐	☐
Applicable to your tasks	☐	☐	☐	☐	☐

Please tell us how we can improve this book:

Thank you for your responses. May we contact you? ☐ Yes ☐ No

When you send comments to IBM, you grant IBM a nonexclusive right to use or distribute your comments in any way it believes appropriate without incurring any obligation to you.

Name

Address

Company or Organization

Phone No.



Cut or Fold
Along Line

Fold and Tape

Please do not staple

Fold and Tape




NO POSTAGE
NECESSARY
IF MAILED IN THE
UNITED STATES

BUSINESS REPLY MAIL

FIRST-CLASS MAIL PERMIT NO. 40 ARMONK, NEW YORK

POSTAGE WILL BE PAID BY ADDRESSEE

IBM Corporation
Information Development
IBM Printing Systems Division
Department H7FE Building 004N
Boulder, CO 80301-9817



Fold and Tape

Please do not staple

Fold and Tape

Cut or Fold
Along Line



Program Number: 5655-M32

Printed in USA

S550-0434-00



Spine information:



Print Services Facility for z/OS

PSF V4R1 for z/OS: Security Guide

Version 4,
Release 1.0