TOSHIBA Photocoupler GaAlAs Ired & Photo IC

TLP2530, TLP2531

Digital Logic Isolation

Line Receiver

Power Supply Control

Switching Power Supply

Transistor Inverter

The TOSHIBA TLP2530 and TLP2531 dual photocouplers consist of a pair of GaAlAs light emitting diode and integrated photodetector. This unit is 8-lead DIP.

Separate connection for the photodiode bias and output transistor collectors improve the speed up to a hundred times that of a conventional phototransistor coupler by reducing the base-collector capacitance.

- TTL compatible •
- Switching speed: tpHL=0.3µs, tpLH=0.3µs(typ.) • (@RL=1.9kΩ)
- Guaranteed performance over temp: 0~70°C •
- Isolation voltage: 2500 Vrms(min.)
- UL recognized: UL1577, file no. E67349

Pin Configuration (top view)



TOSHIBA 11-10C4

Weight: 0.54g

1 **C** 8 2 C 7 3 **C** 6 5 4 C

1. : Anode.1

- 2. : Cathode.1
- 3. : Cathode.2
- 4. : Anode.2
- 5. : Gnd
- 6. : V_{O2}(output 2) 7. : V_{O1}(output 1)
- 8. : V_{CC}

Schematic



Unit in mm

11-10C4

Absolute Maximum Ratings

	Characteristic	Symbol	Rating	Unit	
LED	Forward current(each channel)	(Note 1)	١ _F	25	mA
	Pulse forward current (Each Channel)	(Note 2)	I _{FP}	50	mA
	Total pulse forward current (each channel)	(Note 3)	I _{FPT}	1	А
	Reverse voltage(each channel)		V _R	5	V
	Diode power dissipation (each channel)	(Note 4)	PD	45	mW
Detector	Output current(each channel)		Ι _Ο	8	mA
	Peak output current (each channel)		I _{OP}	16	mA
	Supply voltage		V _{CC}	-0.5~15	V
	Output voltage(each channel)		Vo	-0.5~15	V
	Output power dissipation (each channel)	(Note 5)	PO	35	mW
Ope	erating temperature range	T _{opr}	-55~100	°C	
Stor	rage temperature range	T _{stg}	-55~125	°C	
Lea	d solder temperature(10s)**	T _{sol}	260	°C	
Isolation voltage (AC, 1min., R.H.≤ 60%) (Note 7)			BVS	2500	Vrms

Note: Using continuously under heavy loads (e.g. the application of high temperature/current/voltage and the significant change in temperature, etc.) may cause this product to decrease in the reliability significantly even if the operating conditions (i.e. operating temperature/current/voltage, etc.) are within the absolute maximum ratings.

Please design the appropriate reliability upon reviewing the Toshiba Semiconductor Reliability Handbook ("Handling Precautions"/"Derating Concept and Methods") and individual reliability data (i.e. reliability test report and estimated failure rate, etc).

(Note 1) Derate 0.8mA above 70°C. (Note 2) 50% duty cycle, 1ms pulse width. Derate 1.6mA / °C above 70°C. (Note 3) Pulse width 1µs, 300pps. (Note 4) Derate 0.9mW / °C above 70°C. (Note 5) Derate 1mW / °C above 70°C.

**2mm below seating plane.

Recommended Operating Conditions

Characteristic	Symbol	Min.	Тур.	Max.	Unit
Supply voltage	V _{CC}	0	_	12	V
Forward current, each channel	١ _F	_	16	25	mA
Operating temperature	T _{opr}	-25		85	°C

Note: Recommended operating conditions are given as a design guideline to obtain expected performance of the device. Additionally, each item is an independent guideline respectively. In developing designs using this product, please confirm specified characteristics shown in this document.

Electrical Characteristics Over Recommended Temperature (Ta = 0°C~70°C, unless otherwise noted)

Characteristic		Symbol	Test Condition	Min.	Тур.**	Max.	Unit
	TLP2530	CTR	$I_F = 16mA, V_O = 0.4V$	7	30	_	%
Current transfer ratio	TLP2531	OII	(Note	6) 19	30	_	
(each channel)	TLP2530	СТР	I _F = 16mA, V _O = 0.5V	5	—	_	0/
	TLP2531	CIR	$V_{CC} = 4.5V$ (Note	6) 15	—	_	%
Logic low output	TLP2530	VoL	I _F = 16mA, I _O = 1.1mA V _{CC} = 4.5V	_	0.1	0.4	V
(each channel)	TLP2531		I _F = 16mA, I _O = 2.4mA V _{CC} = 4.5V	_	0.1	0.4	V
Logic high output current (each channel)		I _{ОН}	$I_F = 0mA$, $V_O = V_{CC} = 5.5V$ Ta = 25°C	_	3	500	nA
			I _F = 0mA, V _O = V _{CC} = 15V	—	—	50	μA
Logic low supply curren	nt	ICCL	$I_{F1} = I_{F2} = 16mA$ $V_{O1} = V_{O2} = Open$ $V_{CC} = 15V$	_	160	_	μΑ
Logic high supply curre	ent	Іссн	$I_{F1} = I_{F2} = 0mA$ $V_{O1} = V_{O2} = Open$ $V_{CC} = 15V$		0.05	4	μΑ
Input forward voltage (each channel)		VF	I _F = 16mA, Ta = 25°C	—	1.65	1.7	v
Temperature coefficent of forward voltage(each channel)		ΔV _F / ΔTa	I _F = 16mA	_	-2	_	mV/°C
Input reverse breakdown voltage(each channel)		BV _R	IR = 10μΑ, Ta = 25°C	5	_	_	V
Input capacitance (each channel)		C _{IN}	f = 1MHz, V _F = 0	—	60	_	pF
Input-output insulation leakage current		I _{I–O}	$\label{eq:relative humidity = 45\%} \begin{cases} t = 5s, \ V_{I-O} = 3000V_{dc} \\ Ta = 25^{\circ}C \end{cases} \qquad (Note$	7) —	_	1.0	μA
Resistance (input-output)		R _{I–O}	$V_{I-O} = 500V_{dc}$ (Note	7) —	10 ¹²	_	Ω
Capacitance (input-out	tput)	C _{I–O}	f = 1MHz (Note	7) —	0.6	_	pF
Input-input leakage current		I _{I-I}	Relative humidity = 45% t = 5s, $V_{I-I} = 500V$ (Note	8)	0.005	_	μΑ
Resistance (input-inpu	t)	R _{I–I}	$V_{I-I} = 500V_{dc}$ (Note	8) —	10 ¹¹	_	Ω
Capacitance (input-iutput)		CI-I	f = 1MHz (Note	8) —	0.25		pF

**All typicals at Ta = 25°C.

Switching Characteristics (unless otherwise specified, Ta = 25°C, V_{CC} = 5V, I_F = 16mA)

Characteristic		Symbol	Test Cir– cuit	Test Condition	Min.	Тур.	Max.	Unit
Propagation delay time to logic low	TLP2530	. t _{pHL}	1	R _L = 4.1kΩ	_	0.3	1.5	μs
at output (each channel)	TLP2531			R _L = 1.9kΩ	_	0.2	0.8	
Propagation delay time to logic	TLP2530	t _{pLH}	1	R _L = 4.1kΩ	_	0.5	1.5	μs
high at output (each channel)	TLP2531			R _L = 1.9kΩ		0.3	0.8	
Common mode transient immunity at logic	TLP2530	CM	2	I _F = 0mA, V _{CM} = 400V _{p-p} R _L = 4.1kΩ	_	1500	_	- V / µs
high level output (each channel, Note 9)	TLP2531	CMH		I _F = 0mA, V _{CM} = 400V _{p-p} R _L = 1.9kΩ		1500	_	
Common mode transient immunity at logic	TLP2530			V _{CM} = 400V _{p−p} R _L = 4.1kΩ, I _F = 16mA		-1500	-	V / µs
low level output (each channel, Note 9)	TLP2531	CML	2	V _{CM} = 400 _{p−p} R _L = 1.9kΩ, I _F = 16mA	_	-1500	Ι	
Bandwidth (each channel, Note 10)		BW	3	R _L = 100Ω	_	2	_	MH_Z

(Note 6) DC current transfer ratio is defined as the ratio of output collector current, I_O to the forward LED input current, I_F, times 100%.

(Note 7) Device considered a two-terminal device: Pins 1, 2, 3 and 4 shorted together and pins 5, 6, 7, and 8 shorted together.

- (Note 8) Measured between pins 1 and 2 shorted together, and pins 3 and 4 shorted together.
- (Note 9) Common mode transient immunity in logic high level is the maximum tolerable (positive) dVcm / dt on the leading egde of the common mode pulse, Vcm, to assure that the output will remain in a logic high state(i.e., V_O > 2.0V). Common mode transient immunity in logic low Level is the maximum tolerable (negative) dVcm / dt

Common mode transient immunity in logic low Level is the maximum tolerable (negative) dVcm / dt on the trailing edge of the common mode pulse signal, Vcm, to assure that the output will remain in logic low state(i.e., $V_O > 0.8V$).

(Note 10) The frequency at which the ac output voltage is 3dB below the low frequency asymptote.

<u>TOSHIBA</u>

Test Circuit 1: Switching Time, tpHL, tpLH





Test Circuit 2: Transient Immunity And Typical Waveform





Test Circuit 3: Frequency Response



TOSHIBA













TOSHIBA







RESTRICTIONS ON PRODUCT USE

20070701-EN

- The information contained herein is subject to change without notice.
- TOSHIBA is continually working to improve the quality and reliability of its products. Nevertheless, semiconductor devices in general can malfunction or fail due to their inherent electrical sensitivity and vulnerability to physical stress. It is the responsibility of the buyer, when utilizing TOSHIBA products, to comply with the standards of safety in making a safe design for the entire system, and to avoid situations in which a malfunction or failure of such TOSHIBA products could cause loss of human life, bodily injury or damage to property.
 In developing your designs, please ensure that TOSHIBA products are used within specified operating ranges as set forth in the most recent TOSHIBA products specifications. Also, please keep in mind the precautions and conditions set forth in the "Handling Guide for Semiconductor Devices," or "TOSHIBA Semiconductor Reliability Handbook" etc.
- The TOSHIBA products listed in this document are intended for usage in general electronics applications (computer, personal equipment, office equipment, measuring equipment, industrial robotics, domestic appliances, etc.).These TOSHIBA products are neither intended nor warranted for usage in equipment that requires extraordinarily high quality and/or reliability or a malfunction or failure of which may cause loss of human life or bodily injury ("Unintended Usage"). Unintended Usage include atomic energy control instruments, airplane or spaceship instruments, transportation instruments, traffic signal instruments, combustion control instruments, medical instruments, all types of safety devices, etc.. Unintended Usage of TOSHIBA products listed in his document shall be made at the customer's own risk.
- The products described in this document shall not be used or embedded to any downstream products of which manufacture, use and/or sale are prohibited under any applicable laws and regulations.
- The information contained herein is presented only as a guide for the applications of our products. No responsibility is assumed by TOSHIBA for any infringements of patents or other rights of the third parties which may result from its use. No license is granted by implication or otherwise under any patents or other rights of TOSHIBA or the third parties.
- GaAs(Gallium Arsenide) is used in this product. The dust or vapor is harmful to the human body. Do not break, cut, crush or dissolve chemically.
- Please contact your sales representative for product-by-product details in this document regarding RoHS compatibility. Please use these products in this document in compliance with all applicable laws and regulations that regulate the inclusion or use of controlled substances. Toshiba assumes no liability for damage or losses occurring as a result of noncompliance with applicable laws and regulations.