2．Manual control mode:

In this mode, the dip- switch 10 is flipped to the “OFF” position. Flip the dip-switch 1-3 to set the intensity of Red LEDs, dip-switch 4-6 to set the intensity of Green LEDs and dip-switch 7-9 to set the intensity of Blue LEDs. Please refer to the following table for further information.

Dip-Switch Setting

Intensity	Red(SW1-3)	Green(SW4-6)	Blue(SW7-9)
0	000	000	000
14%	100	100	100
28%	010	010	010
43%	110	110	110
57%	001	001	001
71%	101	101	101
86%	011	011	011
100%	111	111	111

