

PN4248, PN4249, PN4250

PNP SILICON AF LOW NOISE SMALL SIGNAL TRANSISTORS

PN42248, PN4249, PN4250 are PNP silicon planar transistors for AF low noise preamplifier applications.

CASE TO-92A



EBC

ABSOLUTE MAXIMUM RATINGS

		PN4248	PN4250	PN4249
Collector-Base Voltage	-V _{CB0}	40V	40V	60V
Collector-Emitter Voltage	-V _{CEO}	40V	40V	60V
Emitter-Base Voltage	-V _{EB0}	5V	5V	5V
Collector Current	-I _C		50mA	
Total Power Dissipation (T _C ≤ 65°C)	P _{tot}		300mW	
			200mW	
Operating Junction & Storage Temperature	T _j , T _{stg}		-55 to 125°C	

ELECTRICAL CHARACTERISTICS (T_A=25°C unless otherwise noted)

PARAMETER	SYMBOL	PN4248 MIN MAX	P N4249 MIN MAX	PN4250 MIN MAX	UNIT	TEST CONDITIONS
Collector-Base Breakdown Voltage	-BV _{CB0}	40	60	40	V	-I _C =0.01mA I _E =0
Collector-Emitter Breakdown Voltage	-BV _{CES}	40	60	40	V	-I _C =0.01mA V _{BE} =0
Collector-Emitter Breakdown Voltage	-LV _{CEO}	40	60	40	V	-I _C =5mA (Pulsed) I _B =0
Emitter-Base Breakdown Voltage	-BV _{EB0}	5	5	5	V	-I _E =0.01mA I _C =0
Collector Cutoff Current	-I _{CBO}	10 3	10 3	10 3	nA μA	-V _{CB} =40V I _E =0 -V _{CB} =40V I _E =0 T _A =65°C
Emitter Cutoff Current	-I _{EB0}	20	20	20	nA	-V _{EB} =3V I _C =0
Collector-Emitter Saturation Voltage	-V _{CE(sat)}	0.25	0.25	0.25	V	-I _C =10mA -I _B =0.5mA
Base-Emitter Saturation Voltage	-V _{BE(sat)}	0.9	0.9	0.9	V	-I _C =10mA -I _B =0.5mA
D.C. Current Gain	H _{FE}	50 50 50	100 300 100 100	250 700 250 250		-I _C =100μA -V _{CE} =5V -I _C =1mA -V _{CE} =5V -I _C =10mA -V _{CE} =5V

MICRO ELECTRONICS LTD.

38 HUNG TO ROAD, KWUN TONG, HONG KONG. TELEX 43510
KWUN TONG P. O. BOX 69477 CABLE ADDRESS "MICROTRON" FAX: 3-410321
TELEPHONE: 3-430181-6 3-893363 3-892423

- - - Continued - - -

PARAMETER	SYMBOL	PN4248 MIN MAX	PN4249 MIN MAX	PN4250 MIN MAX	UNIT	TEST CONDITIONS
Small Signal Current Gain	h_{fe}	50 1000	100 550	250 800		$-I_C=1mA$ $-V_{CE}=5V$ $f=1kHz$
Input Impedance	h_{ie}		2.5 17	6 20	$K\Omega$	$-I_C=1mA$ $-V_{CE}=5V$ $f=1kHz$
Output Admittance	h_{oe}		5 40	5 50	μS	$-I_C=1mA$ $-V_{CE}=5V$ $f=1kHz$
Voltage Feedback Ratio	h_{re}		10	10	$\times 10^{-4}$	$-I_C=1mA$ $-V_{CE}=5V$ $f=1kHz$
Current Gain-Bandwidth Product	f_T	40	40	50	MHz	$-I_C=0.5mA$ $-V_{CE}=5V$
Collector-Base Capacitance	C_{ob}	6	6	6	pF	$-V_{CB}=5V$ $I_E=0$ $f=1MHz$
Emitter-Base Capacitance	C_{ib}	16	16	16	pF	$-V_{EB}=0.5V$ $I_C=0$ $f=1MHz$
Noise Figure	NF		3	2	dB	$-I_C=20\mu A$ $-V_{CE}=5V$ $R_G=10K\Omega$ $f=1kHz$
			3	2	dB	$-I_C=20\mu A$ $-V_{CE}=5V$ $R_G=10K\Omega$ $f=10Hz-10kHz$
			3	2	dB	$-I_C=250\mu A$ $-V_{CE}=5V$ $R_G=1K\Omega$ $f=1kHz$