


GMR3040-2CKHS

- 15 GMRS / 7 FRS Channels
 - 7 Weather Channels
 - 121 Sub Codes (CTCSS Tone and DCS Code)
 - Up to 30 Mile Range*
 - Internal VOX Circuitry
 - 10 Selectable Call Tone Alerts
 - Backlit LCD Display
 - 2 Headset Boom mics
 - Headset Jack
 - 2 Carabiner Clips
- Roger Beep
 - Battery Charger
 - Battery Level Meter
 - Channel Monitor
 - Channel Scan
 - Keypad Lock
 - DC 9V Jack
 - NOAA Emergency / Weather Channels

*Range may vary depending on environmental and/or topographical conditions.

GMR3040-2CKHS RADIO



- 1 Antenna

2 PTT (Push-To-Talk) Button

3 Call/Lock Button

4 Menu/Power Key

5 Channel Up/Down Key

6 Weather/Monitor Key

7 Speaker

8 Headset Jack/DC 9V

9 Volume Up/Down Key

10 Microphone

11 Battery Level Meter

12 Receive Indicator
- 13 Call Indicator

14 Scan Indicator

15 Channel Indicator

16 Hi Power Indicator

17 Low Power Indicator

18 Transmit Indicator

19 Volume Setting Indicator

20 Keypad Lock Indicator

21 VOX Indicator

22 Weather Indicator

23 Sub Code Indicator

24 Charging Contacts

Congratulations on your purchase of the Uniden GMR3040-2CKHS (General Mobile Radio Service) radio. This lightweight, palm-sized radio is a state-of-the-art device, equipped with many valuable features. Use it at sporting events, to stay in contact with family and friends, hiking, skiing, outdoors, or in a neighborhood watch for vital communication.

PACKAGE CONTENTS

Your package contains two radios, two rechargeable NiMH battery packs, one AC adapter, one charging cradle, two headset boom mics, two belt clips, 2 carabiner clips and this reference guide. A NiMH battery pack or 3 AAA alkaline batteries (not included) powers each unit. To order the following optional accessories, visit our web site at www.uniden.com or call 1-800-554-3988 during regular business hours. **Use only Uniden accessories.**

- NiMH Battery Pack - #BT-1028 or BP-1028
- Charging Cradle - #RC-1287
- Headset - #ZA-133 or ZA-160
- AC Adapter - #AD-0001
- DC Adapter - #DC-1002
- Carabiner Clip - # TSTD0720002

GMRS LICENSE


The radio operates on the General Mobile Radio Service (GMRS) frequencies when using Channels 1-7 and channels 15-22. You must have a GMRS license issued by the Federal Communications Commission to legally use these channels. For licensing information and application forms, visit the FCC online at: www.fcc.gov/wtb/uls or call the FCC hotline at 1-800-418-3676. If you have any questions, you can contact the FCC direct at 1-888-225-5322. No license is required for operation on channels 8-14 or operation on any channel in Canada.

INSTALL THE BATTERY

Each radio uses a supplied NiMH battery pack or 3 AAA alkaline batteries (not included). To install the NiMH battery pack:

- 1) Make sure your radio is OFF.
- 2) Press the tab at the bottom of the battery compartment door to remove the cover.
- 3) Install the NiMH battery pack into the battery compartment. Be certain to follow the instructions written on the label on the battery pack. Installing the battery pack incorrectly will prevent the unit from operating.
- 4) Replace the battery compartment door.

BATTERY LEVEL AND LOW BATTERY ALERT

This unit has a battery level meter on the display to indicate the status of the batteries. When the battery in the unit is low, the battery level meter icon  flashes. Recharge the NiMH battery pack immediately or if you are using alkaline batteries, you must replace the alkaline batteries in order to continue using the radio.

Warning! To avoid the risk of personal injury or property damage from fire or electrical shock, only use the Uniden accessories specifically designated for this product.

CHARGING THE RADIO

If you use the rechargeable NiMH battery pack, two radios can be charged directly or by using the supplied charging cradle.

USING THE RADIO

- 1) Connect the optional DC adapter (#DC-1002) to DC 9V jack of the radio and to a cigarette lighter port.
- 2) Charge the battery pack for 16 hours until the battery indicator stops flashing.

USING THE CHARGING CRADLE

- 1) Connect the AC adapter (#AD-0001) to DC 9V jack and to a standard 120V AC wall outlet.
- 2) Set the charging cradle on the desk or tabletop, and place the radio in the charging cradle with the keypad facing forward.
- 3) Make sure that the LED illuminates. Charge the battery pack for 16 hours and remove the radio from the charging cradle after charging.

Note:

- For charging batteries directly without the cradle, use only the #DC-1002 Cigarette Lighter Adapter cord, available from www.Uniden.com. Other power cords could damage your radio.
- DC 9V jack of the radio is for charging only. Be sure to install the battery before charging.
- Use only the supplied battery and AC adapter or approved accessories from Uniden.
- Charge time may vary depending on the battery life remaining.
- Do not recharge alkaline batteries. Doing so can create a safety hazard or damage the radio.
- For fastest charging, turn off the radio before charging.
- The battery must be installed for the unit to operate, even if the unit is also connected to external power.

- If battery power is low, you cannot operate the radio even using external power. Allow the batteries to charge before using. If you try to transmit while power is low, the radio will automatically turn off.

USING A HEADSET



You can use a headset (#ZA-133 or ZA-160) for more private communications. To use a headset, lift the rubber cover from over the headset jack, then plug in the headset.

Important: Your radio is not weather resistant when using a headset jack. When you remove the headset, be sure to fully press the jack cover into place to restore its weather resistant capability.

USING THE RADIO

In order to get the most out of your new radio, read this reference guide completely before attempting to operate the unit.

TURNING THE RADIO ON AND ADJUSTING THE VOLUME

- 1) Press and hold **MENU**/ to turn the radio ON, and increase the speaker volume by pressing **VOL ▲** . To decrease the volume, press **VOL ▼** .
- 2) Press and hold **MENU**/ again to turn the radio OFF.

ADJUSTING THE SOUND (KEY BEEPS)

Your radio emits a beep each time one of the keys (except for the **PTT** and **CALL/LOCK**) is pressed. To turn this sound OFF, press and hold **CALL/LOCK** while turning ON the radio. Repeat this step to turn the sound ON.

CHOOSING A CHANNEL

Your radio has 22 channels and 121 Sub codes you can use to talk to others. In order to speak to someone, each of you must be set to the same channel and Sub code.

To choose a channel:

With the radio in "Normal" operating mode, press the **CH ▲ / CH ▼** key to increase or decrease the channel number displayed.

Note: Channels 1-7 have a typical range of up to 30 miles. Channels 8-14 have a typical range of up to 5 miles. Channels 15-22 have a typical range of up to 30 miles. You can see which GMRS or FRS channel is active by the icon. The **hi** icon is displayed while scanning GMRS channels, and the **lo** icon is displayed while scanning FRS channels.

TALKING ON YOUR RADIO

To talk to others using the radio:

- 1) Press and hold the **PTT** button and speak in a clear, normal voice about 2-3 inches away from the microphone. While you are transmitting, the **tx** icon appears on the display. To avoid cutting off the first part of your transmission, pause slightly after pressing the **PTT** button before you start talking.
- 2) When you have finished speaking, release the **PTT** button. You can now receive incoming calls. While receiving, **rx** displays.

MONITOR MODE FEATURE

Your radio allows you to listen for weak signals on the current channel at the press of a key.


To turn ON Monitor mode:


- Press and hold **WX/MON** for 2 seconds until two beeps sound. The receiver circuit stays open, and both noise and weak signals can be heard.




To turn OFF Monitor mode:

- Press and hold **WX/MON** for 2 seconds to return to "Normal" mode; the **rx** icon stops blinking and disappears.

ADVANCED FUNCTIONS (MENUS)


Use **MENU**/ to access your radio's advanced functions.




- 1) Press **MENU**/ to enter the menus.
- 2) Additional presses of **MENU**/ advance you through the menus until exiting to "Normal" operating mode.
- 3) Other methods of exiting the Menu function are:
 - a. Press and hold **MENU**/ again.
 - b. Press any key except **CH ▲ / CH ▼** or **VOL ▲ / VOL ▼** and wait 10 seconds until the unit returns to "Normal" mode.

Sub Code

Each of the channels 1-22 may have any one of the codes, OFF, or 1-121 selected. Code **oF** (OFF) indicates no Sub code selected and your radio can receive a signal regardless of the code settings of the transmitting radio.

- 1) Press **MENU**/ to enter *Menu* mode. The subcode indicator flashes.
- 2) Press **CH ▲ / CH ▼** key to increase or



decrease the code number displayed. You can also select **oF** (OFF) at this stage.

- 3) Press **MENU**/ to exit Menu mode.
- 4) Press any key other than **CH ▲ / CH ▼** or **VOL ▲ / VOL ▼** and the radio returns to Idle mode in 10 seconds.


Scan

Your radio has a channel scan feature that allows you to easily scan all 22 channels. When an active channel is detected, the radio pauses on that channel until the channel is clear. Then, after a 2 second delay, the radio continues scanning. Pressing the **PTT** button while the scan is paused on a channel allows you to transmit on that channel.

To turn ON channel scan:

- 1) Press **MENU**/ repeatedly until the **scan...** icon and **oF** blink.
2. Press **CH ▲ / CH ▼** to select Scan mode and press **MENU**/ to start it.


To turn OFF channel scan:

- 1) Press **MENU**/ when the scan setting is **oF**.
- 2) Press any key other than **CH ▲ / CH ▼** or **VOL ▲ / VOL ▼** to turn channel scan off in 10 seconds.

Voice Operated Transmission

Your radio is equipped with a user selectable Voice Operated Transmitter (VOX) that can be used for automatic voice transmissions. The VOX feature is designed to be used with or without a headset with a microphone. Transmission is initiated by speaking into the microphone instead of pressing **PTT**.


To select VOX level:

- 1) Press **MENU**/ repeatedly until the **vox** icon and the VOX sensitivity level (*OFF, 1-5*) blink.
- 2) Press **CH ▲ / CH ▼** to change the VOX sensitivity levels. Use level 1 for increased sensitivity to voice in normally quiet environments, and use a higher level to reduce undesired activation in very noisy environments.

Call Tone

Your radio is equipped with 10 selectable call tones that are transmitted when **CALL/LOCK** is pressed.

To select a call tone:

- 1) Press **MENU**/ repeatedly until the **CALL** icon and *Call Tone* start to blink on the display.
- 2) Press **CH ▲ / CH ▼** to move through the available call tones. Each tone will be heard

through the speaker but will not be transmitted. Cycle through these tones and stay on the tone you want to select.

- 3) Exit Call Tone to set the selected tone.

KEY LOCK


To lock the keypad:

- 1) Press and hold **CALL/LOCK**;  displays.

These functions are not affected by Key Lock:

- Volume adjust
- Call tone transmission
- Enter monitor mode
- PTT transmission
- Power off

To unlock the keypad:

- 1) Press and hold **CALL/LOCK** again;  disappears.

AUTOMATIC POWER SAVE

Your radio has a circuit designed to dramatically extend the life of the batteries. If there is no transmission or an incoming call within 3 seconds, your radio switches to Power Save mode. The radio is still able to receive transmissions in this mode.

LCD BACKLIGHT

The LCD Backlight automatically turns ON when any key (except the **PTT** button) is pressed. The LCD display illuminates for 10 seconds before turning OFF.

ROGER BEEP

Roger Beep is a BEEP that is sent to notify the end of transmission (both PTT and VOX transmission). Roger Beep can be heard through the speaker when both Roger Beep and Key Beep are set to ON. When Roger Beep is set to ON and Key Beep is set to OFF, Roger Beep will not be heard from the speaker but it will be transmitted to your party. When Roger Beep is set to OFF, Roger Beep will neither be heard nor transmitted.

To change Roger Beep setting:

Press and hold **VOL ▲** while turning the radio on and off. If Roger Beep is ON, it will be turned off; if it is OFF, it will be turned on.

USING THE WEATHER RADIO

Your radio can receive weather broadcasts from the NOAA National Weather Service. While using the Weather Radio, you are not able to receive GMRS communications.

- 1) To turn on the Weather Radio Broadcast mode, press **WX/MON**. The ☂ icon appears.
- 2) Press **CH ▲ / CH ▼** to increase or decrease the number to the desired Weather Channel.
- 3) To exit the Weather Radio Broadcast mode, press **WX/MON**. The ☂ icon disappears.

NOAA Weather Radio Frequency List
Channel 1 162.550 MHz Channel 5 162.450 MHz
Channel 2 162.400 MHz Channel 6 162.500 MHz
Channel 3 162.475 MHz Channel 7 162.525 MHz
Channel 4 162.425 MHz

SPECIFICATIONS

Channels	15 GMRS/7 FRS/7 Weather
Sub Codes	38 Sub-Audible Tones 83 DCS Codes
Operating Frequency	
GMRS/FRS:	462.5500 - 467.7125 MHz
WX:	162.4000 - 162.5500 MHz
Power Source	NiMH Battery Pack (BT-1028 or BP-1028) or 3 AAA Alkaline Batteries
Range	Channel 1-7 up to 30 miles Channel 8-14 up to 5 miles Channel 15-22 up to 30 miles
Battery Life	10 Hours typ. - NiMH Battery Pack (5/5/90 duty cycle)

Frequency Chart

Ch.	Freq.	Cross Ref.	Ch.	Freq.	Cross Ref.
1	462.5625	FRS & GMRS 1	12	467.6625	FRS 12
2	462.5875	FRS & GMRS 2	13	467.6875	FRS 13
3	462.6125	FRS & GMRS 3	14	467.7125	FRS 14
4	462.6375	FRS & GMRS 4	15	462.5500	GMRS 11
5	462.6625	FRS & GMRS 5	16	462.5750	GMRS 8
6	462.6875	FRS & GMRS 6	17	462.6000	GMRS 12
7	462.7125	FRS & GMRS 7	18	462.6250	GMRS 9
8	467.5625	FRS 8	19	462.6500	GMRS 13
9	467.5875	FRS 9	20	462.6750	GMRS 10
10	467.6125	FRS 10	21	462.7000	GMRS 14
11	467.6375	FRS 11	22	462.7250	GMRS 15

CTCSS Chart (Hz)

Code	Freq.	Code	Freq.
oF	OFF	20	131.8
1	67.0	21	136.5
2	71.9	22	141.3
3	74.4	23	146.2
4	77.0	24	151.4
5	79.7	25	156.7
6	82.5	26	162.2
7	85.4	27	167.9
8	88.5	28	173.8
9	91.5	29	179.9
10	94.8	30	186.2
11	97.4	31	192.8
12	100.0	32	203.5
13	103.5	33	210.7
14	107.2	34	218.1
15	110.9	35	225.7
16	114.8	36	233.6
17	118.8	37	241.8
18	123.0	38	250.3
19	127.3		

DCS Code List

Tone	Octal	Tone	Octal	Tone	Octal
No.	Code	No.	Code	No.	Code
39	023	67	174	95	445
40	025	68	205	96	464
41	026	69	223	97	465
42	031	70	226	98	466
43	032	71	243	99	503
44	043	72	244	100	506
45	047	73	245	101	516
46	051	74	251	102	532
47	054	75	261	103	546
48	065	76	263	104	565
49	071	77	265	105	606
50	072	78	271	106	612
51	073	79	306	107	624
52	074	80	311	108	627
53	114	81	315	109	631
54	115	82	331	110	632
55	116	83	343	111	654
56	125	84	346	112	662
57	131	85	351	113	664
58	132	86	364	114	703
59	134	87	365	115	712
60	143	88	371	116	723
61	152	89	411	117	731
62	155	90	412	118	732
63	156	91	413	119	734
64	162	92	423	120	743
65	165	93	431	121	754
66	172	94	432		

RBRC INFORMATION

As part of our commitment to protect the environment and conserve natural resources, Uniden voluntarily participates in an RBRC® industry program to collect and recycle used Ni-MH batteries within the US. Please call 1-800-8-BATTERY for information on Ni-MH battery recycling in your area. (RBRC® is a registered trademark of the Rechargeable Battery Recycling Corporation.)



REGULATORY INFORMATION

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:
(1) This device may not cause harmful interference.
(2) This device must accept any interference received, including interference that may cause undesired operation.

Important: Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate this device. Your radio is set up to transmit a regulated signal on an assigned frequency. It is against the law to alter or adjust the settings inside the radio to exceed those limitations. Any adjustments to your radio must be made by qualified technicians.

To be safe and sure:

- Never open your radio's case.
- Never change or replace anything in your radio except the batteries.

Your radio might cause TV or radio interference even when it is operating properly. To determine whether your radio is causing the interference, turn it off. If the interference goes away, your radio is causing it. Try to eliminate the interference by moving your radio away from the receiver. If you cannot eliminate the interference, the FCC requires that you stop using the radio.

Hazardous Environments: Do not operate the radio in hazardous environments. Explosion or fire may result. Do not operate the radio near unshielded electrical blasting caps. Under certain conditions, radios can interfere with blasting operations and may cause an explosion. Turn your radio OFF to prevent accidental transmission when in a blasting area or in areas posted: "Turn off two-way radio." Construction crews often use remote control RF devices to set

off explosives.
Care and Safety: To clean the radio, use a soft cloth dampened with water. Do not use cleaners or solvents because they can harm the body of the unit and leak inside, causing permanent damage. Use a dry, lint-free cloth to clean the battery contacts. Do not submerge the unit in water. If the unit gets wet, turn it off and remove the batteries immediately. Dry the battery compartment with a soft cloth to minimize potential water damage. Leave the battery compartment cover off overnight to ensure complete drying. Do not use the radio until the unit is completely dry.

RF EXPOSURE INFORMATION

WARNING! Read this information before using the radio. In August 1996 the Federal Communications Commission (FCC) of the United States with its action in Report and Order FCC 96-326 adopted an updated safety standard for human exposure to radio frequency electromagnetic energy emitted by FCC regulated transmitters.

Those guidelines are consistent with the safety standard previously set by both U.S. and international standards bodies. The design of the radio complies with the FCC guidelines and these international standards.

Never allow children to operate the radio without adult supervision and the knowledge of the following guidelines.

WARNING! It is up to the user to properly operate this radio transmitter to insure safe operation. Please adhere to the following:

Use only the supplied or an approved antenna. Unauthorized antennas, modifications, or attachments could impair call quality, damage the radio, or result in violation of FCC regulations. Do not use the radio with a damaged antenna. If a damaged antenna comes into contact with the skin, a minor burn may result. Please contact your local dealer for a replacement antenna.

Hand-held Operation (Held-to-Face)

This device was evaluated for typical hand-held (held-to-face) operations with a 1 inch spacing from the front of the radio. For hand-held operation, the radio should be held 1 inch from the user's face in order to comply with FCC RF exposure requirements.

Body-worn Operation

This device was evaluated for body-worn operations with the supplied belt-clip accessory. (All necessary accessories are included in the package; any

additional or optional accessories are not required for compliance with the guidelines.) Third party accessories (unless approved by the manufacturer) should be avoided as these might not comply with FCC RF exposure guidelines.

For more information about RF exposure, please visit the FCC web site at www.fcc.gov.

THREE YEAR LIMITED WARRANTY

Important: Evidence of original purchase is required for warranty service.
WARRANTOR: UNIDEN AMERICA CORPORATION ("Uniden")
ELEMENTS OF WARRANTY: Uniden warrants, for three years, to the original retail owner, this Uniden Product to be free from defects in materials and craftsmanship with only the limitations or exclusions set out below.
WARRANTY DURATION: This warranty to the original user shall terminate and be of no further effect 36 months after the date of original retail sale. The warranty is invalid if the Product is: (A) damaged or not maintained as reasonable or necessary, (B) modified, altered, or used as part of any conversion kits, sub-assemblies, or any configurations not sold by Uniden, (C) improperly installed, (D) serviced or repaired by someone other than an authorized Uniden service center for a defect or malfunction covered by this warranty, (E) used in any conjunction with equipment or parts or as part of any system not manufactured by Uniden, or (F) installed or programmed by anyone other than as detailed by the owner's manual for this product.

STATEMENT OF REMEDY: In the event that the product does not conform to this warranty at any time while this warranty is in effect, warrantor will either, at its option, repair or replace the defective unit and return it to you without charge for parts, service, or any other cost (except shipping and handling) incurred by warrantor or its representatives in connection with the performance of this warranty. Warrantor, at its option, may replace the unit with a new or refurbished unit. **THE LIMITED WARRANTY SET FORTH ABOVE IS THE SOLE AND ENTIRE WARRANTY PERTAINING TO THE PRODUCT AND IS IN LIEU OF AND EXCLUDES ALL OTHER WARRANTIES OF ANY NATURE WHATSOEVER, WHETHER EXPRESS, IMPLIED OR ARISING BY OPERATION OF LAW, INCLUDING, BUT NOT LIMITED TO ANY IMPLIED WARRANTIES OF MERCHANTABILITY OR FITNESS FOR A**

PARTICULAR PURPOSE.THIS WARRANTY DOES NOT COVER OR PROVIDE FOR THE REIMBURSEMENT OVERPAYMENT OF INCIDENTAL OR CONSEQUENTIAL DAMAGES. Some states do not allow this exclusion or limitation of incidental or consequential damages so the above limitation or exclusion may not apply to you. **LEGAL REMEDIES:** This warranty gives you specific legal rights, and you may also have other rights which vary from state to state. This warranty is void outside the United States of America and Canada. **PROCEDURE FOR OBTAINING PERFORMANCE OF WARRANTY:** If, after following the instructions in the owner's manual you are certain that the Product is defective, pack the Product carefully (preferably in its original packaging). Disconnect the battery from the Product and separately secure the battery in its own separate packaging within the shipping carton. The Product should include all parts and accessories originally packaged with the Product. Include evidence of original purchase and a note describing the defect that has caused you to return it.The Product should be shipped freight prepaid, by traceable means, to warrantor at:

Uniden America Service
4700 Amon Carter Blvd. Fort Worth, TX 76155
(800) 297-1023 during regular business hours (CST)
(See www.uniden.com for current hours of operation.)

