

Low Voltage 400mA LDO Regulator

NO.EA-179-120404

OUTLINE

The RP105x Series are 400mA output type CMOS-based voltage regulator ICs with capability of low input voltage (Min. 0.9V) and low output voltage (Min. 0.6V). These ICs are remarkably improved the performance at low input voltage compared with conventional low voltage LDOs, and two power supply voltage type. (Another power source, V_{BIAS} pin voltage must be Min. 2.4V). Each of these ICs consists of a voltage reference unit, an error amplifier, resistor-net for voltage setting, a current limit circuit to avoid the destruction, a UVLO circuit with monitoring input voltage, and so on.

The RP105x Series have the ultra low on resistance output driver, the on resistance is Typ. 0.4Ω ($V_{OUT}=0.8V$, $I_{OUT}=300mA$). The built-in driver is Nch MOSFET, thus the load transient response is excellent, (under the condition of the current between 1mA and 400mA, $t_r=0.5\mu s$, the undershoot level is approximately 50mV).

The output voltage of these ICs is fixed with high accuracy. Since the packages for these ICs are DFN(PLP)1212-6, SOT-23-5 and SC-88A (**Limited**) therefore high density mounting of the ICs on boards is possible.


FEATURES

- Supply Current Typ. $28\mu A$
- Supply Current (Standby Mode) Typ. $0.1\mu A$
- Ripple Rejection Typ. $80dB$ ($f=1kHz$, V_{IN} Ripple)
Typ. $50dB$ ($f=1kHz$, V_{BIAS} Ripple)
- Output Voltage Range $0.6V$ to $1.5V$ ($0.1V$ steps)
(For other voltages, please refer to MARK INFORMATIONS.)
- Input Voltage Range (V_{BIAS}) $2.4V$ to $5.25V$ ($V_{OUT} < 0.8V$)
Set $V_{OUT}+1.6V$ to $5.25V$ ($V_{OUT} \geq 0.8V$)
- Input Voltage Range (V_{IN}) $0.9V$ to V_{BIAS} ($V_{OUT} < 0.8V$)
Set $V_{OUT}+0.1V$ to V_{BIAS} ($V_{OUT} \geq 0.8V$)
- Output Voltage Accuracy Typ. $\pm 15mV$ ($T_{opt}=25^\circ C$)
- Temperature-Drift Coefficient of Output Voltage Typ. $\pm 50ppm/\text{ }^\circ C$
- Dropout Voltage Typ. $180mV$ ($I_{OUT}=400mA$, $V_{OUT}=1.5V$, $V_{BIAS}=3.6V$)
- Line Regulation Typ. $0.02\%/\text{V}$
- Packages DFN(PLP)1212-6, SC-88A (**Limited**), SOT-23-5
- Built-in Fold Back Protection Circuit Typ. $120mA$ (Current at short mode)
- Ceramic capacitors are recommended $C_{BIAS}=C_{IN}=1.0\mu F$ or more, $C_{OUT}=2.2\mu F$ or more

APPLICATIONS

- Power source for battery-powered equipment.
- Power source for electrical appliances such as cameras, VCRs and camcorders.
- Power source for portable communication equipment.

BLOCK DIAGRAMS



SELECTION GUIDE

The output voltage, auto discharge function, package, and the taping type, etc. for the ICs can be selected at the user's request.

Product Name	Package	Quantity per Reel	Pb Free	Halogen Free
RP105Kxx1*-TR	DFN(PLP)1212-6	5,000 pcs	Yes	Yes
RP105Qxx2*-TR-FE	SC-88A (Limited)	3,000 pcs	Yes	Yes
RP105Nxx1*-TR-FE	SOT-23-5	3,000 pcs	Yes	Yes


xx: The output voltage can be designated in the range from 0.6V(06) to 1.5V(15) in 0.1V steps.
(For other voltages, please refer to MARK INFORMATIONS.)

* : CE pin polarity and auto discharge function at off state are options as follows.
(B) "H" active, without auto discharge function at off state
(D) "H" active, with auto discharge function at off state

The products scheduled to be discontinued (be sold to limited customer) : "Limited"

These products will be discontinued in the future. You can not select these products newly.
We will provide these products to the customer who has been using or has ordered them before.
But we recommend changing to other products as soon as possible.

PIN CONFIGURATIONS



PIN DESCRIPTIONS

• DFN(PLP)1212-6

Pin No	Symbol	Pin Description
1	V_{BIAS}	Input Pin 1
2	GND	Ground Pin
3	CE	Chip Enable Pin ("H" Active)
4	V_{IN}	Input Pin 2
5	NC	No Connection
6	V_{OUT}	Output Pin

• SC-88A (**Limited**)

Pin No	Symbol	Pin Description
1	V_{BIAS}	Input Pin 1
2	GND	Ground Pin
3	V_{OUT}	Output Pin
4	V_{IN}	Input Pin 2
5	CE	Chip Enable Pin ("H" Active)

• SOT-23-5

Pin No	Symbol	Pin Description
1	V_{IN}	Input Pin 2
2	GND	Ground Pin
3	CE	Chip Enable Pin ("H" Active)
4	V_{BIAS}	Input Pin 1
5	V_{OUT}	Output Pin

ABSOLUTE MAXIMUM RATINGS

Symbol	Item	Rating	Unit
V_{BIAS}	Input Voltage	6.0	V
V_{IN}	Input Voltage (for Driver)	-0.3 to $V_{BIAS}+0.3$	V
V_{CE}	Input Voltage (CE Pin)	6.0	V
V_{OUT}	Output Voltage	-0.3 to $V_{IN}+0.3$	V
I_{OUT}	Output Current	500	mA
P_D	Power Dissipation (DFN(PLP)1212-6) *	400	mW
	Power Dissipation (SC-88A) * (Limited)	380	
	Power Dissipation (SOT-23-5) *	420	
T_{opt}	Operating Temperature Range	-40 to 85	°C
T_{stg}	Storage Temperature Range	-55 to 125	°C

*) For Power Dissipation, please refer to PACKAGE INFORMATION.

ABSOLUTE MAXIMUM RATINGS

Electronic and mechanical stress momentarily exceeded absolute maximum ratings may cause the permanent damages and may degrade the life time and safety for both device and system using the device in the field. The functional operation at or over these absolute maximum ratings is not assured.

ELECTRICAL CHARACTERISTICS

$V_{BIAS}=V_{CE}=3.6V$, $V_{IN}=\text{Set } V_{OUT}+0.5V$, $I_{OUT}=1mA$, $C_{BIAS}=C_{IN}=1.0\mu F$, $C_{OUT}=2.2\mu F$, unless otherwise noted.

The specification in is checked and guaranteed by design engineering at $-40^{\circ}\text{C} \leq T_{opt} \leq 85^{\circ}\text{C}$.

• RP105x

Symbol	Item	Conditions	Min.	Typ.	Max.	Unit	T _{opt} =25°C
V _{OUT}	Output Voltage	T _{opt} =25°C	Set V _{OUT} -15mV		Set V _{OUT} +15mV	V	
		-40°C ≤ T _{opt} ≤ 85°C	Set V _{OUT} -20mV		Set V _{OUT} +20mV	V	
I _{OUT}	Output Current		400			mA	
ΔV _{OUT} /ΔI _{OUT}	Load Regulation	1mA ≤ I _{OUT} ≤ 400mA		30	50	mV	
V _{DIF}	Dropout Voltage	Please refer to following data					
I _{SS}	Supply Current	I _{OUT} =0mA		28	40	μA	
I _{standby}	Standby Current	V _{CE} =0V		0.1	3.0	μA	
ΔV _{OUT} /ΔV _{IN}	Line Regulation	2.4V ≤ V _{BIAS} ≤ 5.0V		0.02	0.1	%/V	
		Set V _{OUT} +0.3V ≤ V _{IN} ≤ 2.4V		0.02	0.1		
RR	Ripple Rejection	I _{OUT} =30mA, f=1kHz V _{IN} Ripple 0.2Vp-p		80			dB
		I _{OUT} =30mA, f=1kHz V _{BIAS} Ripple 0.2Vp-p		50			
V _{BIAS}	Input Voltage*	V _{OUT} < 0.8V	2.4		5.25	V	
		V _{OUT} ≥ 0.8V	Set V _{OUT} +1.6		5.25		
V _{IN}	Input Voltage (for Driver) *	V _{OUT} < 0.8V	0.9		V _{BIAS}	V	
		V _{OUT} ≥ 0.8V	Set V _{OUT} +0.1		V _{BIAS}		
ΔV _{OUT} /ΔT _{opt}	Output Voltage Temperature Coefficient	-40°C ≤ T _{opt} ≤ 85°C		±50		ppm/°C	
I _{SC}	Short Current Limit	V _{OUT} =0V		120		mA	
I _{CEPD}	CE Pull-down Constant Current			1.0		μA	
V _{CEH}	CE Input Voltage "H"		0.8			V	
V _{CEL}	CE Input Voltage "L"				0.3	V	
V _{IN_UVLO}	V _{IN} Under Voltage Lock Out	I _{OUT} =1.0μA		Set V _{OUT} +50mV	Set V _{OUT} +100mV	V	
t _{delay}	Detector Delay Time			100		μs	
en	Output Noise	BM=10Hz to 100kHz I _{OUT} =30mA, Set V _{OUT} =0.6V		70		μVrms	
R _{LOW}	Nch On Resistance For auto discharge (only D version)	V _{BIAS} =3.6V, V _{CE} ="L"		50		Ω	

*) If Input Voltage range is between 5.25V and 5.50V, the total operational time must be within 500hrs.

All of units are tested and specified under load conditions such that $T_j \approx T_{opt}=25^{\circ}\text{C}$ except for Output Noise, Ripple Rejection, Output Voltage Temperature Coefficient.

RP105x

• Dropout Voltage

Set V _{OUT}	V _{BIA} S	V _{GS}	V _{DIF} (I _{OUT} =300mA) (V)		V _{DIF} (I _{OUT} =400mA) (V)	
			Typ.	Max.	Typ.	Max.
0.6V	3.6V	3.0V	0.115	0.180	0.180	0.320
0.7V	3.6V	2.9V	0.120	0.190	0.180	0.320
0.8V	3.6V	2.8V	0.120	0.190	0.180	0.300
0.9V	3.6V	2.7V	0.120	0.190	0.180	0.300
1.0V	3.6V	2.6V	0.120	0.190	0.180	0.280
1.1V	3.6V	2.5V	0.130	0.200	0.180	0.280
1.2V	3.6V	2.4V	0.130	0.200	0.180	0.280
1.3V	3.6V	2.3V	0.130	0.200	0.180	0.260
1.4V	3.6V	2.2V	0.130	0.200	0.180	0.260
1.5V	3.6V	2.1V	0.130	0.200	0.180	0.260


• Dropout Voltage (V_{GS}(V), V_{DIF}(V), I_{OUT}=200mA)

T_{opt}=25°C

Set V _{OUT}	V _{BIA} S=2.5V		V _{BIA} S=3.0V		V _{BIA} S=3.3V		V _{BIA} S=3.6V		V _{BIA} S=4.2V		V _{BIA} S=5.0V	
	V _{GS} (V)	V _{DIF} (V)										
0.6V	1.9	0.094	2.4	0.093	2.7	0.093	3.0	0.092	3.6	0.092	4.4	0.091
0.7V	1.8	0.094	2.3	0.093	2.6	0.093	2.9	0.092	3.5	0.092	4.3	0.092
0.8V	1.7	0.098	2.2	0.093	2.5	0.093	2.8	0.092	3.4	0.092	4.2	0.092
0.9V	1.6	0.098	2.1	0.094	2.4	0.093	2.7	0.092	3.3	0.092	4.1	0.092
1.0V			2.0	0.094	2.3	0.093	2.6	0.092	3.2	0.092	4.0	0.092
1.1V			1.9	0.096	2.2	0.094	2.5	0.094	3.1	0.093	3.9	0.093
1.2V			1.8	0.098	2.1	0.096	2.4	0.095	3.0	0.095	3.8	0.094
1.3V			1.7	0.098	2.0	0.096	2.3	0.095	2.9	0.095	3.7	0.095
1.4V			1.6	0.098	1.9	0.096	2.2	0.095	2.8	0.095	3.6	0.095
1.5V					1.8	0.096	2.1	0.095	2.7	0.095	3.5	0.095

The specification in  is checked and guaranteed by design engineering at $-40^{\circ}\text{C} \leq \text{T}_{\text{opt}} \leq 85^{\circ}\text{C}$.

All of units are tested and specified under load conditions such that $\text{T}_j \approx \text{T}_{\text{opt}} = 25^{\circ}\text{C}$ except for Output Noise, Ripple Rejection and Output Voltage Temperature Coefficient items.




V_{BIA}S pin voltage must be equal or more than Set V_{OUT}+1.6V.

RECOMMENDED OPERATING CONDITIONS (ELECTRICAL CHARACTERISTICS)

All of electronic equipment should be designed that the mounted semiconductor devices operate within the recommended operating conditions. The semiconductor devices cannot operate normally over the recommended operating conditions, even if when they are used over such conditions by momentary electronic noise or surge. And the semiconductor devices may receive serious damage when they continue to operate over the recommended operating conditions.

TYPICAL APPLICATION



TECHNICAL NOTES

When using these ICs, consider the following points:

Phase Compensation

In these ICs, phase compensation is made for securing stable operation even if the load current is varied. For this purpose, use a capacitor for C_{OUT} with the capacity of equal or more than 2.2 μ F.

(Note: If tantalum capacitors are connected as C_{OUT} , and if the equivalent series resistor (ESR) value is large, the operation might be unstable. Because of this, test these ICs with as same external components as ones to be used on the PCB.)

PCB Layout


Make V_{BIAS} , V_{IN} , and GND lines sufficient. If their impedance is high, noise pickup or unstable operation may result. Connect a capacitor with a capacitance value as much as 1.0 μ F or more between V_{BIAS} pin and GND pin, between V_{IN} pin and GND pin, and as close as possible to the pins.

Set external components, especially the output capacitor, as close as possible to the ICs, and make wiring as short as possible. V_{IN} source is supposed to be the output of the DC/DC converter. The value should be equal or lower than V_{BIAS} voltage.


TYPICAL CHARACTERISTICS

1) Output Voltage vs. Output Current ($C_{BIAS}=1.0\mu F$, $C_{IN}=C_{OUT}=2.2\mu F$, $T_{opt}=25^{\circ}C$)


RP105x06xx




RP105x06xx




RP105x06xx




RP105x10xx






RP105x10xx





RP105x10xx















2) Output Voltage vs. Input Voltage ($C_{BIAS}=1.0\mu F$, $C_{IN}=C_{OUT}=2.2\mu F$, $T_{opt}=25^{\circ}C$)





RP105x















3) Supply Current vs. Input Voltage ($C_{BIAS}=C_{IN}=C_{OUT}=\text{none}$, $T_{opt}=25^{\circ}\text{C}$)





RP105x









4) Output Voltage vs. Temperature ($C_{BIAS}=1.0\mu F$, $C_{IN}=C_{OUT}=2.2\mu F$, $I_{OUT}=1mA$, $V_{BIAS}=3.6V$)




RP105x




5) Supply Current vs. Temperature ($C_{BIAS}=C_{IN}=C_{OUT}=\text{none}$, $V_{BIAS}=3.6V$)



6) Dropout Voltage vs. Output Current ($C_{BIAS}=1.0\mu F$, $C_{IN}=C_{OUT}=2.2\mu F$)




7) Dropout Voltage vs. Set Output Voltage








RP105x

8) Ripple Rejection vs. Input Bias Voltage ($C_{OUT}=2.2\mu F$, Ripple=0.2Vp-p, $T_{opt}=25^{\circ}C$)





9) Ripple Rejection vs. Frequency ($V_{BIAS}=3.6V$, $C_{OUT}=2.2\mu F$, $T_{opt}=25^{\circ}C$)











10) Input Transient Response ($I_{OUT}=30mA$, $C_{OUT}=1.0\mu F$, $tr=tf=5\mu s$, $T_{opt}=25^{\circ}C$)







RP105x





11) Load Transient Response ($V_{BIAS}=3.6V$, $C_{BIAS}=1.0\mu F$, $C_{IN}=C_{OUT}=2.2\mu F$, $tr=tf=0.5\mu s$, $T_{opt}=25^{\circ}C$)












12) Turn On Speed with CE pin ($V_{BIAS}=3.6V$, $C_{BIAS}=1.0\mu F$, $C_{IN}=C_{OUT}=2.2\mu F$, $T_{opt}=25^{\circ}C$)







RP105x










13) Turn Off Speed with CE Pin ($V_{BIAS}=3.6V$, $C_{BIAS}=1.0\mu F$, $C_{IN}=C_{OUT}=2.2\mu F$, $T_{opt}=25^{\circ}C$)




RP105x




14) Turn On Transient with V_{IN} pin ($V_{BIAS}=3.6V$, $C_{BIAS}=1.0\mu F$, $C_{IN}=none$, $C_{OUT}=2.2\mu F$, $T_{opt}=25^{\circ}C$)


RP105x06xx




RP105x06xx




RP105x10xx




RP105x10xx



RP105x15xx



RP105x15xx



ESR vs. Output Current

When using these ICs, consider the following points:

The relations between I_{OUT} (Output Current) and ESR of an output capacitor are shown below.

The conditions when the white noise level is under $40\mu V$ (Avg.) are marked as the hatched area in the graph.

Measurement conditions


Frequency Band: 10Hz to 2MHz

Temperature : $-40^{\circ}C$ to $85^{\circ}C$

Hatched Area : Noise level is under $40\mu V$ (Avg.)

C_{BIAS}, C_{IN} : $1.0\mu F$

C_{OUT} : $2.2\mu F$





1. The products and the product specifications described in this document are subject to change or discontinuation of production without notice for reasons such as improvement. Therefore, before deciding to use the products, please refer to Ricoh sales representatives for the latest information thereon.
2. The materials in this document may not be copied or otherwise reproduced in whole or in part without prior written consent of Ricoh.
3. Please be sure to take any necessary formalities under relevant laws or regulations before exporting or otherwise taking out of your country the products or the technical information described herein.
4. The technical information described in this document shows typical characteristics of and example application circuits for the products. The release of such information is not to be construed as a warranty of or a grant of license under Ricoh's or any third party's intellectual property rights or any other rights.
5. The products listed in this document are intended and designed for use as general electronic components in standard applications (office equipment, telecommunication equipment, measuring instruments, consumer electronic products, amusement equipment etc.). Those customers intending to use a product in an application requiring extreme quality and reliability, for example, in a highly specific application where the failure or misoperation of the product could result in human injury or death (aircraft, spacevehicle, nuclear reactor control system, traffic control system, automotive and transportation equipment, combustion equipment, safety devices, life support system etc.) should first contact us.
6. We are making our continuous effort to improve the quality and reliability of our products, but semiconductor products are likely to fail with certain probability. In order to prevent any injury to persons or damages to property resulting from such failure, customers should be careful enough to incorporate safety measures in their design, such as redundancy feature, firecontainment feature and fail-safe feature. We do not assume any liability or responsibility for any loss or damage arising from misuse or inappropriate use of the products.
7. Anti-radiation design is not implemented in the products described in this document.
8. Please contact Ricoh sales representatives should you have any questions or comments concerning the products or the technical information.

RICOH COMPANY, LTD. Electronic Devices Company



■Ricoh presented with the Japan Management Quality Award for 1999.
Ricoh continually strives to promote customer satisfaction, and shares the achievements of its management quality improvement program with people and society.



■Ricoh awarded ISO 14001 certification.
The Ricoh Group was awarded ISO 14001 certification, which is an international standard for environmental management systems, at both its domestic and overseas production facilities. Our current aim is to obtain ISO 14001 certification for all of our business offices.

<http://www.ricoh.com/LSI/>

RICOH COMPANY, LTD.

Electronic Devices Company

● Higashi-Shinagawa Office (International Sales)
3-32-3, Higashi-Shinagawa, Shinagawa-ku, Tokyo 140-8655, Japan
Phone: +81-3-5479-2857 Fax: +81-3-5479-0502

RICOH EUROPE (NETHERLANDS) B.V.

● Semiconductor Support Centre
Prof. W.H.Keesomlaan 1, 1183 DL Amstelveen, The Netherlands
P.O.Box 114, 1180 AC Amstelveen
Phone: +31-20-5474-309 Fax: +31-20-5474-791

RICOH ELECTRONIC DEVICES KOREA Co., Ltd.

11 floor, Haesung 1 building, 942, Daechidong, Gangnamgu, Seoul, Korea
Phone: +82-2-2135-5700 Fax: +82-2-2135-5705

Room403, No.2 Building, 690#B1 Bo Road, Pu Dong New district, Shanghai 201203,
People's Republic of China
Phone: +86-21-5027-3200 Fax: +86-21-5027-3299

RICOH COMPANY, LTD.
Electronic Devices Company

● Taipei office
Room109, 10F-1, No.51, Hengyang Rd., Taipei City, Taiwan (R.O.C.)
Phone: +886-2-2313-1621/1622 Fax: +886-2-2313-1623



Ricoh completed the organization of the Lead-free production for all of our products. After Apr. 1, 2006, we will ship out the lead free products only. Thus, all products that will be shipped from now on comply with RoHS Directive.