

## 300mA Dual LDO with VD

NO. EA-132-111020

### OUTLINE

The RP151 Series are CMOS-based dual voltage regulator (LDO) ICs equipped with a voltage detector (VD).

LDO function has features of high output voltage accuracy, low supply current, low dropout, and high ripple rejection. Each of these voltage regulator ICs consists of a voltage reference unit, an error amplifier, resistors for setting Output Voltage, a current limit circuit, and a chip enable circuit.

These ICs perform with low dropout voltage due to built-in transistor with low ON resistance, and a chip enable function prolongs the battery life of each system. The line transient response and load transient response of the RP151 Series are excellent, thus these ICs are very suitable for the power supply for hand-held communication equipment.

The output of built-in voltage detector is Nch open drain type.

The output voltage of these ICs is internally fixed with high accuracy (1%). Since the packages for these ICs are DFN(PLP)2020-8 package, dual LDO regulators and VD are included in each packages, high density mounting of the ICs on boards is possible.

### FEATURES


- Supply Current ..... Typ.  $24\mu A \times 2$  (VR1&VR2)
- Standby Current ..... Typ.  $0.1\mu A \times 2$
- Dropout Voltage ..... Typ.  $0.21V$  ( $I_{OUT}=300mA$ ,  $V_{OUT}=2.8V$ )  
Typ.  $0.24V$  ( $I_{OUT}=300mA$ ,  $V_{OUT}=2.5V$ )
- Ripple Rejection ..... Typ.  $80dB$  ( $f=1kHz$ )
- Temperature-Drift Coefficient of Output Voltage ..... Typ.  $\pm 30ppm/^{\circ}C$
- Line Regulation ..... Typ.  $0.02\%/V$
- Output Voltage Accuracy .....  $\pm 1.0\%$
- Input Voltage Range .....  $2.5V$  to  $5.25V$
- Output Voltage Range .....  $1.5V$  to  $3.3V$  (0.1V steps)  
(For details, please refer to MARK INFORMATIONS.)
- Package ..... DFN(PLP)2020-8
- Built-in Fold Back Protection Circuit ..... Typ.  $50mA$
- Built-in Auto Discharge function ..... B Version
- Ceramic capacitors are recommended to be used with this IC ...  $C_{IN}=C_{OUT}=1.0\mu F$  or more
- Detector Threshord ..... Set  $V_{OUT2} \times 92\%$
- Output Delay Time for release ..... Typ.  $10ms$  ( $C_D=0.01\mu F$ )

### APPLICATIONS


- Power source for portable communication equipment.
- Power source for electrical appliances such as cameras, VCRs and camcorders.
- Power source for battery-powered equipment.

**BLOCK DIAGRAMS**

RP151KxxxA



RP151KxxxB




## SELECTION GUIDE

The output voltage, and auto discharge function, etc. for the ICs can be selected at the user's request.

Product Name	Package	Quantity per Reel	Pb Free	Halogen Free
RP151Kxxx*-TR	DFN(PLP)2020-8	5,000 pcs	Yes	Yes
xxx: The combination of output voltage for each channel can be designated by serial numbers. (from 001) The output voltage for each channel can be set in the range from 1.5V to 3.3V in 0.1V steps. (For details, please refer to MARK INFORMATIONS.)				
* : Designation of Mask Option: (A) without auto-discharge function at off state (B) with auto-discharge function at off state				

## PIN CONFIGURATIONS

### ● DFN(PLP)2020-8



## PIN DESCRIPTIONS

### ● DFN(PLP)2020-8

Pin No.	Symbol	Description
1	CE1	Chip Enable Pin 1 ("H" Active)
2	GND	Ground Pin
3	CE2	Chip Enable Pin 2 ("H" Active)
4	C <sub>D</sub>	Delay Select Input Pin
5	D <sub>OUT</sub>	VD Output Pin
6	V <sub>OUT2</sub>	Output Pin 2
7	V <sub>DD</sub>	Input Pin
8	V <sub>OUT1</sub>	Output Pin 1

\*) Tab is GND level. (They are connected to the reverse side of this IC.)

The tab is better to be connected to the GND, but leaving it open is also acceptable.

## ABSOLUTE MAXIMUM RATINGS

Symbol	Item	Rating	Unit
$V_{IN}$	Input Voltage	6.0	V
$V_{CE}$	Input Voltage (CE Pin)	6.0	V
$V_{OUT}$	Output Voltage	-0.3 to $V_{IN}+0.3$	V
$D_{OUT}$	Output Voltage (VD Output Pin Voltage)	-0.3 to 6.0	V
$I_{OUT1}$	Output Current 1	400	mA
$I_{OUT2}$	Output Current 2	400	mA
$P_D$	Power Dissipation (DFN(PLP)2020-8)*	880	mW
$T_{opt}$	Operating Temperature Range	-40 to 85	°C
$T_{stg}$	Storage Temperature Range	-55 to 125	°C

\*) For Power Dissipation, please refer to PACKAGE INFORMATION.

### ABSOLUTE MAXIMUM RATINGS

Electronic and mechanical stress momentarily exceeded absolute maximum ratings may cause the permanent damages and may degrade the life time and safety for both device and system using the device in the field.

The functional operation at or over these absolute maximum ratings is not assured.

## ELECTRICAL CHARACTERISTICS

- RP151KxxxA/B

$V_{IN}$ =Set  $V_{OUT}+1V$  for higher output of the regulator pair,  
 $I_{OUT}=1mA$ ,  $C_{IN}=C_{OUT}=1\mu F$ , unless otherwise noted.

VR							$T_{opt}=25^{\circ}C$
Symbol	Item	Conditions		Min.	Typ.	Max.	Unit
$V_{OUT}$	Output Voltage	$V_{IN}$ =Set $V_{OUT}+1V$ $I_{OUT}=1mA$	$V_{OUT} > 2.0V$	$\times 0.99$		$\times 1.01$	V
			$V_{OUT} \leq 2.0V$	-20		20	mV
$I_{OUT}$	Output Current			300			mA
$\Delta V_{OUT}/\Delta I_{OUT}$	Load Regulation	$1mA \leq I_{OUT} \leq 200mA$			20	40	mV
$V_{DIF}$	Dropout Voltage	$I_{OUT}=300mA$	$1.5V \leq \text{Set } V_{OUT} < 1.7V$		0.40	1.00	V
			$1.7V \leq \text{Set } V_{OUT} < 2.0V$		0.34	0.80	
			$2.0V \leq \text{Set } V_{OUT} < 2.5V$		0.29	0.50	
			$2.5V \leq \text{Set } V_{OUT} < 2.8V$		0.24	0.38	
			$2.8V \leq \text{Set } V_{OUT} \leq 3.3V$		0.21	0.34	
$I_{SS}$	Supply Current	$I_{OUT}=0mA$			24	33	$\mu A$
$I_{standby}$	Standby Current	$V_{CE}=0V$			0.1	3.0	$\mu A$
$\Delta V_{OUT}/\Delta V_{IN}$	Line Regulation	$\text{Set } V_{OUT}+0.5V \leq V_{IN} \leq 5.0V$ (In case that $V_{OUT} \leq 2.0V$ , $2.5V \leq V_{IN} \leq 5.0V$ )			0.02	0.10	%/V
RR	Ripple Rejection	$f=1kHz$ , Ripple $0.2Vp-p$ $V_{IN}=\text{Set } V_{OUT}+1V$ , $I_{OUT}=30mA$ (In case that $V_{OUT} \leq 2.0V$ , $V_{IN}=3V$ )			80		dB
$V_{IN}$	Input Voltage *			2.5		5.25	V
$\Delta V_{OUT}/\Delta T_{opt}$	Output Voltage Temperature Coefficient	$-40^{\circ}C \leq T_{opt} \leq 85^{\circ}C$			$\pm 30$		ppm/ $^{\circ}C$
$I_{SC}$	Short Current Limit	$V_{OUT}=0V$			50		mA
$I_{PD}$	CE Pull-down Current			0.05	0.3	0.6	$\mu A$
$V_{CEH}$	CE Input Voltage "H"				1.5		V
$V_{CEL}$	CE Input Voltage "L"					0.3	V
en	Output Noise	$BW=10Hz \text{ to } 100kHz$			30		$\mu V_{rms}$
$R_{LOW}$	Low Output Nch Tr. ON Resistance (B version only)	$V_{IN}=4.0V$ , $V_{CE}=0V$			30		$\Omega$

\*) The maximum Input Voltage of the ELECTRICAL CHARACTERISTICS is 5.25V. In case of exceeding this specification, the IC must be operated on condition that the Input Voltage is up to 5.5V and the total operating time is within 500hrs.

## RP151K

VD							Topt=25°C
Symbol	Item	Conditions	Min.	Typ.	Max.	Unit	
-V <sub>DET</sub>	Detector Threshold	% of nominal V <sub>OUT2</sub>	90	92		%	
+V <sub>DET</sub>	Released Voltage	% of nominal V <sub>OUT2</sub>		94	96	%	
V <sub>HYS</sub>	Detector Threshold Hysteresis	% of nominal V <sub>OUT2</sub>		2		%	
V <sub>OL</sub>	D <sub>OUT</sub> Output Voltage "L"	I <sub>L</sub> =0.25mA		0.02	0.1	V	
I <sub>DOUT</sub>	D <sub>OUT</sub> Output Leakage Current				1	µA	
t <sub>D</sub>	Reset Delay Time	C <sub>D</sub> =0.01µF		10		ms	
R <sub>D</sub>	Delay Circuit Resistance		0.96	1.35	1.63	MΩ	
V <sub>TCD</sub>	C <sub>D</sub> Pin Threshold Voltage	V <sub>DD</sub> =3.6V	1.7	1.9	2.1	V	

### RECOMMENDED OPERATING CONDITIONS (ELECTRICAL CHARACTERISTICS)

All of electronic equipment should be designed that the mounted semiconductor devices operate within the recommended operating conditions. The semiconductor devices cannot operate normally over the recommended operating conditions, even if when they are used over such conditions by momentary electronic noise or surge. And the semiconductor devices may receive serious damage when they continue to operate over the recommended operating conditions.

## TECHNICAL NOTES

When using these ICs, consider the following points:

### PCB Layout

Make  $V_{DD}$  and GND lines sufficient. If their impedance is high, noise pickup or unstable operation may result.

Connect a capacitor with a capacitance value as much as  $1.0\mu F$  or more as  $C_1$  between  $V_{DD}$  and GND pin, and as close as possible to the pins.

Set the output capacitors  $C_2$  and  $C_3$  for phase compensation, as close as possible to the ICs, and make wiring as short as possible.

$C_D$  external components, especially capacitor  $C_4$ , as close as possible to the ICs and make wiring as short as possible. (Refer to TYPICAL APPLICATION)

### Phase Compensation


In these ICs, phase compensation is made for securing stable operation even if the load current is varied.

For this purpose, connect capacitors with a capacitance value as much as  $1.0\mu F$  or more as  $C_2$  and  $C_3$  with good frequency characteristics and ESR (Equivalent Series Resistance) between  $V_{OUT}$  and GND pin, and as close as possible to the pins.

If you use a tantalum type capacitor and ESR value of the capacitor is large, output might be unstable. Evaluate your circuit with considering frequency characteristics.

Depending on the capacitor size, manufacturer, and part number, the bias characteristics and temperature characteristics are different. Evaluate the circuit with actual using capacitors.

## TYPICAL APPLICATIONS





(External Components)


External Capacitor; Ceramic Type	$C_1, C_2, C_3$
$1.0\mu F$	Kyocera CM05X5R105KD6AB
TDK	C1005JB0J105K
Murata	GRM155B31A105KE15

External Capacitor for delay time  $C_4$


Output delay time ( $t_D$ ) can be set accordance with the capacitance  $C_D$  of external capacitor as below.

$$t_D = 10^6 \times C_{D(S)}$$

**TEST CIRCUITS****Basic Test Circuit****Test Circuit for Supply Current**




Test Circuit for Ripple Rejection




Test Circuit for Load Transient Response





## TYPICAL CHARACTERISTICS






### 1) Output Voltage vs. Output Current ( $T_{opt}=25^{\circ}\text{C}$ )







### 2) Output Voltage vs. Input Voltage ( $T_{opt}=25^{\circ}\text{C}$ )




**3.3V(VR1/VR2)****3) Supply Current vs. Input Voltage ( $T_{opt}=25^{\circ}\text{C}$ )****1.5V(VR1/VR2)****2.5V(VR1/VR2)****3.3V(VR1/VR2)**

**4) Output Voltage vs. Temperature****1.5V(VR1/VR2)****2.5V(VR1/VR2)****3.3V(VR1/VR2)****5) Supply Current vs. Temperature****1.5V(VR1/VR2)****2.5V(VR1/VR2)**

**3.3V(VR1/VR2)****6) Dropout Voltage vs. Output Current****1.5V(VR1/VR2)****2.5V(VR1/VR2)****3.3V(VR1/VR2)**


**7) Dropout Voltage vs. VR\_VSET**

**VR1/VR2**




**8) Ripple Rejection vs. Input Bias (Input Ripple=0.5Vp-p, Topr=25°C)**


**2.5V(VR1)**




**2.5V(VR2)**





**2.5V(VR1)**







**2.5V(VR2)**







### 9) Ripple Rejection vs. Frequency (Ripple=0.5Vp-p)



**3.3V(VR1)**




**3.3V(VR2)**




#### 10) Input Transient Response ( $tr=tf=5\mu\text{s}$ , $T_{opt}=25^\circ\text{C}$ )


**1.5V(VR1)**




**1.5V(VR2)**















**2.5V(VR1)**






**2.5V(VR2)**






**3.3V(VR1)****3.3V(VR2)****11) Load Transient Response ( $tr=tf=500ns$ ,  $T_{opt}=25^{\circ}C$ )****1.5V(VR1)****1.5V(VR2)****1.5V(VR1)****1.5V(VR2)**

















### 12) Turn On Speed with CE pin ( $T_{opt}=25^{\circ}C$ )






**13) Turn Off Speed with CE pin ( $T_{opt}=25^{\circ}\text{C}$ )**


**1.5V(VR1/VR2)**




**1.5V(VR1/VR2)**




**1.5V(VR1/VR2)**




**2.5V(VR1/VR2)**




**2.5V(VR1/VR2)**








**2.5V(VR1/VR2)**









#### 14) Detector Threshold/Released Voltage vs. Temperature





**15) CD Pin Threshold Voltage vs. Temperature****16) Delay Circuit Resistance vs. Temperature**



### 17) Output Delay Time vs. External Capacitance



**18) Nch Driver Output Current vs. Input Voltage****19) Nch Driver Output Current vs.  $V_{DS}$** 

## ESR vs. Output Current

When using these ICs, consider the following points:

The relations between  $I_{OUT}$  (Output Current) and ESR of an output capacitor are shown below.

The conditions when the white noise level is under  $40\mu V$  (Avg.) are marked as the hatched area in the graph.


### Measurement conditions

$V_{IN} = \text{Set } V_{OUT} + 1V$


Frequency Band : 10Hz to 2MHz

Temperature :  $-40^{\circ}\text{C}$  to  $85^{\circ}\text{C}$

**1.5V (VR1/VR2)**



**3.3V (VR1/VR2)**





1. The products and the product specifications described in this document are subject to change or discontinuation of production without notice for reasons such as improvement. Therefore, before deciding to use the products, please refer to Ricoh sales representatives for the latest information thereon.
2. The materials in this document may not be copied or otherwise reproduced in whole or in part without prior written consent of Ricoh.
3. Please be sure to take any necessary formalities under relevant laws or regulations before exporting or otherwise taking out of your country the products or the technical information described herein.
4. The technical information described in this document shows typical characteristics of and example application circuits for the products. The release of such information is not to be construed as a warranty of or a grant of license under Ricoh's or any third party's intellectual property rights or any other rights.
5. The products listed in this document are intended and designed for use as general electronic components in standard applications (office equipment, telecommunication equipment, measuring instruments, consumer electronic products, amusement equipment etc.). Those customers intending to use a product in an application requiring extreme quality and reliability, for example, in a highly specific application where the failure or misoperation of the product could result in human injury or death (aircraft, spacevehicle, nuclear reactor control system, traffic control system, automotive and transportation equipment, combustion equipment, safety devices, life support system etc.) should first contact us.
6. We are making our continuous effort to improve the quality and reliability of our products, but semiconductor products are likely to fail with certain probability. In order to prevent any injury to persons or damages to property resulting from such failure, customers should be careful enough to incorporate safety measures in their design, such as redundancy feature, firecontainment feature and fail-safe feature. We do not assume any liability or responsibility for any loss or damage arising from misuse or inappropriate use of the products.
7. Anti-radiation design is not implemented in the products described in this document.
8. Please contact Ricoh sales representatives should you have any questions or comments concerning the products or the technical information.

## RICOH COMPANY., LTD. Electronic Devices Company



■Ricoh presented with the Japan Management Quality Award for 1999.  
Ricoh continually strives to promote customer satisfaction, and shares the achievements of its management quality improvement program with people and society.



■Ricoh awarded ISO 14001 certification.  
The Ricoh Group was awarded ISO 14001 certification, which is an international standard for environmental management systems, at both its domestic and overseas production facilities. Our current aim is to obtain ISO 14001 certification for all of our business offices.

<http://www.ricoh.com/LSI/>

**RICOH COMPANY, LTD.**  
Electronic Devices Company

● Higashi-Shinagawa Office (International Sales)  
3-32-3, Higashi-Shinagawa, Shinagawa-ku, Tokyo 140-8655, Japan  
Phone: +81-3-5479-2857 Fax: +81-3-5479-0502

**RICOH EUROPE (NETHERLANDS) B.V.**  
● Semiconductor Support Centre

Prof. W.H.Keesomlaan 1, 1183 DL Amstelveen, The Netherlands  
P.O.Box 114, 1180 AC Amstelveen  
Phone: +31-20-5474-309 Fax: +31-20-5474-791

**RICOH ELECTRONIC DEVICES KOREA Co., Ltd.**  
11 floor, Haesung 1 building, 942, Daechidong, Gangnamgu, Seoul, Korea  
Phone: +82-2-2135-5700 Fax: +82-2-2135-5705

**RICOH ELECTRONIC DEVICES SHANGHAI Co., Ltd.**  
Room403, No.2 Building, 690#B1 Bo Road, Pu Dong New district, Shanghai 201203,  
People's Republic of China  
Phone: +86-21-5027-3200 Fax: +86-21-5027-3299

**RICOH COMPANY, LTD.**  
Electronic Devices Company  
● Taipei office  
Room109, 10F-1, No.51, Hengyang Rd., Taipei City, Taiwan (R.O.C.)  
Phone: +886-2-2313-1621/1622 Fax: +886-2-2313-1623



Ricoh completed the organization of the Lead-free production for all of our products. After Apr. 1, 2006, we will ship out the lead free products only. Thus, all products that will be shipped from now on comply with RoHS Directive.