DIR-600 FW 2.01语言包升级操作步骤

1.打开IE浏览器,在地址栏输入: 192.168.0.1,就可登录路由器管理界面

LOGIN	
Log in to the router:	
	User Name
	Password
	Enter the correct password above and then type the characters you see in the nicture
	below,

2. 进入路由器管理界面后, 先出现登录画面, 请在用户栏中输入: admin, 密码为空白, 然后输入图 形验证码, 按"LOG IN"按钮

Product Page :	DIR-600			Hardware Version : B1	Firmware
	LUGIN				
	Log in to the router:				
		User Name	admin		
		Password			
		Enter the co	rrect password above and then		
		below.			
		2000			
		-Qrv			
			Log In		

3. 进入以下画面后,点击画面上方选项"维护/MAINTENANCE",再选中左侧"固件升级/Firmware Update"

DIR-600	SETUP	ADVANCED	MAINTENANCE	STATUS
Device Administration	ADMINISTRATOR SET	TINGS		
Save and Restore	The 'admin' account can a	cross the manageme	ant interface. The admin has i	read/write access
Firmware Update	and can change passwords that you create a password	s. By default there is d to keep your route	no password configured. It is r secure.	highly recommended
System Check	Save Settings Don	't Save Settings		
Schedules				
Log Settings	ADMIN PASSWORD			
	Please enter the same pas	ssword into both box	es, for confirmation.	
	New Pass	word:		
	Confirm Pass	word:		
	ADMINISTRATION			

4. 在语言包升级栏,点击"浏览"按钮,在页面中选择你所存放语言包路径,点击"打开"后,再点击"升级"

選擇檔案					?
 ・ ・	DIR600B1_F DIR600B1_F DIR600B1_F DIR600B1_F DIR600B1_F DIR600B1_F DIR600B1_F DIR600B1_F	FW201 W WB01 W201 W WB01.bin W201 W WB01_langp W201 W WB01_langp W201 W WB01_langp W201 W WB01_langp W201 W WB01_langp W201 W WB01_langp	► ack_de bin ack_fr.bin ack_ko.bin ack_m bin ack_m bin ack_zhrw.bin ack_zhrw.bin	≣* <u>*</u>	
我的電腦	檔名(N): 檔案類型(T):	DIR600B1_FW20: 所有檔案 (*.*)	WWB01_langps	ck_zhen bi 💌	開啓(())

5. 以下为语言包升级进程状态,请稍等

uct Page : DIR-600	Hardware Version : B1	Firmware Version
FIRMWARE UPGRADE		
The F/W is updating		
Please DO NOT POWER OFF the device.		
Please wait for 36 seconds		
VIRELESS		
Copyright © 2004-2007 D-Link Systems, Inc.		

6. 完成语言包升级后, 会跳出以下画面, 如您的显示画面红圈区域与下图相符, 即为升级成功

: DIR-600	硬件版本	:B1 固件版本:2.01
T State		_
登录		
登录进入路由器		
	用户名 [
	名词	
	片,键入您看到的字符	
	秦盛	