



**ANALOG
DEVICES**

Single 0.275% Comparator and Reference with Dual Polarity Outputs

ADCMP361

FEATURES

400 mV $\pm$ 0.275% threshold
Supply range: 1.7 V to 5.5 V
Low quiescent current: 6.5 μ A typical
Input range includes ground
Internal hysteresis: 9.3 mV typical
Low input bias current: $\pm$ 5 nA maximum
Dual open-drain outputs
Small SOT-23 package

APPLICATIONS

Li-Ion monitoring
Threshold detectors
Relay driving
Optoisolator driving
Industrial control systems
Handheld instruments

GENERAL DESCRIPTION

The ADCMP361 is a single low power, high accuracy comparator with a 400 mV reference in a 5-lead SOT-23 package. The internal 400 mV reference provides the ability to monitor low voltage supplies. The device operates on a supply voltage from 1.7 V to 5.5 V and only draws 6.5 μ A typical, making it suitable for low power system monitoring and portable applications. Hysteresis is included in the comparators.

There are dual open-drain outputs to enable the comparator and reference circuit to be used in an inverting or noninverting configuration. The outputs can be pulled to any voltage up to a maximum of 5.5 V. The output stage is guaranteed to sink greater than 5 mA over temperature

The device is suitable for portable, commercial, industrial, and automotive applications.

FUNCTIONAL BLOCK DIAGRAM




Figure 1.




Figure 2. Typical Li-Ion Monitoring Application




Figure 3. Li-Ion Monitoring Waveforms

Rev. 0

Information furnished by Analog Devices is believed to be accurate and reliable. However, no responsibility is assumed by Analog Devices for its use, nor for any infringements of patents or other rights of third parties that may result from its use. Specifications subject to change without notice. No license is granted by implication or otherwise under any patent or patent rights of Analog Devices. Trademarks and registered trademarks are the property of their respective owners.

One Technology Way, P.O. Box 9106, Norwood, MA 02062-9106, U.S.A.
Tel: 781.329.4700
Fax: 781.461.3113
www.analog.com
©2007 Analog Devices, Inc. All rights reserved.

TABLE OF CONTENTS

Features	1	Typical Performance Characteristics	6
Applications	1	Application Information	11
Functional Block Diagram	1	Comparators and Internal Reference	11
General Description	1	Power Supply	11
Revision History	2	Inputs	11
Specifications	3	Outputs	11
Absolute Maximum Ratings	4	Adding Hysteresis	11
Thermal Characteristics	4	Outline Dimensions	12
ESD Caution	4	Ordering Guide	12
Pin Configuration and Function Descriptions	5		

REVISION HISTORY

2/07—Revision 0: Initial Version

www.BDTIC.com/ADI

SPECIFICATIONS

$V_{DD} = 1.7 \text{ V to } 5.5 \text{ V}$, $-40^{\circ}\text{C} \leq T_A \leq +125^{\circ}\text{C}$, unless otherwise noted.

Table 1.

Parameter	Min	Typ	Max	Unit	Test Conditions/Comments
THRESHOLDS ¹					
Rising Input Threshold Voltage	399.3	400.4	401.5	mV	$V_{DD} = 3.3 \text{ V}$, $T_A = 25^{\circ}\text{C}$
	391.2	400.4	407.7	mV	$V_{DD} = 1.7 \text{ V}$
	393.1	400.4	405.9	mV	$V_{DD} = 3.3 \text{ V}$
	393.1	400.4	405.8	mV	$V_{DD} = 5.5 \text{ V}$
Falling Input Threshold Voltage	381.1	391.1	400.9	mV	$V_{DD} = 1.7 \text{ V}$
	381.2	391.1	398.4	mV	$V_{DD} = 3.3 \text{ V}$
	381.0	391.1	398.2	mV	$V_{DD} = 5.5 \text{ V}$
Hysteresis = $V_{TH(R)} - V_{TH(F)}$	2	9.3	13.5	mV	
Threshold Voltage Accuracy			± 0.275	%	$T_A = 25^{\circ}\text{C}$, $V_{DD} = 3.3 \text{ V}$
Threshold Voltage Temperature Coefficient		16		ppm/ $^{\circ}\text{C}$	
POWER SUPPLY					
Supply Current		6.5	9	μA	$V_{DD} = 1.7 \text{ V}$
		7.0	10	μA	$V_{DD} = 5.5 \text{ V}$
INPUT CHARACTERISTICS					
Input Bias Current		0.01	5	nA	$V_{DD} = 1.7 \text{ V}$, $V_{IN} = V_{DD}$
		0.01	5	nA	$V_{DD} = 1.7 \text{ V}$, $V_{IN} = 0.1 \text{ V}$
OPEN-DRAIN OUTPUTS					
Output Low Voltage ²		140	220	mV	$V_{DD} = 1.7 \text{ V}$, $I_{OUT} = 3 \text{ mA}$
		140	220	mV	$V_{DD} = 5.5 \text{ V}$, $I_{OUT} = 5 \text{ mA}$
Output Leakage Current ³		0.01	1	μA	$V_{DD} = 1.7 \text{ V}$, $V_{OUT} = V_{DD}$
		0.01	1	μA	$V_{DD} = 1.7 \text{ V}$, $V_{OUT} = 5.5 \text{ V}$
DYNAMIC PERFORMANCE					
High-to-Low Propagation Delay ^{2, 4}		10		μs	$V_{DD} = 5 \text{ V}$, $V_{OL} = 400 \text{ mV}$
Low-to-High Propagation Delay ^{2, 4}		8		μs	$V_{DD} = 5 \text{ V}$, $V_{OH} = 0.9 \times V_{DD}$
Output Rise time ^{2, 4}		0.5		μs	$V_{DD} = 5 \text{ V}$, $V_O = (0.1 \text{ to } 0.9) \times V_{DD}$
Output Fall time ^{2, 4}		0.07		μs	$V_{DD} = 5 \text{ V}$, $V_O = (0.1 \text{ to } 0.9) \times V_{DD}$

¹ $R_L = 100 \text{ k}\Omega$, $V_O = 2 \text{ V}$ swing.

² 10 mV input overdrive.

³ $V_{IN} = 40 \text{ mV}$ overdrive.

⁴ $R_L = 10 \text{ k}\Omega$.

ABSOLUTE MAXIMUM RATINGS

Table 2.

Parameter	Rating
V_{DD}	−0.3 V to +6 V
IN	−0.3 V to +6 V
OUT, $\overline{\text{OUT}}$	−0.3 V to +6 V
Operating Temperature Range	−40°C to +125°C
Storage Temperature Range	−65°C to +150°C
Lead Temperature	
Soldering (10 sec)	300°C
Vapor Phase (60 sec)	215°C
Infrared (15 sec)	220°C

Stresses above those listed under Absolute Maximum Ratings may cause permanent damage to the device. This is a stress rating only; functional operation of the device at these or any other conditions above those indicated in the operational section of this specification is not implied. Exposure to absolute maximum rating conditions for extended periods may affect device reliability.

THERMAL CHARACTERISTICS

θ_{JA} is specified for the worst-case conditions, that is, a device soldered in a circuit board for surface-mount packages.

Table 3. Thermal Resistance

Package Type	θ_{JA}	Unit
5-Lead SOT-23	240	°C/W

ESD CAUTION



ESD (electrostatic discharge) sensitive device. Charged devices and circuit boards can discharge without detection. Although this product features patented or proprietary protection circuitry, damage may occur on devices subjected to high energy ESD. Therefore, proper ESD precautions should be taken to avoid performance degradation or loss of functionality.

www.BDTIC.com/ADI

PIN CONFIGURATION AND FUNCTION DESCRIPTIONS




Figure 4. Pin Configuration

Table 4. Pin Function Descriptions

Pin No.	Mnemonic	Description
1	OUT	Noninverting Open-Drain Output.
2	GND	Ground.
3	IN	Monitors analog input voltage on comparator. The other input of the comparator is connected to a 400 mV reference.
4	V_{DD}	Power Supply.
5	$\overline{\text{OUT}}$	Inverting Open-Drain Output.

www.BDTIC.com/ADI

TYPICAL PERFORMANCE CHARACTERISTICS




Figure 5. Distribution of Rising Input Threshold Voltage




Figure 8. Distribution of Falling Input Threshold Voltage




Figure 6. Distribution of Hysteresis




Figure 9. Rising Input Threshold Voltage vs. Temperature




Figure 7. Rising Input Threshold Voltage vs. Supply Voltage




Figure 10. Hysteresis vs. Temperature




Figure 11. Hysteresis vs. Supply Voltage




Figure 14. Minimum Supply Voltage




Figure 12. Quiescent Supply Current vs. Supply Voltage




Figure 15. Start-Up Supply Current




Figure 13. Supply Current vs. Output Sink Current




Figure 16. Supply Current vs. Output Sink Current




Figure 17. Supply Current vs. Output Sink Current




Figure 20. Below Ground Input Bias Current




Figure 18. Low Level Input Bias Current




Figure 21. High Level Input Bias Current




Figure 19. Output Saturation Voltage vs. Output Sink Current




Figure 22. Output Saturation Voltage vs. Output Sink Current




Figure 23. Output Saturation Voltage vs. Output Sink Current




Figure 26. Short-Circuit Current vs. Output Voltage




Figure 24. Short-Circuit Current vs. Output Voltage




Figure 27. Output Leakage Current vs. Output Voltage




Figure 25. Propagation Delay vs. Input Overdrive




Figure 28. Rise and Fall Times vs. Output Pull-Up Resistor




Figure 29. Noninverting and Inverting Comparators Propagation Delay

www.BDTIC.com/ADI

APPLICATION INFORMATION

The ADCMP361 is a low power comparator and reference circuit featuring a 400 mV reference that operates from 1.7 V to 5.5 V. The comparator is 0.275% accurate with a built-in hysteresis of 9.3 mV. There are two outputs, one the inverse of the other. This enables the ADCMP361 to be used as an inverting or a noninverting comparator circuit. These open-drain outputs are capable of sinking 40 mA.

COMPARATORS AND INTERNAL REFERENCE

The comparator has one input available externally; the other comparator input is connected internally to the 400 mV reference. The rising input threshold voltage of the comparators is designed to be equal to that of the reference.

POWER SUPPLY

The ADCMP361 is designed to operate from 1.7 V to 5.5 V. A 100 nF decoupling capacitor is recommended between V_{DD} and GND.

INPUTS

The comparator input is limited to the maximum V_{DD} voltage range. The voltage on these inputs can be above V_{DD} but never above the maximum allowed V_{DD} voltage. When adding a resistor string to the input, care must be taken when choosing resistor values. This is due to the fact that the input bias current will be in parallel with the bottom resistor, R2, of the input resistor divider string. This bottom resistor must therefore be chosen carefully in order to reduce the error introduced by this bias current (see Figure 30).

OUTPUTS

The open-drain comparator outputs are limited to the maximum specified V_{DD} voltage range, regardless of the V_{DD} voltage. These outputs are capable of sinking up to 40 mA.

ADDING HYSTERESIS

To prevent oscillations at the output caused by noise or slowly moving signals passing the switching threshold, each comparator has built-in hysteresis of approximately 9.3 mV. Positive feedback can be used to increase hysteresis.





Figure 30. Input Bias Current Effect on Input Resistor String

ADCMP361

OUTLINE DIMENSIONS



COMPLIANT TO JEDEC STANDARDS MO-178-AA
Figure 31. 5-Lead Small Outline Transistor Package [SOT-23]
(RJ-5)
Dimensions shown in millimeters

ORDERING GUIDE

Model	Temperature Range	Package Description	Package Option	Branding
ADCMP361YRJZ-REEL7 ¹	−40°C to +125°C	5-Lead SOT-23	RJ-5	M99

¹ Z = Pb-free part.

www.BDTIC.com/ADI