

頁 |1

1

雙網管理軟體Ver.2

安裝說明書

適用網卡機型: E161、E169u、E180









目錄

1	軟骴	豊版本列表3	頁 2
	1.1	自動雙網管理軟體升級版本列表3	
2	升級	及軟體版本注意事項3	
	2.1	確認網卡驅動程式	
	2.2	確認軟體升級作業環境	
	2.3	確認電力	
	2.4	升級檔下載連結	
3	升級	及操作4	2
4	E18	80韌體版本升級	2
	4.1	E180韌體升級版本列表7	
	4.2	升級注意事項	
	4.3	升級操作	





一一一丁行動網卡人到哪,網路就在哪

1 軟體版本列表

1.1 自動雙網管理軟體升級版本列表

頁 | 3

產品名稱	升級版本號
E161	E161_UTPS16.002.03.07.68_MAC16.001.09.02.68
E169u	E169U_UTPS16.002.03.08.68_MAC16.001.09.01.68
E180	E180_UTPS16.002.03.08.68_MAC16.001.09.01.68

2 升級軟體版本注意事項

2.1 確認網卡驅動程式

在升級前必須已經安裝好華為網卡驅動程式(任何一款)。

2.2 確認軟體升級作業環境

軟體升級環境限定使用Microsoft windows XP作業環境。

2.3 確認電力

請先確認電腦電池是否有足夠的電力,是否有連接上電源,以避免斷電產生,造成軟體升級失敗。(<mark>升級過</mark>

程中斷電、斷線將導致升級中斷 ,可能造成網卡損害)

2.4 升級檔下載連結

E161 :

http://www.emome.net/files/mobileinternets/E161 3G_WiFi connecting Manager.part1.exe





一一一了行動網卡人到哪,網路就在哪

http://www.emome.net/files/mobileinternets/E161 3G_WiFi connecting Manager.part2.rar http://www.emome.net/files/mobileinternets/E161 3G_WiFi connecting Manager.part3.rar

E169u :

http://www.emome.net/files/mobileinternets/E169u 3G_WiFi connecting Manager.part1.exe http://www.emome.net/files/mobileinternets/E169u 3G_WiFi connecting Manager.part2.rar http://www.emome.net/files/mobileinternets/E169u 3G_WiFi connecting Manager.part3.rar

E180:

http://www.emome.net/files/mobileinternets/E180 3G_WiFi connecting Manager.part1.exe http://www.emome.net/files/mobileinternets/E180 3G_WiFi connecting Manager.part2.rar http://www.emome.net/files/mobileinternets/E180 3G_WiFi connecting Manager.part3.rar http://www.emome.net/files/mobileinternets/E180 3G_WiFi connecting Manager.part4.rar

3 升級操作

1. 請將華為網卡插入電腦。 (以E169U & E180網卡版本號為示範案例)

 解壓縮從emome 行動上網WiFi 專區下載的檔案,執行UTPS16.002.03.08.68_MAC16.001.09.01.68,點選 同意(I accept the agreement)後點選下一步(Next)。







一一一丁行動網卡 人到哪,網路就在哪



3. 點選下一步(Next)。

The wizard is ready to update y	your Data Card
Vpdate setting is listed b	below
Iten	Context
Communication port	COMB
Connection status	CONNECTED 002 02 08 68 MAC16 001 00 01 1
Terrent version	1017516.002.03.06.66_MAC16.001.03.01.1
TMFT	356185030756349
Download Mode	Normal Download
<	
Auto remove the device	after undate
Click Next to begin undati	ing your Dashboard Data Card

建議"Auto remove the device after upate"請不要打勾。

當打勾,軟體升級完成,電腦並不會自行偵測網卡。

當沒有打勾,軟體升級完成,電腦會在自行偵測網卡。







頁 |5



4. 點選 (start) 確認開始升級網卡版本。



5. 開始升級過程(升級過程中斷電、斷線將導致升級中斷)

j ^{g,} Dashboard Update Wizard	
Updating Dashboard The wizard is updating the dashboard of your Data Card	
Downloading Programs	1
Start	Gancel









一一一丁行動網卡 人到哪,網路就在哪

6. 升級完成後,確認軟體版本號UTPS16.002.03.08.68_MAC16.001.09.01.68,點選(確定)之後,點選(Finish)

結束軟體升級流程。

7.附加說明:

1.雙網軟體升級完成後,表示網卡內的軟體版本已經更新成雙網管理軟體Ver.2。

2.若電腦內原本就有安裝Mobile Partner軟體,雙網軟體升級完成後,會顯示將舊版mobile partner軟體移除後,

再安裝新的mobile partner,安裝新的mobile partner時才是自動雙網管理軟體。

4 E180 韌體版本升級

4.1 E180 韌體升級版本列表

產品名稱	升級版本號
E180	E180Update_11.126.10.01.68.B418





7

一一一一 行動網卡 人到哪,網路就在哪

4.2 升級注意事項

1.在升級前須已安裝好華為網卡驅動程式(任何一款)。

頁 | 8 2.請先確認電腦電池是否有足夠的電力,是否有連接上電源,以避免斷電產生,造成軟體升級失敗。<mark>(升級過</mark>

程中斷電、斷線將導致升級中斷 ,可能造成網卡損害)

4.3 升級操作

- 1. 請將華為網卡插入電腦。
- 2. 解壓縮從emome 行動上網WiFi 專區下載的檔案,執行E180Update_11.126.10.01.68.B418檔案,點選同意

(I accept the agreement)後點選下一步(Next)。

13 Davide a charte a real
Welcome to Dashboard Update Wizard Is wizard helps you to update the dashboard of your Dashboard Is wizard helps you to update the dashboard of your Dashboard Is wizard helps you to update the dashboard of your Dashboard Is wizard helps you to update the dashboard of your Dashboard Is wizard helps you to update the dashboard of your Dashboard Is wizard helps you to update the update Is accept the agreement between you (either an individual or a single entity) and Huawei Technologies (o, Ltd. ("HUAWEI") for the HUAWEI Software and may include associated media, printed materials, and "online" Is accept the agreement Is accept the agreement Is accept the agreement Is accept the agreement Is an taccept the agreement Is accept the agreement Is accept the agreement Is accept the agreement Is accept the agreement





一一一丁行動網卡人到哪,網路就在哪

3. 點選下一步(Next)。

The wizard is ready to update y	our Data Card	N.
Update setting is listed b	elow	
Iten	Context	
Communication port	COM11	
Connection status	connected	
Current version	11. 126. 10. 00. 68	
Target version	11.126,10.01.68	
IMEI	356185030803075	
Download Mode	Normal Download	
Auto remove the device	after undate	
Click Next to begin updati:	ng your Firmware Data Card	

建議"Auto remove the device after upate"請不要打勾。

當打勾,軟體升級完成,電腦並不會自行偵測網卡。

當沒有打勾,軟體升級完成,電腦會再自行偵測網卡。







頁 |9



4. 點選 (start) 確認開始升級網卡版本。



5. 開始升級 (升級過程中斷電、斷線將導致升級中斷)

🙀 Dashboard Update Wizard	
Updating Dashboard The wizard is updating the dashboard of your Data Card	Ð
Downloading Programs	
	Ī
Start	Gancel





10



6. 升級完成後,確認軟體版本號Update_11.126.10.01.68,點選(確定)之後,點選(Finish)結束軟體升級流程。



11





