

### Input capture with ST62 auto-reload timer

## Introduction

This note presents how to use the Auto-reload timer (ARTimer) of the ST62 to measure durations or frequencies of an input signal.


### Auto-reload timer description

This timer is an 8 bit timer/counter with prescaler. It includes auto-reload PWM, capture and compare capability with one input and one output pins. It can be controlled by the following registers (8 bit):

- Mode Control Register (MC)
- Status registers (SC0, SC1)
- Load register (LR)
- Incremental counter register (TC)
- Compare register (CP)
- Reload/Capture register (RC)

It can also wake-up the MCU from wait mode and exit from stop mode if an external event is present on the input pin. The prescaler ratio can be programmed to choose the timer input frequency  $F_{IN}$  (see Table 1).

**Figure 1. Auto-reload timer block diagram**



**Capture mode with reset**

This can be used to measure time durations or frequencies. This mode is used to measure the time elapsed between two edges of an external signal: two rising edges, two falling edges, or one rising and one falling if the configuration of the timer is modified after the first edge detected.

The minimum duration of one signal to measure depends on the CPU clock and on the required precision. With a 8MHz Quartz crystal, a signal of 8ms duration can be measured with a resolution of 1/64.

**Example:**

Let's measure the time elapsed between two rising edges on TIMIN:

The prescaler ratio must be programmed according to the expected duration to measure. In this example it is programmed to: prescaler ratio = 4, clock source = CPU clock. (in case the duration expected can be longer than the 255 count span of the TC count register, the overflow interrupt can be used to increment a RAM variable, used as the most significant part of the result).

In the program example, waiting for the edge on TIMIN is made by a software loop (jrr 2, SC0, wt\_edge), but it is also possible to use the external event interrupt to read the result immediately after the edge without loading the rest of the program. It is also possible to read the result directly from RC without waiting or using the interrupt, if the duration is required at an asynchronous time, not just after the edge.

**Table 1. Prescaler programming ratio**

Bit 0 Reg. SC1	PS2	PS1	PS0	Prescaler ratio
0	0	0	0	1
0	0	0	1	2
0	0	1	0	4
0	0	1	1	8
0	1	0	0	16
0	1	0	1	32
0	1	1	0	64
0	1	1	1	128
1	0	0	0	3
1	0	0	1	6
1	0	1	0	12

**Programmable example**

```

;***** accumulator *****
A .def 0FFh,0FFh,0FFh ;Accumulator

;***** RAM variable *****

period .def 084h,0FFh,0FFh ;elapsed time


;***** A-R Timer Register Set *****

RC. def 0D9h,0FFh,0FFh ;reload/capture register
CP. def 0DAh,0FFh,0FFh ;compare register
MC. def 0D5h,0FFh,0FFh ;mode control register
SC0. def 0D6h,0FFh,0FFh ;status/control register 0
SC1. def 0D7h,0FFh,0FFh ;status/control register 1
LR. def 0DBh,0FFh,0FFh ;load register
;=====
ldi SC1,01000100b; clock source = CPU,
;prescaler ratio = 4,
;pull-up on TIMIN disabled,
;capture on rising edge of TIMIN
ldi MC, 11000010b;capture with reset, ints. disabled
;PWMOUT disabled, start timer
; .
; . normal program
; .
;now we want to know the elapsed time between last and
;next edge on TIMIN:
res 2, SC0 ;clear external event flag

wt_edge
jrr 2,SC0,wt_edge ;wait for edge on TIMIN, then
ld A,RC ;read elapsed time from reload/capt
ld period,A ;register into variable "period"
    
```

The following figure shows the evolution of the contents of TC and RC during capture operation: a rising edge on TIMIN results in copying the latest value of TC into RC, and clearing TC. Afterwards, TC increments at the selected clock rate until the next capture or until it reaches 255. In the latter case, it wraps to 0. In capture mode, TC always counts from 0 to 255, it is never loaded from the RC register.

**Figure 2. TC and RC Evolution**



## Revision history

**Table 2. Revision history**

Date	Revision	Description of changes
March-1993	1	Initial release
04-July-2008	2	Logo modified

**Please Read Carefully:**

Information in this document is provided solely in connection with ST products. STMicroelectronics NV and its subsidiaries ("ST") reserve the right to make changes, corrections, modifications or improvements, to this document, and the products and services described herein at any time, without notice.

All ST products are sold pursuant to ST's terms and conditions of sale.

Purchasers are solely responsible for the choice, selection and use of the ST products and services described herein, and ST assumes no liability whatsoever relating to the choice, selection or use of the ST products and services described herein.

No license, express or implied, by estoppel or otherwise, to any intellectual property rights is granted under this document. If any part of this document refers to any third party products or services it shall not be deemed a license grant by ST for the use of such third party products or services, or any intellectual property contained therein or considered as a warranty covering the use in any manner whatsoever of such third party products or services or any intellectual property contained therein.

**UNLESS OTHERWISE SET FORTH IN ST'S TERMS AND CONDITIONS OF SALE ST DISCLAIMS ANY EXPRESS OR IMPLIED WARRANTY WITH RESPECT TO THE USE AND/OR SALE OF ST PRODUCTS INCLUDING WITHOUT LIMITATION IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE (AND THEIR EQUIVALENTS UNDER THE LAWS OF ANY JURISDICTION), OR INFRINGEMENT OF ANY PATENT, COPYRIGHT OR OTHER INTELLECTUAL PROPERTY RIGHT.**

**UNLESS EXPRESSLY APPROVED IN WRITING BY AN AUTHORIZED ST REPRESENTATIVE, ST PRODUCTS ARE NOT RECOMMENDED, AUTHORIZED OR WARRANTED FOR USE IN MILITARY, AIR CRAFT, SPACE, LIFE SAVING, OR LIFE SUSTAINING APPLICATIONS, NOR IN PRODUCTS OR SYSTEMS WHERE FAILURE OR MALFUNCTION MAY RESULT IN PERSONAL INJURY, DEATH, OR SEVERE PROPERTY OR ENVIRONMENTAL DAMAGE. ST PRODUCTS WHICH ARE NOT SPECIFIED AS "AUTOMOTIVE GRADE" MAY ONLY BE USED IN AUTOMOTIVE APPLICATIONS AT USER'S OWN RISK.**

Resale of ST products with provisions different from the statements and/or technical features set forth in this document shall immediately void any warranty granted by ST for the ST product or service described herein and shall not create or extend in any manner whatsoever, any liability of ST.

ST and the ST logo are trademarks or registered trademarks of ST in various countries.

Information in this document supersedes and replaces all information previously supplied.

The ST logo is a registered trademark of STMicroelectronics. All other names are the property of their respective owners.

© 2008 STMicroelectronics - All rights reserved

STMicroelectronics group of companies

Australia - Belgium - Brazil - Canada - China - Czech Republic - Finland - France - Germany - Hong Kong - India - Israel - Italy - Japan - Malaysia - Malta - Morocco - Singapore - Spain - Sweden - Switzerland - United Kingdom - United States of America

[www.st.com](http://www.st.com)