



The R5325K Series are CMOS-based seamless dual output LDO regulators featuring 150mA output. Ricoh unique seamless technology smoothly changes its transient response according to output current. Thus, R5325K offers lower supply current in the smaller output current range compared to R5323x (Typ. 90 μ A). Additionally, R5325K can reach low supply current without changing to low power mode using the ECO function, which is required by R5326K (Typ. 5.5 μ A) and R5328K (Typ. 2.5 μ A). Standby mode and auto-discharge function are also available (see Selection Guide). Ceramic capacitors can be used.

FEATURES

- Supply Current (I_{SS}) Typ. 3 μ A \times 2 (V_{IN} =SET V_{OUT} +1.0V)
- Standby Current ($I_{standby}$) Typ. 0.1 μ A \times 2 (V_{IN} =6.0V, CE1/CE2="L")
- Dropout Voltage (V_{DIF}) Typ. 0.21V (I_{OUT} =150mA, V_{OUT} =2.8V)
- Ripple Rejection (RR) Typ. 55dB (f =1kHz)
- Input Voltage Range (V_{IN}) 1.5V to 6.0V
- Output Voltage Range (V_{OUT}) 1.2V to 4.0V* (internally fixed)
- Output Voltage Accuracy \pm 1%
- Temp. coeff. of Output Voltage Typ. \pm 100ppm/ $^{\circ}$ C
- Line Regulation Typ. 0.1%/V
- Fold-back Protection Circuit Current limit Typ. 50mA
- Auto-Discharge function B Version
- Package DFN(PLP)1820-6
- Ceramic capacitors can be used. ...0.1 μ F or more

*) For information about combination of output voltage, please check our website.

BLOCK DIAGRAMS



SELECTION GUIDES


Halogen Free	Package	Q'ty per Reel	Part No.
H/F	DFN(PLP)1820-6	3,000 pcs	R5325Kxxx*-TR

xxx : Specify a combination of output voltage for each output using serial numbers.

* : Select from (A) without auto-discharge function or (B) with auto-discharge function.

PACKAGES

DFN(PLP)1820-6




1	V_{OUT2}
2	V_{DD}
3	V_{OUT1}
4	CE1
5	GND
6	CE2

*) The tab is substrate level (GND).

TYPICAL CHARACTERISTIC

R5325K (VR1/VR2) Dropout Voltage vs. Output Current



APPLICATIONS

- Power source for hand-held communication equipment, cameras, and VCRs
- Power source for battery-powered equipment
- Power source for home appliances



1. The products and the product specifications described in this document are subject to change or discontinuation of production without notice for reasons such as improvement. Therefore, before deciding to use the products, please refer to Ricoh sales representatives for the latest information thereon.
2. The materials in this document may not be copied or otherwise reproduced in whole or in part without prior written consent of Ricoh.
3. Please be sure to take any necessary formalities under relevant laws or regulations before exporting or otherwise taking out of your country the products or the technical information described herein.
4. The technical information described in this document shows typical characteristics of and example application circuits for the products. The release of such information is not to be construed as a warranty of or a grant of license under Ricoh's or any third party's intellectual property rights or any other rights.
5. The products listed in this document are intended and designed for use as general electronic components in standard applications (office equipment, telecommunication equipment, measuring instruments, consumer electronic products, amusement equipment etc.). Those customers intending to use a product in an application requiring extreme quality and reliability, for example, in a highly specific application where the failure or misoperation of the product could result in human injury or death (aircraft, spacevehicle, nuclear reactor control system, traffic control system, automotive and transportation equipment, combustion equipment, safety devices, life support system etc.) should first contact us.
6. We are making our continuous effort to improve the quality and reliability of our products, but semiconductor products are likely to fail with certain probability. In order to prevent any injury to persons or damages to property resulting from such failure, customers should be careful enough to incorporate safety measures in their design, such as redundancy feature, firecontainment feature and fail-safe feature. We do not assume any liability or responsibility for any loss or damage arising from misuse or inappropriate use of the products.
7. Anti-radiation design is not implemented in the products described in this document.
8. Please contact Ricoh sales representatives should you have any questions or comments concerning the products or the technical information.

RICOH COMPANY, LTD. Electronic Devices Company



■ Ricoh presented with the Japan Management Quality Award for 1999.
Ricoh continually strives to promote customer satisfaction, and shares the achievements of its management quality improvement program with people and society.



■ Ricoh awarded ISO 14001 certification.

The Ricoh Group was awarded ISO 14001 certification, which is an international standard for environmental management systems, at both its domestic and overseas production facilities. Our current aim is to obtain ISO 14001 certification for all of our business offices.

<http://www.ricoh.com/LSI/>

RICOH COMPANY, LTD.

Electronic Devices Company

● Higashi-Shinagawa Office (International Sales)

3-32-3, Higashi-Shinagawa, Shinagawa-ku, Tokyo 140-8655, Japan
Phone: +81-3-5479-2857 Fax: +81-3-5479-0502

RICOH EUROPE (NETHERLANDS) B.V.

● Semiconductor Support Centre

Prof. W.H.Keesomlaan 1, 1183 DL Amstelveen, The Netherlands
P.O.Box 114, 1180 AC Amstelveen
Phone: +31-20-5474-309 Fax: +31-20-5474-791

RICOH ELECTRONIC DEVICES KOREA Co., Ltd.

11 floor, Haesung 1 building, 942, Daechidong, Gangnamgu, Seoul, Korea
Phone: +82-2-2135-5700 Fax: +82-2-2135-5705

RICOH ELECTRONIC DEVICES SHANGHAI Co., Ltd.

Room403, No.2 Building, 690#Bi Bo Road, Pu Dong New district, Shanghai 201203,
People's Republic of China
Phone: +86-21-5027-3200 Fax: +86-21-5027-3299

RICOH COMPANY, LTD.

Electronic Devices Company

● Taipei office

Room109, 10F-1, No.51, Hengyang Rd., Taipei City, Taiwan (R.O.C.)
Phone: +886-2-2313-1621/1622 Fax: +886-2-2313-1623



Ricoh completed the organization of the Lead-free production for all of our products. After Apr. 1, 2006, we will ship out the lead free products only. Thus, all products that will be shipped from now on comply with RoHS Directive.