

Model: WCC140WH

140W 3 Port USB-C Wall Charger



User Manual v1.1

#### **Product Features**

Charge a MacBook Pro or Air, Windows Laptop, Chromebook iPad Pro or tablet equipped with a USB-C charging port

Compatible with most USB-C laptops and Chromebooks

Apple • Lenovo • Acer • Asus • HP • Dell • Microsoft • Google

- Latest GaN technology means smaller, lighter, safer and more energy efficient charging
- With 140W of power, you can charge a 2021 MacBook Pro 16" from 0 to 50% in less than 30 minutes using a USB-C to MagSafe charging cable
- Ideal for all MacBooks, Windows laptops and Chromebooks with USB-C charging
- Fast charge the latest iPhone or Android from 0 to 50% in 30 minutes
- Do away with multiple chargers and charge up to two laptops and a phone with this single 140W charger
- USB-C1 Output: PD 3.0 20W Max 5V/3A 9V/2.22A 12V/1.67A
- USB-C2 & C3 Output: PD 3.1 140W Max 5V/3A 9V/3A 12V/3A 15V/3A 20V/5A 28V/5A
- USB-C1 + C2 + C3: 20W + 65W + 65W
- Total Power Output: 140W

# Operating Instructions

- Connect your laptop, MacBook or Chromebook to port USB-C2 or C3
- Connect your phone, iPad, tablet or other USB device to port USB-C1
- When charging multiple devices at the same time, the below table shows how the power is distributed

#### Power Distribution Table

	Ports	USB-C1	USB-C2	USB-C3	Total Output
Single Output	USB-C1	20W	/	/	20W
	USB-C2	/	140W	/	140W
	USB-C3	/	/	140W	140W
2 Outputs	USB-C1+C2	20W	120W	/	140W
	USB-C1+A	20W	/	120W	140W
	USB-C2+A	/	130W		130W
3 Outputs	USB-C1+C2+A	20W	120W		140W

## **Product Diagram**



## **Product Specifications**

Model: WCC140WH

Input: AC 100-240V~50/60Hz 2.0A

USB-C Output C1: USB PD supports 20W Max 5V-3A 9V-2.22A 12V-1.67A

USB-C Output C2 & C3: USB PD3.0 each port supports 140W Max 5V-3A 9V-3A 12V-3A 15V-3A 20V-5A 28V-5A

Total Power Output: 140W

Dimensions: 39mm (W) x 102mm (D) x 75mm (H)

Net Weight: 289

## Package Contents

1 x 140W USB-C Wall Charger

1 x User Manual

















