


1 ROUGH-IN REQUIREMENTS

1. Your towel warmer requires 110V GFCI protected power. This 110V receptacle should be located no further than 18" from the electric plug-in exit location (see figure 2), and not above the electric plug-in exit location.
2. Wall studs or plywood backing is recommended in the wall at all bracket locations. See Fig 2 for bracket locations.

2 INSTALLATION INSTRUCTIONS (see figure 1)

1. Check all items have been received.
 1. Towel Warmer
 2. Fixings Kit
2. Fix wall supports "A" to the wall using the screws provided and in locations as shown on figure 2.
3. Hang and adjust the Towel Warmer using set screws "B" to lock stud "C" in the wallbracket "A". Ensure the Towel Warmer is firmly and safely fixed.

FIGURE 1



3 PLUG-IN CONNECTION

TURN OFF POWER SUPPLY BEFORE PROCEEDING

Do not connect the Towel Warmer to the power supply until all instructions have been read and installation carried out in accord with them. Your towel warmer is 100W (110V) and conforms to CSA standards (File ref: 2422531). Please ensure the CSA label is visible.

1. Turn off power supply.
2. Plug connector in.
3. Switch on power supply.

Warning: In case of damage or failure of the Towel Warmer the unit should be returned to the manufacturer or their distributor. The warranty of 2 years on the Towel Warmer is NOT VALID in case of improper use or installation. Product is designed for use within Canada and the United States only.

4 PRODUCT REGISTRATION

Once installation is complete (and within 60 days of purchase) register your product online to activate your two year warranty. To register visit www.shopicobath.com, click on resources then register your towel warmer or visit www.shopicobath.com/en/warranty. Be sure to have your serial number (7 digit number on silver label at bottom right of towel warmer) along with the date you purchased your towel warmer.

Specifications & Drawings

Code: K6013E / K6014E
24" x 27" Plug-In

Model #	Description	Finish	Weight (lb)	Watts	Volts	WxH (mm)	WxH (Inches)	Metal Type
K6013E	Square Electric Plug-In	Chrome	10	85W	110V	600 x 690	23.5 x 27	Stainless Steel
K6014E	Square Electric Plug-In	Brushed Nickel	10	85W	110V	600 x 690	23.5 x 27	Stainless Steel

Warranty: 2 Years (excludes labor)

Fixings: Screws, and Allen Key (if needed) are included

Care & Maintenance: A periodic wash using warm water and a soft cloth will retain the high quality finish of your towel warmer for many years to come. ON NO ACCOUNT should any household bleaches, detergents, abrasive polishes, steel wool or other cleaning agents be used on this item.

FIGURE 2

