



IMPORTANT

- Read this manual thoroughly, and do not perform installation, operation, maintenance, or inspection unless you fully understand all of the contents.
- Keep this manual in a safe place where you can refer to it easily while installing, operating, and carrying out maintenance or inspections.

ISHIDA CO., LTD.

© ISHIDA Co., Ltd. 2008 All rights are reserved.

No part of this publication may be reproduced, stored in a retrieval system, or transmitted in any form or by any means mechanical, electronic, photocopying, recording, or otherwise without prior written permission of ISHIDA.

NOTICES

IMPORTANT NOTICE

Those who handle the machine must be aware of the hazards involved. These dangers may not be obvious, so it is imperative to follow the instructions detailed in this manual when installing, operating, inspecting, or servicing the machine. Therefore, we recommend that you thoroughly read and understand this manual before installing, operating, inspecting, or servicing the machine. ISHIDA is not liable for any damage, loss or injury that results from incorrect operation, insufficient caution, unauthorized modifications to the machine, or failure to follow the instructions contained in this manual.

LIMITATIONS OF LIABILITY

ISHIDA assumes no responsibility for special, indirect, or consequential damages, loss of profits or commercial loss in any way connected with the machine, whether such claim is based on contract, warranty, negligence, or strict liability.

ISHIDA assumes no responsibility for the user's programming of this machine, or any consequence thereof.

In no event shall ISHIDA be responsible for warranty, repair, or other claims regarding the machine unless ISHIDA's analysis confirms that the machines were properly handled, stored, installed, and maintained and not subject to contamination, abuse, misuse, or inappropriate modification or repair.

CHANGE IN SPECIFICATIONS

Machine specifications and accessories may be changed at any time due to improvements or other reasons. Consult with your ISHIDA representative at any time to confirm the actual specifications of the purchased machine.

ERRORS AND OMISSIONS

The information in this manual has been carefully checked and is believed to be accurate; however, no responsibility is assumed for clerical, typographical or proofreading errors, or omissions.

PRECAUTIONS FOR SAFE USE

It is strongly advised that the following safety measures must be observed to ensure the safe operation of the machine.

WARNING

• Prepare a dedicated power source and always use a power supply with rated voltage. Never connect the machine power input with an AC power supply exceeding the rated voltage. To avoid any potential electrical shock, ensure that the protective ground wire is connected to the main grounding provision.

A power supply that generates voltage variation may cause a malfunction, or using the machine outside of the rated voltage may result in machine failure or danger such as electric shock.

• Do not install the machine near a TV set or radio.

Doing so may cause static to the TV set and/or radio as this machine emits week electric wave.

 Do not allow water or any liquids to come into contact with the machine.


Doing so may result in fire or cause the machine to break down.


- Do not drop or apply a strong shock to the machine. Doing so may cause the machine to break down.
- Do not disassemble, modify, or attempt to repair the machine.

Doing so may damage the original safety functions.

• Do not hold the connector cover when carrying the machine.

Dropping the machine may result in injury or cause the machine to break down.





PRECAUTIONS FOR MACHINE INSTALLATION



Do not install the machine in the following types of places:

- Places subject to high temperatures or high humidity
- Places exposed to direct sunlight
- Places where water or other liquids are easily spilled on the machine
- Places subject to excessive vibration or unstable foundations
- Places exposed to direct cold air from air conditioners or refrigerators
- Places where the floor or foundation is unstable
- Places subject to a lot of dust or dirt
- Places with large voltage fluctuations







PRECAUTION SYMBOLS

This machine is manufactured for use according to proper procedures by a qualified person and only for the purposes described in this manual. The following conventions are used to indicate and classify precautions depending on the level of danger, or seriousness of potential injury. Always heed the information provided in this manual. Failure to heed precautions can result in personal injury or property damage.

The following precaution symbols are used in this manual.

Indicates a potentially hazardous situation which, if not avoided, may result in serious injury or death. Additionally, there may be significant property damage.
Indicates a potentially hazardous situation where, if not avoided, may result in minor or moderate injury or in property damage.

INFOR	Indicates reference information for operation.
REFER	Indicates the referred page for operation.

TABLE OF CONTENTS

CHAPTER	1 BEI	FORE USE	1-1
1.1	SPECI	FICATIONS	1-1
1.2	MODE	L VARIATIONS	1-2
1.3	PART	NAMES AND FUNCTIONS	1-3
	1.3.1	FRONT VIEW (BENCH TYPE)	1-3
	1.3.2	REAR VIEW (BENCH TYPE)	1-3
1.4	OPER/	ATION PANEL	1-4
1.5	ADJUS	STMENTS	1-5
	1.5.1	LEVEL ADJUSTMENT (BENCH TYPE)	1-5
	1.5.2	OPERATION PANEL ANGLE ADJUSTMENT (BENCH TYPE)	1-5
1.6	LABEL	/ RECEIPT ROLL LOADING	1-6
1.7	REMO	VING & REPLACING OF WEIGH PLATTER	1-9
	1.7.1	REMOVING THE WEIGH PLATTER	1-9
	1.7.2	REPLACING THE WEIGH PLATTER	1-9
1.8	CLEAN	NING OF THE MACHINE	1-10
	1.8.1	CLEANING OF THE THEREMAL HEAD	1-10
	1.8.2	CLEANING OF THE LABEL SENSOR	1-11
	1.8.3	CLEANING OF THE PRINT ROLLER AND PRISM	1-12
	1.8.4	PRECAUTIONS WHEN USING CLEANING FLUIDS	1-13
1.9	START	TING PROCEDURES	1-14
	1.9.1	TURNING ON THE POWER	1-14
	1.9.2	PERFORMING ZERO ADJUSTMENT	1-15
	1.9.3	GETTING BACK TO THE INITIAL SCREEN	1-16
CHAPTER	2 LAI	BEL ISSUE	2-1
2.1	LABEL	ISSUE WITHOUT OPERATOR	
	2.1.1	WEIGHING UNIT PRICE PRODUCTS	
	2.1.2	WEIGHING FIXED PRICE PRODUCTS	
	2.1.3	PROCESSING FIXED PRICE PRODUCTS	
	2.1.4	PROCESSING FIXED WEIGHT/FIXED UNIT PRICE PRODUCTS	
2.2		ISSUE WITH OPERATORS	
	2.2.1	WEIGHING UNIT PRICE PRODUCTS	
	2.2.2	WEIGHING FIXED PRICE PRODUCTS	
	2.2.3	PROCESSING FIXED PRICE PRODUCTS	
		PROCESSING FIXED WEIGHT/FIXED UNIT PRICE PRODUCTS	
3.1			
3.2		BY DIFFERENT OPRATORS	
3.3		NG PRODUCT REGISTRATION	
CHAPTER		ACEABILITY PRODUCTS	
4.1	REFEF	RING TO PREVIOUS TRACEABILITY DATA	4-1

	4.2	CHANGING TRACEABILITY DATA	
CHA	PTER	5 TEMPORARY CHANGE OPERATIONS	5-1
	5.1	UNIT PRICE CHANGE	5-1
	5.2	FIXED PRICE CHANGE	5-3
	5.3	AMOUNT DISCOUNT FOR UNIT PRICE	5-5
	5.4	PERCENT DISCOUNT FOR UNIT PRICE	5-7
	5.5	AMOUNT DISCOUNT FOR TOTAL PRICE	5-9
	5.6	PERCENT DISCOUNT FOR TOTAL PRICE	-11
	5.7	PRODUCT QUANTITY CHANGE	-13
	5.8	PRINT QUANTITY SETTING	-15
CHA	PTER	6 SELF-SERVICE OPERATIONS	6-1
	6.1	WEIGHING PRODUCTS	6-1
	6.2	FIXED PRICE PRODUCTS	6-3
СНА	PTER	7 ACCUMULATOR MODE	7-1
	7.1	MANUAL INPUT ACCUMULATION	7-1
	7.2	WEIGHING ACCUMULATION	7-3
	7.3	MANUAL INPUT VOID	7-6
	7.4	WEIGHING VOID	7-9
CHA	PTER	8 TOTAL ADJUST MODE	8-1
	8.1	MANUAL INPUT SUBTRACTION	8-1
	8.2	WEIGHING SUBTRACTION	8-3
	8.3	MANUAL INPUT ADDITION	8-6
	8.4	WEIGHING ADDITION	8-9
СНА	PTER	9 TOTAL MODE	9-1
	9.1	DAILY TOTAL	9-1
	9.2	WEEKLY TOTAL	9-4
	9.3	CUMULATIVE TOTAL	9-6
	9.4	TRACEABILITY TOTAL	9-8
	9.5	PRESET REPORT PRINTING	9-9
	9.6	TOTAL CLEAR	-10
CHA	PTER	10 PROGRAM MODE	0-1
	10.1	PROGRAM MODE ENTRY10	0-1
	10.2	PLU FILE REGISTRATION	0-4
	10.3	CAMPAIGN LIST REGISTRATION	-14
	10.4	OPERATOR REGISTRATION	-19
	10.5	PRESET KEY REGISTRATION	-22
		10.5.1 SETTING PRESET FUNCTIONS	
		10.5.2 ASSIGNING IMAGES ON THE PRESET KEYS	
		10.5.3 COLORING PRESET KEYS	
		10.5.4 CHANGING PRESET KEY SIZES	-30

10.5.5 EDITING PRESET KEY NAMES	10-33
10.5.6 CONFIRMING PRESET KEY DATA	
10.5.7 DELETING PRESET KEYS	10-37
10.5.8 MEMBRANE KEYS	10-39
10.6 ADVERTISEMENT MESSAGE REGISTRATION	10-42
10.7 STORE NAME REGISTRATION	
10.7.1 CHANGING EXISTING STORE DATA	10-46
10.7.2 CREATING NEW STORE DATA	10-49
10.8 DEPARTMENT NAME REGISTRATION	10-53
10.8.1 CREATING NEW DEPARTMENT NAMES	10-53
10.8.2 CHANGING EXISITING DEPARTMENT NAMES	10-57
10.9 GROUP NAME REGISTRATION	
10.9.1 CREATING NEW GROUP NAMES	10-59
10.9.2 CHANGING EXISITING GROUP NAMES	10-62
10.10 COOKING INSTRUCTION REGISTRATION	
10.10.1 CREATING NEW INSTRUCTIONS	10-64
10.10.2 CHANGING EXISITING INSTRUCTIONS	10-67
10.11 NUTRITION FILE REIGISTRATION	10-69
10.11.1 CREATING NEW NUTRITION DATA	10-69
10.11.2 CHANGING EXISTING NUTRITION DATA	10-72
10.12 EXTRA MESSAGE REGISTRATION	10-75
10.12.1 CREATING NEW MESSAGES	10-75
10.12.2 CHANGING EXISITING MESSAGES	10-78
10.13 COUPON MESSAGE REGISTRATION	10-80
10.13.1 CREATING NEW MESSAGES	10-80
10.13.2 CHANGING EXISITING MESSAGES	10-83
10.14 POP MESSAGE REGISTRATION	10-85
10.15 TAX REGISTRATION	
10.16 SCHEME TABLE REGISTRATION	10-88
10.16.1 CREATING NEW TABLES	
10.16.2 CHANGING EXISITING MESSAGES	
10.17 GEN TABLE REGISTRATION	
10.18 LOOKUP TABLE REGISTRATION	10-99
10.18.1 CREATING NEW TABLES	10-99
10.18.2 CHANGING EXISITING TABLES	10-106
10.19 MINCE TRACEABILITY REGISTRATION	10-110
10.20 FIXED PRICE MARK REGISTRATION	10-111
10.20.1 CREATING NEW PRICE MARKS	10-111
10.20.2 CHANGING EXISITING PRICE MARKS	10-113
10.21 FREE MESSAGE REGISTRATION	10-115
10.21.1 CREATING NEW MESSAGES	10-115
10.21.2 CHANGING EXISITING MESSAGES	10-118

1

BEFORE USE


1.1 SPECIFICATIONS

Items	Descriptions				
Use conditions	Temperature: 5 to 35°C				
	Humidity: 30 to 85%, Non condensing.				
Power supply:	AC100 – 240V, 50 / 60Hz				
Power consumption	1.0A/0.5A				
Weight	Bench type: Approx.11.5 kg Pole type: Approx.12.5 kg				
Weighing capacity	15 kg: 0 to 6/0.002 kg, 6 to 15/0.005 kg				
Weighting accuracy	1/3000				
Operator/Customer display	7.0 inch color liquid crystal with back light, 480 X 234dots				
Printing method	Direct thermal method				
Thermal head	2 inches (448dots) and 8 dots/mm				
Printing speed	100mm/second, 120mm/second Note: The printing speed may vary according to label conditions.				
Printing effective size	56mm				
Label size	Label width: 30mm to 60mm Label length: 20mm to 150mm				
Number of label cassettes	7 cassettes				
Input/Output	LAN 1 channel USB 1 channel CF 1 channel Drawer 2 channels				
Program store medium	Flash ROM (32M bytes)				


1.2 MODEL VARIATIONS



Bench Type




Pole Type




Self-service Type



Bakery Type




Elevated Type




Hanging Type

1.3 PART NAMES AND FUNCTIONS

1.3.1 FRONT VIEW (BENCH TYPE)



1.3.2 REAR VIEW (BENCH TYPE)



1.4 **OPERATION PANEL**

										Mode	Size	Under Line	Italic	Normal	Bold
										PgUp	Start	Reverse	Back Space	Char Delete	Line Delete
										PgDn	End	4	\rightarrow	→0← Zero	↔ T Tare
											⊘ Feed	7	8	9	
										▼ ESC	С	4	5	6) Print
										230	0	1	2	3	PLU
€	Q	W	E	R	Т	Υ	U	Ι	0	Р	,	#	\$	% @	*
Lower Case	Α	S	D	F	G	н	J	к	L	;	·	Edit	()	",	!
	Shift	Z	X	С	V	В	Ν	М	•	Space		ew Line	Сору	Insert	Enter

Keys for Usual Use


С	Used to delete an entered numerical value.	Mode	Used to display Menu Select screen.
PLU	Used to call a registered product data.	PgUp	Used to turn the previous page.
() Feed	Used to feed labels.	PgDn	Used to turn the next page.
O Print	Used to issue a label.		Used to jump to the top page.
€ Tare	Used to enter tare weight.		Used to jump to the end page.
→0← Zero	Used to reset a weigh to zero.	ESC	Used to escape from the current mode.

1.5 ADJUSTMENTS

1.5.1 LEVEL ADJUSTMENT (BENCH TYPE)


ACAUTION Install the machine horizontally to use.

Be sure to turn off the power switch before placing the machine on a stable platform, and adjust the machine inclination by turning the four level adjustment feet so that the bubble is located at the center of the level gauge. Accurate measurements cannot be performed if it is not installed horizontally.




1.5.2 OPERATION PANEL ANGLE ADJUSTMENT (BENCH TYPE)


To obtain a better view, adjust the angle of the operation panel within the range between 0 and 70 degrees.




1.6 LABEL / RECEIPT ROLL LOADING

1. Pull out the cassette from the main body.







2. Set a new roll around the roll holder and raise the roll stopper to fix the roll position.




3. Thread the paper as shown in the figures below.



4 For labels, fix the paper end with the backing paper stopper, and gently turn the winding bobbin counterclockwise until the label becomes tight.




5. Slide the label/receipt guide to help smooth paper feeding according to the paper width.




6. Push the cassette straight into the main body to return to its original position.

•Before inserting the cassette unit into the main body, ensure that nothing sticks to the magnet on the bottom of the cassette unit.

•Push the cassette slowly into the main body so as not to get your fingers caught.



7. For labels, press the [FEED] key on the key sheet to issue a label. At this time, confirm that the label is completely peeled off.




Confirm that the backing paper is wound up smoothly. If the backing paper is wound up diagonally, check that the label is set correctly.

1.7 REMOVING & REPLACING OF WEIGH PLATTER


1.7.1 REMOVING THE WEIGH PLATTER

When removing the weigh platter from the main body, lift the front side to pull out the two pins from the two rubber platter holders and remove the platter by pulling it to disengage the two hooks at the rear side of the platter.



1.7.2 REPLACING THE WEIGH PLATTER

When replacing the weigh platter onto the main body, engage the two hooks at the rear side of the platter and lower the platter so that the two pins on the bottom of the platter are inserted into holes of the rubber platter holders.



1.8.4 PRECAUTIONS WHEN USING CLEANING FLUIDS

Use a soft cloth and a neutral detergent to clean the machine.

Do not use thinner, benzene, etc. Doing so may damage the original safety functions. For some parts, use cleaning fluid (isopropyl alcohol).





Do not use cleaning fluid near fire as the fluid is flammable. Do not use cleaning fluid in a poorly ventilated area. Always provide adequate ventilation when cleaning.

Take the following actions in the event of an accident:

If the fluid gets in your eye

- Immediately wash your eye(s) with water for at least 15 minutes, and consult your doctor.
- · If you wear contact lenses, remove and wash them.

If the fluid comes into contact with your skin

- · Immediately rinse the area of contact with water, and then wash with soap.
- If you notice any skin abnormalities at the area of contact, or if any pain persists, consult your doctor.

If the fumes of the fluid are inhaled

- Immediately move the victim to an area where fresh air is available, and have the victim lie down and keep warm.
- · If breathing becomes difficult or stops, provide artificial respiration and seek medical attention immediately.


If the fluid is swallowed

- · Do not try to induce vomiting.
- $\cdot\,$ Do not give the victim anything to drink, and do not rinse the mouth.
- \cdot If vomiting occurs naturally, have the victim lean forward to reduce risk of aspiration.
- $\cdot\,$ Keep the victim warm and seek medical attention.

1.9 STARTING PROCEDURES

1.9.1 TURNING ON THE POWER

1. Push down the "I" side of the Power Switch to turn on the power.



 The Time Check screen appears. Then, check that displayed date and time agree with current date and time, and press the [ENTER] button on the screen to proceed to the next step.

Note: Refer to "Time/Date Set" menu in Adjust Mode when changing the date or time.



3. After a while, the initial screen appears.

PLV 0		21-JU	N-2007(TH	IU) 11:13	TARE kg
	eck the w		0.000		
	ter PLU M	vo. and p	ress [PL	UJ Key.	WEIGHT kg
PLU No. O				PRN MD. <manual></manual>	0.000
RIB STEAK	TOP SIRLOIN	ROUND STEAK	PORK CHOPS	SMOKED SAUSAGE	UNIT PRICE £/kg
ROAST	WHOLE T-BONE	BONELESS GROUND	MAINE	SALMON	0.00
BEEF	STEAK	BEEF EXTRA	LOBSTER FRESH	GUARANTE	TOTAL PRICE £
CASSETTE 1	HAM SANDWICH	HOT SWEET & SOUR WIN	TILAPIA FILLET SKIN-ON	VOID	0.00

1.9.2 PERFORMING ZERO ADJUSTMENT

1. If the weight value is not zero on the initial screen,

PLV O		21-JU	10) 11:15							
	eck the w ter PLU M									
PLU No.			4 SP	PRN MD. <manual></manual>	0.000					
RIB STEAK	TOP SIRLOIN WHOLE	ROUND STEAK BONELESS	PORK CHOPS BONELESS	SMOKED SAUSAGE	UNIT PRICE £7kg					
ROAST BEEF	T-BONE STEAK	GROUND BEEF EXTRA	MAINE LOBSTER FRESH	SALMON FILLET GUARANTE	TOTAL PRICE £					
CASSETTE 1	HAM SANDWICH	HOT SWEET & SOUR WIN	TILAPIA FILLET SKIN-ON	VOID	0.00					

Press the [ZERO] key on the key sheet to perform zero weight adjustment.



2. The "ZERO" indicator lights up and the weight value becomes zero.

PLV O		21-JU	N-2007(TH	10) 11:15	TARE kg
	eck the w	0.000			
	ter PLU N	ZERO WEIGHT kg			
PLU No. O			4 St	PRN MD. <manual></manual>	0.000
RIB STEAK	TOP SIRLOIN	ROUND STEAK	PORK CHOPS	SMOKED SAUSAGE	UNIT PRICE £/kg
ROAST	WHOLE T-BONE	BONELESS GROUND	MAINE	SALMON	0.00
BEEF	STEAK	BEEF EXTRA	LOBSTER FRESH	GUARANTE	TOTAL PRICE £
CASSETTE 1	HAM SANDWICH	HOT SWEET & SOUR WIN	TILAPIA FILLET SKIN-ON	VOID	0.00

1.9.3 GETTING BACK TO THE INITIAL SCREEN

1. To get back to the initial screen from a Menu Select screen, press either the "SALES" field or the icon at the bottom right on the screen.



2. The initial screen appears.


PLU ()	21-JU	N-2007(TI	HU) 11:13	TARE kg
	Check the	0.000			
1	Enter PLU	WEIGHT kg			
PLU N O	0.	1 💝		PRN MD. <manual></manual>	0.000
RIB STEA	SIRLOIN		PORK CHOPS	SMOKED SAUSAGE	UNIT PRICE £/kg
ROAS	WHOLE		BONELESS	SALMON	0.00
BÉÉF	STEAK	EXTRA	LOBSTER FRESH	GUARANTE	TOTAL PRICE £
CASSET 1	TE HAM SANDWIC	HOT SWEET & SOUR WIN	TILAPIA FILLET SKIN-ON	VOID	0.00

LABEL ISSUE


2

2.1 LABEL ISSUE WITHOUT OPERATOR

2.1.1 WEIGHING UNIT PRICE PRODUCTS



2. Enter a desired PLU number using the numeric keys and press the [PLU] key on the key sheet, or simply press a preset key on the screen where the product is allocated.



- **3.** When the product is preset as a traceable item, the traceability screen appears. See Chapter 4 for more details about traceability products.
- **4.** The selected PLU screen appears.


Without Preset Tare Weight

TARE kg		IU) 11:15	21-JUN-2007(THU) 11:							
	ZERO	'	ROAST BEEF							
0.000		COUPONMS 0	FIX UPR +WEIGHT	FIX UPR	F/P	U/P				
T PRICE £/kg	UNIT	-\$(U/P	SP.(U/P)	-%	-\$	SPECIAL				
4.00		0.00	0.00	0.0	0.00	0.00				
		PRN QTY	TOTALADD	S DATE	P DATE	-%(U/P)				
FAL PRICE £	тот	0	<add></add>	27-06-07	21-06-07	0.0				
0.00		FUNCTION GROUP	MULTI	CASSETTE 1	PEEL MD. <indiv></indiv>	PRN MD. <manual></manual>				

With F	With Preset Tare Weight										
PLU 6		21-JU	N-2007(TH	HU) 11:15	NET PT kg						
	RO	AST	0.050								
F	ZERO WEIGHT kg										
U/P	F/P	FIX UPR	FIX UPR +WEIGHT	COUPONMS 0	-0.050						
SPECIAL	-\$	-%	SP.(U/P)	-\$(U/P	UNIT PRICE £/kg						
0.00	0.00	0.0	0.00	0.00	1 00						
-%(U/P)	P DATE	S DATE	TOTALADD	PRN QTY	4.00						
0.0	21-06-07	27-06-07	<add></add>	0	TOTAL PRICE £						
PRN_MD. <manual></manual>	PEEL MD. <indiv></indiv>	CASSETTE 1	MULTI	FUNCTION GROUP	0.00						

Manual Tare Entry

To newly enter a tare weight or overwrite an existing tare weight, enter the tare weight using the numeric keys and press the "TARE" field on the screen.



5.

See Chapter 5 for more details about temporary change operations.

6. Put a product on the weigh platter.

PRODUCT



The weight is measured and the total price is calculated.

TARE kg	HU) 11:15	21-JUN-2007(THU) 11:							
0.000 WEIGHT kg	·	ROAST BEEF							
0.422	COUPONMS 0	FIX UPR +WEIGHT	FIX UPR	F/P	U/P				
NIT PRICE £/kg	-\$(U/P	SP.(U/P)	-%	-\$	SPECIAL				
4.00	0.00	0.00	0.0	0.00	0.00				
4.00	PRN QTY	TOTALADD	S DATE	P DATE	-%(U/P)				
FOTAL PRICE £	0	<add></add>	27-06-07	21-06-07	0.0				
1.69	FUNCTION GROUP	MULTI	CASSETTE 1	PEEL MD. <indiv></indiv>	PRN MD. <manual></manual>				

7	When "N	<u>/IANUAL</u>	" is set ir	n the Prir	nt Mode,	
	PLU 6		21-JU	V-2007(TH	10) 11:15	TARE kg
		RO	'	0.000		
	p					WEIGHT kg
	U/P	F/P	FIX UPR	COUPONMS	0.422	
	SPECIAL	-\$	-%	SP.(U/P)	-\$(U/P	UNIT PRICE £/kg
	0.00	0.00	0.0	0.00	0.00	1 00
	-%(U/P)	P DATE	S DATE	TOTALADD	PRN QTY	4.00
	0.0	21-06-07	27-06-07	<add></add>	0	TOTAL PRICE £
	PRN MD.	PEEL MD.	CASSETTE	MULTI	FUNCTION GROUP	1 60
	<manual></manual>	<indiv></indiv>	1	noeri	GROUP	

Press the [PRINT] key on the key sheet.



The label is issued.

				٦
	_	_		
0 2000	00 000004			
	ISHIDA SAKYO-KU	YOTO JAPA	N	-




Non-traceable products

When "AUTO" is set in the Print Mode,

	IU) 11:15	21-JUN-2007(THU) 11:1							
	ROAST BEEF								
0 V.4 4	COUPONMS 0	FIX UPR +WEIGHT	FIX UPR	F/P	U/P				
\$(U/P UNIT PRICE f	-\$(U/P	SP.(U/P)	-%	-\$	SPECIAL				
0.00	0.00	0.00	0.0	0.00	0.00				
RN QTY	PRN QTY	TOTALADD	S DATE	P DATE	-%(U/P)				
0 TOTAL PRICE	0	<add></add>	27-06-07	21-06-07	0.0				
GROUP 1.	FUNCTION GROUP	MULTI	CASSETTE 0	PEEL MD. <indiv></indiv>	PRN MD. <auto></auto>				

The label is automatically issued as soon as the weighing is stabilized.




2.1.2 WEIGHING FIXED PRICE PRODUCTS

1. Ensure that the initial screen is displayed.

느											
P	PLV O		21-JU	V-2007(TH	10) 11:15	TARE kg					
	: here 1	eck the w		0.000							
I	Ent	ter PLU P	vo. and p	ress [PL	J] Key.	ZERO WEIGHT kg					
F	PLU No. O			PRN MD. <manual></manual>	0.000						
	RIB STEAK	TOP SIRLOIN WHOLE	ROUND STEAK BONELESS	PORK CHOPS BONELESS	SMOKED SAUSAGE	UNIT PRICE £/kg					
	ROAST	T-BONE STEAK	GROUND BEEF	SALMON FILLET	0.00						
С	ASSETTE	HAM	EXTRA HOT SWEET &	FRESH TILAPIA FILLET	GUĂRĂNTE VOID	TOTAL PRICE £					
	I		SOUR WIN	SKIN-ON		0.00					

2. Enter a desired PLU number using the numeric keys and press the [PLU] key on the key sheet, or simply press a preset key on the screen where the product is allocated.




- **3.** When the product is preset as a traceable item, the traceability screen appears. See Chapter 4 for more details about traceability products.
- **4** The selected PLU screen appears.

Witho	Without Preset Tare Weight										
PLU 6		21-JU	N-2007(TH	HU) 11:15	TARE kg						
	RO	AST	-	0.000 ZERO WEIGHT kg							
U/P	F/P	FIX UPR	FIX UPR +WEIGHT	COUPONMS 0	0.000						
SPECIAL	-\$	-%	SP.(U/P)	-\$(U/P							
0.00	0.00	0.0	0.00	0.00							
-%(U/P)	P DATE	S DATE	TOTALADD	PRN QTY							
0.0	21-06-07	27-06-07	<add></add>	0	FIXED PRICE £						
PRN MD. <manual></manual>	PEEL MD. <indiv></indiv>	CASSETTE 1	MULTI	FUNCTION GROUP	4.00						

With F	With Preset Tare Weight											
PLU 6		21-JU	V-2007(TH	IV) 11:15	NET PT kg							
	ROAST BEEF 0.050											
<u>p</u>					ZERO WEIGHT kg							
U/P	F/P	FIX UPR	FIX UPR +WEIGHT	COUPONMS 0	-0.050							
SPECIAL	-\$	-%	SP.(U/P)	-\$(U/P								
0.00	0.00	0.0	0.00	0.00								
-%(U/P)	P DATE	S DATE	TOTALADD	PRN QTY								
0.0	21-06-07	27-06-07	<add></add>	0	FIXED PRICE £							
PRN MD. <manual></manual>	PEEL MD. <indiv></indiv>	CASSETTE 0	MULTI	FUNCTION GROUP	4.00							

Manual Tare Entry

To newly enter a tare weight or overwrite an existing tare weight, enter the tare weight using the numeric keys and press the "TARE" field on the screen.



- **5.** See Chapter 5 for more details about temporary change operations.
- 6. Put a product on the weigh platter.



The weight is measured but the fixed price stays same.

				<u> </u>				
TARE kg	10) 11:15	21-JUN-2007(THU) 11:1						
	ROAST BEEF							
0.422	COUPONMS 0	FIX UPR +WEIGHT	FIX UPR	F/P	U/P			
	-\$(U/P	SP.(U/P)	-%	-\$	SPECIAL			
	0.00	0.00	0.0	0.00	0.00			
	PRN QTY	TOTALADD	S DATE	P DATE	-%(U/P)			
FIXED PRICE £	0	<add></add>	27-06-07	21-06-07	0.0			
4.00	FUNCTION GROUP	MULTI	CASSETTE 0	PEEL MD. <indiv></indiv>	PRN MD. <manual></manual>			

7.	When "N	/ANUAL	" is set ir	nt Mode,		
	PLU 6		21-JU	N-2007(TH	10) 11:15	TARE kg
		RO	'			
	U/P	F/P	FIX UPR	FIX UPR +WEIGHT	COUPONMS 0	0.422
	SPECIAL	-\$	-%	SP.(U/P)	-\$(U/P	
	0.00	0.00	0.0	0.00	0.00	
	-%(U/P)	P DATE	S DATE	TOTALADD	PRN QTY	
	0.0	21-06-07	27-06-07	<add></add>	0	FIXED PRICE £
	PRN_MD. <manual></manual>	PEEL MD. <indiv></indiv>	CASSETTE 0	MULTI	FUNCTION GROUP	4.00

Press the [PRINT] key on the key sheet.








Non-traceable products

When "AUTO" is set in the Print Mode,

PLV 6		21-JU	N-2007(TH	10) 11:15	
	RO				
U/P	F/P	FIX UPR	FIX UPR +WEIGHT	COUPONMS	0.422
SPECIAL	-\$	-%	SP.(U/P)	-\$(U/P	
0.00	0.00	0.0	0.00	0.00	
-%(U/P)	P DATE	S DATE	TOTALADD	PRN QTY	
0.0	21-06-07	27-06-07	<add></add>	0	FIXED PRICE £
PRN MD. <auto></auto>	PEEL MD. <indiv></indiv>	CASSETTE 0	MULTI	FUNCTION GROUP	4.00

The label is automatically issued as soon as the weighing is stabilized.

0 200000 000004
SUPER ISHIDA SHOGOIN SAKYO-KU KYOTO JAPAN
Non-traceable products





PROCESSING FIXED PRICE PRODUCTS 2.1.3


Ensure that the initial screen is displayed. 1.

F	PLV O		21-JU	10) 11:15	TARE kg				
		eck the w ter PLU N							
1	JUNo. O			4 9 0	PRN MD. <manual></manual>	0.000			
	RIB STEAK	TOP SIRLOIN WHOLE	RÓUND STEAK BONELESS	PORK CHOPS BONELESS	SMOKED SAUSAGE	UNIT PRICE £/kg			
	ROAST BEEF	T-BONE STEAK	GROUND BEEF EXTRA	MAINE LOBSTER FRESH	SALMON FILLET GUARANTE	TOTAL PRICE £			
C	ASSETTE	HAM SANDWICH	HOT SWEET & SOUR WIN	TILAPIA FILLET SKIN-ON	VOID	0.00			

Enter a desired PLU number using the numeric keys and press the [PLU] key on the key 2. sheet, or simply press a preset key on the screen where the product is allocated.

kg

U




WIN

When the product is preset as a traceable item, the traceability screen appears. 3. See Chapter 4 for more details about traceability products.

4.	The selected PLU screen appears.							
	PLU 6		21-JU	N-2007(TH	10) 11:15	PCS	1	
		RO	FIXED W	EIGHT	kg			
	U/P	F/P	FIX UPR	FIX UPR +WEIGHT	COUPONMS 0			
	SPECIAL	-\$	-%	SP.(U/P)	-\$(U/P			
	0.00	0.00	0.0	0.00	0.00			
	-%(U/P)	P DATE	S DATE	TOTALADD	PRN QTY	FIXED	PRICE	£
	0.0	21-06-07	27-06-07	<add></add>	0			_
	PRN MD. <manual></manual>	PEEL MD. <indiv></indiv>	CASSETTE 1	MULTI	FUNCTION GROUP		4.0	0

- 5.
- See Chapter 5 for more details about temporary change operations.



Note: To stop printing, press the [PRINT] key again.

2.1.4 PROCESSING FIXED WEIGHT/FIXED UNIT PRICE PRODUCTS

1. Ensure that the initial screen is displayed.

EXAMPLE PLU No.6 "Roast Beef"

PLU O		21-JU	10) 11:15	TARE kg						
	eck the w ter PLU N									
PLU No.			450	PRN MD. <manual></manual>	ZERO WEIGHT kg					
RIB STEAK	TOP SIRLOIN WHOLE	ROUND STEAK BONELESS	PORK CHOPS BONELESS	SMOKED SAUSAGE	UNIT PRICE £/kg					
ROAST BEEF	T-BONE STEAK	GROUND BEEF EXTRA	MAINE LOBSTER FRESH	SALMON FILLET GUARANTE	TOTAL PRICE £					
CASSETTE 1	HAM SANDWICH	HOT SWEET & SOUR WIN	TILAPIA FILLET SKIN-ON	VOID	0.00					

2. Enter a desired PLU number using the numeric keys and press the [PLU] key on the key sheet, or simply press a preset key on the screen where the product is allocated.

	or	PLU	→ [6
7(THU) 11:15 TARE kg	N-2007(TH	21-JU		PLV O
operation. 0.000	fore ope	eight be	eck the w	Che
[PLU] key. ZERO WEIGHT kg	ress [PL	lo. and p	ter PLU N	En En
	<u>KSD</u>		- A A	No .
	PORK	ROUND	TOP	'nn 🕽 🗖
	CHOPS BONELESS	STEAK BONELESS	SIRÍOIN WHOLE	Ч, _{Ак}
	MAINE LOBSTER FRESH	GROUND BEEF EXTRA	T-BONE STEAK	ROAST BEEF
	TILAPIA FILLET SKIN-ON	HOT SWEET & SOUR WIN	HAM SANDWICH	CASSETTE 1


3. When the product is preset as a traceable item, the traceability screen appears. See Chapter 4 for more details about traceability products.

4.	The sele	ected PL	6.			
	PLU 6					
		RO	FIXED WEIGHT kg			
	U/P	F/P	FIX UPR	FIX UPR +WEIGHT	COUPONMS 0	FIXED U.PRI £/kg
	SPECIAL 0.00	-\$ 0.00	-% 0.0	SP.(U/P) 0.00	-\$(U/P 0.00	4.00
	-%(U/P) 0.0	P DATE 21-06-07	S DATE 27-06-07	TOTALADD <add></add>	PRN QTY O	TOTAL PRICE £
	PRN MD. <manual></manual>	PEEL MD. <indiv></indiv>	CASSETTE 1	MULTI	FUNCTION GROUP	0.00

5.

See Chapter 5 for more details about temporary change operations.

6. Enter the fixed weight using the numeric keys on the key sheet and press the "FIXED WEIGHT" field.



7. Press the [PRINT] key on the key sheet to issue the labels.



The label is issued.




0 200000 000004
SUPER ISHIDA

Non-traceable products

Traceable products



The next label is issued.



Note: To stop printing, press the [PRINT] key again.


2.2 LABEL ISSUE WITH OPERATORS

2.2.1 WEIGHING UNIT PRICE PRODUCTS

1. Ensure that the initial screen is displayed.



2. Enter a desired PLU number using the numeric keys and press the [PLU] key on the key sheet, or simply press a preset key on the screen where the product is allocated.



PLV 0		21-JU	IU) 11:15	TARE kg	
	eck the w ter PLU M		0.000		
N₀.			PRN MD.	ZERO WEIGHT kg	
	TOP SIRLOIN		PORK	<manual> SMOKED SAUSAGE</manual>	UNIT PRICE £/kg
	T-BONE STEAK	BONELESS GROUND BEEF EXTRA	BONELESS MAINE LOBSTER FRESH	SALMON FILLET GUARANTE	0.00
CASSETTE 1	HAM SANDWICH	HOT SWEET & SOUR WIN	TILAPIA FILLET SKIN-ON	VOID	0.00

- 3. When the product is preset as a traceable item, the traceability screen appears.
 - See Chapter 4 for more details about traceability products.
- **4**_ The selected product screen appears.

Without Preset Tare Weight


	U								
TARE kg	HU) 11:15	21-JUN-2007(THU) 11:15							
0.000	•	BFFF	AST	RO					
ZERO WEIGHT kg									
0.000	JODY	ERIC	JONE	BETTY	JACK				
UNIT PRICE £/kg	SUBTOTAL DISPLAY	FIX UPR +WEIGHT	FIX UPR	F/P	U/P				
4.00	-£(U/P)	SP.(U/P)	-%	-£	SPECIAL				
TOTAL PRICE £	0.00	0.00	0.0	0.00	0.00				
0.00	OPERATOR GROUP	TARE	VOID	TOTAL DISPLAY	-%(U/P) 0.0				

With Preset Tare Weight

PLU 6		21-JU	IV) 11:15	NET PT kg	
	RO	AST	BEEF		0.050 ZERO WEIGHT kg
JACK	BETTY	JONE	ERIC	JODY	-0.050
U/P	F/P	FIX UPR	FIX UPR +WEIGHT	SUBTOTAL DISPLAY	UNIT PRICE £/kg
SPECIAL	-£	-%	SP.(U/P)	-€(U/P)	4. 00
0.00	0.00	0.0	0.00	0.00	TOTAL PRICE £
-%(U/P) 0.0	TOTAL DISPLAY	VOID	TARE	OPERATOR GROUP	0.00

Manual Tare Entry

To newly enter a tare weight or overwrite an existing tare weight, enter the tare weight using the numeric keys and press the "TARE" field on the screen.



- **5.** See Chapter 5 for more details about temporary change operations.
- 6. Put a product on the weigh platter.



The weight is measured and the total price is calculated.

PLV 6		21-JU	10) 11:15		
	RO	<u> 0.000 </u>			
p.		WEIGHT kg			
JACK	BETTY	JONE	ERIC	JODY	0.422
U/P	F/P	FIX UPR	FIX UPR +WEIGHT	SUBTOTAL DI SPLAY	UNIT PRICE £/kg
SPECIAL	-£	-%	SP.(U/P)	-£(U/P)	4.00
0.00	0.00	0.0	0.00	0.00	TOTAL PRICE £
-%(U/P) 0.0	TOTAL DISPLAY	VOID	TARE	OPERATOR GROUP	1.69

7. Press a operator button on the screen to issue the label.

EXAMPLE Operator "BETTY"								
PLV 6		21-JU	10) 11:15					
	RO	A ST	BEEF	'	0.000			
5	no				WEIGHT kg			
JACK	BETTY	JONE	ERIC	JODY	0.422			
U/P	βm	FIX UPR	FIX UPR +WEIGHT	SUBTOTAL DISPLAY				
SPECIAL		-%	SP.(U/P)	-£(U/P)	4.00			
0.00		0.0	0.00	0.00	TOTAL PRICE £			
-%(U/P) 0.0	TOTAL DISPLAY	VOID	TARE	OPERATOR GROUP	1.69			

The label is issued.

0 2000	00 000004		
SUPER	ISHIDA SAKYO-KU		

2.2.2 WEIGHING FIXED PRICE PRODUCTS

1 <u>Ensure that the initial screen is displayed.</u>

PLV O		21-JUN-2007(THU) 11:15 TARE kg							
	eck the w		0.000						
	ter PLU M	vo. and p	ress [PL	oj key.	ZERO WEIGHT kg				
PLU No. O	100 M		4 9 0	PRN MD. <manual></manual>	0.000				
RIB STEAK	TOP SIRLOIN	ROUND STEAK	PORK CHOPS	SMOKED SAUSAGE	UNIT PRICE £/kg				
ROAST	WHOLE T-BONE	BONELESS GROUND	BONELESS	SALMON	0.00				
BEEF	STEAK	BEEF EXTRA	LÖBSTER FRESH	GUARANTE	TOTAL PRICE £				
CASSETTE 1	HAM SANDWICH	HOT SWEET & SOUR WIN	TILAPIA FILLET SKIN-ON	VOID	0.00				

2. Enter a desired PLU number using the numeric keys and press the [PLU] key on the key sheet, or simply press a preset key on the screen where the product is allocated.

EXAMP 6		יוט	toast Bee	ef"	
PLV O		21-JU	N-2007(TH	HU) 11:15	TARE kg
			fore ope ress [PL		<u> 0.000 </u>
		vo. anu p	ITESS [PL	oj key.	ZERO WEIGHT kg
No.			4 St	PRN MD. <manual></manual>	0.000
(unk	TOP SIRLOIN	ROUND	PORK CHOPS	SMOKED SAUSAGE	UNIT PRICE £/kg
Ч <u>Г</u> АК	WHOLE	STEAK BONELESS	BONELESS		l 0.00
ROAST BEEF	T-BONE STEAK	GROUND BEEF EXTRA	MAINE LOBSTER FRESH	SALMON FILLET GUARANTE	TOTAL PRICE £
CASSETTE 1	HAM SANDWICH	HOT SWEET & SOUR WIN	TILAPIA FILLET SKIN-ON	VOID	0.00

- **3.** When the product is preset as a traceable item, the traceability screen appears.
 - See Chapter 4 for more details about traceability products.
- **4.** The selected product screen appears.


Without Preset Tare Weight

PLV 6		21-JU	HU) 11:15	TARE kg	
	RO	AST	0.000 ZERO WEIGHT kg		
JACK	BETTY	JONE	ERIC	JODY	0.000
U/P	F/P	FIX UPR	FIX UPR +WEIGHT	SUBTOTAL DISPLAY	
SPECIAL	-£	-%	SP.(U/P)	-€(U/P)	
0.00	0.00	0.0	0.00	0.00	FIXED PRICE £
-%(U/P) 0.0	TOTAL DISPLAY	VOID	TARE	OPERATOR GROUP	4.00

With Preset Tare Weight											
PLV 6		21-JU	N-2007(TH	HU) 11:15	NET PT kg						
	RO	AST	'	<u> 0.050 </u>							
5					ZERO WEIGHT kg						
JACK	BETTY	JONE	ERIC	JODY	<u>-0.050</u>						
U/P	F/P	FIX UPR	FIX UPR +WEIGHT	SUBTOTAL DISPLAY							
SPECIAL	-£	-%	SP.(U/P)	-€(U/P)							
0.00	0.00	0.0	0.00	0.00	FIXED PRICE £						
<mark>-%(U/P)</mark> 0.0	TOTAL DISPLAY	VOID	TARE	OPERATOR GROUP	4.00						

Manual Tare Entry

To newly enter a tare weight or overwrite an existing tare weight, enter the tare weight using the numeric keys and press the "TARE" field on the screen.



- **5.** See Chapter 5 for more details about temporary change operations.
- 6. Put a product on the weigh platter.

PRODUCT



The weight is measured and the total price is calculated.

PLU 6		21-JU			
	RO				
JACK	BETTY	JONE	ERIC	JODY	0.422
U/P	F/P	FIX UPR	FIX UPR +WEIGHT	SUBTOTAL DISPLAY	
SPECIAL	-£	-%	SP.(U/P)	-£(U/P)	
0.00	0.00	0.0	0.00	0.00	FIXED PRICE £
-%(U/P) 0.0	TOTAL DISPLAY	VOID	TARE	OPERATOR GROUP	4.00

7. Press a operator button on the screen to issue the label.

EXAMP	EXAMPLE Operator "BETTY"										
PLU 6		21-JU	HU) 11:16								
	RO										
JACK		JONE	ERIC	JODY	0.422						
U/P	(m)	FIX UPR	FIX UPR +WEIGHT	SUBTOTAL DI SPLAY							
SPECIAL	()	-%	SP.(U/P)	-€(U/P)							
0.00		0.0	0.00	0.00	FIXED PRICE £						
-%(U/P) 0.0	TOTAL DISPLAY	VOID	TARE	OPERATOR GROUP	4.00						

The label is issued.


0"200000"000004"	
SUPER ISHIDA shogoin sakyo-ku kyoto japan	

2.2.3 PROCESSING FIXED PRICE PRODUCTS

1. Ensure that the initial screen is displayed.

PLV O		21-JU	V-2007(TH	10) 11:15	TARE kg				
	eck the w ter PLU N								
PLU No. 0			4 9 0	PRN MD. <manual></manual>	0.000				
RIB STEAK	TOP SIRLOIN WHOLE	ROUND STEAK BONELESS	PORK CHOPS BONELESS	SMOKED SAUSAGE	UNIT PRICE £/kg				
ROAST BEEF	T-BONE STEAK	GROUND BEEF EXTRA	MAINE LOBSTER FRESH	SALMON FILLET GUARANTE	TOTAL PRICE £				
CASSETTE 1	HAM SANDWICH	HOT SWEET & SOUR WIN	TILAPIA FILLET SKIN-ON	VOID	0.00				

2. Enter a desired PLU number using the numeric keys and press the [PLU] key on the key sheet, or simply press a preset key on the screen where the product is allocated.



3. When the product is preset as a traceable item, the traceability screen appears. See Chapter 4 for more details about traceability products.

4.	The sele	cted PL	3.					
	PLU 6		21-JU	N-2007(TH	10) 11:15	PCS	1	
		RO	AST	BEEF		FIXED V	FIGHT	kg
	JACK	BETTY	JONE	ERIC	JODY			
	U/P	F/P	FIX UPR	FIX UPR +WEIGHT	SUBTOTAL DISPLAY			
	SPECIAL	-£	-%	SP.(U/P)	-€(U/P)	FIXED	PRICE	£
	0.00	0.00	0.0	0.00	0.00			
	-%(U/P) 0.0	TOTAL DISPLAY	VOID	TARE	OPERATOR GROUP		4.0)()

- **5**. S
 - See Chapter 5 for more details about temporary change operations.

6. Press a operator button on the screen to issue the label.

EXAMP	LE Ope						
PLV 6		21-JU	N-2007(TH	IU) 11:15	PCS	1	
	RO	AST	FIXED V	VEIGHT	kg		
JACK	BETTY	JONE	ERIC	JODY			
U/P	(^I m)	FIX UPR	FIX UPR +WEIGHT	SUBTOTAL DISPLAY			
SPECIAL	\square	-%	SP.(U/P)	-£(U/P)	FIXED	PRICE	£
0.00		0.0	0.00	0.00			
-%(U/P) 0.0	TOTAL DISPLAY	VOID	TARE	OPERATOR GROUP		4.0)()

The label is issued.

0 2000	00 000004		
SUPER	ISHIDA	куото	

2.2.4 PROCESSING FIXED WEIGHT/FIXED UNIT PRICE PRODUCTS

1. Ensure that the initial screen is displayed.

EXAMPLE PLU No.6 "Roast Beef"

PLU O		21-JU	V-2007(TH	10) 11:15	TARE kg					
	eck the w ter PLU N									
PLU No.			450	PRN MD. <manual></manual>	ZERO WEIGHT kg					
RIB STEAK	TOP SIRLOIN WHOLE	ROUND STEAK BONELESS	PORK CHOPS BONELESS	SMOKED SAUSAGE	UNIT PRICE £/kg					
ROAST BEEF	T-BONE STEAK	GROUND BEEF EXTRA	MAINE LOBSTER FRESH	SALMON FILLET GUARANTE	TOTAL PRICE £					
CASSETTE 1	HAM SANDWICH	HOT SWEET & SOUR WIN	TILAPIA FILLET SKIN-ON	VOID	0.00					

2. Enter a desired PLU number using the numeric keys and press the [PLU] key on the key sheet, or simply press a preset key on the screen where the product is allocated.

6	→ [PLU	or		
PLV 0		21-JU	N-2007(TH	10) 11:15	TARE kg
	eck the w ter PLU N				0.000
		vo. and p	1635[FL	ol Key.	ZERO WEIGHT kg
No.		1	450	PRN MD. <manual></manual>	0.000
	TOP SIRLOIN WHOLE	ROUND STEAK BONELESS	PORK CHOPS BONELESS	SMOKED SAUSAGE	
ROAST BEEF	T-BONE STEAK	GROUND BEEF EXTRA	MAINE LOBSTER FRESH	SALMON FILLET GUARANTE	0.00 TOTAL PRICE £
CASSETTE 1	HAM SANDWICH	HOT SWEET & SOUR WIN	TILAPIA FILLET SKIN-ON	VOID	0.00


3. When the product is preset as a traceable item, the traceability screen appears. See Chapter 4 for more details about traceability products.

4.	The sele	cted PL	6.			
	PLV 6		21-JU	N-2007(TH	HU) 11:15	
		RO	AST	BEEF	_	FIXED WEIGHT kg
	JACK	BETTY	JONE	ERIC	JODY	FIXED U.PRI £/kg
	U/P	F/P	FIX UPR	FIX UPR +WEIGHT	SUBTOTAL DISPLAY	4.00
	SPECIAL	-£	-%	SP.(U/P)	-€(U/P)	TOTAL PRICE £
	0.00	0.00	0.0	0.00	0.00	
	-%(U/P) 0.0	TOTAL DISPLAY	VOID	TARE	OPERATOR GROUP	0.00

5.

See Chapter 5 for more details about temporary change operations.

6. Enter the fixed weight using the numeric keys on the key sheet and press the "FIXED WEIGHT" field.



7. Press a operator button on the screen to issue the label.

EXAMP	Dpe	rator "Bl	ETTY"		
PLU 6		21-JU	N-2007(TH	HU) 11:15	
	DO		FIXED WEIGHT kg		
<u>F</u>	KU	нэт	BEEF		0.858
JACK	BETTA	JONE	ERIC	JODY	FIXED U.PRI £/kg
U/P	ر m	FIX UPR	FIX UPR +WEIGHT	SUBTOTAL DI SPLAY	4.00
SPECIAL		-%	SP.(U/P)	-€(U/P)	TOTAL PRICE £
0.00		0.0	0.00	0.00	
-%(U/P) 0.0	TOTAL DISPLAY	VOID	TARE	OPERATOR GROUP	3.43

The label is issued.



RECEIPT ISSUE



3.1 SALES BY THE SAME OPRATOR

- Ensure that the initial screen is displayed. 1. 21-JUN-2007(THU) 11:20 PLU 0 TARE kg () Check the weight before operation. Enter PLU No. and press [PLU] key. ZERO WEIGHT PLU No 0 UNIT PRICE DISPLAY TOTAL PRIC KEY LOC <0N>
- **2-1** Select a desired product category by pressing the corresponding field on the screen.

EXAMPLE Select "Meat" category. PLU 0 21-JUN-2007(THU) 11:20 TARE kg Check the weight before operation. Enter PLU No. and press [PLU] key. PLU No. 0 TOTAL DISPLAY KEY LOCK COND Cond

2-2 The PLU preset screen for the selected category appears. Then, enter a desired PLU number using the numeric keys and press the [PLU] key on the key sheet, or simply press a preset key on the screen where a desired product is allocated.

EXAMP		א נו	No.1 "Ril)r	b Steak".	
PLV 0		21-JU	V-2007(TH	HU) 11:20	TARE kg
Che	eck the w	veight be	fore ope ress [PL	eration.	<u> 0.000 </u>
	ler PLU r	vo. and p	ress [PL	oj key.	ZERO WEIGHT kg
STEAK	TOP SIRLOIN WHOLE	ROUND STEAK BONELESS	PORK CHOPS BONELESS	SMOKED SAUSAGE	0.000
					UNIT PRICE £/kg
$+\langle \rangle$					0.00
					TOTAL PRICE £
					0.00

- 2-3 The PLU screen appears. Weighing Unit Price PLU 21-JUN-2007(THU) 11:20 PLU 1 PT ka RIB 0.05 **STEAK** ZERO WEIGHT kg -() .05 OPE 001 OPE 002 OPE 003 OPE 004 OPE 005 UNIT PRICE OPE 010 OPE 006 OPE 007 OPE 008 OPE 009 3. OPE 011 OPE 012 OPE 013 OPE 014 OPE 015 TOTAL PRIC OPERATOR GROUP TARE TARE TARE TARE
- **2-4** Put a product on the weigh platter.




PLU 1		21-JU	HU) 11:20			
		RIE		<u>0.050</u>		
5		STE4	AK		WEIGHT kg	
OPE 001	OPE 002	OPE 003	OPE 004	OPE 005	0.362	
OPE 006	OPE 007	OPE 008	OPE 009	OPE 010	UNIT PRICE £/kg	
OPE 011	OPE 012	OPE 013	OPE 014	OPE 015	5.98 TOTAL PRICE £	
TARE	TARE	TARE	TARE	OPERATOR GROUP	1.44	


2-5 Press a button on the screen for the operator who has sold the product.

EXAMPLE Select "Operator 002".


PLU 1		21-JU	V-2007(TI	IU) 11:20	NET PT kg		
		RIE STE4					
OPE 001		OPE 003	OPE 004	OPE 005	0.362		
OPE 006	or h	OPE 008	OPE 009	OPE 010	UNIT PRICE £/kg		
OPE 011	OPE	OPE 013	OPE 014	OPE 015	TOTAL PRICE £		
TARE	TARE	TARE	TARE	OPERATOR GROUP	1.44		



3-1 Select a desired product category by pressing the corresponding field on the screen.



3-2 The PLU preset screen for the selected category appears. Then, enter a desired PLU number using the numeric keys and press the [PLU] key on the key sheet, or simply press a preset key on the screen where a desired product is allocated.




3-3 The PLU screen appears.


Fixed	Price	PLU					
PLU 102		21-JU	N-2007(TI	IU) 11:20	PCS	1	
		ie lo Sh c	FIXED V	VEIGHT	kg		
OPE 001	OPE 002	OPE 003	OPE 004	OPE 005			
OPE 006	OPE 007	OPE 008	OPE 009	OPE 010			
OPE 011	OPE 012	OPE 013	OPE 014	OPE 015	FIXED		f
TARE	TARE	TARE	TARE	OPERATOR GROUP		4.5	50

3-4 Press a button on the screen for the operator who has sold the product.

EXAMP	LE Sele	ect "Ope	rator 002	2".			
PLU 102		21-JU	N-2007(TH	HU) 11:20	PCS	1	
	FIXED W	EIGHT	kg				
OPE 001	OPE 002	OPE 003	OPE 004	OPE 005			
OPE 006		OPE 008	OPE 009	OPE 010			
OPE 011	OPE	OPE 013	OPE 014	OPE 015	FIXED		f
TARE	TARE	TARE	TARE	OPERATOR GROUP		4.5	0



4-1 Select a desired product category by pressing the corresponding field on the screen.



4-2 The PLU preset screen for the selected category appears. Then, enter a desired PLU number using the numeric keys and press the [PLU] key on the key sheet, or simply press a preset key on the screen where a desired product is allocated.

EXAMPLE Select PLU No.201 "Live Wild Cherry Clam". 2 0 PLU or OP 2 PLU 102 21-JUN-2007(THU) 11:20 MAINE .0BSTER ITEMS FRESH D۵ 2PC(S) LAYER DIP HOT BARBECUE SPARE RI HAM SANDWICH TOTAL BREAKFST £6.23 SUBTOTAL £5.94 In VAT EXCL £0.29 VAT INCL (£0.00) ADDED PRICE £

4-3 The PLU screen appears.

Weigł	ning Fi	ixed P	rice P	LU	
PLU 201		21-JU	V-2007(TH	HU) 11:21	TARE kg
₽ LI	VE			RRYS	0.000
r.	CL	.AM(l	JSA)		ZERO WEIGHT kg
OPE 001	OPE 002	OPE 003	OPE 004	OPE 005	0.000
OPE 006	OPE 007	OPE 008	OPE 009	OPE 010	
OPE 011	OPE 012	OPE 013	OPE 014	OPE 015	FIXED PRICE £
TARE	TARE	TARE	TARE	OPERATOR GROUP	1.78


4-4 Put a product on the weigh platter.



PLV 201	VE h CL				TARE kg 0.000 WEIGHT kg	
OPE 001	OPE 002	OPE 002	OPE 002	OPE 002 OPE 003 OPE 00	OPE 005	<u> </u>
OPE 006	OPE 007	OPE 008	OPE 009	OPE 010		
OPE 011	OPE 012	OPE 013	OPE 014	OPE 015	FIXED PRICE £	
TARE	TARE	TARE	TARE	OPERATOR GROUP	1.78	

EXAMP	LE Sele	ect "Ope	rator 002	2".	
PLU 201		21-JU	N-2007(TI	HU) 11:21	TARE kg
<u>₽</u> (LI	VE_h			RYS	0.000
	CL	.AM(l	JSA)		WEIGHT kg
OPE 001	OPE 002	OPE 003	OPE 004	OPE 005	0.410
OPE 006	op M	OPE 008	OPE 009	OPE 010	
OPE 011	OPE	OPE 013	OPE 014	OPE 015	FIXED PRICE £
TARE	TARE	TARE	TARE	OPERATOR GROUP	1.78

4-5 Press a button on the screen for the operator who has sold the product.






5-1 Select a desired product category by pressing the corresponding field on the screen.



5-2 The PLU preset screen for the selected category appears. Then, enter a desired PLU number using the numeric keys and press the [PLU] key on the key sheet, or simply press a preset key on the screen where a desired product is allocated.



5-3 The PLU screen appears.

Fixed Unit Price PLU

_								
	10) 11:21	V-2007(TH	21-JU		PLU 4			
FIXED WEIGHT kg		PORK CHOPS						
	BONELESS SIRLOIN							
FIXED U.PRI £/kg	OPE 005	OPE 004	OPE 003	OPE 002	OPE 001			
3.68	OPE 010	OPE 009	OPE 008	OPE 007	OPE 006			
TOTAL PRICE £	OPE 015	OPE 014	OPE 013	OPE 012	OPE 011			
0.00	OPERATOR GROUP	TARE	TARE	TARE	TARE			

5-4

Enter the weight using the numeric keys on the key sheet, and press the "Fixed Weight" field on the screen.

EXAMPLE Weight "400g"



PLU 4		21-JU	N-2007(TH	10) 11:21	
	PO	RK C	HOPS		FIXED WEIGHT kg
📑 🖪	DNEL	ESS	SIRL	OIN	∩0.400
OPE 001	OPE 002	OPE 003	OPE 004	OPE 005	
OPE 006	OPE 007	OPE 008	OPE 009	OPE 010	낭 3.68
OPE 011	OPE 012	OPE 013	OPE 014	OPE 015	TOTAL PRICE £
TARE	TARE	TARE	TARE	OPERATOR GROUP	1.47

5-5 Press a button on the screen for the operator who has sold the product.

EXAMP	LE Sele	ect "Ope	rator 002	2".	
PLU 4		21-JU	N-2007(TI	10) 11:21	
	PO	RK C	HOPS		FIXED WEIGHT kg
5 B(DNEL	ESS	SIRL	OIN	0.400
OPE 001		OPE 003	OPE 004	OPE 005	FIXED U.PRI £/kg
OPE 006	<u>ա</u> հ	OPE 008	OPE 009	OPE 010	3.68
OPE 011	OPELS	OPE 013	OPE 014	OPE 015	TOTAL PRICE £
TARE	TARE	TARE	TARE	OPERATOR GROUP	1.47



6. Press the subtotal field on the screen to display more detailed subtotal data.



7. The detailed subtotal screen appears for confirmation of product registrations. Then, confirm that the detail of the transaction is correct.

SUBTOT	4L	2	1-JVI	N-2007(TH	HU) 11:22	ITI	EMS		4PC(S)
OP 2			τοτά		£9.64	(1)RIB	STEAK	
FIDELITY	OPOINT	r(s)	SUBT VATE VATI	XCL.	£9.19 £0.45 (£0.00)		£/kg 3.98	kg 0.362	£ 1.44
RECEIPT DELETE	RECEIPT <print></print>	OF DRA	PEN WER	CREDIT	OTHER TRAN CASH	(102)M	IAINE LO	BSTERFRE:
VOID	COUPON PAY		PRN PRN>			£/P	C(S) 4.50	PC(S) 1	£ 4.50
						(201)LI	VE WILD	CHERRYS'
					SUBTOTAL GROUP			kg 0.410	£ 1.78

8. Press the [PRINT] key on the key sheet to issue the receipt.



MEMBER SAVINGS	
* RECEIPT FOR PURCH ISHIDA JAPAN http://www.ishida.co.jp 21-JUN-200711:20	
PLU <u>f/kg</u> kg RIB STEAK	f
1 3.98 0.362 Fidelity point: O paint(5)	1.44
PLU <u>f</u> /Pcs Pcs MAINE LOBSTER FRESH DAILY	f
102 4.50 1 FIDELITY POINT: O POINT(5)	4.50
PLU <u>f/kg</u> kg LIVE WILD CHERRYSTONE CLAM(USA)	f
201 0.410 Fidelity point: o point(s)	1.78
PLU <u>f/kg</u> kg PORK CHOPS BONELESS SIRLOIN	f
4 3.68 0.400 FIDELITY POINT: 0 POINT(5)	1.47
^{4 items} Sub-total:	9.19
Total:	9.64 19.64
TOTAL FIDELITY POINT: 21/06/2007 11:21 No. 0046	O POINT MACHINE OI
0 200000 909642 Welcome again Thank You	

The Subtotal screen appears for the settlement. SUBTOTAL(HOLD) 21-JUN-2007(THU) 11:22 ITEMS 4PC(S) TOTAL £9.64 OP 2 TENDERD £9.64 SUBTOTAL VAT EXCL VAT INCL £9.19 £0.45 (£0.00) CHANGE £0.00 **OPOINT(S)** FIDELITY OTHER TRAN CASH RECEIPT RECEIPT DELETE OPEN DRAWER CASH CREDIT <PRINT> £9.64 TAX PRN COUPON COUPON PAY VOID <NO-PRN> £0.00 CREDIT £0.00 O.THAN CASH SUBTOTAL GROUP £0.00

3.2 SALES BY DIFFERENT OPRATORS

Ensure that the initial screen is displayed.




2-1 EXAMPLE Product registration by "Operator 002"

Select a desired product category by pressing the corresponding field on the screen.

EXAMPLE Sele	ect "Meat" category.	
PLV O	21-JUN-2007(THU) 11:2	D TARE kg
	veight before operation. No. and press [PLU] key.	
		ZERO WEIGHT kg
PLU No.		0.000
		UNIT PRICE £/kg
CSIS		0.00
		TOTAL PRICE £
		0.00

2-2 The PLU preset screen for the selected category appears. Then, enter a desired PLU number using the numeric keys and press the [PLU] key on the key sheet, or simply press a preset key on the screen where a desired product is allocated.



- 2-3 The PLU screen appears. Weighing Unit Price PLU 21-JUN-2007(THU) 11:20 PLU 1 PT ka RIB 0.05 **STEAK** ZERO WEIGHT kg -() .05 OPE 001 OPE 002 OPE 003 OPE 004 OPE 005 UNIT PRICE OPE 010 OPE 006 OPE 007 OPE 008 OPE 009 3. OPE 011 OPE 012 OPE 013 OPE 014 OPE 015 TOTAL PRIC OPERATOR GROUP TARE TARE TARE TARE
- **2-4** Put a product on the weigh platter.




PLU 1		21-JU RIE STE	3	HU) 11:20	0.050 WEIGHT kg
OPE 001	OPE 002	OPE 003	OPE 004	OPE 005	0.362
OPE 006	OPE 007	OPE 008	OPE 009	OPE 010	UNIT PRICE £/kg
OPE 011	OPE 012	OPE 013	OPE 014	OPE 015	TOTAL PRICE £
TARE	TARE	TARE	TARE	OPERATOR GROUP	1.44

2-5 Press a button on the screen for the operator who has sold the product.


EXAMPLE Select "Operator 002".

PLU 1		21-JU	V-2007(TI	HU) 11:20	NET PT kg
		RIE			0.050
5		STE4	AK 🛛		WEIGHT kg
OPE 001		OPE 003	OPE 004	OPE 005	0.362
OPE 006	op m	OPE 008	OPE 009	OPE 010	UNIT PRICE £/kg
OPE 011	OPER	OPE 013	OPE 014	OPE 015	5.98
TARE	TARE	TARE	TARE	OPERATOR GROUP	1.44




3-1 EXAMPLE Product registration by "Operator 002"

Select a desired product category by pressing the corresponding field on the screen.



3-2 The PLU preset screen for the selected category appears. Then, enter a desired PLU number using the numeric keys and press the [PLU] key on the key sheet, or simply press a preset key on the screen where a desired product is allocated.

EXAMPLE Select PLU No.102 "Maine Lobster".



The PLU screen appears. 3-3 Fixed Price PLU PLU 102 21-JUN-2007(THU) 11:20 PCS 1 MAINE LOBSTER FIXED WEIGHT kg FRESH DAILY OPE 002 OPE 003 OPE 004 OPE 001 OPE 005 OPE 006 OPE 007 OPE 010 OPE 008 OPE 009 FIXED PRICE OPE 011 OPE 012 OPE 013 OPE 014 OPE 015 4.50 OPERATOR GROUP TARE TARE TARE TARE Press a button on the screen for the operator who has sold the product. 3-4 EXAMPLE Select "Operator 002". PLU 102 21-JUN-2007(THU) 11:20 PCS 1 MAINE LOBSTER FIXED WEIGHT kg FRESH DAILY OPE 002 OPE 003 OPE 001 OPE 004 OPE 005 m OPE 006 OPP OPE 008 OPE 009 OPE 010 FIXED PRICE OPE 011 OPE OPE 013 OPE 014 OPE 015 4.50 OPERATOR GROUP TARE TARE TARE TARE The subtotal for the selected operator is shown on the screen. 3-5 PLU 102 21-JUN-2007(THU) 11:20 OP 2 MAINE LOBSTER ITEMS FRESH DAILY 2PC(S)E PLU No TOTAL 102 £6.23 DISPLAY SUBTOTAL £5.94 VAT EXCL £0.29 VAT INCL (£0.00) ADDED PRICE £ KEY LOO <0N> **4-1 EXAMPLE** Product registration by "Operator 001" Select a desired product category by pressing the corresponding field on the screen.



4-2 The PLU preset screen for the selected category appears.

Then, enter a desired PLU number using the numeric keys and press the [PLU] key on the key sheet, or simply press a preset key on the screen where a desired product is allocated.

EXAMP				Live Wild	d Cherry Clam". I r
PLV 0		21-JU	V-2007(TI	10) 11:21	TARE kg
Che	eck the w	veight be	fore ope	eration.	0.000
	ter PLU r	Vo. and p	ress	oj key.	ZERO WEIGHT kg
LIVE WIL CHERRYST CLAMOUSA	HAM SANDWICH	BREAKFST SANDWICH	MEXICAN 7 LAYER DIP	HOT BARBECUE SPARE RI	0.000
					UNIT PRICE £/kg
-('')					0.00
					TOTAL PRICE £
					0.00

4-3 The PLU screen appears.

Weigh	ning Fi	ixed P	rice P	LU	
PLU 201		21-JU	N-2007(TH	HU) 11:21	TARE kg
Lang U	VE			RRYS	0.000
p		.AM(l	JSA)		ZERO WEIGHT kg
OPE 001	OPE 002	OPE 003	OPE 004	OPE 005	0.000
OPE 006	OPE 007	OPE 008	OPE 009	OPE 010	
OPE 011	OPE 012	OPE 013	OPE 014	OPE 015	FIXED PRICE £
TARE	TARE	TARE	TARE	OPERATOR GROUP	1.78

4-4 Put a product on the weigh platter.





PLU 201		21-JUI IILD AM(U			TARE kg 0.000 WEIGHT kg
OPE 001	OPE 002	OPE 003	OPE 004	OPE 005	<u> </u>
OPE 006	OPE 007	OPE 008	OPE 009	OPE 010	
OPE 011	OPE 012	OPE 013	OPE 014	OPE 015	FIXED PRICE £
TARE	TARE	TARE	TARE	OPERATOR GROUP	1.78

KEY LOOP

<0N>

EXAMP	LE Sele	ect "Ope	rator 001	".	
PLU 201		21-JU	N-2007(TI	10) 11:21	TARE kg
<u>₽</u> [LI	VE_h			RRYS	0.000
F	CL	.AM(l	JSA)		WEIGHT kg
OPE 001	OPE 002	OPE 003	OPE 004	OPE 005	0.410
	OPE 007	OPE 008	OPE 009	OPE 010	
OPE	OPE 012	OPE 013	OPE 014	OPE 015	FIXED PRICE £
TARE	TARE	TARE	TARE	OPERATOR GROUP	1.78

Press a button on the screen for the operator who has sold the product. **4-5**



5-1 **EXAMPLE** Product registration by "Operator 002"

Select a desired product category by pressing the corresponding field on the screen.

VAT EXCL

VAT INCL

ADDED PRICE

£0.08

(£0.00)


£

8

EXAMPLE	Select	"Meat"	category.	



5-2 The PLU preset screen for the selected category appears. Then, enter a desired PLU number using the numeric keys and press the [PLU] key on the key sheet, or simply press a preset key on the screen where a desired product is allocated.



5-3 The PLU screen appears.

Fixed Unit Price PLU

	łU) 11:21	V-2007(TH	21-JU		PLU 4					
FIXED WEIGHT kg										
_	OIN	SIRL	ESS	DNEL	<u>🛃 B(</u>					
FIXED U.PRI £/kg	OPE 005	OPE 004	OPE 003	OPE 002	OPE 001					
3.68	OPE 010	OPE 009	OPE 008	OPE 007	OPE 006					
TOTAL PRICE £	OPE 015	OPE 014	OPE 013	OPE 012	OPE 011					
0.00	OPERATOR GROUP	TARE	TARE	TARE	TARE					

5-4 Enter the weight using the numeric keys on the key sheet, and press the "Fixed Weight" field on the screen.


EXAMPLE Weight "400g"



PLU 4		21-JU	N-2007(TH	10) 11:21	
	PO	RK C	HOPS		FIXED WEIGHT kg
B B	DNEL	ESS	SIRL	OIN	∩ 0.400
OPE 001	OPE 002	OPE 003	OPE 004	OPE 005	
OPE 006	OPE 007	OPE 008	OPE 009	OPE 010	날 3.68
OPE 011	OPE 012	OPE 013	OPE 014	OPE 015	TOTAL PRICE £
TARE	TARE	TARE	TARE	OPERATOR GROUP	1.47

5-5 Press a button on the screen for the operator who has sold the product.

EXAMPLE Select "Operator 002".											
PLU 4		21-JU	N-2007(TH	HU) 11:21							
	PO	RK C	HOPS		FIXED WEIGHT kg						
🚰 🖪	ONEL	ESS	SIRL	OIN	0.400						
OPE 001	OPE 002	OPE 003	OPE 004	OPE 005	FIXED U.PRI £/kg						
OPE 006	<u>ա</u> հ	OPE 008	OPE 009	OPE 010	3.68						
OPE 011	OPELS	OPE 013	OPE 014	OPE 015	TOTAL PRICE £						
TARE	TARE	TARE	TARE	OPERATOR GROUP	1.47						



6. Press the subtotal field on the screen to display more detailed subtotal data.



7. The detailed subtotal screen appears for confirmation of product registrations. Then, confirm that the detail of the transaction is correct

SUBTOTA	۹L	V-2007(TH	HU) 11:21	ITE	MS		3PC(S)			
OP 2			τοτά		£7.78	(1)RIB	STEAK		
FIDELITY	OPOINT	r(s)	SUBT VATE VATI	XCL.	£7.41 £0.37 (£0.00)		E/kg 3.98	kg 0.362	£ 1.44	
RECEIPT DELETE	RECEIPT <print></print>	OF DRA	PEN WER	CREDIT	other Tran Cash	(102)M	AINE LOE	STERFRE	
VOID	COUPON PAY		PRN PRN>				C(S) 4.50	PC(S) 1	£ 4.50	
						(4)PO	RK СНОР	SBONELE	
					SUBTOTAL GROUP		E/kg 3.68	kg 0.400	£ 1.47	

8. Press the [PRINT] key on the key sheet to issue the receipt.



· · · · · · · · · · · · · · · · · · ·
MEMBER
SAVINGS
* RECEIPT FOR PURCHASE *
ISHIDA JAPAN
http://www.ishida.co.jp/ 21-JUN-200711:20
PLU f/kg kg f
RIB STEAK
1 3.98 0.362 1.44 Fidelity point: 0 point(s)
PLU <u>f</u> /Pcs Pcs fl
MAINE LOBSTER FRESH DAILY
102 4.50 1 4.50 FIDELITY POINT: O POINT(S)
PLU <u>f/kg</u> kg f PORK CHOPS
BONELESS SIRLOIN
4 3.68 0.400 1.47 FIDELITY POINT: 0 POINT(S)
^{3 items} Sub-total: 7.41
Total: 7.78
TENDERED: £7.78
TOTAL FIDELITY POINT: O POINT 21/06/2007 11:21 No. 0060 Machine 01
0 ⁰ 20000000077820 Welcome again
Thank You

9. The Subtotal screen appears for the settlement. SUBTOTAL(HOLD) 21-JUN-2007(THU) 11:21 ITEMS 3PC(S) TOTAL £7.78 OP 2 TENDERD £7.78 SUBTOTAL VAT EXCL. VAT INCL. £7.41 £0.37 (£0.00) £0.00 CHANGE FIDELITY **OPOINT(S)** OTHER TRAN CASH RECEIPT RECEIPT DELETE OPEN DRAWER CASH CREDIT <PRINT> £7.78 TAX PRN COUPON COUPON PAY VOID <NO-PRN> £0.00 CREDIT £0.00 O.THAN CASH SUBTOTAL GROUP £0.00

10-1 EXAMPLE Product registration by "Operator 001"

Select a desired product category by pressing the corresponding field on the screen.



EXAMPLE Select "Meat" category.

10-2 The PLU preset screen for the selected category appears. Then, enter a desired PLU number using the numeric keys and press the [PLU] key on the key sheet, or simply press a preset key on the screen where a desired product is allocated.

EXAMPLE Select PLU No.3 "Round Steak".




PLV 0		21-JU	V-2007(TH	10) 11:23	
Che	eck the w	0.000			
	ter PLU M	vo. and p	ress [PL	oj key.	ZERO WEIGHT kg
RIB STEAK	TOP SIRLOIN WHOLE	ROUND STEAK BONELESS	PORK CHOPS BONELESS	SMOKED SAUSAGE	0.000
					UNIT PRICE £/kg
		-(''')			0.00
					TOTAL PRICE £
					0.00

10-3 The PLU screen appears.

Weighing Unit Price PLU

PLU 3		21-JUI JND S ONEL	0.000		
OPE 001	OPE 002	OPE 003	OPE 004	OPE 005	0.000
OPE 006	OPE 007	OPE 008	OPE 009	OPE 010	
OPE 011	OPE 012	OPE 013	OPE 014	OPE 015	FIXED PRICE £
TARE	TARE	TARE	TARE	OPERATOR GROUP	3.98




10-5

Press a button on the screen for the operator who has sold the product.

EXAMPLE Select "Operator 001".

PLU 3	ROL B	TARE kg 0.000 WEIGHT kg			
	OPE 002	OPE 003	OPE 004	OPE 005	<u> </u>
of m	OPE 007	OPE 008	OPE 009	OPE 010	
OPE	OPE 012	OPE 013	OPE 014	OPE 015	FIXED PRICE £
TARE	TARE	TARE	TARE	OPERATOR GROUP	3.98



11 EXAMPLE Receipt issue by "Operator 001"

Press the subtotal field on the screen to display more detailed subtotal data.



12 <u>The Subtotal screen appears for confirmation of product registrations.</u>

SUBTOTA	۱L	2	1-JVI	N-2007(TI	HU) 11:23	IT	EMS	2PC(S)
OP 1			TOTA		£6.04	(201)LIVE WILL	CHERRYS
FIDELITY	Y OPOINT(S) SUBTOTAL <u>£5.76</u> VAT EXCL. <u>£0.28</u> VAT INCL. (<u>£0.00</u>)				kç 0.410			
RECEIPT DELETE	RECEIPT <print></print>	OP DRA	'EN WER	CREDIT	OTHER TRAN CASH	(3)ROUND ST	EAKBONE
VOID	COUPON PAY		PRN PRN>				kç 0.412	
					SUBTOTAL GROUP			

13 Press the [PRINT] key on the key sheet to issue the receipt.



MEMBER SAVINGS
* RECEIPT FOR PURCHASE * ISHIDA JAPAN http://www.ishida.co.jp/ 21-JUN-200711:21
PLU <u>f/kg kg f</u> LIVE WILD CHERRYSTONE CLAM(USA) 201 0.410 1.78 Fidelity Paint: 0 Paint(s)
ROUND STEAK BONELESS 3 0.412 3.98 FIDELITY POINT: 0 POINT(S)
² items Sub-total: 5.76
Total: 6.04 TENDERED: f6.04
TOTAL FIDELITY POINT: O POINT 21/06/2007 11:23 No. 0062 MACHINE 01
0"200000"706043" Welcome again.
Thank You

14	The Sub	total scr	een	he settle	settlement.			
	SUBTOTA	VL(HOLD)	2	1-JVI	N-2007(TH	10) 11:23	ITEMS	2PC(S)
	OP 1			TOTA		£6.04	TENDERD	£6.04
	FIDELITY	OPOINT	r(s)	SUBTOTAL £5.76 VAT EXCL. £0.28 VAT INCL. (£0.00)			CHANGE	£0.00
	RECEIPT DELETE	RECEIPT <print></print>	OP DRA	EN WER	CREDIT	other Tran Cash	CASH	£6.04
	VOID	COUPON PAY		PRN PRN≻			COUPON	£0.00
							CREDIT	£0.00
						SUBTOTAL GROUP	O.THAN CASH	£0.00
								10.00

3.3 VOIDING PRODUCT REGISTRATION

1. To void a product registration that has been made in the transaction, display the Subtotal

screen f	or confir	mati	on o	f produc	t registra	tic	ns.		
SUBTOT	4L	2	1-JVI	N-2007(TI	HU) 11:33	П	EMS	3	BPC(S)
OP 2			τοτά		£7.47	(3)RO	UND STEA	KBONEL
FIDELITY	OPOINT	г(s)	SUBT VATE VATI	XCL.	£7.12 £0.35 (£0.00)			kg 0.412	£ 3.98
RECEIPT DELETE	RECEIPT <print></print>	OF DRA	PEN WER	CREDIT	OTHER TRAN CASH	(103)L/	AKE TROU	TTRUCH,
VOID	COUPON PAY		PRN PRN>			£/	PC(S) 2.50	PC(S) 1	£ 2.50
						(205)H	OT BARBE	CUESPAF
					SUBTOTAL GROUP		£/kg 2.38	kg 0.268	£ 0.64

2. Press to select a desired product registration field.

EXAMPLE Void the third item.

SUBTOTA	SUBTOTAL(HOLD) 21-JUN-2007(THU) 11:33						3PC((S)		
OP 2			TOTA	L	£7.47	(3)ROU	IND STEAKBOI	NEL		
FIDELITY	OPOINT(S)		SUBTOTAL VAT EXCL. VAT INCL.		TT(S) VAT EXCL.		£7.12 £0.35 (£0.00)		kg 0.412 3	£ .98
RECEIPT DELETE	RECEIPT <print></print>		YEN WER	CREDIT	OTHER TRAN CASH	(103)LA	KE TROUTTRU	СН		
VOID	COUPON PAY		PRN PRN>			£/PC(S) 2.50	$\gamma_{C(S)}^{1}$	£ .50		
						(205)/U	ARBECUES			
					SUBTOTAL GROUP	£/kg 2.38	0 kg 0.268 0	£ .64		

Note: To scroll the selection up or down, press the [▲] or [▼] keys on the key sheet.

3.	Press th	e [VOID]	but	reen.					
UI	SUBTOTA	AL(HOLD)	2	1-JVI	N-2007(TH	IU) 11:33	ITEMS	3	PC(S)
	OP 2			TOTA		£7.47	(3)RC	UND STEA	KBONEL
	FIDELITY	OPOINT	r(s)	SUBT VATE VATI	XCL.	£7.12 £0.35 (£0.00)		kg 0.412	£ 3.98
	RECEIPT DELETE	RECEIPT <print></print>	OF DRA	PEN WER	CREDIT	other Tran Cash	(103)L	AKE TROU'	TTRUCH,
		COUPON PAY		PRN PRN>			£/PC(S) 2.50	PC(S) 1	£ 2.50
	_ / հղ							OT BARBE	CUESPAF
	$ \ \ \ \ \ \ \ \ \ \ \ \ \ $					SUBTOTAL GROUP	£/kg 2.38	kg 0.268	£ 0.64

4.	The confirmation screen appears. Then, press the [EXEC] button for execution.
	SURTOTAL(HOLD) 21-UIN-2007(THU) 11:33 UTEMS 3PC(S) 21-JUN-2007(THU) 11:33
	E DESIGNATED CORRECTION
	DO YOU WANT TO DELETE DESIGNATED PRODUCT?
	1827 - 0000 EXEC STOP
	\sim /

5.	The selected item has been voided.									
01	SUBTOTA	۱L	2	1-JUI	N-2007(TH	10) 11:33	ITEMS	2	PC(S)	
	OP 2			TOTA		£6.80	(3)ROU	JND STEA	KBONEL	
	FIDELITY	OPOINT	r (s)	SUBT VATE VATII	XCL.	£6.48 £0.32 (£0.00)		kg 0.412	£ 3.98	
	RECEIPT DELETE	RECEIPT <print></print>	OF DRA	≧EN ₩ER	CREDIT	other Tran Cash	(103)LA	KE TROU'	TTRUCH	
	VOID	COUPON PAY		PRN PRN>			£/PC(S) 2.50	PC(S) 1	£ 2.50	
								T BARBE		
						SUBTOTAL GROUP	£/kg 2.38	kg 0.268	£ 0.64	

6. Press the [PRINT] key on the key sheet to issue the receipt.




MEMBER SAVINGS * RECEIPT FOR PURCHASE * ISHIDA JAPAN http://www.ishida.co.jp/ 21-JUN-200711:32	
PLU <u>f/kg kg f</u> ROUND STEAK BONELESS <u>3</u> 0.412 3.98 Fidelity point: 0 point(s)	
PLU £/Pcs Pcs £ LAKE TROUT TRUCHAS 103 2.50 1 2.50	
FIDELITY POINT: 0 POINT(S) PLU <u>f/kg</u> kg <u>f</u> HOT BARBECUE SPARE RIB PLATTER	
2 items Sub-total: 6.48	Deleted by a dashed line
Total: 6.80 TENDERED: £6.80 TOTAL FIDELITY POINT: 0 POINT	
21/06/2007 11:33 No. 0038 MACHINE 01 0 200000 506803 Welcome again. Thank You	


7	The Sub	total scr	the settle	ement.				
	SUBTOTA	AL(HOLD)	2	1-JVI	N-2007(TH	HU) 11:33	ITEMS	2PC(S)
	OP 2			TOTA	-	£6.80	TENDERD	£6.80
	FIDELITY	OPOINT	r(s)	SUBT VATE VATI	XCL.	£6.48 £0.32 (£0.00)	CHANGE	£0.00
	RECEIPT DELETE	RECEIPT <print></print>	OF DRA	PEN WER	CREDIT	OTHER TRAN CASH	CASH	£6.80
	VOID	COUPON PAY		PRN PRN>			COUPON	£0.00
							CREDIT	£0.00
						SUBTOTAL GROUP	O.THAN CASH	£0.00

TRACEABILITY PRODUCTS

4.1 REFERING TO PREVIOUS TRACEABILITY DATA



2. Enter a desired PLU number using the numeric keys and press the [PLU] key on the key sheet, or simply press a preset key on the screen where the product is allocated.





3. When the product is preset as a traceable item, the Traceability screen appears.

TRACEABILITY		21-JUN-2007(1	FHU) 11:15
6	ROAST BEEF	-	
LOT 01	23456789		
TITLE TEXT	COUNTRY	FACTORY	
Born in:	ARGENTINA	ATTR.1-1	
Breed in:	ARGENTINA	ATTR.1-1	
Breed in #2:	FRANCE	ATTR.2-2]
Slaughtered in:	FRANCE	ATTR.2-2	LIST
Cut Up in:	FRANCE	ATTR.2-2	
		INPUT	


4.

To refer to the previously processed traceability data, press the [LIST] button. 21-JUN-2007(THU) 11:15

TRACEABILITY

6	ROAST BEEF	ROAST BEEF					
LOT 01	23456789						
TITLE TEXT	COUNTRY	FACTORY					
Born in:	ARGENTINA	ATTR.1-1	ותו				
Breed in:	ARGENTINA	ATTR.1-1	(m)				
Breed in #2:	FRANCE	ATTR.2-2					
Slaughtered in:	FRANCE	ATTR.2-2	LIST				
Cut Up in:	FRANCE	ATTR.2-2					
		INPUT	JET J				

The Traceability History screen appears. Then, press to select a desired data field. 5.



6.

The selected data appears. Then, press the [SET] button.

TRACEABILITY	BILITY 21-JUN-2007(1						
6	-						
LOT)123456789						
TITLE TEXT	COUNTRY	FACTORY					
Born in:	ARGENTINA	ATTR.1-1					
Breed in:	ARGENTINA	ATTR.1-1					
Breed in #2:	FRANCE	ATTR.2-2	L ア				
Slaughtered in:	FRANCE	ATTR.2-2] YUL / F				
Cut Up in:	FRANCE	ATTR.2-2					
		INPUT					

7. The selected PLU screen appears.

Weighing Unit Price Products 21-JUN-2007(THU) 11:15 PLU 6 TARE kg ROAST BEEF U R ZERO WEIGHT OUPONMS U/P F/P FIX UPR FIX UPR +WEIGHT U 0 UNIT PRICE SPECIAL SP.(U/P) -\$(U/P -% 0.00 0.00 0.0 0.00 0.00 TOTALADD -%(U/P) P DATE S DATE PRN QTV TOTAL PRI 0.0 21-06-07 27-06-07 <ADD> 0 PRN MD. PEEL MD. CASSETTE FUNCTION GROUP MULTI () <MANUAL> <INDIV> 1

Fixed Price Products										
PLV 6		21-JU	N-2007(TH	HU) 11:15	PCS	1				
	RO	AST	BEEF	-	FIXED V	¥EIGHT	kg			
U/P	F/P	FIX UPR	FIX UPR +WEIGHT	COUPONMS 0						
SPECIAL 0.00	-\$ 0.00	-% 0.0	SP.(U/P) 0.00	-\$(U/P 0.00						
-%(U/P) 0.0	P DATE 21-06-07	S DATE 27-06-07	TOTALADD <add></add>	PRN QTY O	FIXED		£			
PRN_MD. <manual></manual>	PEEL MD. <indiv></indiv>	CASSETTE 1	MULTI	FUNCTION GROUP		4.0)()			

Fixed Unit Price Products


	HU) 11:15	21-JUN-2007(THU) 11:1								
FIXED WEIGHT kg		RO								
FIXED U.PRI £/kg	COUPONMS 0	FIX UPR +WEIGHT	FIX UPR	F/P	U/P					
4.00	-\$(U/P	SP.(U/P)	-%	-\$	SPECIAL					
4.00	0.00	0.00	0.0	0.00	0.00					
TOTAL PRICE £	PRN QTY	TOTALADD	S DATE	P DATE	-%(U/P)					
	0	<add></add>	27-06-07	21-06-07	0.0					
0.00	FUNCTION GROUP	MULTI	CASSETTE 1	PEEL MD. <indiv></indiv>	PRN_MD. <manual></manual>					

Weighing Fixed Price Products

PLU 6		21-JU	N-2007(TH	IU) 11:15	
	RO	AST	BEEF	_	0.000
U/P	F/P	FIX UPR	FIX UPR +WEIGHT	COUPONMS 0	0.000
SPECIAL	-\$	-%	SP.(U/P)	-\$(U/P	
0.00	0.00	0.0	0.00	0.00	
-%(U/P)	P DATE	S DATE	TOTALADD	PRN QTY	
0.0	21-06-07	27-06-07	<add></add>	0	FIXED PRICE £
PRN MD. <manual></manual>	PEEL MD. <indiv></indiv>	CASSETTE 1	MULTI	FUNCTION GROUP	4.00

4.2 CHANGING TRACEABILITY DATA

- Ensure that the initial screen is displayed. 1. PLU 0 21-JUN-2007(THU) 11:15 TARE kg - () O Check the weight before operation. Enter PLU No. and press [PLU] key. E WEIGH PRN MD PLU No <manual> 0 UNIT PRICE RIB STEAK SMOKED SAUSAGE GROUND BEEF EXTRA SALMON MATN ROAST T-BONE STEAK FILLET TOTAL PRICI CASSETTE HOT SWEET & SOUR WIN TILAPIA FILLET SKIN-ON HAM SANDWICH 1
- **2.** Enter a desired PLU number using the numeric keys and press the [PLU] key on the key sheet, or simply press a preset key on the screen where the product is allocated.



3-1 When the product is preset as a traceable item, the Traceability screen appears. Then, confirm whether information on the screen is correct or not. When the data is correct, press the [SET] button.

TRACEABILITY	· · · · ·	21-JUN-2007(1	FHU) 11:15
6	ROAST BEEF		
LOT 01	23456789		
TITLE TEXT	COUNTRY	FACTORY	
Born in:	ARGENTINA	ATTR.1-1	
Breed in:	FRANCE	ATTR.2-2	$ \mathcal{A} $
Breed in #2:	FRANCE	ATTR.2-2	ا_ر / I
Slaughtered in:	FRANCE	ATTR.2-2	YUU /*
Cut Up in:	FRANCE	ATTR.2-2	
		INPUT	JE1

3-2 If the data is not correct, press to select a desired data field.

EXAMPLE Select "France".

TRACEABILITY		21-JUN-2007(1	FHU) 11:15
6	6 ROAST BEEF		
LOT 0	23456789		
TITLE TEXT	COUNTRY	FACTORY	
Born in:	ARGENTINA	ATTR.1-1	
Breed in:		ATTR.2-2	
Breed in #2:		ATTR.2-2	
Slaughtered in:	FRANCE	ATTR.2-2	LIST
Cut Up in:	FRANCE	ATTR.2-2	SET
	\smile	INPUT	

EXAMPLE Change to "Argentina".

LOOKUP T	ABLE	21-JUN-2007(THU)	11:15	1/2
0	NONE			t
1			`	
2	FRANCE		، <mark> </mark>	
3	NETHERLAND			
4				
5	PORTUGAL			
FIND PLU	SEARCH	INPUT		

The data has been changed.

To change the "FACTORY" data, press the corresponding field.

TRACEABILITY		21-JUN-2007(1	FHU) 11:15
6	ROAST BEEF	-	T)
LOT 0	23456789		
TITLE TEXT	COUNTRY	FACTORY	
Born in:	ARGENTINA	ATTR.1-1	
Breed in:	ARGENTINA		
Breed in #2:	FRANCE		
Slaughtered in:	FRANCE		LIST
Cut Up in:	FRANCE	ATT	SET
		INPUT	SEI

Press to select a desired data field.

LOOKUP T	ABLE DATA 21-JUN-2007(THU) 11:15	1/3
0	NONE	
1	ATTR.1-1	
5	ATTR.1-5	
7	ATTR.1-7	
10	ATTR.1-10	
12	ATTR.1-12	
FIND PLU	SEARCH DISP. 1	

TRACEABILITY		21-JUN-2007(1	FHU) 11:15
6	ROAST BEEF	-	
LOT 0	123456789		
TITLE TEXT	COUNTRY	FACTORY	
Born in:	ARGENTINA	ATTR.1-1	
Breed in:	ARGENTINA	ATTR.1-1	
Breed in #2:	FRANCE	ATTR.2-2	/ 〕_
Slaughtered in:	FRANCE	ATTR.2-2	I Щ /т
Cut Up in:	FRANCE	ATTR.2-2	
		INPUT	

The data has been changed. Then, press the [SET] button.

4.


When changing the lot data, press the "LOT" filed.


TRACEABILITY	· · · ·	21-JUN-2007(1	FHU) 11:15
6	ROAST BEEF	-	
LOT 0	123456789		
TITLE TEXT		FACTORY	
Born in:	ARGENTIN	ATTR.1-1	
Breed in:		ATTR.1-1	
Breed in #2:	FRANCE	ATTR.2-2	
Slaughtered in:	FRANCE	ATTR.2-2	LIST
Cut Up in:	FRANCE	ATTR.2-2	SET
		INPUT	

The Traceability Lot Number Set screen appears.



Change the lot number using the [ABC] [ERASE] and [BACK SPACE] buttons, and press the [BACK] button to finish.







The Traceability screen appears. Then, press the [SET] button.

TRACEABILITY		21-JUN-2007(1	FHU) 11:16	
6	ROAST BEEF	-		
LOT A	BC0123456789	C0123456789		
TITLE TEXT	COUNTRY	FACTORY		
Born in:	ARGENTINA	ATTR.1-1	\frown	
Breed in:	ARGENTINA	ATTR.1-1		
Breed in #2:	FRANCE	ATTR.2-2		
Slaughtered in:	FRANCE	ATTR.2-2	YUL fr	
Cut Up in:	FRANCE	ATTR.2-2		
		INPUT	JET J	

5. The selected PLU screen appears.

Weighing Unit Price Products

PLU 6		21-JU	N-2007(TH	HU) 11:15	TARE kg		
	RO	AST	'	0.000			
U/P	F/P	FIX UPR	FIX UPR +WEIGHT	COUPONMS 0	0.000		
SPECIAL	-\$	-%	SP.(U/P)	-\$(U/P	UNIT PRICE £/kg		
0.00	0.00	0.0	0.00	0.00	1 00		
-%(U/P)	P DATE	S DATE	TOTALADD	PRN QTY	4.00		
0.0	21-06-07	27-06-07	<add></add>	0	TOTAL PRICE £		
PRN MD. <manual></manual>	PEEL MD. <indiv></indiv>	CASSETTE 1	MULTI	FUNCTION GROUP	0.00		

Fixed Price Products

PLV 6		21-JU	10) 11:15	PCS	1		
	RO	AST	FIXED 1	#EIGHT	kg		
U/P	F/P	FIX UPR	FIX UPR +WEIGHT	COUPONMS 0			
SPECIAL	-\$	-%	SP.(U/P)	-\$(U/P			
0.00	0.00	0.0	0.00	0.00			
-%(U/P)	P DATE	S DATE	TOTALADD	PRN QTY	FIXED	PRICE	f
0.0	21-06-07	27-06-07	<add></add>	0			-
PRN_MD. <manual></manual>	PEEL MD. <indiv></indiv>	CASSETTE 1	MULTI	FUNCTION GROUP		4.0)()

Fixed	Fixed Unit Price Products						
PLV 6		21-JU	N-2007(TH	10) 11:15			
	RO	AST	FIXED WEIGHT kg				
U/P	F/P	FIX UPR	FIX UPR +WEIGHT	COLPONMS 0	FIXED U.PRI £/kg		
SPECIAL 0.00	-\$ 0.00	-% 0.0	SP.(U/P) 0.00	-\$(U/P 0.00	4.00		
-%(U/P) 0.0	P DATE 21-06-07	S DATE 27-06-07	TOTALADD <add></add>	PRN QTY O	TOTAL PRICE £		
PRN_MD. <manual></manual>	PEEL MD. <indiv></indiv>	CASSETTE 1	MULTI	FUNCTION GROUP	0.00		

Weighing Fixed Price Products

PLV 6		21-JU	V-2007(TH	10) 11:15	TARE kg	
	RO	AST	'	0.000		
U/P	F/P	FIX UPR	FIX UPR +WEIGHT	COUPONMS 0	0.000	
SPECIAL	-\$	-%	SP.(U/P)	-\$(U/P		
0.00	0.00	0.0	0.00	0.00		
-%(U/P)	P DATE	S DATE	TOTALADD	PRN QTY		
0.0	21-06-07	27-06-07	<add></add>	0	FIXED PRICE £	
PRN MD. <manual></manual>	PEEL MD. <indiv></indiv>	CASSETTE 1	MULTI	FUNCTION GROUP	4.00	

TEMPORARY CHANGE OPERATIONS

5.1 UNIT PRICE CHANGE

1. Ensure that the selected PLU screen is displayed.

Weighing Products

TARE kg	10) 11:15	21-JUN-2007(THU) 11:1						
0.000		RO						
ZERO WEIGHT kg	COUPONMS				p			
	0	FIX UPR +WEIGHT	FIX UPR	F/P	U/P			
	-\$(U/P 0.00	SP.(U/P) 0.00	-% 0.0	-\$ 0.00	SPECIAL 0.00			
4.00	PRN QTY	TOTALADD	S DATE	P DATE	-%(U/P)			
TOTAL PRICE £	0	<add></add>	27-06-07	21-06-07	0.0			
0.00	FUNCTION GROUP	MULTI	CASSETTE 1	PEEL MD. <indiv></indiv>	PRN_MD. <manual></manual>			

Fixed Unit Price Products

	10) 11:15	21-JUN-2007(THU) 11:13						
FIXED WEIGHT kg	ROAST BEEF							
FIXED U.PRI £/kg	COUPONMS 0	FIX UPR +WEIGHT	FIX UPR	F/P	U/P			
4.00	-\$(U/P	SP.(U/P)	-%	-\$	SPECIAL			
4.00	0.00	0.00	0.0	0.00	0.00			
TOTAL PRICE £	PRN QTY	TOTALADD	S DATE	P DATE	-%(U/P)			
	0	<add></add>	27-06-07	21-06-07	0.0			
0.00	FUNCTION GROUP	MULTI	CASSETTE 1	PEEL MD. <indiv></indiv>	PRN_MD. <manual></manual>			

2. Enter a desired unit price using the numeric keys and press the "UNIT PRICE" or "FIXED UNIT PRICE" field.



Weighing Products

PLU 6		21-JU	IU) 11:15					
	RO	AST	·	0.000				
1					ZERO WEIGHT kg			
U/P	F/P	FIX UPR	FIX UPR +WEIGHT	COUPONMS	0.000			
SPECIAL	-\$	-%	SP.(U/P)	-\$(U/P	UNIT PRICE £/kg			
0.00	0.00	0.0	0.00	0.00	0 3 80			
-%(U/P)	P DATE	S DATE	TOTALADD	PRN QTY	<u>ov</u>			
0.0	21-06-07	27-06-07	<add></add>	0	TC II RICE £			
PRN MD. <manual></manual>	PEEL MD. <indiv></indiv>	CASSETTE 1	MULTI	FUNCTION GROUP	∕0.00			

Fixed	Unit F	sts			
PLV 6		21-JU	N-2007(TI	10) 11:15	
	RO	AST	-	FIXED WEIGHT kg	
U/P	F/P	FIX UPR	FIX UPR +WEIGHT	COUPONMS 0	FIXED U.PRI £/kg
SPECIAL 0.00	-\$ 0.00	-% 0.0	SP.(U/P) 0.00	-\$(U/P 0.00	3.80
-%(U/P) 0.0	P DATE 21-06-07	S DATE 27-06-07	TOTALADD <add></add>	PRN QTY O	TO RICE £
PRN MD. <manual></manual>	PEEL MD. <indiv></indiv>	CASSETTE 1	MULTI	FUNCTION GROUP	날 0.00

5.2 FIXED PRICE CHANGE

1. Ensure that the selected PLU screen is displayed.

Fixed	Price						
PLU 6		21-JU	N-2007(TH	IU) 11:15	PCS	1	
	RO	AST	_	FIXED V	VEIGHT	kg	
U/P	F/P	FIX UPR	FIX UPR +WEIGHT	COUPONMS 0			
SPECIAL	-\$	-%	SP.(U/P)	-\$(U/P			
0.00	0.00	0.0	0.00	0.00			
-%(U/P)	P DATE	S DATE	TOTALADD	PRN QTY	FIXED	PRICE	f
0.0	21-06-07	27-06-07	<add></add>	0			
PRN MD. <manual></manual>	PEEL MD. <indiv></indiv>	CASSETTE 1	MULTI	FUNCTION GROUP		4.0)0

Weighing Fixed Price Products PLU 6 21-JUN-2007(THU) 11:15 TARE 0.000 ROAST BEEF ZERO WEIGHT 0.000 COUPONMS F/P FIX UPR FIX UPR +WEIGHT U/P 0 SPECIAL -\$ -% SP.(U/P) -\$(U/F 0.00 0.00 0.0 0.00 0.00 S DATE PRN QTY P DATE TOTALADD FIXED PRICE 21-06-07 27-06-07 <ADD> 0.0 0 CASSETTE PRN MD PEEL MD FUNCTION GROUP <u>4.00</u> MULTI <MANUAL> <INDIV> 1

2. Enter a desired price using the numeric keys, and press the "FIXED PRICE" field.



Fixed Price Products

PLV 6		21-JU	IU) 11:15	PCS	1		
	ROAST BEEF						kg
U/P	F/P	FIX UPR	FIX UPR +WEIGHT	COUPONMS 0			
SPECIAL	-\$	-%	SP.(U/P)	-\$(U/P			
0.00	0.00	0.0	0.00	0.00			
-%(U/P)	P DATE	S DATE	TOTALADD	PRN QTY	FIXED	PRICE	£
0.0	21-06-07	27-06-07	<add></add>	0			
PRN MD.	PEEL MD.	CASSETTE	MULTI	FUNCTION GROUP		.3.8	SO
<manual></manual>	<indiv></indiv>	1		GNUUF	L/I	\mathbf{n}	
						5	

Weigh	Weighing Fixed Price Products									
PLU 6		21-JU	N-2007(TH	1U) 11:15	TARE kg					
	RO	AST	-	0.000						
U/P	F/P	FIX UPR	FIX UPR +WEIGHT	COUPONMS 0	0.000					
SPECIAL	-\$	-%	SP.(U/P)	-\$(U/P						
0.00	0.00	0.0	0.00	0.00						
-%(U/P)	P DATE	S DATE	TOTALADD	PRN QTY						
0.0	21-06-07	27-06-07	<add></add>	0	FIXED PRICE £					
PRN MD. <manual></manual>	PEEL MD. <indiv></indiv>	CASSETTE 1	MULTI	FUNCTION GROUP	3.80					
					24					

5.3 AMOUNT DISCOUNT FOR UNIT PRICE

1. Ensure that the selected PLU screen is displayed.

Weighing Unit Price Products

PLU 6		21-JU	IU) 11:15	TARE kg	
	RO	AST	'	0.000	
U/P	F/P	FIX UPR	FIX UPR +WEIGHT	COUPONMS	ZERO WEIGHT kg
SPECIAL	-\$	-%	SP.(U/P)	-\$(U/P	UNIT PRICE £/kg
0.00 -%(U/P)	0.00 P DATE	0.0 S DATE	0.00 TOTALADD	0.00 PRN QTY	4.00
0.0 PRN MD.	21-06-07 PEEL MD.	27-06-07 CASSETTE	<add></add>	0 FUNCTION	
<manual></manual>	<indiv></indiv>	1	MULTI	ĞŘŎÚP	0.00

Fixed Unit Price Products

	10) 11:15	21-JUN-2007(THU) 11:15							
FIXED WEIGHT kg	·								
FIXED U.PRI £/kg	COUPONMS 0	FIX UPR +WEIGHT	FIX UPR	F/P	U/P				
4.00	-\$(U/P 0.00	SP.(U/P) 0.00	-% 0.0	-\$ 0.00	SPECIAL 0.00				
TOTAL PRICE £	PRN QTY O	TOTALADD <add></add>	S DATE 27-06-07	P DATE 21-06-07	-%(U/P) 0.0				
0.00	FUNCTION GROUP	MULTI	CASSETTE 1	PEEL MD. <indiv></indiv>	PRN_MD. <manual></manual>				

2. Enter a desired discount amount using the numeric keys, and press the "-\$ (U/P)" field.

EXAMPLE Discount amount "\$1.00".



Weighing Unit Price Products

TARE kg	IU) 11:15	21-JUN-2007(THU) 11:1						
0.000 ZERO WEIGHT kg		ROAST BEEF						
0.000	COUPONMS	FIX UPR +WEIGHT	FIX UPR	F/P	U/P			
UNIT PRICE £/kg	-\$(U/P	SP.(U/P)	-%	-\$	SPECIAL			
3 00	1.00	0.00	0.0	0.00	0.00			
<u></u>	PRN QI	TOTALADD	S DATE	P DATE	-%(U/P)			
TOTAL PRICE £	0()'''	<add></add>	27-06-07	21-06-07	0.0			
0.00		MULTI	CASSETTE 1	PEEL MD. <indiv></indiv>	PRN MD. <manual></manual>			

Fixed	Unit F	ts			
PLV 6		21-JU	N-2007(TH	HU) 11:15	
	RO	AST	-	FIXED WEIGHT kg	
U/P	F/P	FIX UPR	FIX UPR +WEIGHT	COUPONMS 0	FIXED U.PRI £/kg
SPECIAL 0.00	-\$ 0.00	-% 0.0	SP.(U/P) 0.00	-\$(U/P 1.00	3.00
-%(U/P) 0.0	P DATE 21-06-07	S DATE 27-06-07	TOTALADD <add></add>		TOTAL PRICE £
PRN MD. <manual></manual>	PEEL MD. <indiv></indiv>	CASSETTE 1	MULTI		<u>6.00 ر</u>

5.4 PERCENT DISCOUNT FOR UNIT PRICE

1. Ensure that the selected PLU screen is displayed.

Weighing Unit Price Products

PLU 6		21-JU	IU) 11:15	TARE kg	
	RO	AST	-	0.000 ZERO WEIGHT kg	
U/P	F/P	FIX UPR	FIX UPR +WEIGHT	COUPONMS 0	0.000
SPECIAL	-\$	-%	SP.(U/P)	-\$(U/P	UNIT PRICE £/kg
0.00	0.00	0.0	0.00	0.00	4.00
-%(U/P)	P DATE	S DATE	TOTALADD	PRN QTY	4.00
0.0	21-06-07	27-06-07	<add></add>	0	TOTAL PRICE £
PRN MD. <manual></manual>	PEEL MD. <indiv></indiv>	CASSETTE 1	MULTI	FUNCTION GROUP	0.00

Fixed Unit Price Products

	21-JUN-2007(THU) 11:15							
FIXED WEIGHT kg	ROAST BEEF							
FIXED U.PRI £/kg	COUPONMS 0	FIX UPR +WEIGHT	FIX UPR	F/P	U/P			
4.00	-\$(U/P 0.00	SP.(U/P) 0.00	-% 0.0	-\$ 0.00	SPECIAL 0.00			
TOTAL PRICE £	PRN QTY O	TOTALADD <add></add>	S DATE 27-06-07	P DATE 21-06-07	-%(U/P) 0.0			
0.00	FUNCTION GROUP	MULTI	CASSETTE 1	PEEL MD. <indiv></indiv>	PRN_MD. <manual></manual>			

2. Enter a desired discount percentage using the numeric keys on the key sheet, and press the "-% (U/P)" field.

EXAMPLE Discount percentage "10%".



PLU 6		21-JU	TARE kg		
	RO				
U/P	F/P	FIX UPR	FIX UPR +WEIGHT	COUPONMS	ZERO WEIGHT kg
SPECIAL 0.00	-\$ 0.00	-% 0.0	SP.(U/P) 0.00	-\$(U/P 0.00	UNIT PRICE £/kg
-%(U/P) 10.0∩	P DATE 21-06-07	S DATE 27-06-07	TOTALADD <add></add>	PRN QTV O	3.60 TOTAL PRICE £
	NOIV>	CASSETTE 1	MULTI	FUNCTION GROUP	0.00
	{	1	1		

PLU 6		21-JU	N-2007(TH	HU) 11:15	
	RO	AST	BEEF		FIXED WEIGHT kg
U/P	F/P	FIX UPR	FIX UPR +WEIGHT	COUPONMS	FIXED U.PRI £/kg
SPECIAL 0.00	-\$ 0.00	-% 0.0	SP.(U/P) 0.00	-\$(U/P 0.00	3.60
-%(U/P) 10.0∩	P DATE 21-06-07	S DATE 27-06-07	TOTALADD <add></add>	PRN QTY O	TOTAL PRICE £
	REEL MD. JINDIV>	CASSETTE 1	MULTI	FUNCTION GROUP	0.00

5.5 AMOUNT DISCOUNT FOR TOTAL PRICE

1. Ensure that the selected PLU screen is displayed.

Fixed Price Products

PLU 6		21-JU	10) 11:15	PCS	1		
	RO	FIXED V	VEIGHT	kg			
U/P	F/P	FIX UPR	FIX UPR +WEIGHT	COUPONMS 0			
SPECIAL	-\$	-%	SP.(U/P)	-\$(U/P			
0.00	0.00	0.0	0.00	0.00			
-%(U/P)	P DATE	S DATE	TOTALADD	PRN QTY	FIXED	PRICE	£
0.0	21-06-07	27-06-07	<add></add>	0			
PRN MD. <manual></manual>	PEEL MD. <indiv></indiv>	CASSETTE 1	MULTI	FUNCTION GROUP		4.0)0

Weighing Fixed Price Products

PLV 6		21-JU	HU) 11:15	TARE kg						
	RO	AST	0.000							
U/P	F/P	FIX UPR	0.000							
SPECIAL	-\$	-%	SP.(U/P)	-\$(U/P						
0.00	0.00	0.0	0.00	0.00						
-%(U/P)	P DATE	S DATE	TOTALADD	PRN QTY						
0.0	21-06-07	27-06-07	<add></add>	0	FIXED PRICE £					
PRN MD. <manual></manual>	PEEL MD. <indiv></indiv>	CASSETTE 1	MULTI	FUNCTION GROUP	4.00					

2. Enter a desired discount amount using the numeric keys, and press the "-\$" field.

EXAMPLE Discount amount "\$1.00".



Fixed Price Products

PLV 6		21-JU	IV) 11:15	PCS	1		
	RO	FIXED V	VEIGHT	kg			
U/P	F/P	FIX UPR	FIX UPR +WEIGHT	COUPONMS 0			
SPECIAL	-\$	-%	SP.(U/P)	-\$(U/P			
0.00	1.00	0.0	0.00	0.00			
-%(U/P)	P DAT	S DATE	TOTALADD	PRN QTY	FIXED	PRICE	f
0.0	21-06	-06-07	<add></add>	0			-
PRN MD. <manual></manual>	PEEL MD <indiv< th=""><th>ASSETTE</th><th>MULTI</th><th>FUNCTION GROUP</th><th></th><th>3.0</th><th>)(</th></indiv<>	ASSETTE	MULTI	FUNCTION GROUP		3.0)(

Weigh	ning Fi	ixed P	rice P	roduct	ts.
PLU 6		21-JU	N-2007(TH	10) 11:15	TARE kg
	RO	AST			
U/P	F/P	FIX UPR	FIX UPR +WEIGHT	COUPONMS	0.000
SPECIAL	-\$	-%	SP.(U/P)	-\$(U/P	
0.00	1.00	0.0	0.00	0.00	
-%(U/P)	P DAT	S DATE	TOTALADD	PRN QTY	
0.0	21-06	-06-07	<add></add>	0	FIXED PRICE £
PRN MD. <manual></manual>	PEEL MD KINDIV	ASSETTE	MULTI	FUNCTION GROUP	3.00

5.6 PERCENT DISCOUNT FOR TOTAL PRICE

1. Ensure that the selected PLU screen is displayed.

Fixed Price Products

PCS 1	IU) 11:15	21-JUN-2007(THU) 11:15						
FIXED WEIGHT kg	ROAST BEEF							
	COUPONMS 0	FIX UPR +WEIGHT	FIX UPR	F/P	U/P			
	-\$(U/P	SP.(U/P)	-%	-\$	SPECIAL			
	0.00	0.00	0.0	0.00	0.00			
FIXED PRICE £	PRN QTY	TOTALADD	S DATE	P DATE	-%(U/P)			
	0	<add></add>	27-06-07	21-06-07	0.0			
4.00	FUNCTION GROUP	MULTI	CASSETTE 1	PEEL MD. <indiv></indiv>	PRN MD. <manual></manual>			

Weighing Fixed Price Products

TARE kg	IV) 11:15	21-JUN-2007(THU) 11:15						
0.000 ZERO WEIGHT kg	ROAST BEEF							
0.000	COUPONMS	FIX UPR +WEIGHT	FIX UPR	F/P	U/P			
	-\$(U/P	SP.(U/P)	-%	-\$	SPECIAL			
	0.00	0.00	0.0	0.00	0.00			
	PRN QTY	TOTALADD	S DATE	P DATE	-%(U/P)			
FIXED PRICE £	0	<add></add>	27-06-07	21-06-07	0.0			
4.00	FUNCTION GROUP	MULTI	CASSETTE 1	PEEL MD. <indiv></indiv>	PRN_MD. <manual></manual>			

2. Enter a desired discount percentage using the numeric keys on the key sheet, and press the "-%" field.



21-JUN-2007(THU) 11:15						
ROAST BEEF						
UPR COUPON		F/P	U/P			
(U/P) -\$(U/F	-% SP	-\$	SPECIAL			
00 0.00	0.00	0.00	0.00			
ALADD PRN QT	DAT TA	P DATE	-%(U/P)			
DD> 0	06('''')	21-06-07	0.0			
		PEEL MD. <indiv></indiv>	PRN MD. <manual></manual>			

Weigł	ning Fi	xed P	rice P	roduct	S
PLU 6		21-JU	N-2007(TH	1U) 11:15	TARE kg
	RO	AST	BEEF	'	
U/P	F/P	FIX UPR	FIX UPR +WEIGHT	COUPONMS 0	0.000
SPECIAL	-\$	-%	SP.(U/P)	-\$(U/P	
0.00	0.00	10.0	0.00	0.00	
-%(U/P)	P DATE	S DAT	TOTALADD	PRN QTY	
0.0	21-06-07	27-06	ADD>	0	FIXED PRICE £
PRN MD. <manual></manual>	PEEL MD. <indiv></indiv>	CASSE	MULTI	FUNCTION GROUP	3.60

5.7 PRODUCT QUANTITY CHANGE

1. Ensure that the selected PLU screen is displayed.

Fixed	Price						
PLV 6		HU) 11:15	PCS	1			
	RO	AST	FIXED V	FIGHT	kg		
U/P	F/P	FIX UPR	FIX UPR +WEIGHT	COUPONMS 0			
SPECIAL	-\$	-%	SP.(U/P)	-\$(U/P			
0.00	0.00	0.0	0.00	0.00			
-%(U/P)	P DATE	S DATE	TOTALADD	PRN QTY	FIXED	PRICE	£
0.0	21-06-07	27-06-07	<add></add>	0			
PRN MD. <manual></manual>	PEEL MD. <indiv></indiv>	CASSETTE 1	MULTI	FUNCTION GROUP		4.0)0

2. Enter a desired quantity using the numeric keys, and press the "PCS" field.

EXAMPLE Quantity "2 pieces"

2

PCS 2	LU 6 21-JUN-2007(THU) 11:15					
	ROAST BEEF					
<u>C</u>	COUPONMS 0	FIX UPR +WEIGHT	FIX UPR	F/P	U/P	
	-\$(U/P	SP.(U/P)	-%	-\$	SPECIAL	
	0.00	0.00	0.0	0.00	0.00	
FIXED PRICE £	PRN QTY	TOTALADD	S DATE	P DATE	-%(U/P)	
	0	<add></add>	27-06-07	21-06-07	0.0	
4.00	FUNCTION GROUP	MULTI	CASSETTE 1	PEEL MD. <indiv></indiv>	PRN MD. <manual></manual>	

3. To select a desired fix price mark, press the "PCS" field again.

5 neiu ayan		p1000 an	oo mang			10 00100
2	PCS	10) 11:15	V-2007(TH	21-JU		PLV 6
<mark>Пліснт kg</mark>	FIXE	·	BEEF	AST	RO	
		COUPONMS 0	FIX UPR +WEIGHT	FIX UPR	F/P	U/P
		-\$(U/P	SP.(U/P)	-%	-\$	SPECIAL
		0.00	0.00	0.0	0.00	0.00
D PRICE £	FIXED	PRN QTY	TOTALADD	S DATE	P DATE	-%(U/P)
		0	<add></add>	27-06-07	21-06-07	0.0
4.00		FUNCTION GROUP	MULTI	CASSETTE 1	PEEL MD. <indiv></indiv>	PRN MD. <manual></manual>

4. The Fix Price mark List screen appears. Then, select a desired mark by pressing the corresponding field.

EXAMP	LE Pric	e mark "	PC. PCS	S."		
FIX PRICE	E MARK LI	sт	21-	JUN-2007	(THV) 11	:15 1/3
0	NONE					
1	oz oz					
2	lb lb					Ī
3	kg kg			Ī		
4	99			1		
5	PC. PCS	i.	0			1
FIND PLU		SEA	(h)	INPUT]
			Y			
PLU 6		21-JU	N-2007(TI	HU) 11:15	PCS	2PCS.
	RO	AST	BEEF		FIXED W	EIGHT kg
U/P	F/P	FIX UPR	FIX UPR +WEIGHT	COUPONMS 0		
SPECIAL	-\$	-%	SP.(U/P)	-\$(U/P		
0.00 -%(U/P)	0.00 P DATE	0.0 S DATE	0.00 TOTALADD	0.00 PRN QTY		
0.0	21-06-07	27-06-07	<add></add>		FIXED	PRICE £
PRN MD. <manual></manual>	PEEL MD. <indiv></indiv>	CASSETTE 1	MULTI	FUNCTION GROUP		4.00

5.8 PRINT QUANTITY SETTING

1. Ensure that the selected PLU screen is displayed and "AUTO" is selected in the Printing Mode.

Fixed Price Products

EXAMPLE Print quantity "3".

PLU 6		21-JU	10) 11:15	PCS	1		
	RO	FIXED ¥	VEIGHT	kg			
U/P	F/P	FIX UPR	FIX UPR +WEIGHT	COUPONMS 0			
SPECIAL	-\$	-%	SP.(U/P)	-\$(U/P			
0.00	0.00	0.0	0.00	0.00			
-%(U/P)	P DATE	S DATE	TOTALADD	PRN QTY	FIXED	PRICE	£
0.0	21-06-07	27-06-07	<add></add>	0			
PRN MD. <auto></auto>	PEEL MD. <indiv></indiv>	CASSETTE 1	MULTI	FUNCTION GROUP		4.()0

2. Enter a desired number of labels and press the "PRN QTY (Print Quantity)" field on the screen.

PLV 6		21-JU	N-2007(TH	HU) 11:15	PCS	1	
.	RO	AST	BEEF	'	FIXED ¥	FIGHT	kg
U/P	F/P	FIX UPR	FIX UPR +WEIGHT	COUPONMS			
SPECIAL	-\$	-%	SP.(U/P)	-\$(U/P			
0.00	0.00	0.0	0.00	0.00			
-%(U/P)	P DATE	S DATE	TOTALADD	PRN QTY	FIXED	PRICE	£
0.0	21-06-07	27-06-07	<add></add>	3∩			
PRN MD.	PEEL MD.	CASSETTE	MULTI	FUNC IN		4.0	ነበ
<auto></auto>	<indiv></indiv>	1	HOLTI	GR(/'''		T.V	<i>'</i> U

3. Press the [PRINT] key on the key sheet.



The set number of labels will be issued.



Note: To interrupt the issue of labels, press the [PRINT] key again. To continue the issue of labels, press the [PRINT] key again.

6


SELF-SERVICE OPERATIONS

6.1 WEIGHING PRODUCTS

1. Ensure that the initial screen is displayed.




2. Select a desired product by pressing the corresponding button on the screen.





3.	The selected proc	selected product screen appears.					
0.							
	6	ROWEIGHT kg UNIT PRICE £/kg TOTAL PRICE £ 0.0000 4.00 0.000 TARE kg					
	ZERO WEIGHT						
	0.00	0 4.00	0.00				
	0.00						
			SEARCH				




6.2 FIXED PRICE PRODUCTS


1. Ensure that the initial screen is displayed.



2. Select a desired product by pressing the corresponding button on the screen.



3. The selected product screen appears. Then, press the [LABEL PRINT] button on the screen to issue the label.



ACCUMULATOR MODE

7.1 MANUAL INPUT ACCUMULATION

1. To get the Operation Menu Select screen, press the [MODE] key on the key sheet.

Mode

Then, press the "ACC (Accumulator)" filed.

MENU SELECT	21-JUN-2007(THU) 15:35	1/1
OPERATE	SALES	
TOTAL	م م م	
PROGRAM	ant (^m)	
🔮 SETUP	£~~	
ADJUST	TOTAL ADJUST	

2. The Accumulator (Input Number Accumulation) screen appears.

ACC1(INPU	T NUM ACC)		21-JUN-2007(*	THV) 15:35			
0	<		>	ſ			
DAILY	PCS	WEIGHT(kg)	PRICE(£)	SPECIAL			
TOTAL	0	0.000	0.00				
INPUT	0	0.000	0.00	SPEC.U/P TRACE			
CALC.	0	0.000	0.00	HISTORY			
NUM. VOID	Lot No.						

3. Enter a desired PLU number and press the [PLU] key on the key sheet.



The Input Number Accumulation screen for the selected product appears.

ACC1(INPU	T NUM ACC)		21-JUN-2007(THU) 15:35		
6	<	ROAST BEEF	>			
DAILY	PCS	WEIGHT(kg)	PRICE(£)	SPECIAL		
TOTAL	7	2.094	12.51			
INPUT	0	0.000	0.00	SPEC.U/P		
CALC.	7	2.094	12.51	HISTORY		
	Lot No.					
NUM. VOID	WGT. VOID NUM	1. ACC WGT. ACC	INPUT	ACC		



4. Enter a quantity, weight, and price that are to be accumulated and press the corresponding fields for registration. Then, press the [ACC] button on the screen.

EXAMPL	Quantity '	1 pc.", Weight	"169g", Price	"\$0.84"
ACC1(INPU	T NUM ACC)		21-JUN-2007(THU) 15:35
6	<	ROAST BEEF	>	
DAILY	PCS	WEIGHT(kg)	PRICE(£)	SPECIAL
TOTAL	7	2.094	12.51	
INPUT	1	0.169	0.84	SPEC.U/P
CALC.				<u>u</u>
NUM. VOID				ACC

5. <u>The confirmation screen appears. Then, press the [EXEC] but</u>ton on the screen.

A	ACC1 (INPUT NUM ACC)	21-IIIN-2007(THU) 15:35
ſ		21-JUN-2007(THU) 15:35
l	CHECK FOF	RADD
	IS IT OK TO CALCULATE DESIGNATED DATA?	
l	11006 - 0000	EXEC STOP

	-	ration has be T NUM ACC)	en completed.	21-JUN-2007(*	THU) 15:3
	6 < ROAST BEEF >) t
	DAILY	PCS	WEIGHT(kg)	PRICE(£)	SPECIAL
	TOTAL	8	2.263	13.35	
	INPUT	0	0.000	0.00	SPEC.U/P
	CALC.	8	2.263	13.35	HISTORY
		Lot No.			VOID
١	NUM. VOID	WGT. VOID NUM	1. ACC WGT. ACC	INPUT	ACC


7.2 WEIGHING ACCUMULATION

1. To get the Operation Menu Select screen, press the [MODE] key on the key sheet.

Then, press the "ACC (Accumulator)" filed. 21-JUN-2007(THU) 15:35 MENU SELECT 1/1 🗖 OPERATE TOTAL ACC1 1000 🕍 PROGRAM 100 SETUP 100 📟 ADJUST 🛵 TOTAL ADJUST 21-JUN-2007(THU) 15:35 ACC1 (INPUT NUM ACC) < t > SPECIAL TOTAL 0 0.000 0.00 SPEC.U/P 0 0.000 0.00 INPUT 0.000 0.00 0 CALC. NUM. ACC WGT. ACC NUM. VOID WGT. VOID INPUT

Mode

2. To get the Weighing Accumulation screen, press the [WGT. ACC] tab.



3. Enter a desired PLU number and press the [PLU] key on the key sheet.



The Weighing Accumulation screen for the selected product appears.


ACC1 (WEIG	FHU) 15:35			
6	<	ROAST BEEF		
TARE(kg)	WEIGHT(kg)	UNIT PRICE(£/kg)	PRICE(£)	SPECIAL
0.000 ZERO	0.000	4.00	0.00	SPEC.U/P
TOTAL	2.685	9 PC(S)	15.04	HISTORY
	Lot No.			VOID
NUM. VOID	WGT. VOID NUM	1. ACC WGT. ACC	INPUT	ACC

4. Put a product on the weigh platter and press the [ACC] button on the screen..



ACC1 (WEIG	ACC1(WEIGHTING ACC) 21–JUN–2007(THU) 15:35							
6	<	ROAST BEEF	>					
TARE(kg)	WEIGHT(kg)	UNIT PRICE(£/kg)	PRICE(£)	SPECIAL				
0.000	0.422	4.00	1.69	SPEC.U/P				
TOTAL	2.685	9 PC(S)	15.04	신원				
NUM. VOID								

5. The confirmation screen appears. Then, press the [EXEC] button on the screen.



6. Remove the product from the weigh platter.



A	ACC1 (WEIGHTING ACC) 21–JUN–2007(TH						
	5 < TARE(kg) WEIGHT(kg)		ROAST BEEF	ROAST BEEF >			
ſ			UNIT PRICE(£/kg)	PRICE(£)	SPECIAL		
	0.000 ZERO	0.000	4.00	0.00	SPEC.U/P		
li	TOTAL	3.107	10 PC(S)	16.73	HISTORY		
		Lot No.			VOID		
ľ	NUM. VOID	WGT. VOID NUT	M. ACC WGT. ACC	INPUT	ACC		

7.3 MANUAL INPUT VOID

1. To get the Operation Menu Select screen, press the [MODE] key on the key sheet.

Then, press the "ACC (Accumulator)" filed. 21-JUN-2007(THU) 15:35 MENU SELECT 1/1 🗖 OPERATE TOTAL ACC1 lood 🕍 PROGRAM 100 SETUP haa 🛵 TOTAL ADJUST 📟 ADJUST 21-JUN-2007(THU) 15:35 ACC1 (INPUT NUM ACC) < t > SPECIAL TOTAL 0 0.000 0.00 SPEC.U/P 0 0.000 0.00 INPUT 0.000 0.00 CALC. 0 NUM. ACC WGT. ACC NUM. VOID WGT. VOID INPUT

Mode

2. To get the Input Number Void screen, press the [NUM. VOID] tab.

 ACC1(INPUT NUM VOID)
 21-JUN-2007(THU) 15:35

 0

 DAILY
 PCS

 WEIGHT(kg)
 PRICE(E)

 SPECIAL
 0

0.000

WGT. ACC

0.000

INPUT

0

0

NUM, ACC

NUM, VOID WGT. VOID

SPEC.U/P

VOID

0.00


3. Enter a desired PLU number and press the [PLU] key on the key sheet.




The Input Number Void screen for the selected product appears.

ACC1 (INPUT NUM VOID) 21-JUN-					21-JUN-2007	(THU) 15:35
6 < ROA				ST BEEF	>	
DAILY	PCS		WEI	GHT(kg)	PRICE(£)	SPECIAL
TOTAL		10		3.107	16.73	
INPUT		0		0.000	0.00	SPEC.U/P
CALC.		10		3.107	16.73	TRACE
CALC.	Lot No.	10		3.107	16.73	VOID
NUM. VOID	WGT, VOID	NUM	1. ACC	WGT. ACC	INPUT	ACC

4. Enter a quantity, weight, and price that are to be voided and press the corresponding fields for registration. Then, press the [VOID] button on the screen.



5. <u>The confirmation screen appears. Then, press the [EXEC] button on the screen.</u>



6.

The registration has been completed. 21-JUN-2007(THU) 15:36 < > t ROAST BEEF SPECIAL 2.938 15.89 TOTAL 9 SPEC.U/P 0 0.00 INPUT 0.000 2.938 15.89 9 CALC. NUM, VOID WGT, VOID NUM, ACC WGT. ACC INPUT

7.4 WEIGHING VOID


1. To get the Operation Menu Select screen, press the [MODE] key on the key sheet.

Then, press the "ACC (Accumulator)" filed. 21-JUN-2007(THU) 15:35 MENU SELECT 1/1 🗖 OPERATE TOTAL ACC1 1000 🕍 PROGRAM hood SETUP haa 🛵 TOTAL ADJUST 📟 ADJUST 21-JUN-2007(THU) 15:35 ACC1 (INPUT NUM ACC) < t > SPECIAL TOTAL 0 0.000 0.00 SPEC.U/P 0 0.000 0.00 INPUT 0.000 0.00 0 CALC. NUM. ACC WGT. ACC NUM. VOID WGT. VOID INPUT

Mode

2. To get the Weighing Void screen, press the [WGT. VOID] tab. ACC1 (WEIGHTING VOID) 21-JUN-2007(THU) 15:35 < > SPECIAL 0.000 SPEC.U/P 0.000 0.00 0.00 ZERO 0.000 0.00 TOTAL 0 VOID U. WGT. VOID NUM. ACC NUM, VOID WGT. ACC INPUT

3. Enter a desired PLU number and press the [PLU] key on the key sheet.



The Weighing Void screen for the selected product appears.


ACC1 (WEIG	ACC1 (WEIGHTING VOID) 21-JUN-2007(T					
6	<	ROAST BEEF	>) t		
TARE(kg)	WEIGHT(kg)	UNIT PRICE(£/kg)	PRICE(£)	SPECIAL		
0.000 ZERO	0.000	4.00	0.00	SPEC.U/P		
TOTAL	2.938	9 PC(S)	15.89	HISTORY		
	VOID					
NUM, VOID	WGT, VOID NUM	4. ACC WGT. ACC	INPUT	ACC		

4. Put a product on the weigh platter and press the [VOID] button on the screen..




ACC1 (WEIGHTING VOID) 21-JUN-2007(THU						
6	<	ROAST BEEF	>) t		
TARE(kg)	WEIGHT(kg)	UNIT PRICE(£/kg)	PRICE(£)	SPECIAL		
0.000	0.422	4.00	1.69			
TOTAL	2.938	9 PC(S)	15.89			
	LOT NO.					
NUM. VOID	ACC					

5. The confirmation screen appears. Then, press the [EXEC] button on the screen.



6. Remove the product from the weigh platter.



TOTAL ADJUST MODE

8.1 MANUAL INPUT SUBTRACTION

1. To get the Operation Menu Select screen, press the [MODE] key on the key sheet.



Then, press the "TOTAL ADJUST" filed.



то	TOTAL ADJUST(INPUT NUM SUB) 21-JUN-2007(TI							FHU) 15:35
	0	<					>	
	DAILY	PCS		WEI	GHT(kg)	PRICE(£)		SPECIAL
	TOTAL		0		0.000		0.00	
	INPUT		0		0.000	0.	00	SPEC.U/P
	CALC.		0		0.000		0.00	HISTORY
		Lot No.						SUB
	NUM. SUB	WGT. SUB	NUM	. ADD	WGT. ADD	INPUT		ADD

2. Enter a desired PLU number and press the [PLU] key on the key sheet.




The Total Adjust (Input Number Subtraction) screen for the selected product appears.

-	FOTAL ADJ	UST(INPUT NU	21-JUN-2007(*	THV) 15:35	
	6	<	ROAST BEEF	>	
Í	DAILY	PCS	WEIGHT(kg)	PRICE(£)	SPECIAL
	TOTAL	39	5.936	130.16	
	INPUT	0	0.000	0.00	SPEC.U/P
	CALC.	39	5.936	130.16	HISTORY
		Lot No.			SUB
	NUM. SUB	WGT. SUB NUM	I. ADD WGT. ADD	INPUT	ADD



3. Enter a quantity, weight, and price that are to be subtracted and press the corresponding fields for registration. Then, press the [SUB] button on the screen.



4. The confirmation screen appears. Then, press the [EXEC] button on the screen.

ł	ACC1(INPUT NUM ACC)	21-IIIN-2007(THII) 15:35
ſ		21-JUN-2007(THU) 15:35
l	СНЕСК FO	RADD
	IS IT OK TO CALCULATE DESIGNATED DATA?	
	11006 - 0000	EXEC STOP

_		ne registration has been completed.						
	TOTAL AD.	JUST(II	NPUT NU	M SUB)	21-JUN-2007(THU) 15:3			
[6	<		ROAST BEEF	>			
l	DAILY		PCS 👘	WEIGHT(kg)	PRICE(£)	SPECIAL		
	TOTAL		38	5.767	129.32			
	INPUT		0	0.000	0.00	SPEC.U/P		
	CALC.		38	5.767	129.32	HISTORY		
		Lot	N0.			SUB		
	NUM. SUB	WGT.S	UB NUM	I. ADD WGT. ADD	INPUT	ADD		

8.2 WEIGHING SUBTRACTION

1. To get the Operation Menu Select screen, press the [MODE] key on the key sheet.



Then, press the "TOTAL ADJUST" filed.



٦	TOTAL ADJUST(INPUT NUM SUB) 21-JUN-2007(TH					
	0 < >					
ſ	DAILY	PCS	WEIGHT(kg)	PRICE(£)	SPECIAL	
	TOTAL	0	0.000	0.00		
	INPUT	0	0.000	0.00	SPEC.U/P	
	CALC.	0	0.000	0.00	HISTORY	
		SUB				
	NUM. SUB	WGT. SUB NUM	I. ADD WGT. ADD	INPUT	ADD	

2. To get the Total Adjust (Weighing Subtraction) screen, press the [WGT. SUB] tab.

TOTAL ADJUST(WEIGHTING SUB) 21-JUN-2007(THU) 15:35						
0	F					
TARE(kg)	WEIGHT(kg)	UNIT PRICE(£/kg)	PRICE(£)	SPECIAL		
0.000 ZERO	0.000	0.00	0.00	SPEC.U/P		
TOTAL		0	0.00	TRACE		
	SUB					
NUM. SUB	ADD					

3. Enter a desired PLU number and press the [PLU] key on the key sheet.



The Total Adjust (Weighing Subtraction) screen for the selected product appears.


TOTAL ADJUST(WEIGHTING SUB) 21–JUN–2007(THU) 15:35						
6	6 < ROAST BEEF >					
TARE(kg)	WEIGHT(kg)	UNIT PRICE(£/kg)	PRICE(£)	SPECIAL		
0.000 ZERO	0.000	4.00	0.00	SPEC.U/P		
TOTAL	5.767	38 PC(S)	129.32	HISTORY		
	SUB					
NUM, SUB	WGT. SUB NUM	I. ADD WGT. ADD	INPUT	ADD		

4. Put a product on the weigh platter and press the [SUB] button on the screen.



TOTAL ADJ	UST(WEIGHTIN	21-JUN-2007(THU) 15:35	
6	<	ROAST BEEF	>) t
TARE(kg)	WEIGHT(kg)	UNIT PRICE(£/kg)	PRICE(£)	SPECIAL
0.000	0.422	4.00	1.69	R.U/P
TOTAL	5.767	38 PC(S)	129.32	<u>I YU</u>
	SUB			
NUM. SUB	WGT. SUB	1. ADD WGT. ADD	INPUT	ADD

5. <u>The confirmation screen appears. Then, press the [EXEC] button on the screen.</u>



6. Remove the product from the weigh platter.



TOTAL ADJ	TOTAL ADJUST(WEIGHTING SUB) 21–JUN–2007(T					
6	6 < F		>			
TARE(kg)	WEIGHT(kg)	UNIT PRICE(£/kg)	PRICE(£)	SPECIAL		
0.000 ZERO	0.000	4.00	0.00	SPEC.U/P		
TOTAL	5.345	37 PC(S)	127.63	TRACE		
	Lot No.					
NUM. SUB	WGT. SUB	I. ADD WGT. ADD	INPUT	ADD		

8.3 MANUAL INPUT ADDITION

1. To get the Operation Menu Select screen, press the [MODE] key on the key sheet.



Then, press the "TOTAL ADJUST" filed.



TOTAL ADJUST(INPUT NUM SUB) 21-JUN-2007(TH						
ĺ	0 < >					
ſ	DAILY	PCS	WEIGHT(kg)	PRICE(£)	SPECIAL	
l	TOTAL	0	0.000	0.00		
l	INPUT	0	0.000	0.00	SPEC.U/P	
l					TRACE HISTORY	
l	CALC.	0	0.000	0.00	SUB	
	Lot No.					
	NUM. SUB	WGT. SUB NUM	I. ADD WGT. ADD	INPUT	ADD	

2. To get the Total Adjust (Input Number Addition) screen, press the [NUM. ADD] tab. TOTAL ADJUST(INPUT NUM ADD) 21-JUN-2007(THU) 15:35

0	<		>			
DAILY	PCS	WEIGHT(kg)	PRICE(£)	SPECIAL		
TOTAL	0	0.000	0.00			
INPUT	م	0.000	0.00	SPEC.U/P		
		<u>ا</u>		TRACE		
CALC.		0.000	0.00			
	SUB					
NUM. SUB	WGT. SUB NUM	ADD WGT. ADD	INPUT	ADD		


3. Enter a desired PLU number and press the [PLU] key on the key sheet.




The Total Adjust (Input Number Addition) screen for the selected product appears.

TOTAL ADJUST(INPUT NUM ADD) 21–JUN–2007(THU) 15:35						
6) t					
DAILY	PCS	WEIGHT(kg)	PRICE(£)	SPECIAL		
TOTAL	37	5.345	127.63			
INPUT	0	0.000	0.00	SPEC.U/P		
CALC.	37	5.345	127.63	HISTORY		
	SUB					
NUM, SUB	WGT.SUB NU	M. ADD WGT. ADD	INPUT	ADD		

4. Enter a quantity, weight, and price that are to beaded and press the corresponding fields for registration. Then, press the [ADD] button on the screen.



5. The confirmation screen appears. Then, press the [EXEC] button on the screen.



6.	The regist	ration has be	en completed.			
	TOTAL ADJ	TOTAL ADJUST(INPUT NUM ADD) 21-JUN-2007(T				
	6	<	ROAST BEEF	>		
	DAILY	PCS	WEIGHT(kg)	PRICE(£)	SPECIAL	
	TOTAL	38	5.514	128.47		
	INPUT	0	0.000	0.00	SPEC.U/P	
	CALC.	38	5.514	128.47	HISTORY	
		Lot No.			SUB	
	NUM. SUB	WGT. SUB NUM	ADD WGT. ADD	INPUT	ADD	

8.4 WEIGHING ADDITION

1. To get the Operation Menu Select screen, press the [MODE] key on the key sheet.

Mode Then, press the "TOTAL ADJUST" filed. MENU SELECT 21-JUN-2007(THU) 15:35 1/1 🖵 OPERATE 前 ACC1 🔨 TOTAL ACC2 📲 🖉 PROGRAM SETUP ACC3 ADJUST TOTAL ADJUST TOTAL ADJUST(INPUT NUM SUB) 21-JUN-2007(THU) 15:35 < > SPECIAL TOTAL 0 0.000 0.00 SPEC.U/P 0 0.000 0.00 INPUT 0 0.000 0.00 CALC. SUB WGT. SUB NUM. ADD WGT. ADD NUM, SUB

To get the Total Adjust (Weighing Add) screen, press the [WGT. ADD] tab. 2. TOTAL ADJUST(WEIGHTING ADD) 21-JUN-2007(THU) 15:35 < > SPECIAL 0.000 SPEC.U/P 0.000 0.00 0.00 ZERO 0.000 TOTAL 0.00 0 11 ADD NUM, SUB WGT. SUB NUM, ADD WGHADD INPUT

3. Enter a desired PLU number and press the [PLU] key on the key sheet.



The Total Adjust (Weighing Add) screen for the selected product appears.


TOTAL ADJUST(WEIGHTING ADD) 21-JUN-2007(TH					
6 <		ROAST BEEF	>		
TARE(kg)	WEIGHT(kg)	UNIT PRICE(£/kg)	PRICE(£)	SPECIAL	
0.000 ZERO	0.000	4.00	0.00	SPEC.U/P	
TOTAL	5.514	38 PC(S)	128.47	HISTORY	
	SUB				
NUM. SUB	WGT.SUB NUM	1. ADD WGT, ADD	INPUT	ADD	

4. Put a product on the weigh platter and press the [ADD] button on the screen..



TOTAL ADJUST(WEIGHTING ADD) 21–JUN–2007(TH					
6	<	ROAST BEEF	>		
TARE(kg)	WEIGHT(kg)	UNIT PRICE(£/kg)	PRICE(£)	SPECIAL	
0.000	0.422	4.00	1.69	SPEC.U/P	
TOTAL	5.514	38 PC(S)	128.47	17 권	
NUM. SUB	Lot No.	4. ADD WGT. ADD	INPUT		

5. <u>The confirmation screen appears. Then, press the [EXEC] button on the screen.</u>




6. Remove the product from the weigh platter.




TOTA	TOTAL ADJUST(WEIGHTING ADD) 21-JUN-2007(TI					
6	6 <		ROAST BEEF	>		
TAR	RE(kg)	WEIGHT(kg)	UNIT PRICE(£/kg)	PRICE(£)	SPECIAL	
z	0.000 ERO	0.000	4.00	0.00	SPEC.U/P	
ТС	TAL	5.936	39 PC(S)	130.16	HISTORY	
	LOT NO.					
NUM	4. SUB	WGT. SUB NU	M. ADD WGT. ADD	INPUT	ADD	

TOTAL MODE

9.1 DAILY TOTAL



2. The Daily Total screen appears.



3. To obtain the Hourly Total screen, press the [HOUR.] tab. To change the pages, press the [▼] or [▲] button on the screen.

a 1 a 1				
PROD DAILY TOTAL(HOUR)	21	-JUN-2007	(THU) 15:	35 1/5
[
No. HOURLY(hh:mm)	PCS	WEIGHT(kg)	PRICE(£)	
0 00:00 ~ 00:59	0	0.000	0.00	
1 01:00 ~ 01:59	0	0.000	0.00	
2 02:00 ~ 02:59	0	0.000	0.00	
3 03~~ 03:59	0	0.000	0.00	
4 04:59	0	0.000	0.00	JIM
	0	0.000	0.00	
TOTAL HOUR. DEPT. GR	OUP ITE	M OPER.	CLASS	, •
	•			
	-			

i



PROD DAILY TOTAL(HOUR) 21-JUN-2007(THU) 15:35						
No. HOURLY(hh:mm)	PCS	WEIGHT(kg)	PRICE(£)			
20 20:00 ~ 20:59	0	0.000	0.00			
21 21:00 ~ 21:59	0	0.000	0.00			
22 22:00 ~ 22:59	0	0.000	0.00			
23 23:00 ~ 23:59	0	0.000	0.00	(**)		
				지		
TOTAL	0	0.000	0.00			
TOTAL HOUR. DEPT. GROUP ITEM OPER. CLASS						

4. To obtain the Department Total screen, press the [DEPT.] tab. To change the pages, press the [▼] or [▲] button on the screen.

PROD DAILY TOTAL(DEPT)	D DAILY TOTAL(DEPT) 21-JUN-2007(THU) 15:35						
No. DEPARTMENT	PCS W	EIGHT(kg)	PRICE(£)				
$- \overline{\lambda}$							
тот							
TOTAL HOUR, DEPT, GR	OUP ITEM	OPER.	CLASS	السار			

5. To obtain the Group Total screen, press the [GROUP] tab.


To change the pages, press th	e $[\bullet]$ or $[\bullet]$ button on the screen.
-------------------------------	--

PROD D	AILY TOTAL(GROUP)	21	1/1		
N0,	GROUP	PCS	WEIGHT(kg)	PRICE(£)	
╟───┼					
	<u> </u>	<u> </u>			
	TOTAL				
TOTAL	HOUR. DEPT. GR		EM OPER.	CLASS	


6. To obtain the Designated Item Total screen, press the [ITEM] tab.

PROD DAILY TOTAL(ITEM)	21-JUN-2007(THU) 15:35
0	
PCS WEIGHT(kg) 0 0.000 TOTAL HOUR. DEPT. GROUP ITEM	PRICE(£) 0.00


Enter a desired PLU number using the numeric keys and press the [PLU] key on the key sheet.



7. To obtain the Operator Total screen, press the [ORER.] tab.



8. To obtain the Class Total screen, press the [CLASS] tab.



NO	The object of analysis is not specified.
DEPT.	The object of analysis is specified to be departments.
GROUP	The object of analysis is specified to be groups.
PLU No.	Analysis is performed in ascending PLU number order.
ABC PRICE	Analysis is performed in descending price order.
ABC WEIGHT	Analysis is performed in descending weight order.
ABC PCS	Analysis is performed in descending quantity order.
Z PRICE	Analysis is performed in ascending price order.
Z WEIGHT	Analysis is performed in ascending weight order.
Z PCS	Analysis is performed in ascending quantity order.

9.2 WEEKLY TOTAL

1. Press the "PRODUCTION WEEKLY TOTAL" filed. MENU SELECT 21-JUN-2007(THU) 15:35 1/2



2. The Weekly Total screen appears.

To change the pages, press the $[\bullet]$ or $[\bullet]$ button on the screen.

PROD WEEKLY TOTAL(WEEK) 21-JUN-2007(THU) 15:35						
No. WEEK HOULY	NO. WEEK HOULY PCS WEIGHT(kg) PRICE(£)					
0 SUN	0	0.000	0.00			
1 MON	0	0.000	0.00			
2 TUE	0	0.000	0.00			
3 WED	0	0.000	0.00			
4 THU	7	2.954	11.83	JUID		
TOTAL	13	5.306	23.99	\sum		
				Y		
WEEK SUN MON TUE	WED	THU FRI	SAT			

PROD	PROD WEEKLY TOTAL(WEEK) 21-JUN-2007(THU) 15:35				
N0.	WEEK HOULY	PCS	WEIGHT(kg)	PRICE(£)	
5	FRI	0	0.000	0.00	
6	SAT	0	0.000	0.00	
	TOTAL	0	0.000	0.00	\bigcirc
WEEK	SUN MON TUE	WED	THU FRI	SAT	

3. To obtain total for the day-of-the week, press a desired day-of-the week tab. To change the pages, press the [▼] or [▲] button on the screen.

PROD WEEKLY TOTAL(SUN) 21-JUN-2007(THU) 15:35						
No. HOURLY	PCS	WEIGHT(kg)	PRICE(£)			
0 00:00 ~ 00:59	0	0.000	0.00			
1 01:00 ~ 01:59	0	0.000	0.00			
2 02:00 ~ 02:59	0	0.000	0.00			
3 0 ~ 03:59	0	0.000	0.00			
4 4 ~ 04:59	0	0.000	0.00	JIM		
	0	0.000	0.00			
	WED	THU FRI	SAT	· •		

OD	WEEKLY TOTAL(SUN)	21	-JUN-2007	(THU) 15:3	5 5/5
N0.	HOURLY	PCS	WEIGHT(kg)	PRICE(£)	t
20	20:00 ~ 20:59	0	0.000	0.00	
21	21:00 ~ 21:59	0	0.000	0.00	∣└∩
22	22:00 ~ 22:59	0	0.000	0.00	/m
23	23:00 ~ 23:59	0	0.000	0.00	
					אל
	TOTAL	0	0.000	0.00	


9.3 CUMULATIVE TOTAL

 Press the "PRODUCTION CUMULATIVE TOTAL" filed.

 MENU SELECT
 21-JUN-2007(THU) 15:35
 1/2



2. The Cumulative Total screen appears.




3. To obtain total for each department, press the [DEPT.] tab on the screen.To change the pages, press the [▼] or [▲] button on the screen.

-					
PROD CUMULATI	VE TOTAL(DI	EPT) 21-	-JUN-2007((THU) 15:35	1/1
No. DEPA	RTMENT	PCS	WEIGHT(kg)	PRICE(£)	L
ТОТ					
TOTAL HOUR			M OPER.	CLASS	


4. To obtain total for each group, press the [GROUP] tab on the screen. To change the pages, press the $[\bullet]$ or $[\bullet]$ button on the screen.

3 - 1 - 3 , 1 -										
PROD CUMULATIVE TOTAL(GROUP)21-JUN-2007(THU) 15:35										
No. GROUP	PCS	WEIGHT(kg)	PRICE(£)							
5	<u>}</u>									
TOTAL	\geq									
TOTAL HOUR DEPT, GR	J .OUP	EM OPER.	CLASS	J						



9.4 TRACEABILITY TOTAL


1. Press the "TRACEABILITY TOTAL" filed.



2. The Traceability Item screen appears.

To change the pages, press the $[\bullet]$ or $[\bullet]$ button on the screen.

To obtain Traceability Total screen, press the [DETAIL] button on the screen.



3. The Traceability Total screen appears.


TRACEABILITY	TOTAL		21-JUN	-2007(THU) 15:35	1/1
ITEM No.	00000001					
ITEM NAME	GROUND BE	EF/(TEX	(AS)			
	LOT NO.			PRICE(£)	DATE	
	40.	PCS		PRICE(E)	TIME	
L						

9.5 PRESET REPORT PRINTING


1. <u>Press the "PRESET REPORT" filed.</u>



2. The Preset Report screen appears.



3. Select desired reports by pressing the corresponding fields. Press the [STRAT] button to issue selected join reports.




9.6 TOTAL CLEAR

- Press the [v] button on the screen. 1. MENU SELECT 21-JUN-2007(THU) 15:35 1/2 PROD DAILY TOTAL OPERATE 🔨 TOTAL E PROD WEEKLY TOTAL 📄 🍯 PROGRAM PROD CUMULATIVE TOTAL TRACEABILITY TOTAL SETUP 🛯 ADJUST PRESET REPORT
- **2.** The second page of the Menu Select screen appears.


To obtain the Total Clear screen, press the "TOTAL CLEAR" field on the screen.




3. The Total Clear screen appears.



4 Select desired reports to be cleared by pressing the corresponding fields.





6. The confirmation screen appears. Then, press the [EXEC] button on the screen for execution.

-	OTAL CLEAR	21-11N-2007(THII) 15:35 21-JUN-2007(THU) 15:35
	DELETE CHE	ск
	IS IT OK TO DELETE SELECTED TOTAL?	
	12001 - 0000	EXEC STOP

PROGRAM MODE

1.



10.1 PROGRAM MODE ENTRY

- Ensure that the initial screen is displayed. PLV 0 21-JUN-2007(THU) 11:13 TARE kq 0.0Check the weight before operation. Enter PLU No. and press [PLU] key. ZERO WEIGHT 0.00UNIT PRICE GROUND BEEF (OREGON) GROUND BEEF (UTAH) <u>GROUND</u> ICED SLICED BEEF SPECIAL (TĚXÁS) () ROASI BEEF SPECIAL ROAST BEEF LAMB T-BONE STEAK TOTAL PRICE PRN MD CASSETTE OPERATOR GROUP 0.0SUBTOTAL DISPLAY <AUTO> 1
- 2. Press the [MODE] key on the key sheet.




The Operation Menu Select screen appears.

Then, press the [PROGRAM] button on the screen.

MENU SELECT		21-JUN-2007(THU)	11:13	1/1
OPERATE	SALES			
TOTAL	<u> </u> ACC1			
PROGRAM	ACC2 🔒			
SE DI	💼 ассз			
ADJ		ADJUST		

- **3.** The Program Menu Select screen appears.
 - To change the pages, press the $[\bullet]$ or $[\bullet]$ button on the screen.

MENU SELECT	21-JUN-2007(THU) 11:13	1/8
OPERATE	PLU PLV FILE	
ΤΟΤΑΙ	🗙 CAMPAIGN	
PROGRAM	P OPERATORS	-Thu
SETUP	PRESET KEY	5
ADJUST	Henoel AD MSG	



MENU SELECT	21-JUN-2007(THU) 11:1	3 5/8
	PCS PCS BUX	
TOTAL	FREE1	
PROGRAM	FREE2	
SETUP	FREE3	52
ADJUST	FREE4	
MENU SELECT	21-JUN-2007(THU) 11:1	3 6/8
OPERATE	FREE5	
TOTAL	FREE6	
PROGRAM	FREE7	
실 SETUP	FREE8	52
ADJUST	FREE9	
MENU SELECT	21-JUN-2007(THU) 11:1	3 7/8
MENU SELECT	21-JUN-2007(THU) 11:1	3 7/8
		3 7/8
	FREE10	3 7/8
OPERATE TOTAL	FREE10 FREE11	3 7/8
OPERATE TOTAL PROGRAM	FREE10 FREE11 FREE12	3 7/8
OPERATE TOTAL PROGRAM SETUP	FREE10 FREE11 FREE12 FREE13	
OPERATE TOTAL PROGRAM SETUP ADJUST	FREE10 FREE11 FREE12 FREE13 FREE14	
OPERATE TOTAL PROGRAM SETUP ADJUST MENU SELECT	FREE10 FREE11 FREE12 FREE13 FREE14 21–JUN–2007(THU) 11:1 FREE15	
OPERATE TOTAL PROGRAM SETUP COPERATE OPERATE	FREE10 FREE11 FREE12 FREE13 FREE14 21–JUN–2007(THU) 11:1	
OPERATE TOTAL PROGRAM SETUP COMPANY MENU SELECT MENU SELECT COPERATE TOTAL	FREE10 FREE11 FREE12 FREE13 FREE14 21–JUN–2007(THU) 11:1 FREE15	

Note: To exit the Program Mode, press the [ESC] (Escape) key on the key sheet.

10.2 PLU FILE REGISTRATION

 Press the "PLU FILE" field on the Program Menu Select screen.


 MENU SELECT
 21-JUN-2007(THU) 11:16



- **2.** The Item List screen appears.
 - To change the pages, press the $[\bullet]$ or $[\bullet]$ button on the screen

ITEM LIST	21-JUN-2007(THU) 11:1	6 1/225
1	GROUND BEEF/(TEXAS)	
2	GROUND BEEF/(OREGON)	
3	GROUND BEEF/(UTAH)	
4	SLICED BEEF	
5	SLICED BEEF/SPECIAL	_ /m
6	ROAST BEEF	
FIND PLU	SEARCH DISP. 1	DELETE

3. Press to select a desired field. Then, press the [DETAIL] button on the screen.



4.	The Item Detail screen appears. To edit the PLU name, press the [EDIT] button on the	he screen
	ITEM DETAIL 21-JUN-2007(T	HU) 11:16
	C C ROAST BEEF > EDIT	L
	SALES MODE MARKDOWN MODE OPEN PRICE < 0:WEIGHT > 0:NORMAL > 0:YES	
	UNIT PRICE M/D AMOUNT QTY UNIT TYPE TAX FIXED	PREVIEW
	TARE 2nd TARE P. TARE F. TARE UNDER WGT UPPER WGT 0.000 0.000 0.0 NO YES 0.000 0.000	INPUT
	SALE1 SALE2 MESSAGE IMAGE PRINT DATE CODE	DELETE

5. The text edit screen appears.

Edit a text according to the procedure explained in Appendix "Text Editing".

	ITEM DETAIL(ITEM NAME EDIT) 21–JUN–2007(THU) 11:1									
RO	ROAST BEEF									
Q	W	E	R	T	Y	U		0	P	
A	s	D	F	G	н		К	L		
	Z	×	С		B		м	,		
No. CHAR REMAIN 6 010 5109			STYLE /		FONT 15/30x15	INP	υT	ERASE		


6.

Ensure that the first sales related screen is displayed.

Sales Mode: Weighing Product

	ITEM	DETA	AIL 👘						21-	JUN-2	:007(ТΗ	U) 11:16
		6	<		ROAST BEEF			> EDIT					
		SALES	MODE		MA	ARKDOWI	N MODE		OP	EN PRIC	E	1L	
	<	0:WE	EIGHT	>	<	0:NORM	MAL	>	<	0:YES	>		
	UNIT	PRICE	M/D	AMOUN		QTY	UNIT T	YPE	TAX	FIXE	D WGT		
Y	∼่⁴	.00		0.00		1	5:ST				.000		PREVIEW
/	TAR	E 2	nd TARE	P. TAR		E, TA	RE	UN	DER WGT	UPPE	RWGT		INPUT
U	0.00		0.000	0.0		NO	YES		0.000	<u> </u>	000	Л	
		1	SALE2	MESSA	GE	IMAGE	PRIN	т	DATE		DE		DELETE

Sales Mode: Fixed Price Product



Sales Mode: Weighing Fixed Price Product

	J	04 UUU 0007/T	
ITEM DETAIL		21-JUN-2007(T	HU) 11:16
6 <	ROAST BEEF	> EDIT	
SALES MODE	MARKDOWN MODE	OPEN PRICE	
< 2:WGT F/PRI >	< 0:NORMAL >	< 0:YES >	
FIXED PRICE M/D AMOU	NT QTY UNIT TYPE	TAX FIXED WGT	
4.00 0.00	0 0:NO PRN	0.000	PREVIEW
TARE 2nd TARE P. TA	ARE F. TARE UND	DER WGT UPPER WGT	INPUT
0.000 0.000 0.0	D NO YES	0.000 0.000	
L			
SALE1 SALE2 MESS	AGE IMAGE PRINT	DATE CODE	DELETE

ITEM DE	TAIL				21-J	UN-2007(THV) 11:16
6	<	R	oast b	EEF	>	EDIT	
SAL	ES MODE		MARKDOWN	N MODE	OPE	N PRICE	1
< 3	FIX UPR	> <	0:NORM	1AL >	< 0	eyes >	
UNIT PR	ice M/D	AMOUNT	QTY	UNIT TYPE	TAX	FIXED WGT	
4.00		0.00		0:NO PRN	0	0.000	PREVIEW
TARE	2nd TARE	P. TARE	F. TAF	RE	IDER WGT	UPPER WGT	
0.000	0.000	0.0	NO	YES	0.000	0.000	
4					_		
SALE1	SALE2	MESSAGE	IMAGE	PRINT	DATE	CODE	DELETE

Sales Mode: Fixed Unit Price Product

ITEM	DESCRIPTION
	Press the [<] or [>] button to select a desired sales mode.
	0: Weighing product
SALES MODE	1: Fixed price product
	2: Weighing fixed price product
	3: Fixed unit price product
	Press the [<] or [>] button to select a desired markdown mode.
	0: Normal price
	1: Special price
MARKDOWN	2: Amount discount for total price
MODE	3: Percent discount for total price
	4: Special unit price
	5: Amount discount for unit price
	6: Percent discount for unit price
OPEN PRICE	Press the [<] or [>] button to select whether or not to allow an open
	price system.
UNIT PRICE	Enter a unit price or fixed price, and press this field.
FIXED PRICE	
M/D AMOUNT	Enter a markdown amount or percentage and press this field.
QTY (Quantity)	Enter a packed quantity, and press this field.
	Press this field to display the Fix Price Mark List screen.
	FIX PRICE MARK LIST 21-JUN-2007(THU) 11:16 1/2
	0 NONE
	1 0Z 0Z
	2 PACK PACKS
UNIT TYPE	3 kg kg
	4 g g / M
	5 PC. PCS.
	Press to select a desired field.
TAX	Enter a desired number and press this field.
FIXED WEIGHT	Enter a fixed weight, and press this field.
TARE	Enter a tare weight, and press this field.
UNDER WEIGHT	Enter a lower weight limit, and press this field.
UPPER WEIGHT	Enter a upper weight limit, and press this field.

21-JUN-2007(THU) 11:16 t ROAST BEEF > EDIT < POINT FLAG POINTS POINT TYPE > < > < 0:OFF 0:WGT 0

R Lup					PREVIEW
SALE1 SALE2	MESSAGE IMA	GE PRINT	DATE	CODE	DELETE

ITEM	DESCRIPTION
POINT	Press the [<] or [>] button to select whether or not to use the Point Flag.
FLAG	0: OFF
FLAG	1: ON
POINT	Press the [<] or [>] button to select a desired Point Type.
TYPE	0: Weight
	1: Fixed weight
POINTS	Enter a desired number and press this field


8-1 Press the [MESSAGE] tab to select the message related screen.

ITEM DETAIL(M	ESSAGE)	21-JUN-2007(THU) 11:16	1/6
6 <	ROAS	T BEEF	>	
NUTRITION(USA)	0 NONE			
EXTRA MESSAGE1	NONE			
EXTRA MESSAGE2	NONE			PREVIEW
EXTRA MESSAGE3				INPUT
SALE1 SALE2		PRINT DATE	CODE	


8-2 Press to select a desired field.

EXAMPLE "E	Extra Message 1	"-		
ITEM DETAIL(MI	ESSAGE)	21-JUN-2007	(THV) 11:16	1/6
6 <	ROAS	T BEEF		Ł
NUTRITION(USA)	0 NONE			
EXTRA MESSAGE1	0 NONE			
EXTRA MESSAGE2	0 NONE	<u> </u>		PREVIEW
EXTRA MESSAGE3	0 NONE	<u>४</u>		INPUT
SALE1 SALE2	MESSAGE	PRINT DATE	CODE	

8-3 EXAMPLE "Extra Message BB". EXTRA MSG1 LIST 21-JUN-2007(THU) 11:16 1/1 0 NONE EXTRA MESSAGE AA 1 2 EXTRA MESSAGE BB m 3 EXTRA MESSAG FIND PLU DISP. LINE 1 INPUT ITEM DETAIL(MESSAGE) 21-JUN-2007(THU) 11:17 1/6 < ROAST BEEF > NONE 0 EXTRA MESSAGE BB V 2 PREVIEW 0 NONE INPUT 0 NONE SALE1 SALE2 MESSAGE IMAGE PRINT DATE CODE



9-2 Press to select a desired field.




The Extra Message List screen appears. Then, press to select a desired field.

9-3 The Image List screen appears. Then, press to select a desired field and press the [SET] button.

EXAM	PLE Select "Image	No.8'	
IMAGE1 LIST 21-JUN-2007(THU) 11:16			1-JUN-2007(THU) 11:16 1/4
No.	IMAGE	No.	IMAGE
0	NO IMAGE	5	
1		6	
2		8	MEMBER SAVINGS
3	ister Pastu Task	9	
4	<u>N# 4773 -</u>	10	YOU SAVED #3'

10. Select whether or not to print Safe handling Image by pressing a desired field.





11-1 Press the [PRINT] tab to select the print related screen.

 ITEM DETAIL(PRINT)
 21-JUN-2007(THU) 11:16

 5
 <</td>

 ROAST BEEF
 >





11-3 The Format List screen appears. Then, select a desired format by pressing the corresponding field.


EXAMPLE Select "Format No.5".	
FORMAT LIST 21-JUN-2007(THU) 11:16	1/9
0 NONE	t
1 / W:56.00 X H:76.00	
2 / W:56.00 X H:85.00	
3 / W:56.00 X H:59.00	
4 / W:56.00 X H:73.00	
5 / W:56.00 X H:59.00	
ITEM DETAIL(PRINT) 21-JUN-2007(THU)) 11:16
6 < ROAST BEEF >	t_]
FIRST LABEL FORMAT NO. 5 0	
FIRST LABEL PRINT SECOND LABEL PRINT < 1:YES	REVIEW
SALE1 SALE2 MESSAGE IMAGE PRINT DATE CODE	

ITEM	DESCRIPTION
FIRST LABEL	Press the [<] or [>] button to select whether or not to print the first labels.
PRINT	1: YES 2: NO
SECOND LABEL PRINT	Press the [<] or [>] button to select whether or not to print the second labels. 1: YES 2: NO

Note: The same procedure applies to the Second Label Format Number setting.

12.

Pressing the [DATE] tab to select the date related screen. ITEM DETAIL(DATE) 21-JUN-2007(THU) 11:16



ITEM	DESCRIPTION
PACK DATE PRINT	Select whether or not to print the Pack Date.
	Press the [<] or [>] button to select a desired printing method.
PACK TIME PRINT	0: No print
	1: Designated time
	2: System clock time
	This field is available only when "Designated time" is selected in
PACK TIME DATA	"PACK TIME PRINT".
	Enter the time and press this field.
SB DATE PRINT	Select whether or not to print the Sell-By Date.
	Press the [<] or [>] button to select a desired printing method.
SB TIME PRINT	0: No print
00 11112 1 11111	1: Designated time
	2: Relative time
	This field is available only when "Yes" is selected in "SB TIME
SB TIME DATA	PRINT".
	Enter the number of hours and press this field.
SHELF LIFE	This field is available only when "Yes" is selected in "SB DATE
(days)	PRINT".
	Enter the number of days and press this field.
UB DATE PRINT	Select whether or not to print the Use-By Date.
	This field is available only when "Yes" is selected in "UB DATE
UB DATE DATA	PRINT".
	Enter the number of hours and press this field

Select the code related screen by pressing the [CODE] tab.ITEM DETAIL(CODE)21-JUN-2007(THU) 11:17 13. t < ROAST BEEF > ITEM CODE REGI CODE POS FLAG BARCODE 00311006 0000000000000000 0 02 POS REFERENCE BARCODE TYPE POS FORMAT < 0:REFER 0:REFER > REFER PREVIEW TRACE ENABLE DEPARTMENT NO. GROU INPUT З YES 🗸 NO SALE1 SALE2 MESSAGE IMAGE PRINT DATE CODE

ITEM	C	DESCE	RIPTION		
ITEM CODE	Enter an item code and p	Enter an item code and press this field.			
REGISTER CODE	*	Enter the register code and press this field.			
POS FLAG	This field is available only	•			
		REFERENCE". Enter the POS flag number and press this field.			
BARCODE	Enter the barcode number and press this field.				
	Select one of the followin	ng refe	erence methods		
POS REFERENCE	0: Refer				
	1: PLU file		"DILLE"		
	This field is available only REFERENCE".	y wne	n "PLU File" is select	ed in "POS	
	REFERENCE .				
	Press this field to get the	Barco	ode Type screen and	press to	
	select one of the PLU typ				
	BARCODE TYPE		21-JUN-2007(THU) 11:	17 1/1	
	00 REFER	07	RSS-14 STO		
BARCODE TYPE	01 NON PLU 13	08	RSS-14 LIM		
	02 NON PLU 8	09	RSS-14 EXP		
	03 PLU 13	10	ITF		
	04 PLU 8	11	Not Available		
	05 RSS-14				
	06 RSS-14 ST				
	-				
	Press this field to get the	Barco	ode Format screen ar	nd press to	
	Press this field to get the select one of the barcode			nd press to	
	Press this field to get the select one of the barcode				
	select one of the barcode		ats.		
	select one of the barcode BARCODE FORMAT	e form	ats. 21-JUN-2007(THU) 11:1		
POS FORMAT	Select one of the barcode BARCODE FORMAT	e form	ats. 21-JUN-2007(THU) 11:1 FFCCCCCCWWWW(C/D)		
POS FORMAT	Select one of the barcode BARCODE FORMAT	e form	ats. 21-JUN-2007(THU) 11:1 FFCCCCCCCWWWW(C/D) FCCCCCCCWWWWW(C/D)		
POS FORMAT	Select one of the barcode BARCODE FORMAT	e form 07 08 09	ats. 21-JUN-2007(THU) FFCCCCCCCWWWW(C/D) FCCCCCCCWWWWW(C/D) FCCCCCCUIIIII(C/D)		
POS FORMAT	Select one of the barcode BARCODE FORMAT	e form 07 08 09 04	ats. 21-JUN-2007(THU) FFCCCCCCCWWWW(C/D) FCCCCCCCWWWWW(C/D) FCCCCCCUIUIII(C/D) FFCCCCCCCPPPP(C/D) ×		

	BARCODE FORMAT	21-JUN-2007(THU) 11:18 2/3		
	0E Not Available	15 FFCCCCPPPPPP(C/D)		
	0F FFCCCCC(0)PPPP(C/D)	16 FCCCWWWWPPPP(C/D)		
	10 FFCCCCCWWWWW(C/D)	17 FFCCCCQQPPPP(C/D)		
	11 FFCCCCCPPPPP(/10)(C/D)			
	12 FFCCCCC(C/P)PPPP(/10)(C/D)			
	13 FFCCCCC(C/W)WWWW(C/D)	1A FCCCCPPPPPPP(C/D)		
	14 FCCCCCPPPPPP(C/D)	1B FIIIIIIPPPPP(/10)(C/D)		
	BARCODE FORMAT	21-JUN-2007(THU) 11:18 3/3		
	1C FFIIIIIIPPPP(/10)(C/D)			
	1D FCCCCCCPPPPP(/10)(C/D)			
	1E FFCCCCCCPPPP(/10)(C/D)			
	1F FFCCCCCQQQQQ(C/D)			
TRACE ENABLE		nable a traceability function.		
	Press this field to get the I			
DEPARTMENT No.	Set the desired department simply by pressing the field on the list, or pressing the "Department No." field after a numeric			
	entry.			
GROUP No.	Pressing this field displays the Group List. Set the desired group simply by pressing the field on the list, or			
GROUP NU.	pressing the "Group No." f			

10.3 CAMPAIGN LIST REGISTRATION

1. Press the "CAMPAIGN" field on the Program Menu Select screen.



2. The Campaign List appears.

To change	e the pages, press th	ne [➡] or [▲] button on	the screen
CAMPAIGN	LIST	21-JUN-2007(THU) 11:1	9 1/1
1	15-FEB-2008 ~ 15-FEB	8-2008	
			DETAIL
		INPUT	DELETE

3. Create a new campaign file by entering a campaign number and pressing the [PLU] key on the key sheet.




The confirmation screen appears. Then, press the [ENTER] button.


CAMPAIGN LIST	21-IIIN-2007(THI) 11:19 1/1 21-JUN-2007(THU) 11:19
PROG	RAM СНЕСК
Designated item is not pr Are you sure you want to Press ENTER to continue Press CANCEL to go back	o continue?
13001 - 0000	
	())

4	The designated Campaign Data List screen appears.							
	CAMPAIG	N DATA LIST		21-JU	N-2007(TH	U) 11:20	1/1	
	CAMPAIGN	I N0 2						
	START DAT	E(DD/MM/YYYY)	21-JUN-2007	START	TIME(HH:MM)	00:00		
	END DATI	e(dd/ <mark>mm</mark> /yyyy)	21-JUN-2007	END T	IME(HH:MM)	23:59		
	ITEM NO	ITE	EM NAME		MD MODE	MD PRI		
							CALL	
							DELETE	
					INPUT			


5. Enter the campaign start date and press the "Start Date" display field. .




6. Enter the start time and press the "Start Time" display field. .



7. Enter the campaign end date and press the "End Date" display field. .



8. Enter the end time and press the "End Time" display field.



1/1

CALL

9. Press the [CALL] button to call up Item List screens

CAMPAIGN DATA LIST		21-JUN-2007(TH	IU) 11:21	1/1
CAMPAIGN No 2	INPUT THE TIM	IES(24 HOUR) AND DAT	res(8 digit)	t
START DATE(DD/MM/YYYY)	25-JUN-2007	START TIME(HH:MM)	08:00	
END DATE(DD/MM/YYYY)	27-JUN-2007	END TIME(HH:MM)	21:00	
ITEM NO ITE	EM NAME	MD MODE	MD PRI	
			í	CALL
				JUD
			(\mathcal{S}
		INPUT		

INPUT

The Item List screen appears. Then, press to select a desired item field. 10.

EXAMPL	E PLU number "4"	
ITEM LIST	21-JUN-2007(THU) 11:2	1 1/225
1	GROUND BEEF/(TEXAS)	
2	GROUND BEEF/(OREGON)	
3	GROUND BEEF/(UTAH)	
4		
5		
6	ROAST BEEF	
FIND PLU		

- 11.
- The Campaign Data List screen appears. Then, press the [CALL] button again when selecting the next item.

CAMPAIG	N DATA LIST		21-JU	N-2007(TH	U) 11:21	1/1
CAMPAIGN	1 N0 2	INPUT THE TIN	4ES(24 H	OUR) AND DAT	ES(8 DIGIT)	
START DAT	FE(DD/MM/YYYY)	25-JUN-2007	START	TIME(HH:MM)	08:00	
END DAT	E(DD/MM/YYYY)	27-JUN-2007	END T	IME(HH:MM)	21:00	
ITEM NO	ITI	EM NAME		MD MODE	MD PRI	
4	SLICED BEEF			SPECIAL	0.00	
						CALL
				匚''''〗		
				$\Box \lambda I$		
				INPUT		DELETE

The pop-up list appears. Then, press to select a desired field.


EXAMP	LE Percent	t discount '	'-%"			
CAMPAIO	IN DATA LIST		21-JU	V-2007(T	HU) 11:2	1 1/1
CAMPAIG	N NO 2	INPUT THE TIM	1ES(24 HC		ECIAL	
START DA	TE(DD/MM/YYYY)	25-JUN-2007	START			
END DAT	E(DD/MM/YYYY)	27-JUN-2007	END T		-f	
ITEM NO	ITI	EM NAME		MD M	-%	
4	SLICED BEEF			SPEC SPI	ES THR	CALL
				U	<u>('''')</u> -[
					A	
				U	/	DELETE
				INPUT		
CAMPAIO	IN DATA LIST		21-JU	V-2007(T	HU) 11:2	2 1/1
CAMPAIG	N NO 2	INPUT THE TIM	1ES(24 HC	UR) AND DA	ATES(8 DIGI	
START DA	TE(DD/MM/YYYY)	25-JUN-2007	START	тіме(нн:мм) 08:00	
END DAT	E(DD/MM/YYYY)	27-JUN-2007	END T	іме(нн:мм)	21:00	
ITEM NO	ITI	EM NAME		MD MODE	MD PRI	
4	SLICED REFE			-*/	0.0	

CALL

DELETE

INPUT

12. Enter a numeric value and press the "Markdown Price" field for registration.



13. Repeat steps 9 through 12 for further registration. Then, press the Return button to finalize this procedure.

CAMPAIG	N DATA LIST		21-JU	N-2007(TI	HU) 11:2	3 1/1
CAMPAIGN	1 N0 2	INPUT THE TIM	1ES(24 H	DUR) AND DA	TES(8 DIGIT	
START DAT	FE(DD/MM/YYYY)	25-JUN-2007	START	тіме(нн:мм)	08:00	<u> </u>
END DAT	e(dd/mm/yyyy)	27-JUN-2007	END T	IME(HH:MM)	21:00	din)
ITEM NO	ITI	EM NAME		MD MODE	MD PRI	Σ
4	SLICED BEEF			-%	10.0	-Ch
6	ROAST BEEF			SPECIAL	1.00	CATL
						DELETE
				INPUT		DELETE

The Campaign List screen appears.

CAMPAIGN	LIST	21-JUN-2007(THU)	11:23	1/1
1	15-FEB-2008 ~ 15-FEB	-2008		Ļ
2	25-JUN-2007 ~ 27-JUN	V-2007		
				DETAIL
		INPUT		DELETE

10.4 OPERATOR REGISTRATION

 Press the "OPERATORS" field on the Program Menu Select screen.


 MENU SELECT
 21-JUN-2007(THU) 12:12
 1/8



2. The Operator List screen appears.

C	PERATOR	LIST 21-JU	N-2007(THU)	12:12	1/1
	1	JOHAN			t
	2	ANDERS		`	
	3	LARS			
	4	RAINER			
	5	MALCOLM			
	6	RICH			DETAIL
	FIND PLU	SEARCH DISP.			DELETE


3. To create a new operator, enter the operator number and press the [PLU] key on the key sheet.





7

The confirmation screen appears. Press the [ENTER] button.



4. The

 Operator Edit screen appears for the selected operator number.

 OPERATOR EDIT
 21-JUN-2007(THU) 12:13



Edit a text according to the procedures described in Appendix "Text Editing".

OPERA	TOR ED	IT				21-J	UN-20	07(TH	U) 12:13
TAR	оіѕн	IDA_							L
Q	W	E	R	T	V V	U		0	P
A	s	D	F	G	н		К	L	
	Z	x	С		В		м	,	
No. 7	CHA 01*		MAIN 013	STYLE /		FONT 07/14x07	INP	UΤ	ERASE


5.

Press the [ESC] key on the key sheet to escape from text editing mode.



The confirmation screen appears.


Then, press the [SAVE] button to save the data.



6.	The edited text has been registered.
•••	OPERATOR LIST 21-JUN-2007(THU) 12:13 2/2
	7 TARO ISHIDA
	DETAIL
7	Press the Return button to finalize this procedure.
7.	OPERATOR LIST 21–JUN–2007(THU) 12:13 2/2

10.5 PRESET KEY REGISTRATION

10.5.1 SETTING PRESET FUNCTIONS



- 2. The Preset Key (Panel) screen appears. PRESET KEY(PANEL) 21-JUN-2007(THU) 12:20 1/39 SET IMAGE COLOR SIZE EDIT DELETI DATA NEW MEMBRANE PANEL INPUT
- 3. Ensure that the [SET] button is selected.

PRESET KEY(PANEL)	21-JUN-2007(THU) 12:20 1/39
	SIZP EDIT DATA NEW
PANEL	

4_ Press a desired button to which a preset function will be assigned.

PRESET KEY(PANEL)	21-JUN-2007(THU) 12:20 1/39
	SET IMAGE COLOR SIZE EDIT DATA
PANEL	INPUT

5.

Available functions are listed on the screens. To change the pages, press the [-] or [-] button on the screen.

	ange the pages, pre	33 UIC	[]][]]	
FUNC	TION LIST		21-JUN-2007(THU) 12	:20 1/5
0	NO	31	FEED	
64	CATEGORY SELECT	30	PRINT]
62	GROUP SELECT	68	2nd LABEL ONLY PRINT	
94	FUNCTION GROUP	46	PRN QTY	ודען
95	OPERATOR GROUP	70	CASSETTE] /m
1	PLU	75	AUTO PRINT MODE] \/
76	PLU No.	26	PEEL MD.	
			INPUT	
FUNC	TION LIST		21-JUN-2007(THU) 12	2/5
27	LABEL BATCH	43	TOTAL DISPLAY	
65	TARGET	15	SUBTOTAL DISPLAY	
2	TARE	44	CALCULATOR	
8	SAVE	73	ERROR LOG	
78	TOTAL ADD	4	MULTI	_ /m
74	KEY LOCK	77	1/2	<u> 5</u> /
10	VOID	32	U/P	
			INPUT	
FUNC	TION LIST		21-JUN-2007(THU) 12	:20 3/5
3	F/P	25	-£(U/P)	
72	FIX UPR	66	-%(U/P)	
19	FIX UPR +WEIGHT	33	P DATE	
5	SPECIAL	34	S DATE	
6	-£	9	РОР] /m
7	-%	11	COUPON MSG	1SZ
20	1			
20	SP.(U/P)	16	EXTRA1	CLT.
20	SP.(U/P)	16	EXTRA1	SET
	SP.(U/P)	16		
	1	16 52	INPUT	
FUNC	TION LIST		INPUT 21-JUN-2007(THU) 12	
FUNC	TION LIST EXTRA2	52	INPUT 21-JUN-2007(THU) 12 FREE6	
FUNC 17 18	EXTRA2	52	INPUT 21-JUN-2007(THU) 12 FREE6 FREE7	
FUNC 17 18 47	TION LIST EXTRA2 EXTRA3 FREE1	52 53 54	INPUT 21-JUN-2007(THU) 12 FREE6 FREE7 FREE8	
FUNC 17 18 47 48	TION LIST EXTRA2 EXTRA3 FREE1 FREE2	52 53 54 55	INPUT 21-JUN-2007(THU) 12 FREE6 FREE7 FREE8 FREE9	
FUNC 17 18 47 48 49	TION LIST EXTRA2 EXTRA3 FREE1 FREE2 FREE3	52 53 54 55 56	INPUT 21-JUN-2007(THU) 12 FREE6 FREE7 FREE8 FREE9 FREE10	

FUNCTION LIST	21-JUN-2007(THU) 12:20 5/5
59 FREE13	67 FORMAT2
60 FREE14	37 BAR Y/N
61 FREE15	79 TRACE
23 IMAGE1	80 PASSPORT
24 IMAGE2	92 BROWSER
45 IMAGE3	
22 FORMAT	

6. Press to select the desired function on the list, and press the [SET] button.

EXAMPLE Select PLU function.

FUNCTION LIST	21-JUN-2007(THU) 12:21 1/5
0 NO	31 FEED
64 CATEGORY SELECT	30 PRINT
	68 2nd LABEL ONLY PRINT
	46 PRN QTY
	70 CASSETTE
76 PLU No.	
	INPUT SET

7. The Item List screen appears. Then, press to select a desired field.


EXAMPL	Select PLU No.2.			
ITEM LIST		21-JUN-2007(THU)	12:21	1/225
1	GROUND BEEF/(TEXAS)			Ł
2	GROUND BEEF/(OREGO		`	
3	GROUND BEEF/(UTAH)	_/m	(
4	SLICED BEEF	\leq \square		
5	SLICED BEEF/SPECIAL			
6	ROAST BEEF			
FIND PLU	SEARCH	DISP. 1 LINE 1 INPUT		

The selected PLU has been assigned. 8. PRESET KEY(PANEL) 21-JUN-2007(THU) 12:21 1/39 GROUND BEEF (OREGON) SET IMAGE COLOR SIZE EDIT DELETE DATA NEW MEMBRANE PANEL INPUT

9. Repeat steps 4 through 8 for more registrations.

10.5.2 ASSIGNING IMAGES ON THE PRESET KEYS

1. Press the "PRESET KEY" field on the screen.



2.	The Pres	et Key (F	Panel) so	reen ap	pears.		
	PRESET KE	Y(PANEL)		21-	JUN-2007(THU) 12:2	1 1/39
	GROUND BEEF (OREGON)	SLICED BEEF	ROAST BEEF			SET IMAGE COLOR SIZE EDIT DATA	DELETE NEW
	PANEL	MEMBRAN	E		INPUT		J

3. Press the [IMAGE] button.

PRESET KE	Y(PANEL)		21-	JUN-2007(THU) 12:21	1/39
GROUND BEEF (OREGON)	SLICED BEEF	ROAST BEEF			SET MMAGE CO AR ED DA	
PANEL	MEMBRAN	E		INPUT]'	

4 Press a desired preset key where the function is already assigned.

EXAMPLE Select "Roast Beef"

PRESET K	EY(PANEL)		21-JUN-2007(TI	HU) 12:21	1/39
GROUND BEEF (OREGON)	SLICED BEEF	REAST		SET ÍMAGE COLOR SIZE EDIT DATA	D ELETE NEW
PANEL	MEMBRAN	E	INPUT		

5.	The Im	age List screen app	bears.		
01	IMAGE L	_IST	21-	-JUN-2007(THU) 12:2	2 1/4
	No.	IMAGE	No.	IMAGE	
	0	NO IMAGE	6		
	1	2	7	<u> </u>	
	2	*	8	**	DETAIL
	3		9		
	5	4	10	***	SET

6. Press to select a desired image.

EXAM	PLE Image No.3			
IMAGE I	LIST	21-	JUN-2007(THU) 12:2	2 1/4
No.	IMAGE	No.	IMAGE	
0	NO IMAGE	6		
1	2	7	000	
2	1	8	00	DETAIL
3		9		
5		10	144	SET
	{			

7.	The imag	e has be	en assig	jned.			
	PRESET KE	Y(PANEL)		21-	JUN-2007(THU) 12:2	2 1/39
	GROUND BEEF (OREGON)	SLICED BEEF				SET MAGE COLOR SIZE EDIT DATA	DELETE
	PANEL	MEMBRANI	E		INPUT		,

8. Repeat steps 4 through 7 for more registrations.

10.5.3 **COLORING PRESET KEYS** Press the "PRESET KEY" field on the screen. 1. MENU SELECT 21-JUN-2007(THU) 12:20 1/8 P OPERATE PLU PLV FILE TOTAL ☆ CAMPAIGN 📲 🗳 PROGRAM **OPERATORS** 🍐 SETUP 👯 PRESETYKEY ADJUST Hello! AD M The Preset Key (Panel) screen appears. 2. PRESET KEY(PANEL) 21-JUN-2007(THU) 12:21 1/39

_						
Í	GROUND BEEF (OREGON)	SLICED BEEF	ROAST BEEF		SET IMAGE	L
					COLOR SIZE	
					EDIT DATA	DELETE
	PANEL	MEMBRAN	5			NEW
	PANEL			INPUT		

3. Press the [COLOR] button. Then, ensure that "Back Color" is selected.

I	PRESET KE	Y(PANEL)		21-	JUN-2007(1		12:21	1/39
	GROUND BEEF (OREGON)	SLICED BEEF	ROAST BEEF				GE	t_
						COL SIZ ED	2E	
						DA BAG	ск	DELETE
	PANEL	MEMBRAN	E		INPUT			

4_ Press to select a desired preset key.


EXAMPLE Select	t "Roast Bee	f"
PRESET KEY(PANEL)		21-JUN-2007(THU) 12:21 1/39
GROUND BEEF (OREGON) SLICED BEEF	ROAST DIAL	SET IMAGE COLOR SIZE EDIT DATA BACK COLOR
PANEL	E	INPUT

5.	The Preset Key (Color) screen appears. Then, press to select a desired color.
0.	PRESET KEY(COLOR) 21-JUN-2007(THU) 12:22
	d m
6.	Selected color has been given to the background of the key.
υ.	PRESET KEY(PANEL) 21-JUN-2007(THU) 12:22 1/39
	GROUND BEEF (OREGON) BEEF BEEF BEEF
	BACK COLOR
	PANEL
_	
7.	Press the [BACK COLOR] button to change to the [FORE COLOR] button.
	PRESET KEY(PANEL) 21–JUN–2007(THU) 12:22 1/39
	GROUND BEEF (OREGON) SLICED BEEF BEEF SET IMAGE
	(OREGON) BEEF BEEF IMAGE
	PANEL MEMBRANE

8. Press to select a desired preset key.

EXAMPLE Select "Roast Beef"

PRESET KEY(PANEL)		21-JUN-2007(1/39	
GROUND BEEF (OREGON) BEEF			SET IMAGE COLOR SIZE EDIT DATA	► DELETE NEW
	:	INPU		



11. Repeat steps 4 through 10 for more registrations.

10.5.4 CHANGING PRESET KEY SIZES

1. Press the "PRESET KEY" field on the screen.



2. The Preset Key (Panel) screen appears.

	PRESET KEY(PANEL)				21-JUN-2007(THU) 12:21		
	GROUND BEEF (OREGON)	SLICED BEEF	ROAST BEEF			SET IMAGE COLOR SIZE EDIT DATA	
ļ	PANEL	MEMBRAN	E		INPUT		

3. Press the [SIZE] button, and ensure that "SMALL" is selected.

	PRESET KE	Y(PANEL)		21-JUN-2007(THU) 12:21	1/39
	GROUND BEEF (OREGON)	SLICED BEEF	ROAST BEEF	CC OR SIZE EDIT DATA	DELETE
Ļ	PANEL	MEMBRAN	E	INPUT	

Press the [SMALL] button to change to the [MIDDLE] button.

	PRESET KE	Y(PANEL)		21-	21-JUN-2007(THU) 12:21		
ſ	GROUND	SUICED	DOAST			SET	t
	GROUND BEEF (OREGON)	SLICED BEEF	ROAST BEEF			IMAGE	
						COLOR	
						✓ SIZE	
						EDIT	DELETE
						DATA	DELETE
						MIDDLE	NEW
6	PANEL	MEMBRAN	E		INPUT		
						\sum	
						\bigcirc	

PRES	PRESET KEY(PANEL) 21-JUN-2007(THU) 12:21								
	DUND EF GON)	SLICED BEEF	ROAST BEEF			SET IMAGE			
							DELETE		
P/	ANEL	MEMBRAN	Ε		INPUT	LARGE	NEW		

Press the [MIDDLE] button to change to the [LARGE] button.

4-1 Change the size of a desired key.

EXAMPLE Change to the middle size of the "Roast Beef" key.

Ensure that the [MIDDLE] button is selected.

I	PRESET KEY(PANEL)				21-JUN-2007(THU) 12:21		
	GROUND BEEF (OREGON)	SLICED BEEF	ROAST			SET IMAGE COLOR SIZE EDIT DATA MIDDLE	DELETE NEW
	PANEL	MEMBRAN	E		INPUT		

Press the "Roast Beef" key.

	PRESET KE	Y(PANEL)		21-JUN-2007(THU) 12:21			1/39
	GROUND BEEF (OREGON)	SLICED BEEF	REAST			SET IMAGE COLOR SIZE EDIT DATA	DELETE NEW
ļ	PANEL	MEMBRAN	E		INPUT		

4-2 Change the size of a desired key.

EXAMPLE Change to the large size of the "Roast Beef" key.


Ensure that the [LARGE] button is selected.


P	PRESET KEY(PANEL)				21-JUN-2007(THU) 12:21		
	GROUND BEEF (OREGON)	SLICED BEEF	ROAST BEEF			SET IMAGE	L
						EDIT DATA	DELETE
ľ	PANEL	MEMBRAN	F		INPUT	LARGE	NEW


Press the "Roast Beef" key.

PRESET KEY(PANEL)	21-JUN-2007(THU) 12:21	1/39
GROUND (OREGON) SLICED BEEF ROAST FEEF	SET IMAGE COLOR SIZE EDIT DATA LARGE	DELETE

5. Repeat steps 3 through 4-2 for more registrations.







8.		The edited text has been registered. PRESET KEY(PANEL) 21-JUN-2007(THU) 1								
	PRESET KE	Y(PANEL)		21-	JUN-2007((THU) 12:21 1/39				
	GROUND BEEF (OREGON)	SLICED BEEF	BEEF FILLET			SET IMAGE				
						DATA DELETE				
	l					NEW				
	PANEL	MEMBRAN	E		INPU	T				

9. Repeat steps 4 through 8 for more registrations.

10.5.6 CONFIRMING PRESET KEY DATA

1. Press the "PRESET KEY" field on the screen.



2. The Preset Key (Panel) screen appears.


	PRESET KEY(PANEL)				21-JUN-2007(THU) 12:21			
ſ	GROUND BEEF (OREGON)	SLICED BEEF	ROAST BEEF			SET IMAGE COLOR SIZE EDIT DATA	DELETE	
Ĺ	PANEL	MEMBRAN	E		INPUT		, 	

3. Press to select the [DATA] button.

PRE	RESET KEY(PANEL)				21-JUN-2007(THU) 12:21		
		SLICED BEEF	ROAST			SET IMAGE COLOR SIZE EDIT DATA	DELETE
Ŀ	ANEL	MEMBRAN	E		INPUT		

4_ Press a desired preset key. The related data is displayed on the button.

EXAMPLE '	'Beef Fillet" ar	nd the PLU No.6		
PRESET KEY(PA	NEL)	21-JUN-2007(T	HU) 12:21	1/39
GROUND BEEF (OREGON) BE			SET IMAGE COLOR SIZE EDIT DATA	DELETE
PANEL MET	MBRANE	INPUT		



PRESE	ТКЕ	Y(PANEL)		21-	JUN-20070	(THU) 12:21	1739
	ND F ON)	SLICED BEEF	ROAST BEEF			SET IM RE C EL DATA	
PAN	IEL	MEMBRAN	ε		INPU		NEW


3. Press a desired preset key to be deleted.


EXAMPLE Delete the [Roast Beef] key".

	PRESET KE	Y(PANEL)		21-	JUN-2007(THU) 12:21	1/39
	GROUND BEEF (OREGON)	SLICED BEEF	ROAST			SET IMAGE COLOR SIZE EDIT DATA	DELETE NEW
Ì	PANEL	MEMBRAN	E		INPUT		

4. The Function List screen appears, and the assigned function field is highlighted.

FUNC	FION LIST		21-JUN-2007(THU) 12:2	1/5
0	NO	31	FEED	
64	CATEGORY SELECT	30	PRINT	
62	GROUP SELECT	68	2nd LABEL ONLY PRINT	
94	FUNCTION GROUP	46	PRN QTY	
95	OPERATOR GROUP	70	CASSETTE	
1	PLU	75	AUTO PRINT MODE	
76	PLU No.	26	PEEL MD.	
			INPUT	





The selected key number and name are shown on the screen. To assign a desired function to the selected key, press the Name field.



5. The Function List screen appears.

FUNC	TION LIST		21-JUN-2007(THU) 12:2	1 1/5
0	NO	31	FEED	
64	CATEGORY SELECT	30	PRINT	
62	GROUP SELECT	68	2nd LABEL ONLY PRINT	
94	FUNCTION GROUP	46	PRN QTY	
95	OPERATOR GROUP	70	CASSETTE	
1	PLU	75	AUTO PRINT MODE	
76	PLU NO.	26	PEEL MD.	SET
			INPUT	


6. Select a desired function to be assigned by pressing the corresponding field, and press the [SET] button.

EXAMPLE Select "PLU"

FUNC	TION LIST		21-JUN-2007(THU) 12:2	1 1/5
0	NO	31	FEED	
64	CATEGORY SELECT	30	PRINT	
62	GROUP S	68	2nd LABEL ONLY PRINT	
94	FUNCTIO	46	PRN QTY	
95		70	CASSETTE	125
1	PLU	75	AUTO PRINT MODE	lui P
76	PLU NO.	26	PEEL MD.	
			INPUT	

7. The Item List screen appears. Then, press to select a desired field.

EXA	MPL	E PLU No.5	
ITEM	I LIST	21-JUN-2007(THU) 12:21	1/225
	1	GROUND BEEF/(TEXAS)	t
	2	GROUND BEEF/(OREGON)	
	3	GROUND BEEF/(UTAH)	
	4	SLICED BEEF	
	5	SLICED BEEF/SPECIAL	
	6		
FIN			



10.6 ADVERTISEMENT MESSAGE REGISTRATION

Press the "AD MSG (Advertisement Message)" field on the Program Menu Select screen.


 MENU SELECT
 21-JUN-2007(THU) 12:16
 1/8



2-1 The Advertisement Message List screen appears. When creating the first message, press the [NEW] button.


AD MESSAGE LIST	21-JUN-2007(THU) 12:16	1/1
		t
		$\overline{\mathbf{A}}$
		\
		NEW
FIND PLU	SEARCH	DELETE


2-2 When creating a message other than the first one, enter a desired message number using the numeric keys and press the [PLU] key on the key sheet.






3. The confirmation screen appears.





The Advertisement Message Edit screen appears.




Edit a desired message according to the procedures described in Appendix "Text Editing".

AD MES	SAGE I	EDIT				21-J	UN-200)7(THU) 12:17
AD	М	ESSA	١GE		_				Ł
Q	w	E	R	T	Y	U		0	P
A	s	D	F	G	н		К	L	
	z	×	С		В		м	,	
No. 1	СН/ 01		MAIN 046				INP	UT	ERASE

Press the [ESC] key on the key sheet to escape from text editing mode.


ESC

The confirmation screen appears. Then, press the [SAVE] button to save the data.



5.	The Advertisement Mes	sage (Text) screen for the designated message number appears.
	01 < Al	D MESSAGE AA
	TEXT DISPLAY TYPE < 0:NONE	IMAGE DISPLAY TYPE < 0:NONE
	C DISPLAY SPEED	EDIT
	TEXT	
	ITEM	DESCRIPTION
	TEXT DISPLAY TYPE	Press the [<] or [>] button to select a desired display type. 0: None 1: Slide 2: Flash
	IMAGE DISPLAY TYPE	Press the [<] or [>] button to select a desired display type. 0: None 1: Slide 2: Flash
	TEXT DISPLAY SPEED	Press the [<] or [>] button to select a desired display speed. 0: Fast 1: Medium 2: Slow
	DISPLAY COUNT	Enter a display count data and press this field.
6.	Press the [IMAGE] tab. AD MESSAGE(IMAGE)	Then, the Advertisement Message (Image) screen appears. 21-JUN-2007(THU) 12:17
	01 < A	D MESSAGE AA
	IMAGE1	
	When setting an image,	
7.	AD MESSAGE(IMAGE)	21-JUN-2007(THU) 12:17
		D MESSAGE AA
		IMAGE2 0
	TEXT IMAGE	


INPUT




10.7 STORE NAME REGISTRATION

10.7.1 CHANGING EXISTING STORE DATA

- Press the "STORE NAME" field on the Program Menu Select screen. 1. 21-JUN-2007(THU) 12:20 MENU SELECT 2/8 OPERATE H TOTAL DEPA чт 🕍 PROGRAM ÉGROU 🔵 SETUP COOKING INSTRUCTION Fat X ProteinX NUTRITION(USA) 📟 ADJUST
- **2.** The default store data screen appears. When changing the store data, press the [EDIT] button.






	STORE(ADDRESS E	EDIT)			21-J	UN-200) 7(THU) 12:22			
	ню	GASH	IYAM	A_K	YO	то	JA		L			
	Q	W E	R	Т	Y	U	-	0	Р			
	A	S D	F	G	H		к					
		z x	С		В		м	,				
	No. 9998	CHAR 023	REMAIN 025	STYLE /		ONT 5/30x15		υт	ERASE			
10.	Press t	he [ESC]	key on t	Ċ	shee SC	t to es	cape	rom te	ext edit	ng mo	ode.	
		nfirmatior		appea	rs. Th				-	on.		
	STORF(ADDRESS I							<u>) 12:22</u> 12:22			
			PR	OGRAI	м сне	СК						

	PROGRAM CHECK
	Are you sure you want to save changes? To confirm changes press SAVE to undo changes press CANCEL
	The store address has been abanged
11.	The store address has been changed. STORE LIST 21-JUN-2007(1) 12:22 2/3
	STORE No. 9998
	NAME ISHIDA MART
	ADDRESS HIGASHIYAMA KYOTO JAPAN
	Set the default Store No. to be printed on the label.
	PRINTER1 9998 PRINTER2 9998 EDIT
	INPUT

10.7.2 CREATING NEW STORE DATA

1. Press the "STORE NAME" field on the Program Menu Select screen.



2. The default store data screen appears.

STORE LIST	21-JUN-2007(THU) 12:20	1/2
STORE No. 9998] (t
NAME ISHIDA CO	"LTD/UNI 7/	
ADDRESS http://www	w.ishida.co.jp/	•
Set the default Stor	e No. to be printed on the label.	
PRINTER1 9998	PRINTER2 9998	EDIT
		DELETE
	INPUT	

3. When creating a new store data, enter the desired store number and press the [PLU] key.



The confirmation screen appears. Then, press the [ENTER] button.

TORFLIST 21-III	N-2007(THI) 12:21 1/2 21-JUN-2007(THU) 12:21
PROGRAM CHE	ЕСК
Designated item is not programme Are you sure you want to continu Press ENTER to continue Press CANCEL to go back.	
13001 - 0000	
	()
	K

4. The Store Name Edit screen appears for the selected store number.



5. Edit a text according to the procedures described in Appendix "Text Editing".



6. Press the [ESC] key on the key sheet to escape from text editing mode.


The confirmation screen appears. Then, press the [SAVE] button.

ESC



7. The store name has been registered

STORE LIST		21-JU	N-2007(THU)	12:22	1/3
STORE No.	0001				Ł
NAME	HYPER ISHIDA				
ADDRESS					•
Set the d	lefault Store No	to be printed.	d on the labe	ь.	
PRINTER1	9998	PRINTER2	9998		EDIT
			INPUT		DELETE




Q	W B	E R	T	Υ			0 P
A	s C	F	G	н		к	
	z 🛛	:] C		В		м][, <u> </u>
No.	CHAR 018	REMAIN 030	STYLE		FONT 15/30x15	INPUT	ERASE

11. Press the [ESC] key on the key sheet to escape from text editing mode.

ESC

The confirmation screen appears. Then, press the [SAVE] button.



12.	The store address has been registered.						
	STORE LIST		21-JUN	-2007(THU) 12:2	3 1/3		
	STORE No.	0001					
	NAME	HYPER ISHIDA					
	ADDRESS	BIWAKO SHIGA J	APAN				
	Set the	default Store No.	to be printed	l on the label.			
	PRINTER1	9998	PRINTER2	9998	EDIT		
				INPUT	DELETE		


13. Enter a desired store number as a default store data and press the "Printer 1" or "Printer 2" display field.

EXAMPLE	Set the store number "1" for printer #1.
1	

STORE LIST		21-JUN-2007(THU) 12:	23 1/3
STORE No.	0001		
NAME	HYPER ISHIDA		
ADDRESS	BIWAKO SHIGA JAPA	N	
Set the	default Store No. to b	e printed on the label.	
PRINTER1		81NTER2 9998	
		INPUT	DELETE
	C)		

10.8 DEPARTMENT NAME REGISTRATION

10.8.1 CREATING NEW DEPARTMENT NAMES



Q

1

W

Z

CHAR

000

R

E

С

REMAIN

1025

G

v

STYLE

7

Ε

D

v

Н

В

U

Ν

0

М


INPUT

Р


ERASE

5.	Edit a text according to the procedures described in Appendix "Text Editing".
	DEPARTMENT EDIT 21–JUN–2007(THU) 12:25
	Z X C V B N M , .
	No. CHAR REMAIN STYLE FONT INPUT ERASE 1 013 1012 / 30x15/30x15 INPUT ERASE
6.	Press the [ESC] key on the key sheet to escape from text editing mode.
	ESC
	The confirmation screen appears. Then, press the [SAVE] button.
	DEPARTMENT EDIT 21-UIN-2007(THU) 12:25 21-JUN-2007(THU) 12:25
	PROGRAM CHECK
	Are you sure you want to save changes? To confirm changes press SAVE to undo changes press CANCEL
	19001 - 0000 SAVE CANCEL
7.	The edited text has been registered.
	DEPARTMENT LIST 21-JUN-2007(T 12:26 1/1
	FIND PLU SEARCH INPUT

8. When creating more department names, enter a desired department number using the numeric keys and press the [PLU] key on the key sheet.



The confirmation screen appears. Then, press the [ENTER] button.



9. The Department Name Edit screen appears.



10. Edit a text according to the procedures described in Appendix "Text Editing".

		MEN	т ве		JUN-2007(TH	10) 12:26
Q	W E	E) R		Y U		P
A	s 🛛) F	G	н ј	KL	
	Z X	; C		B	М ,	
N0. 2	CHAR 013	REMAIN 1012	STYLE	FONT 30x15/30x15	INPUT	ERASE

11_ Press the [ESC] key on the key sheet to escape from text editing mode.



The confirmation screen appears. Then, press the [SAVE] button.



12.	The edite			
	DEPARTME	INT LIST	21-JUN-2007(THU) 12:2	.6 1/1
	1	DEPARTMENT AA		
	2	DEPARTMENT BB		
				DETAIL
	FIND PLU	SEARCH	INPUT	DELETE

13. Repeat steps 8 through 12 for more registrations.

10.8.2 CHANGING EXISITING DEPARTMENT NAMES

1. Press the "Department" field on the Program Menu Select screen.



2. The Department List screen appears.

DEPARTME	INT LIST	21-JUN-2007(THU)	12:25	1/1
1	DEPARTMENT AA			t
2	DEPARTMENT BB		`	
				DETAIL
FIND PLU	SEARCH	INPUT		DELETE

3. When changing an existing data, press to select a desired field.

DEPARTME	INT LIST	21-JUN-2007(THU)	12:25	1/1
1	DEPARTMENT AA			t
2	DEPARTMENT BB	<u></u>	<u> </u>	
		/m		
		\leq		
				DETAIL
FIND PLU	SEAR	CH		DELETE

4. <u>The Department Name Edit screen appears for the selected department.</u>



5. Edit a text according to the procedures described in Appendix "Text Editing".



6. Press the [ESC] key on the key sheet to escape from text editing mode.

ESC The confirmation screen appears. Then, press the [SAVE] button.



7. The edited text has been registered.

DEPARTME	NT LIST	21-JUN-2007(THU)	12:25	1/1
1	DEPARTMENT AA			ſ
2	DEPT. BB		, 🗌	
				DETAIL
FIND PLU	SEARCH	INPUT		DELETE

8. Repeat steps 3 through 7 for more registrations.

10.9 GROUP NAME REGISTRATION

10.9.1 CREATING NEW GROUP NAMES

1.	Press the "Group" field on the Program Menu Select screen.
	MENU SELECT 21–JUN–2007(THU) 12:30 2/8
2.	The Group List screen appears. Then, press the [NEW] button.
	GROUP LIST 21–JUN–2007(THU) 12:30 1/1
3.	The confirmation screen appears. Then, press the [ENTER] button.
	21-JUN-2007(THU) 12:30
	PROGRAM CHECK
	Designated item is not programmed. Are you sure you want to continue?
	Press ENTER to continue Press CANCEL to go back.
	13001 - 0000 ENTER CANCEL
4.	The Group Name Edit screen appears.
4 .	GROUP EDIT 21-JUN-2007(THU) 12:30
	QWERTYUIOP ASDFGHJKL

INPUT

ERASE

No

1

CHAR

000


REMAIN

1025

STYLE

7

- 5. Edit a text according to the procedures described in Appendix "Text Editing". GROUP EDIT 21-JUN-2007(THU) 12:30 t **GROUP AA** Q 0 R Т A D G н S к v М 7 х С R Ν REMAIN STYLE CHAR INPUT ERASE 1 008 1017 Press the [ESC] key on the key sheet to escape from text editing mode. 6. ESC The confirmation screen appears. Then, press the [SAVE] button. GROUP FOIT 21-111N-2007(THII) 12:30 21-JUN-2007(THU) 12:30 **PROGRAM CHECK** Are you sure you want to save changes? To confirm changes press SAVE to undo changes press CANCEL 19001 - 0000 CANCEL S 'E 7. The edited text has been registered. 21-JUN-2007(T GROUP LIST 12:30 1/1 1 **GROUP AA** DETAIL FIND PLU DELETE INPUT
 - **8.** When creating more group names, enter a desired group number using the numeric keys and press the [PLU] key on the key sheet.



The confirmation screen appears. Then, press the [ENTER] button.



9. The Group Name Edit screen appears.



10. Repeat steps 5 through 9 for more registrations.

10.9.2 CHANGING EXISITING GROUP NAMES

1. Press the "Group" field on the Program Menu Select screen.



2. The Group List screen appears.

GROUP LIS	Т	21-JUN-2007(THU)	12:33	1/1
1	GROUP AA			t
2	GROUP BB		`	
				DETAIL
FIND PLU	SEARCH	INPUT		DELETE

3. When changing an existing data, press to select a desired field.

GROUP LIS	Т		21-JUN-2007(THU)	12:33	1/1
1	GROUP AA				t
2	GROUP BB	0			
		/m	٦		
			/		
		9			
					DETAIL
FIND PLU		SEARCH	INPUT	- P	DELETE


The Group Edit screen appears for the selected group 4. GROUP EDIT 21-JUN-2007(THU) 12:33 **GROUP BB** Q U 0 Р W П Ε A S D F Η К Z REMAIN CHAR STYLE INPUT ERASE 2 008 1017 7

```
Edit a text according to the procedures described in Appendix "Text Editing".
5.
      GROUP EDIT
                                               21-JUN-2007(THU) 12:33
        GRP._BB
                                                            0
         Q
               W
                            R
                                   Т
                                         γ
                                                U
                                  G
         A
                      D
                            F
                                         Η
               S
                      х
                            C
                                   v
                                                      М
                                         B
                                                Ν
               2
                 CHAR
                        REMAIN
                                 STYLE
                                                       INPUT
                                                                ERASE
          2
                 007
                         1018
                                   7
     Press the [ESC] key on the key sheet to escape from text editing mode.
6.
                                      ESC
     The confirmation screen appears. Then, press the [SAVE] button.
                                               21-111N-2007(THI) 12:33
      GROUP FOIT
                                              21-JUN-2007(THU) 12:33
                             PROGRAM CHECK
        Are you sure you want to save changes?
To confirm changes press SAVE
          to undo changes press CANCEL
         19001 - 0000
                                                   SA
                                                       ٧E
                                                      m
7.
     The edited text has been registered.
                                       21-JUN-2007(THO) 12:33
      GROUP LIST
                                                                 1/1
           1
                 GROUP AA
                                                                t
           2
                 GRP. BB
                                                               DETAIL
         FIND
PLU
                                                               DELETE
                                               INPUT
```

8. Repeat steps 3 through 7 for more registrations.

10.10 COOKING INSTRUCTION REGISTRATION

10.10.1 CREATING NEW INSTRUCTIONS



 The Cooking Time List screen appears. Then, press the [NEW] button.


 COOKING TIME LIST

 21-JUN-2007(THU)

 12:40



3. The confirmation screen appears. Then, press the [ENTER] button.



4. The Cooking Time Edit screen appears.

COOKING TIME ED	IT		21-JU	JN-2007(THU) 12	:40
QWE	R	Т	Y U	1 0 P	
	╡				╡
A S D	F	G	нјј	К	
ZX	С		BN	м , .	٦
			FONT		=
1 000	511	/	16x07/16x07	INPUT ERAS	SE
			10/07/16/07		

```
5.
     Edit a text according to the procedures described in Appendix "Text Editing".
                                            21-JUN-2007(THU) 12:40
      COOKING TIME EDIT
                                                             t
       COOKING INSTRUCTION AA
        Q
                                                         0
              w
                     F
                          R
                                             U
        A
                                G
                                       Н
                    D
                                                   К
                                v
              7
                    х
                          С
                                       В
                                             N
                                                   М
                       REMAIN
               CHAR
                               STYLE
                                                   INPUT
                                                             ERASI
         1
                022
                        489
                                 2
     Press the [ESC] key on the key sheet to escape from text editing mode.
6.
                                   ESC
     The confirmation screen appears. Then, press the [SAVE] button.
      COOKING TIME EDIT
                                             21-IIIN-2007(THII) 12:40
                                            21-JUN-2007(THU) 12:40
                            PROGRAM CHECK
        Are you sure you want to save changes?
        To confirm changes press SAVE
         to undo changes press CANCEL
        19001 - 0000
                                                 SAVE
                                                   m
7.
     The edited text has been registered.
     COOKING TIME LIST
                                     21-JUN-2007(T
                                                      12:41
                                                              1/1
          COOKING INSTRUCTION AA
                                          0
                                                    0
                                                            DETAIL
                                                            DELET
                                            INPUT
```

8. Enter a numeric value for each filed using the numeric keys and press the corresponding field for registration.



	COOKING TIME LIST 21–JUN–2007(THU) 12:41 1/1
	No. COOKING METHOD BASE TIME MIN/kg
	DETAIL
	INPUT
9.	When creating more instructions, enter a desired cooking instruction number using the numeric keys and press the [PLU] key on the key sheet.
	numenc keys and press the [FLO] key on the key sheet.
	EXAMPLE Cooking instruction number "2".
	The confirmation screen appears. Then, press the [ENTER] button.
	COOKING TIME LIST 21-111N-2007(THII) 12:41 1/1 21-JUN-2007(THU) 12:41
	PROGRAM CHECK
	Designated item is not programmed.
	Are you sure you want to continue?
	Press CANCEL to go back.
	13001 - 0000 ENTER CANCEL
- 40	
10.	The Cooking Time Edit screen appears.
	A S D F G H J K L
	NO. CHAR REMAIN STYLE FONT INPUT ERASE

11. Repeat steps 5 through 10 for more registrations.

10.10.2 CHANGING EXISITING INSTRUCTIONS


1. Press the "Cooking Instruction" field on the Program Menu Select screen.



2. The Cooking Time List screen appears.

CO 0	KING TIME LIST	21-JUN-200	7(THU) 12:4	1/1
No.	COOKING METHOD	BASE TIME	MIN/kg	
1	COOKING INSTRUCTION AA	35	20	
2	COOKING INSTRUCTION BB	20	25	
				DETAIL
				DETAIL
		INPL	JT	DELETE


3. When changing an existing data, press to select a desired field and press the [DETAIL] button.



4 The Cooking Time Edit screen appears for the selected instruction

COOKING TIME E	DIT	21-	-JUN-2007(THU) 12:45
	STRUCTION	I BB	
QWE	RT		
	F G	ГНЈ	KL
		BN	
No. CHAR 2 022	REMAIN STY 489 /	FONT / 16x07/16x0	INPUT

5. Edit a text according to the procedures described in Appendix "Text Editing".



6. Press the [ESC] key on the key sheet to escape from text editing mode.

ESC The confirmation screen appears. Then, press the [SAVE] button.



7. The edited text has been registered.

C0 0	KING TIME LIST	1-JUN-200	7(THU) 12:	46 1/1			
N0.	COOKING METHOD	BASE TIME	MIN/kg				
1	COOKING INSTRUCTION AA	35	20				
2	COOKING INST, BB	20	25				
				DETAIL			
	DELETE						
	INPUT						

8. Repeat steps 3 through 7 for more registrations.

10.11 NUTRITION FILE REIGISTRATION


10.11.1 CREATING NEW NUTRITION DATA

1.		enu Select screen.	
	MENU SELECT	JUN-21-2007(THU) 12	:54 2/8
	OPERATE	STORE NAME	
	ΤΟΤΑL		
	PROGRAM	R GRO	
	SETUP		
	ADJUST		

2. The Nutrition List screen appears. Then, press the [NEW] button.



3. The confirmation screen appears. Then, press the [ENTER] button.



4. The Nutrition Data Programming screen for the selected nutrition number appears. When creating a text for "Serving Size", press the [EDIT] button.

NUTRITION DATA PROGRAMMING JUN-21-2007(THU) 12:55						
NUTRITION NO.	1 5	ERVING SI	ZE			
TOTAL CALORIES		SERVING PER CONT		ALORIE RM FAT	0	
TOTAL FAT	0g	0%	CARBOHYDRATE	Og	0%	
SATURATED FAT	0g	0%	DIETARY FIBER	Og	0%	
CHOLESTEROL	Omg	0%	PROTEIN	Og	0%	EQT
SODIUM	Omg	0%	SUGARS	Og	0%	
TRANS FAT	0g					۲m
VITAMIN A% 0	VITAMIN	C% 0	CALCIUM% 0	IRON%	0	
				INPUT		

5.	The Nutrition Edit screen appears.
	NUTRITION EDIT JUN-21-2007(THU) 12:55
	A S D F G H J K L
	No. CHAR REMAIN STYLE FONT INPUT ERASE 1 000 018 / 15x07/15x07 INPUT ERASE
	Edit a text according to the procedures described in Appendix "Text Editing".
6.	NUTRITION EDIT JUN-21-2007(THU) 12:55
	SIZE 1
	1 006 012 / 16x07/16x07 INPUT ERASE
7.	Press the [ESC] key on the key sheet to escape from text editing mode.
	ESC
	The confirmation screen appears. Then, press the [SAVE] button.
	NUTRITION FOIT UN-21-2007(THI) 12:55 JUN-21-2007(THU) 12:55
	PROGRAM CHECK
	Are you sure you want to save changes?
	To confirm changes press SAVE to undo changes press CANCEL
	μ · · · · · · · · · · · · · · · · · · ·
	19001 - 0000 SAVE CANCEL
8.	The edited text has been registered. Then, enter a nutrition data for each field using the numeric keys and press the corresponding field for registration.
	NUTRITION DATA PROGRAMMING JUN-21-2007(THU) 12:55
	NUTRITION No. 1 SERVING SIZE SIZE 1
	TOTAL 0 SERVING 0 CALORIE 0 CALORIE 0
	TOTAL FAT 0g 0% CARBOHYDRATE 0g 0% SATURATED FAT 0g 0% DIETARY FIBER 0g 0%
	CHOLESTEROL 0mg 0% PROTEIN 0g 0%
	SODIUM 0mg 0% SUGARS 0g 0%
	(''')
	L L

9. When creating more nutrition data, enter a desired nutrition number using the numeric keys and press the [PLU] key on the key sheet.



The confirmation screen appears. Then, press the [ENTER] button.

N	UITRITION LIST IIIN-21-2	2007(THU) 12:56 1/1
ī	L	UN-21-2007(THU) 12:56
	PROGRAM CHECK	<
	Designated item is not programmed. Are you sure you want to continue? Press ENTER to continue Press CANCEL to go back.	
	13001 - 0000	ENTER CANCEL

10. Repeat steps 4 through 9 for more registrations.

10.11.2 CHANGING EXISTING NUTRITION DATA

1. Press the "Nutrition (USA)" field on the Program Menu Select screen.



2. <u>The Nutrition List screen appears.</u>


NUTRITIO	N LIST	JUN-21-2007(THU)	12:58	1/1
1	SIZE 1			t
2	SIZE 2		`	
				DETAIL
FIND PLU	SEARCH	DISP. 1 LINE 1 INPUT		DELETE

3. Select a desired nutrition number.

E	XAMPL	 Nutrition num 	nber "2".	
N	UTRITIO	N LIST	JUN-21-2007(THU) 12:58	1/1
	1	SIZE 1		ľ,
	2	SIZE 2		
			Γη	
				DETAIL
	FIND PLU	SEAF		DELETE

or press the [PLU] key on the key sheet after a numeric entry.





v

STYLE

7

REMAIN

011

В

Ν

М

INPUT

ERASE

Z

CHAR

007

No

2


8. Press the [ESC] key on the key sheet to escape from text editing mode.

The confirmation screen appears. Then, press the [SAVE] button.

ESC



9. The edited text has been registered. When necessary, enter a nutrition data for each field using the numeric keys and press the corresponding field for registration.



10. Press the Return button after making necessary changes.

NUTRITION DATA PROGRAMMING JUN-21-2007(THU) 12:59							
NUTRITION NO.	2	SERVING SI	ZE	SIZE BB			
TOTAL CALORIES	0	SERVING PER CONT	0		LORIE M FAT	0	
TOTAL FAT	Og	0%	CARBOHYDRA	TE	Og	10%	("")
SATURATED FAT	Og	0%	DIETARY FIBE	R	10g	0%	24
CHOLESTEROL	Omg	0%	PROTEIN		Og	0%	EDIT
SODIUM	Omg	0%	SUGARS		Og	0%	
TRANS FAT	Og						
VITAMIN A% 0 VITAMIN C% 20 CALCIUM% 0 IRON% 0 DELETE							

11. Repeat steps 3 through 10 for more registrations.

10.12 EXTRA MESSAGE REGISTRATION


10.12.1 CREATING NEW MESSAGES



2. The Extra Message List screen appears. Then, press the [NEW] button.

En Third Contract	
	t
	17 5
	WY P
FIND PLU	DELET

3. The confirmation screen appears. Then, press the [ENTER] button.




The Extra Message Edit screen appears.

4.

EXTRA MSG1 EDIT	<u> </u>				UN-200	0 7(THU) 13:03
_						t
QWE	R	T	Y			0 P
ASD	F	G	н		к	
ZX	С		В		м	
No. CHAR 1 000	REMAIN 2048	STYLE /		ONT 15/30x15	INP	UT ERASE

5. Edit a text according to the procedures described in Appendix "Text Editing".



6.

Press the [ESC] key on the key sheet to escape from text editing mode.

ESC The confirmation screen appears. Then, press the [SAVE] button.

EXTRA MSG1 EDIT	<u>21-IIIN-2007(THII) 13:04</u>
	21-JUN-2007(THU) 13:04
PROGRAM CH	ЕСК
Are you sure you want to save ch To confirm changes press SAVE to undo changes press CANCEL	anges?
19001 - 0000	SAVE CANCEL

7. The edited text has been registered.

EXTRA MS	G1 LIST	21-JUN-2007(THU)	13:04	1/1
1	EXTRA MESSAGE AA			Ł
			'	
				DETAIL
FIND PLU	SEARCH	DISP. 1 LINE 1		DELETE

8. When creating more messages, enter a desired message number using the numeric keys and press the [PLU] key on the key sheet.



The confirmation screen appears. Then, press the [ENTER] button.



9. Repeat steps 4 through 8 for more registrations.

10.12.2 CHANGING EXISITING MESSAGES

1. Press the "Extra Message" field on the Program Menu Select screen.



2. The Extra Message List screen appears.

EXTRA MSC	G1 LIST	21-JUN-2007(THU)	13:06	1/1
1	EXTRA MESSAGE AA			t
2	EXTRA MESSAGE BB		`	
				DETAIL
FIND PLU	SEARCH	DISP. 1 LINE 1		DELETE

3. Select a desired message number.


EXAMPLE Message number "2".

Press a desired field,

EXTRA MSC	G1 LIST	21-JUN-2007(THU)	13:06	1/1
1	EXTRA MESSAGE AA			Ł
2	EXTRA MESSAGE BB	-	<u> </u>	
		٦Ų		
		5		
				DETAIL
FIND PLU	SEARCH		_ (DELETE

or press the [PLU] key on the key sheet after a numeric entry.







10.13 COUPON MESSAGE REGISTRATION

10.13.1 CREATING NEW MESSAGES

- 1. Press the "Coupon Message" field on the Program Menu Select screen. 21-JUN-2007(THU) 13:10 MENU SELECT 3/8 MS6 EXTRA MESSAGE1 **OPERATE** TOTAL MS6 EXTR ESSAGE2 📲 🖉 PROGRAM MS6 EXTE **SAGE3** COUPON MESSAGE SETUP ADJUST POP MESSAGE 27
- 2. The Coupon Message List screen appears. Then, press the [NEW] button.



3. The confirmation screen appears. Then, press the [ENTER] button.



4 <u>The Coupon Message Edit screen appears.</u>


COUPON MSG EDIT 21-JUN-2007(THU) 1) 13:10				
									Ł
Q	w	E	R		Y	U		0	P
	s	D	F	G	н		к	L	
	z	×	с		B		м	,	
No. 1	CH4 00		MAIN 048	STYLE /		FONT 15/30x15	INP	υт	ERASE

```
5.
     Edit a text according to the procedures described in Appendix "Text Editing".
                                            21-JUN-2007(THU) 13:11
      COUPON MSG EDIT
                                                             t
       COUPON MESSAGE AA
        Q
                                             U
                                                         0
                    F
                          R
        A
                    D
                                G
                                      н
                                                   К
              S
                                             М
              7
                    х
                          С
                                v
                                      R
                                             N
                      REMAIN
               CHAR
                               STYLE
                                          FONT
                                                   INPUT
                                                            ERASE
                                       30x15/30x15
                017
                       2031
          1
     Press the [ESC] key on the key sheet to escape from text editing mode.
6.
                                   ESC
     The confirmation screen appears. Then, press the [SAVE] button.
      COMPON MSG EDIT
                                            21-IIIN-2007(THIN 13.11
                                            21-JUN-2007(THU) 13:11
                           PROGRAM CHECK
        Are you sure you want to save changes?
        To confirm changes press SAVE
         to undo changes press CANCEL
                                                SAVE
                                                         CANCEL
        19001 - 0000
     The edited text has been registered.
7.
     COUPON MSG LIST
                                    21-JUN-2007(T
                                                      13:11
                                                              17
          1
                COUPON MESSAGE AA
                                                           DETAIL
        FIND
PLU
                                    DISP.
LINE
                                         1
                                                            DELETE
                                            INPUT
```

8. When creating more messages, enter a desired message number using the numeric keys and press the [PLU] key on the key sheet.



The confirmation screen appears. Then, press the [ENTER] button.



9. Repeat steps 4 through 8 for more registrations.

10.13.2 CHANGING EXISITING MESSAGES

1. Press the "Extra Message" field on the Program Menu Select screen.



2. The Coupon Message List screen appears.

COUPON N	ISG LIST	21-JUN-2007(THU)	13:23	1/1
1	COUPON MESSAGE AA			t
2	COUPON MESSAGE BB			
				DETAIL
FIND PLU	SEARCH	DISP. 1 LINE 1		DELETE

3. Select a desired message number.

EXAMPLE Message number "2".

Press a desired field,

COUPON M	ISG LIST	21-JUN-2007(THU)	13:23	1/1
1	COUPON MESSAGE AA			t)
2	COUPON MESSAGE BI		_ `	
		Ոլ		
				DETAIL
FIND PLU	SEARCH	DISP. 1 LINE 1	(DELETE

or press the [PLU] key on the key sheet after a numeric entry.



4.	Press the [DETAIL] button.
	COUPON MSG LIST 21-JUN-2007(THU) 13:23 1/1
	1 COUPON MESSAGE AA
	2 COUPON MESSAGE BB
	DETAIL
5.	The Coupon Message Edit screen appears.
	COUPON MSG EDIT 21–JUN–2007(THU) 13:23
	COUPON MESSAGE BB
	A S D F G H J K L
	NO. CHAR REMAIN STYLE FONT INPUT ERASE
	2 017 2031 / <u>30x15/30x15</u>
6,	Edit a text according to the procedures described in Appendix "Text Editing".
0,	COUPON MSG EDIT 21–JUN–2007(THU) 13:24
	Q W E R T Y U I O P
	No. CHAR REMAIN STYLE FONT
	2 013 2035 / 30x15/30x15 INPUT ERASE
	Drage the IESCI key on the key sheet to accore from taxt aditing mode
7.	Press the [ESC] key on the key sheet to escape from text editing mode.
	ESC
	The confirmation screen appears. Then, press the [SAVE] button.
	COMPON MSC FOIT 21-IIIN-2007(THII) 13:24
	21-JUN-2007(THU) 13:24
	PROGRAM CHECK
	Are you sure you want to save changes? To confirm changes press SAVE
	to undo changes press CANCEL
	19001 - 0000 SAVE CANCEL
8.	Repeat steps 3 through 7 for more registrations.

10.14 POP MESSAGE REGISTRATION

1. Press the "POP Message" field on the Program Menu Select screen.



2. The message list screen appears.

POP MSG I	IST	21-JUN-2007(THU)	13:34	1/1
1	SPECIAL!			Ţ
2	ON SALE!		`	
3	DISCOUNTED			
4	ADVERTISED			
5	REFRIGERATE			
6	GOOD BUY			DETAIL
FIND PLU	SEARCH	DISP. 1 LINE 1 INPUT		DELETE

3. Enter a desired message number and press the [PLU] key on the key sheet.

EXAMPLE Message number "7".



The confirmation screen appears. Then, press the [ENTER] button.

PROGRAM CHECK Designated item is not programmed. Are you sure you want to continue? Press ENTER to continue Press CANCEL to go back. I3001 - 0000 ENTER CANCEL
Are you sure you want to continue? Press ENTER to continue Press CANCEL to go back.
13001 - 0000 ENTER CANCEL

The POP Message Edit screen appears. 4. POP MSG EDIT 21-JUN-2007(THU) 13:35 t 0 Q w R U F Т A D G н к Π S v Μ 7 х С В CHAR REMAIN STYLE FONT INPUT ERASI 000 2048 30x15/30x15 7 B / R

Edit a text according to the procedures described in Appendix "Text Editing".

POP MSG EDI	T		21-J	UN-2007(THU) 13:35
POP	IESSA	GE 7	3	t
QW	E	i T	V U	
AS		G	L H	K
Z			BN	M , .
	IAR REMAII 15 2034	N STYLE	FONT 30x15/30x15	INPUT

5. P Press the [ESC] key on the key sheet to escape from text editing mode.

ESC

The confirmation screen appears. Then, press the [SAVE] button.

	POP MSC FDIT 21-UIN-2007(THU) 13:35
	21-JUN-2007(THU) 13:35
	PROGRAM CHECK
	Are you sure you want to save changes? To confirm changes press SAVE to undo changes press CANCEL
	19001 - 0000 SAVE CANCEL
6.	The edited text has been registered.
0.	POP MSG LIST 21-JUN-2007(TH) 13:35 2/2
	7 POP MESSAGE 7
	FIND PLU SEARCH DISP. 1 LINE 1 INPUT
7.	Repeat steps 3 through 6 for more registrations.

10.15 TAX REGISTRATION

- 1. Press the "Tax" field on the Program Menu Select screen.
 - MENU SELECT 21-JUN-2007(THU) 13:40 4/8
- **2.** The Tax List screen appears.

AX			21-JUN-200	07(THU) 13:4	0 1/2
TAX No.		TAX TYPE		TAX RATE	
0	EXCLUSIVE	INCLUSIVE	EXEMPT	5.00 %	
1	EXCLUSIVE	INCLUSIVE	EXEMPT	5.00 %	
2	EXCLUSIVE	INCLUSIVE	EXEMPT	5.00 %	
3	EXCLUSIVE	INCLUSIVE	EXEMPT	5.00 %	
4	EXCLUSIVE	INCLUSIVE	EXEMPT	5.00 %	
			INF	PUT	

3. When changing a tax system, press to select a desired field.

TAX 21-JUN-2007(THU) 13:40 1/2							
	TAX No.	TAX TYPE			TAX RATE		
	0	EXCLUSIVE	INCLUSIVE	EXEMPT	5.00 %		
	1	EXCLUSIVE	INCLUSIVE	EXEMPT	5.00 %		
	Ž	EXCLUSIVE	INCLUSIVE	EXEMPT	5.00 %		
	\Box m	EXCLUSIVE	INCLUSIVE	EXEMPT	5.00 %		
	$\Box /$	EXCLUSIVE	INCLUSIVE	EXEMPT	5.00 %		

ITEM	DESCRIPTION
TAX TYPE	Press to select one of tax types.
	Exclusive tax
	Inclusive tax
	Tax exemption
TAX RATE	Enter a numeric value and press this field.

10.16 SCHEME TABLE REGISTRATION


10.16.1 CREATING NEW TABLES

1.	Press the "Scheme Table" field on the Program Menu Select screen.						
	MENU SELECT 21–JUN–2007(THU) 13:45 4/8						
	ADJUST ADJUST						
2.	The Scheme Table screen appears. Then, press the [NEW] button.						
	SCHEME TABLE 21-JUN-2007(THU) 13:45 1/1						
	FIND PLU SEARCH INPUT DELETE						
3.	The confirmation screen appears. Then, press the [ENTER] button.						
01	SCHEME TARLE 21-UIN-2007(THU) 13:45 1/1 21-JUN-2007(THU) 13:45						
	PROGRAM CHECK						
	Designated item is not programmed.						
	Are you sure you want to continue? Press ENTER to continue						
	Press CANCEL to go back.						
	13001 - 0000 ENTER CANCEL						
4.	The Scheme Table Detail (Basic) screen appears. Then, press the [EDIT] button.						
	SCHEME TABLE DETAIL 21–JUN–2007(THU) 13:45						
	RETAIN LOT NO 0:NO DATE LIMIT CONTROL 0:NO						

INPUT

NO 00 SET 000 CONTROL 0:NO SCHEME ID RECORD

BASIC




	DESCRIPTION
ITEM	DESCRIPTION
RETAIN LOT No.	Press to select whether or not to use this lot number.
	0: No
	1: Yes
PASSPORT FORMAT No.	Enter a numeric value and press this field.
ICON No.	Enter a numeric value and press this field.
LIFE OFFSET	Enter a numeric value and press this field.
WEIGHT LIMIT CONTROL	Press to select whether or not to control the weight limit.
	0: No
	1: Yes
DATE LIMIT CONTROL	Press to select whether or not to control the date limit.
	0: No
	1: Yes
LOSS %	Enter a numeric value and press this field

SCHEME TABLE DETAIL 21-JUN-2007(THU) 13:46							
01 <	01 < SCHEME TABLE 1 >						
	AI	START	STOP	MAX DIGIT			
LOT/CARCASS		00	00	00			
GTIN		00	00	00			
WEIGHT	$[\mathcal{N}]$	00	00	00	EDIT		
BASIC		RECORD	INPU	T			

ITEM	DESCRIPTION
LOT/CARCASS	Enter a numeric value and press the corresponding field.
GTIN	Enter a numeric value and press the corresponding field.
WEIGHT	Enter a numeric value and press the corresponding field.
PASSPORT LOT START	Enter a numeric value and press this field.
PASSPORT GTIN START	Enter a numeric value and press this field.

SCHEME TABLE D	ETAIL	21-	-JUN-2007	(THU) 13:	<mark>46</mark> 1/4
01 <	sc	>			
TITLE TEXT	START	ST OP	AI	VARIABLE	
	00	00		0:NO	
	00	00		0:NO	
	00	$\int 0 $		0:NO	EDIT
	00			0:NO	
		๚/	<		
BASIC SCI	HEME ID	RECORD	INPUT		DELETE

9. When creating more tables, enter a desired table number using the numeric keys and press the [PLU] key on the key sheet.



The confirmation screen appears. Then, press the [ENTER] button.

Ş		007/THU 13:46	1/1
Ī	21	1-JUN-2007(THU)	13:46
ľ	PROGRAM CHECK		
	Designated item is not programmed. Are you sure you want to continue? Press ENTER to continue Press CANCEL to go back.	R	
	13001 - 0000		EL

10. Repeat steps 4 through 9 for more registrations.

10.16.2 CHANGING EXISITING MESSAGES

1. Press the "Scheme Table" field on the Program Menu Select screen.

MENU SELECT	21-JUN-2007(THU) 13:51 4/8					
OPERATE						
TOTAL	SCHEME TABLE					
PROGRAM						
SETUP						
ADJUST	MINCE TRACEABILITY					

2. The Scheme Table screen appears.


SCHEME TA	ABLE	21-JUN-2007(THU) 1	3:51	1/1
1	SCHEME TABLE 1			Ł
2	SCHEME TABLE 2		`	
				DETAIL
FIND PLU	SEARCH	INPUT		DELETE

3. Select a desired table number by pressing the corresponding field.

Ε	XAMPL	Table number "	'2".		
S	СНЕМЕ ТА	ABLE	21-JUN-2007(THU) 1	3:52	1/1
	1	SCHEME TABLE 1			Ł
	2	SCHEME TABLE 2	<u> </u>		
			_/m		
			\mathcal{L}		
					DETAIL
	FIND PLU	SEARC	H	_ (DELETE

or press the [PLU] key on the key sheet after a numeric entry.





SCHEME TABLE DETAIL 21–JUN–2007(THU) 13:52							
02 <	sc	>					
	AI	START	STOP	MAX DIGIT			
LOT/CARCASS		00	00	00			
GTIN		00	00	00			
WEIGHT		00	00	00	EDIT		
PASSPORT LOT START 0 0 0							
BASIC	BASIC SCHEME ID RECORD INPUT						

ITEM	DESCRIPTION
LOT/CARCASS	Enter a numeric value and press the corresponding field.
GTIN	Enter a numeric value and press the corresponding field.
WEIGHT	Enter a numeric value and press the corresponding field.
PASSPORT LOT START	Enter a numeric value and press this field.
PASSPORT GTIN START	Enter a numeric value and press this field.

SCHEME TABLE DETAIL 21-JUN-2007(THU) 13:52					5 <mark>2</mark> 1/4
02 <	sc				
TITLE TEXT	START	STOP	Al	VARIABLE	
	00	00		0:NO	
	00	00		0:NO	
	00	00		0:NO	EDIT
	00	00		0:NO	
			<		
BASIC SCH	EME ID	RECORD	INPU		DELETE

6. When changing the table name, press the [EDIT] button.


SCHEME TABLE DETAIL 21–JUN–2007(THU) 13:52							
02 <	02 < SCHEME TABLE 2						
RETAIN LOT NO	0:NO	DATE LIMIT CONTROL	0:NO				
PASSPORT FORMAT NO	00	LOSS %	00				
ICON No	00			EDIT			
LIFE OFFSET	000						
WEIGHT LIMIT CONTROL	0:NO						
BASIC SCHEME ID RECORD INPUT							

The Scheme Table Edit screen appears.SCHEME TABLE EDIT2 7. 21-JUN-2007(THU) 13:52 t **SCHEME TABLE 2** Q U 0 W Ε R П D П Ζ v В No CHAR REMAIN INPUT ERASE 2 014 018

8,	Edit a text according to the procedures described in Appendix "Text Editing".
0.	SCHEME TABLE EDIT 21–JUN–2007(THU) 13:52
	SCHEME TABLE BB
	QWERTYUIOP
	A S D F G H J K L
	ZXCVBNM,.
	No. CHAR REMAIN 2 015 017
9.	Press the [ESC] key on the key sheet to escape from text editing mode.
	The confirmation screen appears. Then, press the [SAVE] button.
	SCHEME TARLE EDIT 21-UIN-2007(THU) 13:52 21-JUN-2007(THU) 13:52
	PROGRAM CHECK
	Are you sure you want to save changes? To confirm changes press SAVE to undo changes press CANCEL
	19001 - 0000 SAVE CANCEL
10.	The edited text has been registered. Then, press the Return button.
	SCHEME TABLE DETAIL 21–JUN–2007(THU) 13:52
	02 < SCHEME TABLE BB >
	RETAIN LOT NO 0:NO DATE LIMIT CONTROL 0:NO PASSPORT FORMAT NO 00 LOSS % 00
	WEIGHT LIMIT CONTROL 0:NO
	BASIC SCHEME ID RECORD INPUT
11.	The Scheme Table screen appears.
	SCHEME TABLE 21-JUN-2007(THU) 13:53 1/1
	1 SCHEME TABLE 1
	2 SCHEME TABLE BB
	DETAIL
12.	Repeat steps 3 through 11 for more registrations.

10.17 GEN TABLE REGISTRATION

1. Press the "GEN Table" field on the Program Menu Select screen.




2. The GEN Table screen appears.


GEN TABLE	21-JU	N-2007(1	THU) 13:5	5 1/2
TITLE TEXT	START	STOP	ATTR ID	
GEN 1:	0	0	1	
GEN 2:	0	0	2	
GEN 3:	0	0	9999	
GEN 4:	0	0	1	
GEN 5:	0	0	2	EDIT
		INPUT]	DELETE

3. Select a desired GEN table by pressing the corresponding field.

GEN TABLE	21-JU	N-2007(1	FHU) 13:5	5 1/2
TITLE TEXT	START	STOP	ATTR ID	
GEN 1:	0	0	1	
GEN 2:	0	0	2	
GEN 3:	0	0	9999	
GEN 4:	0	0	1	
GEN 5:	0	0	2	EDIT
		INPUT		DELETE

4. Enter a numeric value and press the corresponding field.





9.


The edited text has been registered.

GEN TABLE	21-JU	N-2007(1	'HU) 13:5	6 1/2
TITLE TEXT	START	STOP	ATTR ID	
GEN 1:	0	0	1	
GEN TABLE 2:	0	0	2	
GEN 3:	0	0	9999	
GEN 4:	0	0	1	
GEN 5:	0	0	2	EDIT
		INPUT		DELETE

10. Repeat steps 3 through 9 for more registrations.

10.18 LOOKUP TABLE REGISTRATION

10.18.1 CREATING NEW TABLES



5.

- The Lookup Header Table Edit screen appears. LOOKUP HEADER TABLE EDIT 21-JUN-2007(THU) 13:58 Q U 0 R A G Н D х С ۷ В Ν М Z CHAR REMAIN STYLE FONT INPUT ERASE 30x15/30x15 1 000 032 1
- 6. Edit a text according to the procedures described in Appendix "Text Editing".

LOOKOP HEADEK TABLE EDIT						21-1	UN-20	J7(THU) 13:58
υ.κ	•							£
Q	w	E	R		Y	U	I	0 P
A	s	D	F	G	н		к	
	z	X	С		В		м	
No. 1	CHA 004		MAIN 028	STYLE /		FONT 15/30x15	INP	UT


7. Press the [ESC] key on the key sheet to escape from text editing mode.

ESC The confirmation screen appears. Then, press the [SAVE] button.



8. The edited text has been registered. Then, press the [NEW] button.

LOOKUP TABLE DAT	A LIST 21-	JUN-2007(THU) 13:	59 1/1
1 <	U.K.	> EDIT	
DATA No.	DATA TE	хт	
]
			NEW
			1 (17)
		INPUT	T ح




The Lookup Data Table Edit screen appears. 10. LOOKUP DATA TABLE EDIT 21-JUN-2007(THU) 13:59 t U W R Т Y 0 Р 0 F п S Н К A D F v В М REMAIN STYLE CHAR FONT INPUT FRASI 000 30x15/30x15 1 032 7


11. Edit a text according to the procedures described in Appendix "Text Editing".


LOOKU	LOOKUP DATA TABLE EDIT 21-JUN						UN-20	07(TH	U) 13:59
EE	EEG 032_								
Q	W	E	R	T	Y	U		0	P
A	s	D	F	G	н		К	L	
	Z	X	С		В		М	,	
No. 1	СН4 00		MAIN 025	STYLE		FONT 15/30x15	INP	υτ	ERASE


12. Press the [ESC] key on the key sheet to escape from text editing mode.

ESC










NEW



26. Press the [ESC] key on the key sheet to escape from text editing mode.



The confirmation screen appears. Then, press the [SAVE] button.



27. The edited text has been registered. Then, press the Return button.

LOOKUP TABLE	DATA LIST	21-JUN-	-2007(T	HU) 14:02	2 1/1
2 <	NETHERLA	NDS	>	EDIT	
DATA No.	DA	ТА ТЕХТ			
					NEW
					(
-			INPUT		DELE

28.	The Look	The Lookup Table screen appears						
20.	LOOKUP T	ABLE	21-JUN-2007(THU) 14:02	1/1				
	1	U.K.						
	2	NETHERLANDS						
				DETAIL				
	FIND PLU	SEARCH	INPUT	DELETE				

- 29. Repeat
- Repeat steps 22 through 28 for more header registrations.

10.18.2 CHANGING EXISITING TABLES

1. Press the "Lookup Table" field on the Program Menu Select screen.



2. <u>The Lookup Table screen appears.</u>


LOOKU	P TABLE	21-JUN-2007(THU) 14:05	1/1
1	U.K.		Ł
2	NETHERLANDS		
			DETAIL
FIND PLU	SEARCH		DELETE

3. Select a desired header table by pressing the corresponding field.

EXAMPL	Table number "2".	
LOOKUP T	ABLE 21-JUN-2007(THU) 14:05	5 1/1
1	U.K.	
2		
	<u>ا ا ا ا ا ا ا ا ا ا ا ا ا ا ا ا ا ا ا </u>	
		DETAIL
FIND PLU	SEARCH	DELETE

or press the [PLU] key on the key sheet after a numeric entry.





1 011 021 / 30x15/30x15 INPUT ERASE

FONT

STYLE

CHAR

REMAIN

7. Edit a text according to the procedures described in Appendix "Text Editing". LOOKUP HEADER TABLE EDIT 21-JUN-2007(THU) 14:06 FRANCE Т U Q E S D G Н к A Π v м х В Z REMAIN STYLE CHAR FONT INPUT ERASE 005 026 30x15/30x15 1 7

Press the [ESC] key on the key sheet to escape from text editing mode. 8. ESC The confirmation screen appears. Then, press the [SAVE] button. LOOKIIP HEADER TARLE EDIT 21-111N-2007(THIN_14-06 21-JUN-2007(THU) 14:06 **PROGRAM CHECK** Are you sure you want to save changes? To confirm changes press SAVE to undo changes press CANCEL 19001 - 0000 SAVE CANCEL The edited text has been registered. **9** LOOKUP TABLE DATA LIST 21-JUN-2007(THU) 14:05 1/ EDIT < FRANCE > DATA TEX EEG 0532 1 EEG 552 2 DETAIL DELETE INPUT 10. When changing the data text, select a desired data text by pressing the corresponding field. and press the [DETAIL] button. LOOKUP TABLE DATA LIST 21-JUN-2007(THU) 14:05 1/1 EDIT < FRANCE > DATA TEXT 1 EEG 0532 2 EEG 552 IN DE DI INPUT 11. The Lookup Data Table Edit screen appears. LOOKUP DATA TABLE EDIT 21-JUN-2007(THU) 14:06 EEG 0532 Q R U A G н v 7 х R Ν М CHAR REMAIN STYLE FONT INPUT ERASE 30x15/30x15 1 008 024 7

12. Edit a text according to the procedures described in Appendix "Text Editing". LOOKUP DATA TABLE EDIT 21-JUN-2007(THU) 14:06



13. Press the [ESC] key on the key sheet to escape from text editing mode.

The confirmation screen appears. Then, press the [SAVE] button.

ι	OOKIIP DATA TARI F FDIT	21-IIIN-2007(THII) 14:06
Γ		21-JUN-2007(THU) 14:06
	PROGRAM CHE	СК
	Are you sure you want to save cha To confirm changes press SAVE to undo changes press CANCEL	nges?
ſ	19001 - 0000	SAVE CANCEL

14. The edited text has been registered.

LOOKUP TA	BLE DATA LIST 21-JUN-2007(THU) 14:0	l <mark>6</mark> 1/1
2	< FRANCE > EDIT	t
DATA No.	DATA TEXT	
1	EEG 0254	
2	EEG 552	
		DETAIL
	INPUT	DELETE

- **15.** Repeat steps 10 through 14 for more data text registrations.
- **16.** Repeat steps 3 through 15 for more header table text registrations.

10.19 MINCE TRACEABILITY REGISTRATION


1. Press the "Mince Traceability" field on the Program Menu Select screen.

 MENU SELECT
 21-JUN-2007(THU) 14:10



2.	The M	ince Traceability screer	n appears	S.	
	MINCE	TRACEABILITY		21-JUN-2	007(THU) 14:10
		Able to set	1~99		t
		START	00		
		STOP	00		
		PASSPORT FORMAT No.	00		
				INPUT	

3. Enter a numeric value and press the corresponding field for registration. Then, press the Return button to finalize this procedure.



10.20 FIXED PRICE MARK REGISTRATION

10.20.1 CREATING NEW PRICE MARKS

1. Press the "Fixed Mark" field on the Program Menu Select screen.



2.	The Fix Price Mark List screen appears.					
	FIX PRICE N	ARK LIST 21-JUN-20	07(THU) 14:20	1/1		
	1	0Z 0Z		t		
	2	lb lb				
	3	kg kg				
	4	g g				
	5	PC. PCS.				
				DETAIL		
	FIND PLU	SEARCH		DELETE		

3. Enter a desired mark number using the numeric keys and press the [PLU] key on the key sheet.

EXAMPLE Mark number "6".




The confirmation screen appears. Then, press the [ENTER] button.

F	IX PRICE MARK LIST 21-111N-2007(THII) 14:20 171 21-JUN-2007(THU) 14:20
ľ	PROGRAM CHECK
	Designated item is not programmed. Are you sure you want to continue? Press ENTER to continue Press CANCEL to go back.
	13001 - 0000 ENTER CANCEL

The Fix Price Mark Edit screen appears. 4. FIX PRICE MARK EDIT 21-JUN-2007(THU) 14:20 t Q R 0 Π A G C REMAIN STYLE CHAR INPUT ERASE 6 000 020 1 Edit a text according to the procedures described in Appendix "Text Editing". 5. 21-JUN-2007(THU) 14:20 FIX PRICE MARK EDIT BOX BOXES R 0 A D R G С CHAR REMAIN STYLE INPUT ERASE 6 009 011 Press the [ESC] key on the key sheet to escape from text editing mode. 6. ESC The confirmation screen appears. Then, press the [SAVE] button. FIX PRICE MARK EDIT 21-111N-2007(THIN 14:20 21-JUN-2007(THU) 14:20 **PROGRAM CHECK** Are you sure you want to save changes? To confirm changes press SAVE to undo changes press CANCEL CANCE 19001 - 0000 SAVE 7. The edited text has been registered. To finalize this procedure, press the Return button. 21-JUN-2007(THU) 14:20 FIX PRICE MARK LIST 1/11 oz oz lb lb 2 3 kg kg 4 g g 5 PC. PCS. BOX BOXES 6 DETAIL FIND PLU DELETE INPUT

10.20.2 CHANGING EXISITING PRICE MARKS

1. Press the "Fixed Mark" field on the Program Menu Select screen.



2. Select a desired mark number by pressing the corresponding field.

EXAMPL	Mark number "2".		
FIX PRICE	MARK LIST	21-JUN-2007(THU) 14:2	1/1
1	0Z 0Z		
2	lb lb	ſ	
3	kg kg) m	
4	99		
5	PC. PCS.		
6	BOX BOXES	[DETAIL
FIND PLU	SEARCH	INPUT	DELETE

or press the [PLU] key on the key sheet after a numeric entry.



3. The Fix Price Mark Edit screen appears. FIX PRICE MARK EDIT 21-JUN-2007(THU) 14:21 lb lb Q W R Т N U 0 Н A D v м Z В Ν No CHAR REMAIN STYLE INPUT ERASE 2 005 015 7

Edit a text according to the procedures described in Appendix "Text Editing". 4. FIX PRICE MARK EDIT 21-JUN-2007(THU) 14:21 PACK PACKS Π 0 Q R Т v P w S D F G Η С v R Μ CHAR REMAIN STYLE INPUT ERASI 010 010 2 Press the [ESC] key on the key sheet to escape from text editing mode. 5. ESC The confirmation screen appears. Then, press the [SAVE] button. FIX PRICE MARK EDIT 21-IIIN-2007(THII) 14:21 21-JUN-2007(THU) 14:21 **PROGRAM CHECK** Are you sure you want to save changes? To confirm changes press SAVE to undo changes press CANCEL 19001 - 0000 SAVE The edited text has been registered. 6. FIX PRICE MARK LIST 21-JUN-2007(THU) 14:21 1/1 oz oz 1 2 PACK PACKS 3 kg kg 4 g g 5 PC. PCS. 6 BOX BOXES DETAIL FIND PLU DELETE INPUT 7. Repeat steps 2 through 6 for more registrations.

10.21 FREE MESSAGE REGISTRATION

10.21.1 CREATING NEW MESSAGES

- **1.** Press the "Free" field on the Program Menu Select screen.

 MENU SELECT
 21-JUN-2007(THU)
 14:25
 5/8

 Image: Operate in the program Mark in the program in the
- 2. The Free Message List screen appears. Then, press the [NEW] button.

FREE1 LIST	21-JUN-2007(THU) 14:25	1/1
		t
	/	5
	L	Цľ
		NEW
FIND PLU	SEARCH DISP. 1	DELETE

3. The confirmation screen appears. Then, press the [ENTER] button.



4. The Free Message Edit screen appears.

FREE1 EDIT 21-J				UN-2007(TH	14:25
_					t_
QW	ER		Y U	O	P
AS	DF	G	Н	K L	
	х с		BN	M ,	
No. CHAR	2048	STYLE /	FONT 30x15/30x15	INPUT	ERASE

5. Edit a text according to the procedures described in Appendix "Text Editing". **FREE1 EDIT 21-JUN-2007(THU) 14:25**



6. Press the [ESC] key on the key sheet to escape from text editing mode.

The confirmation screen appears. Then, press the [SAVE] button.

ESC

F	REF1 FNIT	21-IIIN-2007(THII) 14:25
Π		21-JUN-2007(THU) 14:25
	PROGRAM CHE	ск
	Are you sure you want to save cha To confirm changes press SAVE to undo changes press CANCEL	nges?
Ĩ	19001 - 0000	


7. The edited text has been registered.

FREE1 LIST		21-JUN-2007(THU)	14:26	1/1
1	FREE MESSAGE AA			t
			`	
				DETAIL
FIND PLU	SEARCH	DISP. 1 LINE 1		DELETE

8. Enter a desired message number using the numeric keys and press the [PLU] key on the key sheet.



Enter a desired message number using the numeric keys and press the [PLU] key on the key sheet.





The confirmation screen appears. Then, press the [ENTER] button.

F,	RFF1 LIST	21-11N-2007(THII) 14·26 1/1
T		21-JUN-2007(THU) 14:26
	PROGRA	м снеск
	Designated item is not prog Are you sure you want to c Press ENTER to continue Press CANCEL to go back.	
	13001 - 0000	ENTER CANCEL

9. Repeat steps 4 through 8 for more registrations.

10.21.2 CHANGING EXISITING MESSAGES

1. Press the "Fixed Mark" field on the Program Menu Select screen.

MENU SELECT	21-JUN-2007(THU) 14:30	5/8
OPERATE		
ΤΟΤΑΙ	FREE1	
PROGRAM	≣ €(¹ m)	
SETUP	FR C	
ADJUST	FREE4	æ

2. The Free Message List screen appears.


FREE1 LIST		21-JUN-2007(THU)	14:30	1/1
1	FREE MESSAGE AA			Ł
2	FREE MESSAGE BB		`	
				DETAIL
FIND PLU				DELETE

3. Select a desired message number by pressing the corresponding field.

EXAMPL	Message number "2".	
FREE1 LIST	21-JUN-2007(THU) 14:30	1/1
1	FREE MESSAGE AA	Ł
2		
		DETAIL
FIND PLU	SEARCH DISP. 1	DELETE

or press the [PLU] key on the key sheet after a numeric entry.





8. Repeat steps 3 through 7 for more registrations.

10.22 CHECK LABEL REGISTRATION


1. Press the "Check Label" field on the Program Menu Select screen.

MENU SELECT	21-JUN-2007(THU) 14:35	8/8
OPERATE	FREE15	
TOTAL		
PROGRAM	(III)	
SETUP	ц Ц	
ADJUST		

2. The Check Label screen appears.

CHECK LABEL	21-JUN-2007(THU) 14:35
ISSUE BEFOR	E
START No.	END No. 5996 START
	INPUT

3. Enter Start Number and End Number using the numeric keys and press the corresponding fields for registration.



ISSUE BEFORE START NO. 100 ST NPUT	START NO. 100 END NO. 1000 ST	CHECK LABEL		21-JUN-2007	(THV) 1
100 1000 ST	100 1000 ST	[ISSUE BEFORE		t
] ST

TEXT EDITING




A.1 OPERATION PANEL AND KEY FUNCTIONS

Operation Panel

										Mode	Size	Under Line	Italic	Normal	Bold
										PgUp	Start	Reverse	Back Space	Char Delete	Line Delete
										PgDn	End	←	\rightarrow	→0← Zero	↔ T Tare
											or Feed	7	8	9	
										▼ ESC	С	4	5	6	O Print
										ESC	0	1	2	3	PLU
€	Q	W	E	R	Т	Υ	U	Ι	0	Р	,	#	\$	% @	*
Lower Case	Α	S	D	F	G	н	J	к	L	;	•	Edit	()	" ,	!
	Shift	z	X	С	V	В	Ν	М	•	Space	• Ne	ew Line	Сору	Insert	Enter


Text Editing Keys

Back Space	Used to delete a character by moving the cursor back by one character.	Size	Used to select a font size for a text displayed on the screen.
Char Delete	Used to delete a character at the place where the cursor is positioned.	Insert	Used to insert a character, or select characters followed by depressions of the $[\rightarrow]$ or $[\leftarrow]$ key.
Line Delete	Used to delete a line text.	\rightarrow	Used to move the cursor to right. Also used to select characters for changing the style.
Normal	Used to specify a normal character style.	(Used to move the cursor to left. Also used to select characters for changing the style.
Bold	Used to specify a bold character style.	Lower Case	Used to select either lower-case or upper-case character mode for a text to be entered.



A.2 NORMAL CHARACTER EDITING

- **1.** Confirm that the text edit screen is displayed.
 - Select a desired character size by using the [Size] key on the key sheet.





The selected size is displayed in the "FONT" display field.

ITEM DE	TAIL(I	TEM N/	AME EI)IT)		JUN-	14-200	0 7(TH	U) 23:08
									ſ
Q	w [E	R	Т	Y			0	P
A	s [D	F	G	н		к	L	
	z	x	С		В	N	м	,	
No. 4	CHAR 000		MAIN 119	STYLE /		FONT 15/56x28	INP	υτ	ERASE

2. Press the [Lower Case] key on the key sheet to select whether to use upper-case characters or lower-case characters.

ITEM DETAIL		E EDIT)		IIIM-	14-200)7(THU) 23:08
				1014	14 200	57(1110) 23.00
•						
Q W	E	R T		U		ΟΡ
AS	D	F G	н		К	
			В		м	
			Ľ			لنالنا
No. CH	AR REMAI	N STYLE	F	ONT	<u> </u>	
4 00	0 5119	1	30x1	5/60x30	INP	UT ERASE



ITEM D	ETAIL(ITEM N	JUN-	-14-200	0 7(THU	J) 23:08			
				Ł					
Ŀ			_		_				
q	w	e	r	t	У	u	i	0	р
a	s	d	f	g	h	j	k		
	z	x	C		b	n	m	С	E
N0.	CHA 000		MAIN 5119	STYLE /		FONT 15/60x30	INP	UT	ERASE

3. Enter desired characters using alpha-numeric keys on the key sheet or the screen.



Upper-	Upper-case characters													
ITEM D	ETAIL(I	TEM N	JUN	-14-200	0 7(THU	J) 23:09								
GO	UD,	A C	HE					ſ						
Q	w	E	R	T	Y	U		0	P					
A	s	D	F	G	н	J	К	L						
	z	x	С		В		M	,						
No. 4						FONT 30/60x30	INP	υт	ERASE					

Lower	-case	chara	cters							
ITEM D	ETAIL(I	TEM N	AME EI	DIT)	JUN-14-2007(THU) 23:09					
go	uda	ch	ees	e					Ł	
q	w	е	r	t	У	u	i	0	p	
a	s	d	f	g	h	j	k			
	z	x	C	v	b	n	m	С	E	
N0.	CHA 011		MAIN 107	STYLE /		FONT 80/60x30	INP	UT	ERASE	

- To change to a new line, press the [New Line] key on the key sheet. 4. New Line Enter desired characters. ((W S I S S Shift) ITEM DETAIL(ITEM NAME EDIT) JUN-14-2007(THU) 23:10 Ŧ (SWISS) Q U 0 P W Ε Y П A G S D F н П К х С v В Ν М 7 CHAR REMAIN STYLE FONT INPUT ERASE 4 021 5099 60x30/60x30
- 5. To finalize the editing, press the [ESC] key on the key sheet.



The confirmation screen appears. Then, press the [SAVE] button to save the data.



A.3 SPECIAL CHARACTER EDITING

1. Confirm that the text edit screen is displayed. ITEM DETAIL(ITEM NAME EDIT) JUN-14-2007(THU) 23:12

•									
Q	w	E	R	T	Y			0	P
A	s	D	F	G	н		К	L	
	z	X] C		В		м	<u>,</u>	
N0.	CHAR		REMAIN	STYLE		FONT		ит Ì	ERASE
4	000		5119	1	30>	(15/30x15	INPUT		EKASE

2. To select a desired character style using the following keys.



The selected style is displayed in the "STYLE" display field.

EXAMPLE

Select reversed charact	ers.		
ITEM DETAIL(ITEM NAME E	DIT)	JUN-1	4-2007(THU) 23:12
•			t
QWER		Y U	1 0 P
ASDF	G	НЈЈ	K L
ZXC		B N	м,,.
No. CHAR REMAIN 4 000 5119	STYLE B / R	FONT 30x15/30x15	INPUT

3. Enter desired characters using alpha-numeric keys on the key sheet or the screen.

GO	U	D		● s	pace	С	Н	E	E
ITEM DETAIL	L(ITEM N	AME EI)IT)		JUN-	-14-20	0 7(TH	U) 23:13	
GOUL	DAC	HE	Se					1	
QW	E	R	T	γ	U	I	0	P	
AS	D	F	G	н		К	L		
	X	С		В		м	,		
		MAIN 5107	STYLE B / R		FONT 15/30x15	INF	тυч	ERASE	

S

Е

4. Press the [ESC] key on the key sheet.
ESC
The confirmation screen appears. Then, press the [SAVE] button to save the data.

Image: the image: the image is the image i


A.4 LINE DELETION

1. Confirm that the text edit screen for a desired PLU is displayed. ITEM DETAIL(ITEM NAME EDIT) JUN-14-2007(THU) 23:18



2. To delete the character line, press the [Line Delete] key on the key sheet.

Line



3. Press the [ESC] key on the key sheet.




The confirmation screen appears. Then, press the [SAVE] button to save the data.


EM DETAIL(ITEM NAME EDIT)	UIN-14-2007(THU) 23:18 JUN-14-2007(THU) 23:18
PROGRAM C	снеск
Are you sure you want to save To confirm changes press SAV to undo changes press CANCE	E
19001 - 0000	

A.5 CHARACTER DELETION


1. To Make a correction for a misspelled word, move the cursor to a place where misspelling is made by using the $[\rightarrow]$ or $[\leftarrow]$ key.



2. Press the [Character Delete] key on the key sheet to delete the misspelled character.




3. Enter the correct character using the alpha-numeric keys.



4 Press the [ESC] key on the key sheet.




The confirmation screen appears. Then, press the [SAVE] button to save the data.



A.6 CHARACTER BACKSPACING


1. To delete a wrong character that was just entered, press the [Back Space] key on the key sheet to move the cursor back by one character.





ITEM D	ETAIL(ITEM NA	ME EI	DIT)		JUN-	-14-200	0 7(THU	J) 23:23
GO	DUD	-							Ł
Q	W	E	R	T	Y	U		0	P
A	s	D	F	G	н		К	L	
	Z	×	с		B		M	,	
N0. 4	CH4		MAIN 115	STYLE /		ONT 15/30x15	INP	υт	ERASE

2. Enter a correct character.



3.	Complete the text.	
0.	ITEM DETAIL(ITEM NAME EDIT)	JUN-14-2007(THU) 23:23
	GOUDA CHEESE	t
	QWERTY	Y U I O P
	ASDFGH	H J K L
		BNM, .
	No. CHAR REMAIN STYLE 4 012 5107 /	FONT 30x15/30x15 INPUT ERASE

4. Press the [ESC] key on the key sheet.

	D
ESC	I.

The confirmation screen appears. Then, press the [SAVE] button to save the data.

ITEM DETAIL (ITEM NAME EDIT)	HIN-14-2007(THI) 23:23 JUN-14-2007(THU) 23:23
PROGRAM CHE	ск
Are you sure you want to save cha To confirm changes press SAVE to undo changes press CANCEL	anges?
19001 - 0000	



44 SANNO-CHO, SHOGOIN, SAKYO-KU KYOTO, 606-8392 JAPAN PHONE: 81-75-771-4141 FACSIMILE: 81-75-751-1634 URL: http://www.ishidajapan.com Design and specifications are subject to change without notice.